

OPS/MVS for JES2/JES3 14.0
CA RS 2206 Service List

1

Service	Description	Type
LU05478	EXTSECCMDRULE ACCESS DENIED MESSAGE AND WARN MODE ADDED	PTF
LU05612	SSM ENDS AFTER OPS5005S ABEND SOC4 IN OPPFPR +4DE	PTF
LU05737	OPS0047I MESSAGE IS MISSING THE JES2 RELEASE NUMBER	PTF
LU05807	OPSLOG FUNCTION FILTERS DESC/ROUTCDE/DISP/MSGID 11-12 FAILED	PTF
LU05943	SECURITY OR INTEGRITY PROBLEM	** PRP **
LU06030	SECURITY OR INTEGRITY PROBLEM	** PRP **
LU06069	RECOVERABLE SOC4 ABEND DUE TO UNEXPECTED BRANCH	PTF
The CA RS 2206 service count for this release is 7		

OPS/MVS for JES2/JES3
CA RS 2206 Service List for CCLXE00

2

FMID	Service	Description	Type
CCLXE00	LU05478	EXTSECCMDRULE ACCESS DENIED MESSAGE AND WARN MODE ADDED	PTF
	LU05612	SSM ENDS AFTER OPS5005S ABEND SOC4 IN OPPFPR +4DE	PTF
	LU05737	OPS0047I MESSAGE IS MISSING THE JES2 RELEASE NUMBER	PTF
	LU05807	OPSLOG FUNCTION FILTERS DESC/ROUTCDE/DISP/MSGID 11-12 FAILED	PTF
	LU06069	RECOVERABLE SOC4 ABEND DUE TO UNEXPECTED BRANCH	PTF
The CA RS 2206 service count for this FMID is 5			

OPS/MVS for JES2/JES3
CA RS 2206 Service List for CCLXE01

3

FMID	Service	Description	Type
CCLXE01	LU05943	SECURITY OR INTEGRITY PROBLEM	** PRP **
	LU06030	SECURITY OR INTEGRITY PROBLEM	** PRP **
The CA RS 2206 service count for this FMID is 2			

Service	Details																						
LU05478	LU05478 M.C.S. ENTRIES = ++PTF (LU05478) EXTSECCMDRULE ACCESS DENIED MESSAGE AND WARN MODE ADDED PROBLEM DESCRIPTION: When using EXTSECCMDRULE=YES to secure command rules, EXTSECSHOW=YES may be too verbose to track blocked attempts run these command rules. A new message (OPS2113I) has been added to log denied attempts. EXTSECCMDRULE=WARN was also added. Here command rules are not secured but all relevant messages for access allowed and denied are still issued. This option will help during feature implementation without causing any impact on normal operations. SYMPTOMS: Only EXTSECSHOW=YES can be used to track access denials for secured command rules via EXTSECCMDRULE. IMPACT: Unable to track access denials without the need for EXTSECSHOW=YES. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 16702 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00215-CLX140 DESC(EXTSECCMDRULE ACCESS DENIED MESSAGE AND WARN MODE ADDED). ++VER (Z038) FMID (CCLXE00) PRE (LU00477 LU00715 LU01211 LU02161 LU02417 LU03149 LU03258 LU03418 LU03790 LU03819 SO15067 SO15502 SO15505 SO15565 SO15876) SUP (LT02046 LT05064 LT05434 LT05478 LU02046 LU05064) ++HOLD (LU05478) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22137) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> <tr> <td>SEQUENCE</td><td>After APPLY</td></tr> <tr> <td>PURPOSE</td><td>To activate load modules updated by this PTF</td></tr> <tr> <td>USERS</td><td>All OPS/MVS users</td></tr> <tr> <td>AFFECTED</td><td></td></tr> <tr> <td>KNOWLEDGE</td><td>Basic z/OS systems programming skills</td></tr> <tr> <td>REQUIRED</td><td></td></tr> <tr> <td>ACCESS</td><td>- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any</td></tr> <tr> <td>REQUIRED</td><td>deployed copies</td></tr> <tr> <td></td><td>- Authority to issue MVS system commands</td></tr> <tr> <td></td><td>- Authority to stop and start OPS/MVS</td></tr> </table> *****	OPS/MVS	Version 14.0	SEQUENCE	After APPLY	PURPOSE	To activate load modules updated by this PTF	USERS	All OPS/MVS users	AFFECTED		KNOWLEDGE	Basic z/OS systems programming skills	REQUIRED		ACCESS	- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any	REQUIRED	deployed copies		- Authority to issue MVS system commands		- Authority to stop and start OPS/MVS
OPS/MVS	Version 14.0																						
SEQUENCE	After APPLY																						
PURPOSE	To activate load modules updated by this PTF																						
USERS	All OPS/MVS users																						
AFFECTED																							
KNOWLEDGE	Basic z/OS systems programming skills																						
REQUIRED																							
ACCESS	- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any																						
REQUIRED	deployed copies																						
	- Authority to issue MVS system commands																						
	- Authority to stop and start OPS/MVS																						

Service	Details
	* STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details		
LU05612	LU05612 M.C.S. ENTRIES = ++PTF (LU05612) SSM ENDS AFTER OPS5005S ABEND SOC4 IN OPPFPR +4DE PROBLEM DESCRIPTION: An invalid substring entry with unbalanced parenthesis in an SSM action clause may cause a SOC4 ABEND in module OPPFPR. SYMPTOMS: OPS5005S ABEND X'000C4000' in subtask exit OPSYSTZS+X'F1078286' IMPACT: The STATEMAN subtask ends. CIRCUMVENTION: Fix the invalid action text. PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 16422 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00219-CLX140 DESC(SSM ENDS AFTER OPS5005S ABEND SOC4 IN OPPFPR +4DE). ++VER (Z038) FMID (CCLXE00) PRE (LU03790) SUP (LT05018 LT05612) ++HOLD (LU05612) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22136) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details		
LU05737	LU05737 M.C.S. ENTRIES = ++PTF (LU05737) OPS0047I MESSAGE IS MISSING THE JES2 RELEASE NUMBER PROBLEM DESCRIPTION: The OPS/MVS message, OPS0047I JES2 default offset table found for JES2 release, is missing the JES2 release level that was detected in OPS/MVS load module OPJ2DF. SYMPTOMS: The OPS0047I message is issued without a JES2 release level listed as the last word in the message text. IMPACT: Unable to verify the correct OPS/MVS JES2 offset table matches the currently installed JES2 release level. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 16967 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00226-CLX140 DESC(OPS0047I MESSAGE IS MISSING THE JES2 RELEASE NUMBER). ++VER (Z038) FMID (CCLXE00) PRE (LU00442 LU02484 LU03790) SUP (LT05737) ++HOLD (LU05737) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22124) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details
LU05807	LU05807 M.C.S. ENTRIES = ++PTF (LU05807) OPSLOG FUNCTION FILTERS DESC/ROUTCDE/DISP/MSGID 11-12 FAILED PROBLEM DESCRIPTION: OPS/REXX OPSLOG function expanded format to extract messages from an OPSLOG cannot filter on the message MCS descriptor code (DESC), the message route code (ROUTCDE), the final AOF event disposition (DISP), and the 11th and 12th message identifiers (MSGID). SYMPTOMS: Messages returned are not according to the set filters mentioned in PROBLEM DESCRIPTION, or error appears when using more than 10 message IDs. IMPACT: Cannot use OPSLOG function for filtering as mentioned in PROBLEM DESCRIPTION. CIRCUMVENTION: Use the ISPF OPSVIEW OPSLOG PROFILE panel for filtering, and reference the returned messages in the OPSLOG. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 17069 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00228-CLX140 DESC(OPSLOG FUNCTION FILTERS DESC/ROUTCDE/DISP/MSGID 11-12 FAILED). ++VER (Z038) FMID (CCLXE00) PRE (LU00058 LU00060 LU03082 LU03513 LU03790 S014824) SUP (LT00610 LT01967 LT02521 LT05807 LU00610 LU01967 LU02521) ++HOLD (LU05807) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22137) COMMENT (<pre> +-----+ OPS/MVS Version 14.0 +-----+ SEQUENCE After APPLY +-----+ PURPOSE To activate load modules updated by this PTF +-----+ USERS All OPS/MVS users AFFECTED +-----+ KNOWLEDGE Basic z/OS systems programming skills REQUIRED +-----+ ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS +-----+ ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. </pre>

Service	Details
	Refer to GIM23903I messages in the SMPOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details		
LU05943	LU05943 M.C.S. ENTRIES = ++PTF (LU05943) SECURITY OR INTEGRITY PROBLEM PROBLEM DESCRIPTION: Security or Integrity Problem. For more details access Security Advisories using the following URL: support.broadcom.com/security-advisory/security-advisories-list.html Broadcom recommends that you subscribe to notifications for Security Advisories for the associated products that you support in your organization. Please use the following URL to register for proactive notifications: https://support.broadcom.com/user/notifications.html SYMPTOMS: N/A IMPACT: Security or Integrity Problem. CIRCUMVENTION: N/A PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 16893 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00231-CLX140 DESC (SECURITY OR INTEGRITY PROBLEM). ++VER (Z038) FMID (CCLXE01) PRE (LU03791 LU03946 LU04002 LU05148) SUP (FC15146 IC15146 LT05617 LT05943) ++HOLD (LU05943) SYSTEM FMID(CCLXE01) REASON (ACTION) DATE (22138) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After Apply. PURPOSE To activate the updates in this PTF USERS All users of NIM-SM AFFECTED KNOWLEDGE Basic z/OS system programming skills. REQUIRED ACCESS Authority to stop and start NIM-SM REQUIRED ***** * STEPS TO PERFORM * ***** To redeploy your instance of NIM SM with the war file in this PTF, you will need to locate ca-nim-sm.war under your USS path name defined by	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	SMP/E DDDEF CCLXHFSM (i.e. /opsmvs/directory/CCLXHFS). Place this war file in your target NIM SM USS directory and restart.). LINK('../ca-nim-sm.war') PARM(PATHMODE(0,7,5,5)).

Service	Details																
LU06030	LU06030 M.C.S. ENTRIES = ++PTF (LU06030) SECURITY OR INTEGRITY PROBLEM PROBLEM DESCRIPTION: Security or Integrity Problem. For more details access Security Advisories using the following URL: support.broadcom.com/security-advisory/security-advisories-list.html Broadcom recommends that you subscribe to notifications for Security Advisories for the associated products that you support in your organization. Please use the following URL to register for proactive notifications: https://support.broadcom.com/user/notifications.html SYMPTOMS: N/A IMPACT: Security or Integrity Problem. CIRCUMVENTION: N/A PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 17227 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00233-CLX140 DESC (SECURITY OR INTEGRITY PROBLEM). ++VER (Z038) FMID (CCLXE01) PRE (LU00044 LU00122 LU00462 LU00633 LU01212 LU03582 LU03791 LU03946 LU04002 LU05148 LU05380 S014492 S015022 S015068 S015241 S015821 S015877) SUP (AC15146 EC15146 GC15146 HC15146 JC15146 LT01162 LT02570 LT04224 LT04967 LT05432 LT05627 LT05691 LT06018 LT06030 LU02570 LU04224 LU05432 LU05627 LU05691 S014857 S015148 S015200 ST14857 ST14979 ST15148 ST15200) ++HOLD (LU06030) SYSTEM FMID (CCLXE01) REASON (DYNACT) DATE (22145) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> <tr> <td>SEQUENCE</td><td>After APPLY</td></tr> <tr> <td>PURPOSE</td><td>To deploy a new version of Mainframe Team Center - Automation</td></tr> <tr> <td>USERS</td><td>All OPS/MVS MTC-A users</td></tr> <tr> <td>AFFECTED</td><td></td></tr> <tr> <td>KNOWLEDGE</td><td>Basic z/OS systems programming skills and knowledge of</td></tr> <tr> <td>REQUIRED</td><td>your new or existing MTC-A installation and configuration</td></tr> <tr> <td>ACCESS</td><td>- Read/write access to the USS directories where your new</td></tr> </table>)	OPS/MVS	Version 14.0	SEQUENCE	After APPLY	PURPOSE	To deploy a new version of Mainframe Team Center - Automation	USERS	All OPS/MVS MTC-A users	AFFECTED		KNOWLEDGE	Basic z/OS systems programming skills and knowledge of	REQUIRED	your new or existing MTC-A installation and configuration	ACCESS	- Read/write access to the USS directories where your new
OPS/MVS	Version 14.0																
SEQUENCE	After APPLY																
PURPOSE	To deploy a new version of Mainframe Team Center - Automation																
USERS	All OPS/MVS MTC-A users																
AFFECTED																	
KNOWLEDGE	Basic z/OS systems programming skills and knowledge of																
REQUIRED	your new or existing MTC-A installation and configuration																
ACCESS	- Read/write access to the USS directories where your new																

Service	Details
	<pre> REQUIRED or existing installation of MTC-A resides - Authority to STOP and START your MTC-A Web Application +-----+-----+ ***** * STEPS TO PERFORM * ***** Run The MTC-A Configuration Batch Job Sample JCL to execute the configuration script, mtcacfg.sh, is provided in yourHLQ.CCLXCNTL(OPMOIACG). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Set CCLXCLS0 to the fully qualified MVS dataset name of the SMP/E CLIST target library installed by FMID CCLXxr0 OPS/MVS Base. (eg. 'yourHLQ.CCLXCLS0') 3. Set CCLSHFSM to the USS mount point of the zFS installed by FMID CLXxr1 OPS/MVS OPSLOG WebView and Web Features. 4. Set TOMCATCONF to the USS path of your deployed Tomcat server's "context" directory. Typically: <catalina_base>/conf/Catalina/localhost 5. Set MTCADepLOY to the USS path where you wish to deploy the MTCA Web App. A new directory called '/mtca' will be created on this path and will contain the mtcaApp.war as well as '/conf' and '/log' sub-directories. The configuration script creates the MTC-A directory structure at your chosen deployment location and defines the context for MTC-A to your Tomcat installation. If a previous MTC-A installation exists, your current configuration is saved as 'MTCADepLOY/mtca/conf/config.yaml.YY_MM_DD_hh_mm_ss'. Your configuration is then automatically merged and upgraded to the version supplied within this PTF. Verify the STDOUT of the configuration batch job for messages indicating the addition of fields to the 'conf.yaml' that must be set specifically for your site before MTC-A is restarted. If your '/mtca' directory is on path 'a/b/c/mtca' supply path '/a/b/c' as your value for the deploy location). LINK('..../conf.yaml') PARM(PATHMODE(0,7,5,5)). LINK('..../mtcacfg.sh') PARM(PATHMODE(0,7,5,5)). LINK('..../mtcaApp.war') PARM(PATHMODE(0,7,5,5)). </pre>

Service	Details		
LU06069	LU06069 M.C.S. ENTRIES = ++PTF (LU06069) RECOVERABLE SOC4 ABEND DUE TO UNEXPECTED BRANCH PROBLEM DESCRIPTION: A recoverable SOC4 ABEND in OPS/MVS module OPPCSSRU could occur due to an unexpected code branch. SYMPTOMS: ABEND code SOC4 in OPS/MVS module OPPCSSRU would be observed in OPSLOG and in OPS/MVS ABEND reporting parameters. IMPACT: None. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 17242 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00236-CLX140 DESC (RECOVERABLE SOC4 ABEND DUE TO UNEXPECTED BRANCH) . ++VER (Z038) FMID (CCLXE00) PRE (LU00913 LU03790) SUP (LT00679 LT03721 LT06062 LT06069 LU00679 LU03721) ++HOLD (LU06069) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22146) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details	
	CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).	
MCS	LU05478	STARTS ON PAGE 0002
MCS	LU05612	STARTS ON PAGE 0004
MCS	LU05737	STARTS ON PAGE 0005
MCS	LU05807	STARTS ON PAGE 0007
MCS	LU05943	STARTS ON PAGE 0009
MCS	LU06030	STARTS ON PAGE 0010
MCS	LU06069	STARTS ON PAGE 0013

OPS/MVS for JES2/JES3 14.0
CA RS 2206 Product/Component Listing

18

Product Family	Product	Release
Systems Management	CA OPS/MVS BASE	14.00.00
The CA RS 2206 Product/Component Count for this release is 1		

CA RS Level	Service	FMID
CAR2206	LU06069	CCLXE00
	LU06030	CCLXE01
	LU05943	CCLXE01
	LU05807	CCLXE00
	LU05737	CCLXE00
	LU05612	CCLXE00
	LU05478	CCLXE00
CAR2205	LU05691	CCLXE01
	LU05627	CCLXE01
	LU05517	CCLXE00
	LU05432	CCLXE01
	LU05380	CCLXE01
	LU05358	CCLXE00
CAR2204	LU05306	CCLXE00
	LU05297	CCLXE00
	LU05260	CCLXE00
	LU05234	CCLXE00
	LU05216	CCLXE00
	LU05215	CCLXE01
	LU05214	CCLXE00
	LU05148	CCLXE01
	LU05096	CCLXE00
	LU05064	CCLXE00
	LU05045	CCLXE00
	LU05016	CCLXE00
	LU05009	CCLXE00
	LU04902	CCLXE00
	LU04793	CCLXE00
CAR2203	LU04913	CCLXE00
	LU04889	CCLXE00
	LU04888	CCLXE00
	LU04768	CCLXE00
	LU04738	CCLXE00
	LU04575	CCLXE00
	LU04473	CCLXE00
	LU03819	CCLXE00
CAR2202	LU04341	CCLXE00
	LU04292	CCLXE00
	LU04224	CCLXE01
	LU04194	CCLXE00
	LU04184	CCLXE00
	LU04168	CCLXE00
	LU04163	CCLXE00
	LU04106	CCLXE00
	LU03744	CCLXE00
	LU03513	CCLXE00
CAR2201	LU04002	CCLXE01

CA RS Level	Service	FMID
	LU03946	CCLXE01
	LU03884	CCLXE01
	LU03852	CCLXE00
	LU03792	CCLXE03
	LU03791	CCLXE01
	LU03790	CCLXE00
	LU03721	CCLXE00
	LU03582	CCLXE01
CAR2112	LU03548	CCLXE00
	LU03512	CCLXE03
	LU03481	CCLXE00
	LU03418	CCLXE00
	LU03387	CCLXE00
	LU03373	CCLXE01
	LU03334	CCLXE00
	LU03258	CCLXE00
CAR2111	LU03303	CCLXE00
	LU03179	CCLXE00
	LU03165	CCLXE01
	LU03149	CCLXE00
	LU03137	CCLXE00
	LU03119	CCLXE00
	LU03099	CCLXE00
	LU03084	CCLXE00
	LU03082	CCLXE00
	LU03072	CCLXE00
	LU03049	CCLXE00
	LU03011	CCLXE00
CAR2110	LU02790	CCLXE00
	LU02570	CCLXE01
	LU02514	CCLXE00
	LU02484	CCLXE00
	LU02253	CCLXE01
	LU02252	CCLXE00
CAR2109	LU02562	CCLXE00
	LU02545	CCLXE00
	LU02521	CCLXE00
	LU02515	CCLXE00
	LU02478	CCLXE00
	LU02417	CCLXE00
	LU02313	CCLXE00
	LU02285	CCLXE00
	LU02105	CCLXE00
CAR2108	LU02209	CCLXE00
	LU02161	CCLXE00
	LU02080	CCLXE00
	LU02046	CCLXE00

CA RS Level	Service	FMID
	LU02021	CCLXE00
	LU01967	CCLXE00
CAR2107	LU01929	CCLXE00
	LU01862	CCLXE00
	LU01797	CCLXE00
	LU01655	CCLXE00
	LU01630	CCLXE00
	LU01562	CCLXE01
	LU01212	CCLXE01
	LU01211	CCLXE00
	LU01140	CCLXE01
CAR2106	LU01398	CCLXE00
	LU01310	CCLXE00
	LU01080	CCLXE00
	LU00913	CCLXE00
CAR2105	LU01117	CCLXE00
	LU01116	CCLXE00
	LU00998	CCLXE00
	LU00876	CCLXE00
	LU00741	CCLXE00
	LU00717	CCLXE00
	LU00679	CCLXE00
CAR2104	LU00716	CCLXE01
	LU00715	CCLXE00
	LU00677	CCLXE00
	LU00634	CCLXE00
	LU00633	CCLXE01
	LU00632	CCLXE00
	LU00610	CCLXE00
	LU00496	CCLXE00
	LU00477	CCLXE00
	LU00462	CCLXE01
	LU00442	CCLXE00
	LU00407	CCLXE00
	LU00361	CCLXE00
	LU00235	CCLXE00
CAR2103	LU00278	CCLXE00
	LU00210	CCLXE00
	LU00188	CCLXE00
	LU00122	CCLXE01
	LU00121	CCLXE00
CAR2102	SO15877	CCLXE01
	SO15876	CCLXE00
	LU00117	CCLXE00
	LU00113	CCLXE00
	LU00078	CCLXE00
	LU00077	CCLXE00

CA RS Level	Service	FMID
	LU00074	CCLXE00
	LU00067	CCLXE00
	LU00063	CCLXE00
	LU00060	CCLXE00
	LU00058	CCLXE00
	LU00057	CCLXE00
	LU00044	CCLXE01
	LU00040	CCLXE00
CAR2101	S015920	CCLXE00
	S015902	CCLXE00
	S015821	CCLXE01
	S015820	CCLXE00
	S015729	CCLXE00
	LU00028	CCLXE00
	LU00025	CCLXE00
CAR2012	S015758	CCLXE00
	S015662	CCLXE00
	S015610	CCLXE00
	S015578	CCLXE00
	S015569	CCLXE00
	S015565	CCLXE00
	S015526	CCLXE00
	S015515	CCLXE00
	S015505	CCLXE00
	S015502	CCLXE00
	S015497	CCLXE00
CAR2011	S015373	CCLXE00
	S015324	CCLXE00
	S015241	CCLXE01
	S015200	CCLXE01
	S015151	CCLXE00
	S015148	CCLXE01
	S015069	CCLXE00
	S015068	CCLXE01
	S015067	CCLXE00
	S014750	CCLXE00
CAR2010	S015022	CCLXE01
	S015018	CCLXE00
	S014993	CCLXE00
	S014932	CCLXE00
	S014903	CCLXE00
	S014875	CCLXE00
	S014871	CCLXE00
	S014857	CCLXE01
	S014824	CCLXE00
	S014801	CCLXE00
	S014646	CCLXE00

CA RS Level	Service	FMID
	S014644	CCLXE00
	S014609	CCLXE00
CAR2009	S014537	CCLXE00
	S014492	CCLXE01
	S014477	CCLXE00
	S014434	CCLXE01
	S014412	CCLXE00