

OPS/MVS 14.0
CA RS 2303 Service List

1

Service	Description	Type
LU08784	MTC-A SSM GLOBAL EXCEPTION VIEW	PTF
LU08898	ABEND SOC4 USING ADDRESS AOF WITH MSF DEFAULT SYSTEM IN RULE	PTF
LU08960	SECURITY OR INTEGRITY PROBLEM	** PRP **
LU09019	SSMGAV2 MOVEABLE RESOURCE NOT DELETED ON ORIGINATING SYSTEM	PTF
LU09025	ACTMODE NOT WORKING FOR SSMGAV2 RESOURCE	PTF
LU09064	SOC4 AT OPSCFU+4968 USING ADDRESS WTO/OPSWTO CROSS-SYSTEM	PTF
LU09073	SSMGAV2 RESOURCES INCORRECTLY DELETED FROM SSM TABLE	PTF
LU09173	ENFORCE OPSVASRV RULE RESTRICTIONS IN EXTERNAL SUBROUTINES	PTF
LU09259	OPSBCEPII SHUTDOWN DELAY IF INITIALIZATION COMMANDS NOT USED	PTF
The CA RS 2303 service count for this release is 9		

OPS/MVS
CA RS 2303 Service List for CCLXE00

2

FMID	Service	Description	Type
CCLXE00	LU08898	ABEND SOC4 USING ADDRESS AOF WITH MSF DEFAULT SYSTEM IN RULE	PTF
	LU09019	SSMGAV2 MOVEABLE RESOURCE NOT DELETED ON ORIGINATING SYSTEM	PTF
	LU09025	ACTMODE NOT WORKING FOR SSMGAV2 RESOURCE	PTF
	LU09064	SOC4 AT OPSCFU+4968 USING ADDRESS WTO/OPSWTO CROSS-SYSTEM	PTF
	LU09073	SSMGAV2 RESOURCES INCORRECTLY DELETED FROM SSM TABLE	PTF
	LU09173	ENFORCE OPSVASRV RULE RESTRICTIONS IN EXTERNAL SUBROUTINES	PTF
	LU09259	OPSBCEPII SHUTDOWN DELAY IF INITIALIZATION COMMANDS NOT USED	PTF
The CA RS 2303 service count for this FMID is 7			

OPS/MVS
CA RS 2303 Service List for CCLXE01

3

FMID	Service	Description	Type
CCLXE01	LU08784	MTC-A SSM GLOBAL EXCEPTION VIEW	PTF
	LU08960	SECURITY OR INTEGRITY PROBLEM	** PRP **
The CA RS 2303 service count for this FMID is 2			

OPS/MVS 14.0
CA RS 2303 - PTF LU08784 Details

4

Service	Details
LU08784	LU08784 M.C.S. ENTRIES = ++PTF (LU08784) REWORK(2023044) MTC-A SSM GLOBAL EXCEPTION VIEW ENHANCEMENT DESCRIPTION: This PTF introduces a new SSM Global Exception view for MTC-A. This new view allows users to easily see SSM resources where the CURRENT state does not equal the DESIRED state. Each OPS Instance connected to MTC-A that has SSM Resources in a mismatched state will be displayed in this new view. PRODUCT(S) AFFECTED: OPS/MVS Web Components Version 14.0 Related Problem: OPSMVS 19436 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00329-CLX140 DESC(MTC-A SSM GLOBAL EXCEPTION VIEW). ++VER (Z038) FMID (CCLXE01) PRE (LU00044 LU00122 LU00462 LU00633 LU01212 LU02570 LU03582 LU03791 LU03946 LU04002 LU04224 LU05148 LU05380 LU05432 LU05627 LU05691 LU06030 LU06134 LU06641 LU06786 LU07434 LU07986 LU08173 S014492 S014857 S015022 S015068 S015148 S015200 S015241 S015821 S015877) SUP (LT01162 LT04967 LT06018 LT06114 LT06121 LT06122 LT06123 LT06132 LT06868 LT07083 LT07392 LT07821 LT08784 ST14979) ++HOLD (LU08784) SYSTEM FMID(CCLXE01) REASON (DOC) DATE (23044) COMMENT (OPS/MVS Version 14.0 ***** * PUBLICATION * ***** See the "New Features" topic in the OPS/MVS documentation set at http://techdocs.broadcom.com/opsmvs) ++HOLD (LU08784) SYSTEM FMID(CCLXE01) REASON (DYNACT) DATE (23044) COMMENT (OPS/MVS Version 14.0 ***** SEQUENCE After APPLY ***** PURPOSE To deploy a new version of Mainframe Team Center - Automation ***** USERS All OPS/MVS MTC-A users AFFECTED ***** KNOWLEDGE Basic z/OS systems programming skills and knowledge of REQUIRED your new or existing MTC-A installation and configuration </

Service	Details
	<pre> +-----+-----+ ACCESS - Read/write access to the USS directories where your new REQUIRED or existing installation of MTC-A resides - Authority to STOP and START your MTC-A Web Application +-----+-----+ ***** * STEPS TO PERFORM * ***** Run The MTC-A Configuration Batch Job Sample JCL to execute the configuration script, mtcacfg.sh, is provided in yourHLQ.CCLXCNTL(OPMOIACG). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Set CCLXCLS0 to the fully qualified MVS dataset name of the SMP/E CLIST target library installed by FMID CCLXxr0 OPS/MVS Base. (eg. 'yourHLQ.CCLXCLS0') 3. Set CCLSHFSM to the USS mount point of the zFS installed by FMID CLXxr1 OPS/MVS OPSLOG WebView and Web Features. 4. Set TOMCATCONF to the USS path of your deployed Tomcat server's "context" directory. Typically: <catalina_base>/conf/Catalina/localhost 5. Set MTCADeploy to the USS path where you wish to deploy the MTCA Web App. A new directory called '/mtca' will be created on this path and will contain the mtcaApp.war as well as '/conf' and '/log' sub-directories. The configuration script creates the MTC-A directory structure at your chosen deployment location and defines the context for MTC-A to your Tomcat installation. If a previous MTC-A installation exists, your current configuration is saved as 'MTCADeploy/mtca/conf/config.yaml.YY_MM_DD_hh_mm_ss'. Your configuration is then automatically merged and upgraded to the version supplied within this PTF. Verify the STDOUT of the configuration batch job for messages indicating the addition of fields to the 'conf.yaml' that must be set specifically for your site before MTC-A is restarted. If your '/mtca' directory is on path 'a/b/c/mtca' supply path '/a/b/c' as your value for the deploy location). ++HOLD (LU08784) SYSTEM FMID(CCLXE01) REASON (ENH) DATE (23044) COMMENT (+-----+-----+ OPS/MVS Web Components Version 14.0 +-----+-----+ SEQUENCE After Apply +-----+-----+ PURPOSE To learn more about this enhancement +-----+-----+ USERS All MTC-A users AFFECTED +-----+-----+ KNOWLEDGE Knowledge of your MTC-A installation REQUIRED +-----+-----+ </pre>

Service	Details
	<pre> ACCESS Necessary MTC-A specific authorization REQUIRED +-----+-----+ +-----+-----+ ***** * STEPS TO PERFORM * ***** See the "New Features" topic in the OPS/MVS documentation set at http://techdocs.broadcom.com/opsmvs). LINK('..../conf.yaml') PARM(PATHMODE(0,7,5,5)). LINK('..../mtcacfg.sh') PARM(PATHMODE(0,7,5,5)). LINK('..../mtcaApp.war') PARM(PATHMODE(0,7,5,5)). </pre>

Service	Details		
LU08898	LU08898 M.C.S. ENTRIES = ++PTF (LU08898) REWORK(2023039) ABEND SOC4 USING ADDRESS AOF WITH MSF DEFAULT SYSTEM IN RULE PROBLEM DESCRIPTION: Using ADDRESS AOF with ADDRESS OPSCTL MSF DEFAULT SYSTEM(msfid) to a remote connected OPS/MVS from a NOWAIT rule causes an SOC4 abend in module OPSMMG. SYMPTOMS: The following message will be observed in OPSLOG after the rule completes: OPS3151H ABEND X'000C4000' IN MESSAGE QUEUE TAG CHECK OPSMMG+X'00003B1E' IMPACT: The ADDRESS AOF command may not complete on the remote system. CIRCUMVENTION: Use ADDRESS AOF with the SYSTEM keyword to send the AOF command. PRODUCT(S) AFFECTED: OPS/MVS Base Version 14.0 OPS/MVS Base Release 13.5 Related Problem: OPSMVS 19526 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00334-CLX140 DESC(ABEND SOC4 USING ADDRESS AOF WITH MSF DEFAULT SYSTEM IN RULE). ++VER (Z038) FMID (CCLXE00) PRE (LU03513 LU03790 LU05310 LU06695) SUP (LT08898) ++HOLD (LU08898) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (23039) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated.	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details
LU08960	LU08960 M.C.S. ENTRIES = ++PTF (LU08960) REWORK(2023033) SECURITY OR INTEGRITY PROBLEM PROBLEM DESCRIPTION: Security or Integrity Problem. For more details access Security Advisories using the following URL: support.broadcom.com/security-advisory/security-advisories-list.html Broadcom recommends that you subscribe to notifications for Security Advisories for the associated products that you support in your organization. Please use the following URL to register for proactive notifications: https://support.broadcom.com/user/notifications.html SYMPTOMS: N/A IMPACT: Security or Integrity Problem. CIRCUMVENTION: N/A PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 Related Problem: OPSMVS 19487 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00338-CLX140 DESC(SECURITY OR INTEGRITY PROBLEM). ++VER (Z038) FMID (CCLXE01) PRE (LU03791 LU03946 LU04002 LU05148 LU05943) SUP (AC08955 LT05617 LT08830 LT08960) ++HOLD (LU08960) SYSTEM FMID(CCLXE01) REASON (DYNACT) DATE (23033) COMMENT (<pre> +-----+ OPS/MVS Version 14.0 +-----+-----+ SEQUENCE After APPLY +-----+-----+ PURPOSE To activate a new version of ca-nim-sm.war +-----+-----+ USERS CA NIM-SM Users AFFECTED +-----+-----+ KNOWLEDGE Knowledge of your site's NIM SM deployment REQUIRED +-----+-----+ ACCESS Permissions to update the NIM SM deployment REQUIRED +-----+-----+ ***** * STEPS TO PERFORM * ***** FOR NIM SM ----- To redeploy your instance of NIM SM with the war file in this PTF, you </pre>

Service	Details
	will need to locate ca-nim-sm.war under your USS path name defined by SMP/E DDDEF CCLXHFSM (i.e. /opsmvs/directory/CCLXHFS). Place this war file in your target NIM SM USS directory and restart. For more information about deploying CA NIM SM, see CA Normalized Integration Management for Service Management at http://techdocs.broadcom.com). LINK('../ca-nim-sm.war') PARM(PATHMODE(0,7,5,5)).

Service	Details
LU09019	LU09019 M.C.S. ENTRIES = ++PTF (LU09019) REWORK(2023038) SSMGAV2 MOVEABLE RESOURCE NOT DELETED ON ORIGINATING SYSTEM PROBLEM DESCRIPTION: The INSERT SQLCODE may not be returned to the originating system if there is excess message traffic caused by subsequent ROUTE ALL commands. SYMPTOMS: The resource is moved to the new system but the GAV2104E move failed message is issued on the originating system. IMPACT: The resource is not deleted from the originating system. resulting in duplicate resources. CIRCUMVENTION: None PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 19618 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00340-CLX140 DESC(SSMGAV2 MOVEABLE RESOURCE NOT DELETED ON ORIGINATING SYSTEM) . ++VER (Z038) FMID (CCLXE00) PRE (LU03790) SUP (LT08939 LT09019 LU08939)

Service	Details
LU09025	LU09025 M.C.S. ENTRIES = ++PTF (LU09025) REWORK(2023038) ACTMODE NOT WORKING FOR SSMGAV2 RESOURCE PROBLEM DESCRIPTION: If an SSMGAV2 resource is moved to a new system while in a DOWN state, updating the ACTMODE on the new system does not execute an action. SYMPTOMS: Changes to the ACTMODE of the resource do not fire actions. IMPACT: Unable to control the resource by updating the ACTMODE. CIRCUMVENTION: Set the CURRENT_STATE to 'UNKNOWN' to execute the SSMSTATE rule. Once this is complete, updating the ACTMODE will work. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 19621 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00341-CLX140 DESC(ACTMODE NOT WORKING FOR SSMGAV2 RESOURCE). ++VER (Z038) FMID (CCLXE00) PRE (LU02478 LU03790 LU04889 LU08399) SUP (LT02080 LT09025 LU02080)

Service	Details																				
LU09064	LU09064 M.C.S. ENTRIES = ++PTF (LU09064) REWORK(2023046) SOC4 AT OPSCFU+4968 USING ADDRESS WTO/OPSWTO CROSS-SYSTEM PROBLEM DESCRIPTION: An ABEND SOC4 occurs in OPSCFU when a WTO is issued using the ADDRESS WTO OPS/REXX Host environment or the OPSWTO command processor with the following attributes: - The OSFSECURITY parameter is set to NOSECURITY. - The WTOID option is used without specifying a variable. - The request is a cross-system request using the SYSTEM keyword. SYMPTOMS: ABEND SOC4 at OPSCFU+00004968 IMPACT: The request is terminated. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 19586 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00342-CLX140 DESC(SOC4 AT OPSCFU+4968 USING ADDRESS WTO/OPSWTO CROSS-SYSTEM). ++VER (Z038) FMID (CCLXE00) PRE (LU03790 LU06695) SUP (LT09064) ++HOLD (LU09064) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (23046) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> <table border="1"> <tr> <td>SEQUENCE</td><td>After APPLY</td></tr> <tr> <td>PURPOSE</td><td>To activate load modules updated by this PTF</td></tr> <tr> <td>USERS</td><td>All OPS/MVS users</td></tr> <tr> <td>AFFECTED</td><td></td></tr> <tr> <td>KNOWLEDGE</td><td>Basic z/OS systems programming skills</td></tr> <tr> <td>REQUIRED</td><td></td></tr> <tr> <td>ACCESS</td><td>- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any deployed copies</td></tr> <tr> <td>REQUIRED</td><td>- Authority to issue MVS system commands</td></tr> <tr> <td></td><td>- Authority to stop and start OPS/MVS</td></tr> </table> ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the	OPS/MVS	Version 14.0	SEQUENCE	After APPLY	PURPOSE	To activate load modules updated by this PTF	USERS	All OPS/MVS users	AFFECTED		KNOWLEDGE	Basic z/OS systems programming skills	REQUIRED		ACCESS	- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any deployed copies	REQUIRED	- Authority to issue MVS system commands		- Authority to stop and start OPS/MVS
OPS/MVS	Version 14.0																				
SEQUENCE	After APPLY																				
PURPOSE	To activate load modules updated by this PTF																				
USERS	All OPS/MVS users																				
AFFECTED																					
KNOWLEDGE	Basic z/OS systems programming skills																				
REQUIRED																					
ACCESS	- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any deployed copies																				
REQUIRED	- Authority to issue MVS system commands																				
	- Authority to stop and start OPS/MVS																				

Service	Details
	specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details																		
LU09073	LU09073 M.C.S. ENTRIES = ++PTF (LU09073) REWORK(2023041) SSMGAV2 RESOURCES INCORRECTLY DELETED FROM SSM TABLE PROBLEM DESCRIPTION: A test to determine if an SSMGAV2 resource was moved (recovered) to another system while OPS/MVS was down, used the desired system value rather than the current system value. SYMPTOMS: SSMGAV2 moveable resources that failed a move request from the current system are deleted from the STCTBL after an IPL or cycle of OPS/MVS. IMPACT: SSMGAV2 moveable resources are deleted from the STCTBL. CIRCUMVENTION: Resolve all move failures before stopping OPS/MVS. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 19638 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00343-CLX140 DESC(SSMGAV2 RESOURCES INCORRECTLY DELETED FROM SSM TABLE). ++VER (Z038) FMID (CCLXE00) PRE (LU02161 LU02417 LU02478 LU03084 LU03790 LU04575 LU04889 LU08259 S015151 S015578) SUP (LT07189 LT09073 LU07189) ++HOLD (LU09073) SYSTEM FMID(CCLXE00) REASON (ACTION) DATE (23041) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> <tr> <td>SEQUENCE</td><td>After APPLY</td></tr> <tr> <td>PURPOSE</td><td>Reset ISPF statistics for updated AOF rule(s)</td></tr> <tr> <td>USERS</td><td>Users with AOF rules</td></tr> <tr> <td>AFFECTED</td><td></td></tr> <tr> <td>KNOWLEDGE</td><td>ISPF</td></tr> <tr> <td>REQUIRED</td><td></td></tr> <tr> <td>ACCESS</td><td>Product libraries</td></tr> <tr> <td>REQUIRED</td><td></td></tr> </table> ***** * STEPS TO PERFORM * ***** This PTF installs updated AOF rule(s) into SMP/E Target library CCLXRULM with no ISPF statistics. You will not be able to auto-enable the updated rule(s) until you reset their ISPF statistics. You can use ISPF option 3.5 to manually reset the ISPF statistics for the updated rule(s). You can use ISPF option 3.3 to manually copy the updated	OPS/MVS	Version 14.0	SEQUENCE	After APPLY	PURPOSE	Reset ISPF statistics for updated AOF rule(s)	USERS	Users with AOF rules	AFFECTED		KNOWLEDGE	ISPF	REQUIRED		ACCESS	Product libraries	REQUIRED	
OPS/MVS	Version 14.0																		
SEQUENCE	After APPLY																		
PURPOSE	Reset ISPF statistics for updated AOF rule(s)																		
USERS	Users with AOF rules																		
AFFECTED																			
KNOWLEDGE	ISPF																		
REQUIRED																			
ACCESS	Product libraries																		
REQUIRED																			

Service	Details
	rule(s) to your deployed ruleset(s) .).

Service	Details
LU09173	LU09173 M.C.S. ENTRIES = ++PTF (LU09173) REWORK(2023059) ENFORCE OPSVASRV RULE RESTRICTIONS IN EXTERNAL SUBROUTINES PROBLEM DESCRIPTION: The OPSVASRV OPS/REXX function is erroneously allowed to execute in an external subroutine that is called by an AOF rule type other than REQ, API or ARM. The OPSVASRV function can cause a wait condition and should not be allowed to execute within rule types other than REQ, API or ARM SYMPTOMS: The OPSVASRV function is successful when run in a rule type other than an REQ, API or ARM rule. IMPACT: The OPSVASRV function was running in an environment that should be restricted to commands that cannot cause a wait. CIRCUMVENTION: Run the OPSVASRV code in an OPSOSF server. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 19711 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00344-CLX140 DESC(ENFORCE OPSVASRV RULE RESTRICTIONS IN EXTERNAL SUBROUTINES). ++VER (Z038) FMID (CCLXE00) PRE (LU00715 LU03149 LU03790 LU05478 LU06695) SUP (BL06695 LT02046 LT03119 LT05064 LT07266 LT07317 LT09173 LU02046 LU03119 LU05064 LU07266 LU07317) ++HOLD (LU09173) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (23059) COMMENT (<pre> +-----+ OPS/MVS Version 14.0 +-----+-----+ SEQUENCE After APPLY +-----+-----+ PURPOSE To activate load modules updated by this PTF +-----+-----+ USERS All OPS/MVS users AFFECTED +-----+-----+ KNOWLEDGE Basic z/OS systems programming skills REQUIRED +-----+-----+ ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS +-----+-----+ ***** * STEPS TO PERFORM * ***** </pre>

Service	Details
	1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details																		
LU09259	LU09259 M.C.S. ENTRIES = ++PTF (LU09259) REWORK(2023054) OPSBBCPII SHUTDOWN DELAY IF INITIALIZATION COMMANDS NOT USED PROBLEM DESCRIPTION: If the OPSBCPII server does not use an initialization commands file at start-up, shutdown of the server is delayed significantly. (By default, member OPIICMDS the installed CCLXCNTL SMP/E target library is used as the initialization commands file.) SYMPTOMS: The following message appears in the OPSBCPII server joblog: OPSBBCPII CASV0174I MSG CASV0174I Waiting for active commands to terminate OPSBBCPII CASV0174I MSG CASV0174I Continuing to wait for active commands to terminate OPSBBCPII CASV0360E MSG CASV0360E Error on command: 'ATTACH PGM=OPIIDRV,,EXEC Parm=RESTAPI,,SERVER=OPSS' IMPACT: Significant OPSBCPII server shutdown delays. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 19781 (C) 2023 Broadcom Inc and/or its subsidiaries; All rights reserved R00345-CLX140 DESC(OPSBCPII SHUTDOWN DELAY IF INITIALIZATION COMMANDS NOT USED). ++VER (Z038) FMID (CCLXE00) PRE (LU00028 LU01116 LU02313 LU03137 LU03334 LU03790 LU04106) SUP (LT09259) ++HOLD (LU09259) SYSTEM FMID(CCLXE00) REASON (ACTION) DATE (23054) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> <tr> <td>SEQUENCE</td><td>After applying the PTF and before starting the OPSBCPII Server.</td></tr> <tr> <td>PURPOSE</td><td>To address OPSBCPII shutdown delays.</td></tr> <tr> <td>USERS</td><td>All users of the OPSBCPII Server not using the OPSIICMDS</td></tr> <tr> <td>AFFECTED</td><td>member to issue initialization commands at startup.</td></tr> <tr> <td>KNOWLEDGE</td><td>Basic z/OS system programming skills.</td></tr> <tr> <td>REQUIRED</td><td></td></tr> <tr> <td>ACCESS</td><td>Authority to stop and start OPS/MVS.</td></tr> <tr> <td>REQUIRED</td><td></td></tr> </table> ***** * STEPS TO PERFORM * *****	OPS/MVS	Version 14.0	SEQUENCE	After applying the PTF and before starting the OPSBCPII Server.	PURPOSE	To address OPSBCPII shutdown delays.	USERS	All users of the OPSBCPII Server not using the OPSIICMDS	AFFECTED	member to issue initialization commands at startup.	KNOWLEDGE	Basic z/OS system programming skills.	REQUIRED		ACCESS	Authority to stop and start OPS/MVS.	REQUIRED	
OPS/MVS	Version 14.0																		
SEQUENCE	After applying the PTF and before starting the OPSBCPII Server.																		
PURPOSE	To address OPSBCPII shutdown delays.																		
USERS	All users of the OPSBCPII Server not using the OPSIICMDS																		
AFFECTED	member to issue initialization commands at startup.																		
KNOWLEDGE	Basic z/OS system programming skills.																		
REQUIRED																			
ACCESS	Authority to stop and start OPS/MVS.																		
REQUIRED																			

Service	Details	
	1. After applying the PTF, restart the OPSBCPII Server by issuing the following command: "F OPSx,RESTART(HWS)" where OPSx is the OPS/MVS subsystem id.	
	).	
MCS	LU08784	STARTS ON PAGE 0002
MCS	LU08898	STARTS ON PAGE 0004
MCS	LU08960	STARTS ON PAGE 0006
MCS	LU09019	STARTS ON PAGE 0008
MCS	LU09025	STARTS ON PAGE 0008
MCS	LU09064	STARTS ON PAGE 0009
MCS	LU09073	STARTS ON PAGE 0011
MCS	LU09173	STARTS ON PAGE 0012
MCS	LU09259	STARTS ON PAGE 0014

OPS/MVS 14.0
CA RS 2303 Product/Component Listing

21

Product Family	Product	Release
Automation	CA OPS/MVS BASE	14.00.00
The CA RS 2303 Product/Component Count for this release is 1		

OPS/MVS 14.0
All CA RS Levels Service List

CA RS Level	Service	FMID
CAR2303	LU09259	CCLXE00
	LU09173	CCLXE00
	LU09073	CCLXE00
	LU09064	CCLXE00
	LU09025	CCLXE00
	LU09019	CCLXE00
	LU08960	CCLXE01
	LU08898	CCLXE00
	LU08784	CCLXE01
	LU08939	CCLXE00
	LU08919	CCLXE00
CAR2302	LU08857	CCLXE00
	LU08802	CCLXE01
	LU08792	CCLXE00
	LU08782	CCLXE00
	LU08742	CCLXE01
	LU08709	CCLXE00
	LU08706	CCLXE00
	LU08668	CCLXE01
	LU08651	CCLXE00
	LU08512	CCLXE00
	LU08223	CCLXE00
CAR2301	LU08561	CCLXE00
	LU08541	CCLXE00
	LU08501	CCLXE00
	LU08482	CCLXE00
	LU08436	CCLXE00
	LU08399	CCLXE00
	LU08377	CCLXE00
	LU08374	CCLXE00
	LU08344	CCLXE01
CAR2212	LU08339	CCLXE00
	LU08259	CCLXE00
	LU08226	CCLXE00
	LU08173	CCLXE01
	LU07986	CCLXE01
	LU07985	CCLXE00
	LU07640	CCLXE00
	LU07332	CCLXE00
CAR2211	LU07647	CCLXE00
	LU07464	CCLXE00
CAR2210	LU07472	CCLXE01
	LU07434	CCLXE01
	LU07425	CCLXE00
	LU07322	CCLXE00
	LU07317	CCLXE00
	LU07266	CCLXE00

CA RS Level	Service	FMID
	LU07240	CCLXE01
	LU07189	CCLXE00
	LU07158	CCLXE00
	LU07066	CCLXE00
	LU06983	CCLXE00
CAR2209	LU07052	CCLXE01
	LU07051	CCLXE00
	LU06929	CCLXE00
	LU06926	CCLXE01
	LU06925	CCLXE00
	LU06878	CCLXE00
	LU06871	CCLXE00
	LU06802	CCLXE01
	LU06786	CCLXE01
	LU06695	CCLXE00
CAR2208	LU06678	CCLXE00
	LU06642	CCLXE00
	LU06641	CCLXE01
	LU06626	CCLXE00
	LU06533	CCLXE00
	LU06529	CCLXE00
	LU06522	CCLXE00
	LU06513	CCLXE00
	LU06468	CCLXE00
	LU05310	CCLXE00
CAR2207	LU06343	CCLXE01
	LU06342	CCLXE00
	LU06262	CCLXE00
	LU06179	CCLXE01
	LU06134	CCLXE01
	LU06133	CCLXE00
	LU05921	CCLXE00
CAR2206	LU06069	CCLXE00
	LU06030	CCLXE01
	LU05943	CCLXE01
	LU05807	CCLXE00
	LU05737	CCLXE00
	LU05612	CCLXE00
	LU05478	CCLXE00
CAR2205	LU05691	CCLXE01
	LU05627	CCLXE01
	LU05517	CCLXE00
	LU05432	CCLXE01
	LU05380	CCLXE01
	LU05358	CCLXE00
CAR2204	LU05306	CCLXE00
	LU05297	CCLXE00

OPS/MVS 14.0
All CA RS Levels Service List

CA RS Level	Service	FMID
	LU05260	CCLXE00
	LU05234	CCLXE00
	LU05216	CCLXE00
	LU05215	CCLXE01
	LU05214	CCLXE00
	LU05148	CCLXE01
	LU05096	CCLXE00
	LU05064	CCLXE00
	LU05045	CCLXE00
	LU05016	CCLXE00
	LU05009	CCLXE00
	LU04902	CCLXE00
	LU04793	CCLXE00
CAR2203	LU04913	CCLXE00
	LU04889	CCLXE00
	LU04888	CCLXE00
	LU04768	CCLXE00
	LU04738	CCLXE00
	LU04575	CCLXE00
	LU04473	CCLXE00
	LU03819	CCLXE00
CAR2202	LU04341	CCLXE00
	LU04292	CCLXE00
	LU04224	CCLXE01
	LU04194	CCLXE00
	LU04184	CCLXE00
	LU04168	CCLXE00
	LU04163	CCLXE00
	LU04106	CCLXE00
	LU03744	CCLXE00
	LU03513	CCLXE00
CAR2201	LU04002	CCLXE01
	LU03946	CCLXE01
	LU03884	CCLXE01
	LU03852	CCLXE00
	LU03792	CCLXE03
	LU03791	CCLXE01
	LU03790	CCLXE00
	LU03721	CCLXE00
	LU03582	CCLXE01
CAR2112	LU03548	CCLXE00
	LU03512	CCLXE03
	LU03481	CCLXE00
	LU03418	CCLXE00
	LU03387	CCLXE00
	LU03373	CCLXE01
	LU03334	CCLXE00

CA RS Level	Service	FMID
	LU03258	CCLXE00
CAR2111	LU03303	CCLXE00
	LU03179	CCLXE00
	LU03165	CCLXE01
	LU03149	CCLXE00
	LU03137	CCLXE00
	LU03119	CCLXE00
	LU03099	CCLXE00
	LU03084	CCLXE00
	LU03082	CCLXE00
	LU03072	CCLXE00
	LU03049	CCLXE00
	LU03011	CCLXE00
CAR2110	LU02790	CCLXE00
	LU02570	CCLXE01
	LU02514	CCLXE00
	LU02484	CCLXE00
	LU02253	CCLXE01
	LU02252	CCLXE00
CAR2109	LU02562	CCLXE00
	LU02545	CCLXE00
	LU02521	CCLXE00
	LU02515	CCLXE00
	LU02478	CCLXE00
	LU02417	CCLXE00
	LU02313	CCLXE00
	LU02285	CCLXE00
	LU02105	CCLXE00
CAR2108	LU02209	CCLXE00
	LU02161	CCLXE00
	LU02080	CCLXE00
	LU02046	CCLXE00
	LU02021	CCLXE00
	LU01967	CCLXE00
CAR2107	LU01929	CCLXE00
	LU01862	CCLXE00
	LU01797	CCLXE00
	LU01655	CCLXE00
	LU01630	CCLXE00
	LU01562	CCLXE01
	LU01212	CCLXE01
	LU01211	CCLXE00
	LU01140	CCLXE01
CAR2106	LU01398	CCLXE00
	LU01310	CCLXE00
	LU01080	CCLXE00
	LU00913	CCLXE00

CA RS Level	Service	FMID
CAR2105	LU01117	CCLXE00
	LU01116	CCLXE00
	LU00998	CCLXE00
	LU00876	CCLXE00
	LU00741	CCLXE00
	LU00717	CCLXE00
	LU00679	CCLXE00
CAR2104	LU00716	CCLXE01
	LU00715	CCLXE00
	LU00677	CCLXE00
	LU00634	CCLXE00
	LU00633	CCLXE01
	LU00632	CCLXE00
	LU00610	CCLXE00
	LU00496	CCLXE00
	LU00477	CCLXE00
	LU00462	CCLXE01
	LU00442	CCLXE00
	LU00407	CCLXE00
	LU00361	CCLXE00
	LU00235	CCLXE00
CAR2103	LU00278	CCLXE00
	LU00210	CCLXE00
	LU00188	CCLXE00
	LU00122	CCLXE01
	LU00121	CCLXE00
CAR2102	S015877	CCLXE01
	S015876	CCLXE00
	LU00117	CCLXE00
	LU00113	CCLXE00
	LU00078	CCLXE00
	LU00077	CCLXE00
	LU00074	CCLXE00
	LU00067	CCLXE00
	LU00063	CCLXE00
	LU00060	CCLXE00
	LU00058	CCLXE00
	LU00057	CCLXE00
	LU00044	CCLXE01
	LU00040	CCLXE00
CAR2101	S015920	CCLXE00
	S015902	CCLXE00
	S015821	CCLXE01
	S015820	CCLXE00
	S015729	CCLXE00
	LU00028	CCLXE00
	LU00025	CCLXE00

OPS/MVS 14.0
All CA RS Levels Service List

CA RS Level	Service	FMID
CAR2012	S015758	CCLXE00
	S015662	CCLXE00
	S015610	CCLXE00
	S015578	CCLXE00
	S015569	CCLXE00
	S015565	CCLXE00
	S015526	CCLXE00
	S015515	CCLXE00
	S015505	CCLXE00
	S015502	CCLXE00
	S015497	CCLXE00
CAR2011	S015373	CCLXE00
	S015324	CCLXE00
	S015241	CCLXE01
	S015200	CCLXE01
	S015151	CCLXE00
	S015148	CCLXE01
	S015069	CCLXE00
	S015068	CCLXE01
	S015067	CCLXE00
	S014750	CCLXE00
CAR2010	S015022	CCLXE01
	S015018	CCLXE00
	S014993	CCLXE00
	S014932	CCLXE00
	S014903	CCLXE00
	S014875	CCLXE00
	S014871	CCLXE00
	S014857	CCLXE01
	S014824	CCLXE00
	S014801	CCLXE00
	S014646	CCLXE00
	S014644	CCLXE00
	S014609	CCLXE00
CAR2009	S014537	CCLXE00
	S014492	CCLXE01
	S014477	CCLXE00
	S014434	CCLXE01
	S014412	CCLXE00