

CA 1 Tape Management 14.0
CA RS 2005 Service List

Service	Description	Type
S011630	TMSHC012 CA 1_FREE_DSNB_QUICK_SCAN FALSE ALERT	PTF
S012305	FORCE WRKFLS=NO PROCESSING FOR VIRTUAL/LOGICAL WORM VOLUMES	PTF
S012316	Security or Integrity Problem	** PRP **
S012740	BYTES USED AND COMPRESSION RATIO NOT CORRECT	PTF
The CA RS 2005 service count for this release is 4		

CA 1 Tape Management
CA RS 2005 Service List for CAL0E00

2

FMID	Service	Description	Type
CAL0E00	SO11630	TMSHC012 CA 1_FREE_DSNB_QUICK_SCAN FALSE ALERT	PTF
	SO12305	FORCE WRKFLS=NO PROCESSING FOR VIRTUAL/LOGICAL WORM VOLUMES	PTF
The CA RS 2005 service count for this FMID is 2			

CA 1 Tape Management
CA RS 2005 Service List for CBAFE00

FMID	Service	Description	Type
CBAFE00	S012316	Security or Integrity Problem	** PRP **
	S012740	BYTES USED AND COMPRESSION RATIO NOT CORRECT	PTF
The CA RS 2005 service count for this FMID is 2			

Service	Details
SO11630	<p>SO11630 M.C.S. ENTRIES = ++PTF (SO11630)</p> <p>TMSHC012 CA 1_FREE_DSNB_QUICK_SCAN FALSE ALERT</p> <p>PROBLEM DESCRIPTION:</p> <p>Both the USED DSNBS IN FREECHAIN and DSNB QUICK SCAN Health Checks may give an erroneous error stating that a USED DSNB was found in the DSNB Free Chain.</p> <p>Additionally, the USED DSNBS IN FREECHAIN Health Check may loop if a unused DSNB in the FREECHAIN points to a previous unused DSNB in the FreeCHAIN.</p> <p>SYMPTOMS:</p> <p>The DSNB Quick Scan Health Check and USED DSNBS IN FREECHAIN may issue a false positive messages.</p> <p>The USED DSNBS IN THE FREECHAIN Health Check does not end.</p> <p>IMPACT:</p> <p>Low</p> <p>CIRCUMVENTION:</p> <p>None. For the loop, the Health Check will need to be interrupted.</p> <p>Using SDSF, place an 'H' beside the running Health Check.</p> <p>PRODUCT(S) AFFECTED:</p> <p>CA 1 Tape Management Version 14.0</p> <p>Related Problem:</p> <p>1 2327</p> <p>Copyright (C) 2020 CA. All rights reserved. R00139-AL0140-SP1</p> <p>DESC(TMSHC012 CA 1_FREE_DSNB_QUICK_SCAN FALSE ALERT).</p> <p>++VER (Z038)</p> <p>FMID (CAL0E00)</p> <p>PRE (R086720 S007488)</p> <p>SUP (ST11630)</p> <p>++HOLD (SO11630) SYSTEM FMID(CAL0E00)</p> <p>REASON (ACTION) DATE (20086)</p> <p>COMMENT (</p> <pre> +-----+ CA 1 Tape Management Version 14.0 +-----+-----+ SEQUENCE After Apply +-----+-----+ PURPOSE To activate the change without an IPL. +-----+-----+ USERS All users AFFECTED +-----+-----+ KNOWLEDGE How to issue commands (directly, through SDSF or REQUIRED through CA Sysview) +-----+-----+ ACCESS Ability to issue modify commands to the CAHC REQUIRED space +-----+-----+ ***** * STEPS TO PERFORM * ***** In order for this APAR to take effect, issue the following command; F CAHC,DISPLAY TASKS </pre>

Service	Details
	<p>A CA_1 task will be displayed as OWNERxxx where xxx is a number. Issue the following command with the correct number to delete the task:</p> <pre>F CAHC,DELETE OWNERxxx</pre> <p>This will delete all the CA_1 Health Checks. Now run TMSINIT to restart all the CA_1 Health Checks to pick up the updated CA1_used_DSNB_free_chain and CA1_Free_DSNB_Quick_Scan Healthchecks.).</p>

Service	Details
SO12305	<p>SO12305 M.C.S. ENTRIES = ++PTF (SO12305)</p> <p>FORCE WRKFLS=NO PROCESSING FOR VIRTUAL/LOGICAL WORM VOLUMES</p> <p>PROBLEM DESCRIPTION:</p> <p>When logical WORM tapes are scratched the worm fields will be reset by TMSCLEAN. If a logical WORM tape is created as a work tape with WRKFLS YES and then CTSSYNC is used to scratch the tape that is in the library, the worm flag is still on, which causes IECTMS3 NOT SCRATCH (70) if the tape is reused as scratch. With this solution applied, those volumes will be assigned a 1 day retention which will require that it be scratched by CA 1 the WORM fields will be reset.</p> <p>SYMPTOMS:</p> <p>Tape mounts may receive IECTMS3 NOT SCRATCH (70) messages. As well as S613-40 abends for tapes that had been synchronized with CTSSYNC.</p> <p>IMPACT:</p> <p>Job abends when volumes were mounted that had been created using a temporary dataset and WRKFLS=YES.</p> <p>CIRCUMVENTION:</p> <p>Set WRKFLS=NO in the TMOOPTxx member of CTAPOPTN. This will eliminate any work files from being created.</p> <p>PRODUCT(S) AFFECTED:</p> <p>CA 1 Tape Management Version 14.0</p> <p>Related Problem:</p> <p>1 2339</p> <p>Copyright (C) 2020 CA. All rights reserved. R00143-AL0140-SP1</p> <p>DESC(FORCE WRKFLS=NO PROCESSING FOR VIRTUAL/LOGICAL WORM VOLUMES).</p> <p>++VER (Z038)</p> <p>FMID (CAL0E00)</p> <p>PRE (R086720 R095361 S007538)</p> <p>SUP (ST12305)</p> <p>++HOLD (SO12305) SYSTEM FMID(CAL0E00)</p> <p>REASON (DYNACT) DATE (20086)</p> <p>COMMENT (</p> <pre> +-----+ CA 1 Tape Management Version 14.0 +-----+-----+ SEQUENCE AFTER APPLY +-----+-----+ PURPOSE TO ACTIVATE THE CHANGE WITHOUT AN IPL. +-----+-----+ USERS ALL USERS. AFFECTED +-----+-----+ KNOWLEDGE HOW TO MODIFY AND SUBMIT THE CAIRIM PROCESS. REQUIRED +-----+-----+ ACCESS ABILITY TO SUBMIT CAIRIM WITH THE MODIFIED CONTROL REQUIRED STATEMENTS. +-----+-----+ ***** * STEPS TO PERFORM * ***** MODIFY THE CAIRIM CONTROL STATEMENTS AS FOLLOWS WHERE SVC=XXX IS </pre>

CA 1 Tape Management 14.0
CA RS 2005 - PTF SO12305 Details

7

Service	Details
	REPLACED WITH THE CA 1 SVC NUMBER USED ON YOUR SYSTEM. PRODUCT(CA-1/MVS) VERSION(LOEO) INIT(LOEOINIT) - PARM(REINIT,LPA=TMS00SVC,SVC=XXX) LOADLIB(YOUR 14.0 CTAPLINK)) .

Service	Details
SO12316	<p>SO12316 M.C.S. ENTRIES = ++PTF (SO12316)</p> <p>Security or Integrity Problem</p> <p>PROBLEM DESCRIPTION:</p> <p>Security or Integrity Problem.</p> <p>SYMPTOMS.</p> <p>N/A</p> <p>IMPACT.</p> <p>Security or Integrity Problem.</p> <p>CIRCUMVENTION:</p> <p>N/A</p> <p>PRODUCT(S) AFFECTED:</p> <p>CA COMMON TAPE FUNCTIONS Version 14.0</p> <p>Related Problem:</p> <p>CM-\$F 312</p> <p>Copyright (C) 2020 CA. All rights reserved. R00053-BAF140-SP1</p> <p>DESC(Security or Integrity Problem).</p> <p>++VER (Z038)</p> <p>FMID (CBAFE00)</p> <p>PRE (R094755)</p> <p>SUP (AC12678 R089925 R097628 S007340 ST07062 ST07340</p> <p>ST12316 TR89925 TR97628)</p> <p>++HOLD (SO12316) SYSTEM FMID(CBAFE00)</p> <p>REASON (DYNACT) DATE (20097)</p> <p>COMMENT (</p> <pre> +-----+ CA COMMON TAPE FUNCTIONS Version 14.0 +-----+-----+ SEQUENCE AFTER APPLY +-----+-----+ PURPOSE TO ACTIVATE THE CHANGE WITHOUT AN IPL. +-----+-----+ USERS ALL USERS. AFFECTED +-----+-----+ KNOWLEDGE HOW TO MODIFY AND SUBMIT THE CAIRIM PROCESS. REQUIRED +-----+-----+ ACCESS ABILITY TO SUBMIT CAIRIM WITH THE MODIFIED CONTROL REQUIRED STATEMENTS. +-----+-----+ ***** * STEPS TO PERFORM * ***** THESE INSTRUCTIONS ONLY PERTAIN TO CA 1 CLIENTS AND NOTHING NEEDS TO BE DONE FOR CA TLMS CLIENTS. THE FOLLOWING INSTRUCTIONS FOR CA 1 CLIENTS ONLY APPLIES IF THE CA 1 CATALOG INTERCEPT OF IGG026DU IS THE LAST DYNAMIC INTERCEPT OF THIS EXIT. THE IGG026DU EXIT IS A CSECT IN THE IGC0002F LOAD MODULE. IF THERE ARE OTHER PRODUCTS THAT ALSO DYNAMICALLY INTERCEPT IGG026DU IN IGC0002F, THEY MUST BE REMOVED IN A LIFO (LAST-IN, FIRST-OUT) ORDER PRIOR TO THE FOLLOWING CONTROL STATEMENTS BEING USED. IF YOU ARE UN-SURE IF THERE ARE OTHER PRODUCTS THAT INTERCEPT </pre>

CA 1 Tape Management 14.0
CA RS 2005 - PTF SO12316 Details

Service	Details
	<p>THE IGG026DU EXIT POINT, THEN IT MIGHT BE BEST TO WAIT FOR AN IPL TO ACTIVATE THIS PTF.</p> <p>MODIFY THE CAIRIM CONTROL STATEMENTS AS FOLLOWS; PARM(REINIT,COSI=YES) LOADLIB(HLQ.CTAPLINK)) .</p>

Service	Details
SO12740	<p>SO12740 M.C.S. ENTRIES = ++PTF (SO12740)</p> <p>BYTES USED AND COMPRESSION RATIO NOT CORRECT</p> <p>PROBLEM DESCRIPTION:</p> <p>If an IBM VTS is being used with the new LZ4/ZSTD compression and the virtual volumes are defined with a 25Gb capacity, the bytes-written value may cause the Read-Buffered-Log to overflow.</p> <p>Also, if the obtain compression ratio is something like 99.7% or 99.8% the compression ratio is rounded up to 100% producing invalid results when reports are generated or the data is viewed through Vantage.</p> <p>SYMPTOMS:</p> <p>The Byte-Percentage value and the compression-ratio will be reported as zero even though they should both be non-zero.</p> <p>If the file is highly compressable, a compression ratio of 100% may be reported that makes generated reports in-correct.</p> <p>IMPACT:</p> <p>Correct reporting of the number of bytes written by the application and the correct reporting of the number of bytes stored in cache are not correct.</p> <p>Incorrect reporting of tape usage.</p> <p>CIRCUMVENTION:</p> <p>Define the virtual-volumes as 8Gb capacity until the CA solution, an IBM micro-code solution to the TS77xx and a z/OS solution have all been applied.</p> <p>PRODUCT(S) AFFECTED:</p> <p>CA COMMON TAPE FUNCTIONS Version 14.0</p> <p>Related Problem:</p> <p>CM-\$F 313</p> <p>Copyright (C) 2020 CA. All rights reserved. R00056-BAF140-SP1</p> <p>DESC(BYTES USED AND COMPRESSION RATIO NOT CORRECT) .</p> <p>++VER (Z038)</p> <p>FMID (CBAFE00)</p> <p>PRE (R086715 R093331)</p> <p>SUP (R089926 R094583 R098211 S006907 S007989 ST06907</p> <p>ST07989 ST12479 ST12740 TR89926 TR94583 TR98211)</p> <p>++HOLD (SO12740) SYSTEM FMID(CBAFE00)</p> <p>REASON (DOC) DATE (20105)</p> <p>COMMENT (</p> <p>+-----+</p> <p> CA COMMON TAPE FUNCTIONS Version 14.0 </p> <p>+-----+</p> <p>*****</p> <p>* PUBLICATION *</p> <p>*****</p> <p>A new error message has been added - CTSOCE05</p> <p>CTSOCE05 - 4KDBW is non-zero, 4KCBW is zero</p> <p>Reason:</p> <p>The UCBCX_ATT3490_4KDBW field in the UCB Tape Extension is non-zero but the UCBCX_ATT3490_4KCBW field is zero.</p> <p>Action:</p> <p>This message indicates that 2 fields that should always be zero or non-zero together are not "in sync" with each other. Please verify that IBM APAR OA52915 has been applied to all LPAR's sharing the TS77xx VTS Library.</p> <p>) .</p>

Service	Details	
	<pre> ++HOLD (S012740) SYSTEM FMID(CBAFE00) REASON (DYNACT) DATE (20105) COMMENT (+-----+ CA COMMON TAPE FUNCTIONS Version 14.0 +-----+ SEQUENCE AFTER APPLY +-----+ PURPOSE TO ACTIVATE THE CHANGE WITHOUT AN IPL. +-----+ USERS ALL USERS. AFFECTED +-----+ KNOWLEDGE HOW TO MODIFY AND SUBMIT THE CAIRIM PROCESS. REQUIRED +-----+ ACCESS ABILITY TO SUBMIT CAIRIM WITH THE MODIFIED CONTROL REQUIRED STATEMENTS. +-----+ ***** * STEPS TO PERFORM * ***** THESE INSTRUCTIONS PERTAIN TO CA 1 AND CA TLMS CLIENTS FOR CA 1 CLIENTS - MODIFY THE CAIRIM CONTROL STATEMENTS AS FOLLOWS; PRODUCT(CA-1/MVS) VERSION(LOE0) INIT(LOE0INIT) - PARM(REINIT,LPA=CTSOCE00) LOADLIB(YOUR 14.0 CTAPLINK) FOR CA TLMS CLIENTS - MODIFY THE CAIRIM STATEMENTS AS FOLLOWS; PRODUCT(CA-TLMS/MVS) VERSION(TLE0) INIT(TLE0INIT) - PARM(REINIT,LPA=CTSOCE00) LOADLIB(YOUR 14.0 CTAPLINK)). MCS S011630 STARTS ON PAGE 0002 MCS S012305 STARTS ON PAGE 0003 MCS S012316 STARTS ON PAGE 0005 MCS S012740 STARTS ON PAGE 0006 </pre>	

CA 1 Tape Management 14.0
CA RS 2005 Product/Component Listing

12

Product Family	Product	Release
Storage	CA COMMON TAPE FUNCTIONS	14.00.00
	CA OSI/COMMON COMPONENT	14.00.00
	CA 1 TAPE MANAGEMENT	14.00.00
The CA RS 2005 Product/Component Count for this release is 3		

CA RS Level	Service	FMID
CAR2005	S012740	CBAFE00
	S012316	CBAFE00
	S012305	CAL0E00
	S011630	CAL0E00
CAR2004	S012517	CAL0E00
CAR2003	S011804	CAL0E00
	S011771	CBAFE00
	S011703	CAL0E00
	S011511	CAL0E00
CAR2002	S010887	CAL0E00
	S010632	CAL0E00
	S010333	CAL0E00
CAR2001	S011264	CAL0E00
	S010814	CAL0E00
	S009946	CAL0E00
	S009456	CAL0E00
CAR1912	S010297	CAL0E00
	S009659	CAL0E00
CAR1911	S010518	CAL0E00
	S010147	CAL0E00
CAR1910	S009988	CBAFE00
	S009350	CBAFE00
	S009154	CAL0E00
	S008504	CBAFE00
CAR1908	S009194	CAL0E00
	S009176	CAL0E00
	S008253	CAL0E00
CAR1907	S008332	CAL0E00
	S008267	CAL0E00
	S007488	CAL0E00
	S007340	CBAFE00
CAR1906	S008118	CAL0E00
	S008095	CAL0E00
	S007989	CBAFE00
	S007783	CAL0E00
	S007609	CAL0E00
CAR1905	S007914	CBAFE00
	S007538	CAL0E00
CAR1904	S007375	CAL0E00
CAR1903	S006753	CAL0E00
	S006049	CAL0E00
	R090435	CAL0E00
CAR1902	S007077	CBAFE00
	S006907	CBAFE00
	S006489	CAL0E00
CAR1901	S006465	CBAFE00
	S006408	CAL0E00

CA RS Level	Service	FMID
CAR1811	S005393	CAL0E00
CAR1810	S005132	CAL0E00
	S005090	CAL0E00
	S001325	CBAFE00
CAR1809	S004566	CBAFE00
	S003737	CBAFE00
	S001864	CAL0E00
CAR1808	S004014	CAL0E00
	S003575	CAL0E00
	S000102	CAL0E00
CAR1807	S003703	CAL0E00
CAR1805	S000771	CAL0E00
CAR1804	S001019	CAL0E00
	S000375	CBAFE00
	R099657	CAL0E00
CAR1803	S000376	CBAFE00
	R098235	CAL0E00
CAR1802	R098044	CAL0E00
	R097589	CAL0E00
CAR1801	R098719	CAL0E00
	R097628	CBAFE00
	R097141	CAL0E00
CAR1712	R098735	CAL0E00
	R098491	CAG8E00
	R098398	CAL0E00
	R098211	CBAFE00
	R097676	CAL0E00
CAR1711	R098303	CAL0E00
	R098301	CAL0E00
	R097930	CAL0E00
	R097124	CAL0E00
	R096957	CAL0E00
CAR1710	R097352	CAL0E00
	R097172	CAL0E00
	R096979	CAL0E00
	R096826	CAL0E00
CAR1709	R096641	CAL0E00
	R096031	CBAFE00
	R094642	CAL0E00
	R094173	CAG8E00
CAR1708	R096858	CAL0E00
	R096268	CAL0E00
	R096101	CAL0E00
	R095361	CAL0E00
CAR1707	R096603	CAL0E00
	R095649	CAL0E00
	R094615	CAL0E00

CA RS Level	Service	FMID
	R094583	CBAFE00
CAR1706	R095275	CAL0E00
	R095272	CAL0E00
CAR1704	R094755	CBAFE00
	R094667	CAL0E00
CAR1703	R094451	CAL0E00
	R094379	CAL0E00
	R094258	CBAFE00
	R093860	CAL0E00
CAR1702	R093819	CAL0E00
	R086715	CBAFE00
	R083248	CBAFE00
CAR1701	R093682	CAL0E00
	R093432	CAL0E00
	R093392	CAL0E00
	R093331	CBAFE00
	R093264	CAL0E00
	R093190	CBAFE00
	R093128	CAL0E00
	R092538	CAL0E00
	R092030	CAL0E00
	R091646	CAL0E00
CAR1612	R092223	CAL0E00
	R091897	CAL0E00
	R091750	CAL0E00
CAR1610	R091971	CBAFE00
	R091847	CBAFE00
	R091846	CAL0E00
	R091479	CAL0E00
	R091460	CAL0E00
	R091301	CBAFE00
	R091217	CAL0E00
CAR1609	R090987	CBAFE00
	R090945	CBAFE00
	R089926	CBAFE00
	R089758	CAL0E00
CAR1608	R091200	CAL0E00
CAR1607	R090243	CBAFE00
CAR1606	R089925	CBAFE00
	R089876	CAL0E00
	R089572	CAL0E00
CAR1605	R089616	CAL0E00
	R089533	CBAFE00
	R089514	CAL0E00
	R089319	CAL0E00
	R089262	CAL0E00
	R088724	CAL0E00

CA RS Level	Service	FMID
	R088419	CAL0E00
CAR1604	R087942	CBAFE00
CAR1603	R088098	CAL0E00
	R088088	CAL0E00
	R087844	CBAFE00