

CA OPS/MVS for JES2 13.0
CA RS 2005 Service List

1

Service	Description	Type
S012493	OSF SERVER HANGS WHEN ISSUING IMS COMMANDS VIA THE IMS BMP	PTF
S012596	OPS3724T WTO MAY CONTAIN ZERO'S FOR PROGRAM NAME	PTF
S012626	OPSJES2 INPQ FUNCTION RETURNS 0 JOBS FOR Z/OS 2.4	PTF
S012660	POSSIBLE ABEND SOC4 AFTER INSTALLING IBM PTF UJ01558	PTF
S012671	PASSWORD MASKING IGNORED FOR SECURITY EVENT	PTF
S012827	OPSJES2 NOT DISPLAYING REMOTE PRINTERS	PTF
The CA RS 2005 service count for this release is 6		

CA OPS/MVS for JES2
CA RS 2005 Service List for CCLXD00

2

FMID	Service	Description	Type
CCLXD00	S012493	OSF SERVER HANGS WHEN ISSUING IMS COMMANDS VIA THE IMS BMP	PTF
	S012596	OPS3724T WTO MAY CONTAIN ZERO'S FOR PROGRAM NAME	PTF
	S012626	OPSJES2 INPQ FUNCTION RETURNS 0 JOBS FOR Z/OS 2.4	PTF
	S012660	POSSIBLE ABEND SOC4 AFTER INSTALLING IBM PTF UJ01558	PTF
	S012671	PASSWORD MASKING IGNORED FOR SECURITY EVENT	PTF
	S012827	OPSJES2 NOT DISPLAYING REMOTE PRINTERS	PTF
The CA RS 2005 service count for this FMID is 6			

Service	Details
SO12493	SO12493 M.C.S. ENTRIES = ++PTF (SO12493) OSF SERVER HANGS WHEN ISSUING IMS COMMANDS VIA THE IMS BMP PROBLEM DESCRIPTION: When an IMS command is sent to the OPS/MVS IMS BMP, and the response exceeds the maximum number of lines specified by OPS/MVS parameter REXXMAXQUEUE, OPS13520 message is issued indicating the following: OPS13520 MESSAGE SEND OVERFLOW ERROR, DETECTED AT OPPCSSRU+ At this point the OSF Server hangs waiting for the command response ECB to be posted. The ECB is never posted and eventually, after the number of seconds specified by OPS/MVS parameter OSFWAIT, the server times out and terminates SYMPTOMS: The OPS13520 message and a hung OSF Server. IMPACT: Command responses are not returned to the Rexx exec due to the hung server. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: CA OPS/MVS Base Release 13.0 Related Problem: OPSMVS 1665 Copyright (C) 2020 CA. All rights reserved. R00237-CLX130-SP1 DESC(OSF SERVER HANGS WHEN ISSUING IMS COMMANDS VIA THE IMS BMP). ++VER (Z038) FMID (CCLXD00) SUP (ST12493) ++HOLD (SO12493) SYSTEM FMID(CCLXD00) REASON (ACTION) DATE (20092) COMMENT (<pre> +-----+ CA OPS/MVS Base Version 13.0 +-----+-----+ SEQUENCE Before issuing IMS commands to the OPS IMS BMP. +-----+-----+ PURPOSE To prevent OSF Server hangs when using the OPS IMS BMP. +-----+-----+ USERS All users of the OPS IMS BMP. AFFECTED +-----+-----+ KNOWLEDGE Basic z/OS system programming skills. REQUIRED +-----+-----+ ACCESS Authority to stop and start the OPS IMS BMP. REQUIRED +-----+-----+ ***** * STEPS TO PERFORM * ***** 1. After applying the PTF, use the OPSVIEW 4.1.1 panel to toggle the IMSxxINITBMP parameter from YES to NO to stop the BMP. 2. Once the BMP is stopped, toggle the IMSxxINITBMP parameter from NO to YES to restart the BMP. </pre>

CA OPS/MVS for JES2 13.0
CA RS 2005 - PTF SO12493 Details

Service	Details
	Note: The OPS/MVS CCLXLOAD library must be included in the BMP PROC STEPLIB or module OPIMBP must be copied to the IMS RESLIB for the change to be picked up when the BMP restarts.).

Service	Details		
SO12596	SO12596 M.C.S. ENTRIES = ++PTF (SO12596) OPS3724T WTO MAY CONTAIN ZERO'S FOR PROGRAM NAME PROBLEM DESCRIPTION: The OPS3724T message text may contain zeros in place of the program name or the ruleset.rule name from where the command originated. SYMPTOMS: The OPS3724T message will display x'0000' in place of the program name or ruleset.rule name that is dispatching work to an OSF server. IMPACT: Unable to identify the program name or ruleset.rule that is sending commands to an OSF server. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 13.0 CA OPS/MVS Base Release 13.5 Related Problem: OPSMVS 1668 Copyright (C) 2020 CA. All rights reserved. R00239-CLX130-SP1 DESC(OPS3724T WTO MAY CONTAIN ZERO'S FOR PROGRAM NAME). ++VER (Z038) FMID (CCLXD00) PRE (R094507 R095980 R096478 S000300 S009264 S011482) SUP (ST12596) ++HOLD (SO12596) SYSTEM FMID(CCLXD00) REASON (ACTION) DATE (20092) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 13.0</td></tr> </table> SEQUENCE After Apply PURPOSE To activate load modules updated by this PTF. USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems administration skills. REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. This PTF updates load module OPRWFU. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a STEPLIB	CA OPS/MVS Base	Version 13.0
CA OPS/MVS Base	Version 13.0		

Service	Details
	used by the OPS/MVS main address space, a link listed loadlib, etc. 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent mechanism. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent mechanism. 5. Choose one of these two methods to begin using the updated load module: a. STOP OPS/MVS and START OPS/MVS OR b. Issue MVS command: F OPSS,RELOAD(OPRWFU)).

Service	Details		
S012626	S012626 M.C.S. ENTRIES = ++PTF (S012626) OPSJES2 INPQ FUNCTION RETURNS 0 JOBS FOR Z/OS 2.4 PROBLEM DESCRIPTION: The OPSJES2 function is not returning the correct number of jobs for the INPQ keyword after upgrading to z/OS 2.4. SYMPTOMS: The OPSJES2('I','INPQ','A') function always returns 0 jobs. IMPACT: Automation using the OPSJES2 function to gather input queue information will fail. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 13.0 CA OPS/MVS Base Version 13.5 Related Problem: OPSMVS 1671 Copyright (C) 2020 CA. All rights reserved. R00240-CLX130-SP1 DESC(OPSJES2 INPQ FUNCTION RETURNS 0 JOBS FOR Z/OS 2.4). ++VER (Z038) FMID (CCLXD00) PRE (R098697) SUP (R095028 S006787 S011788 S012593 ST06787 ST11788 ST12593 ST12626 TR95028) ++HOLD (S012626) SYSTEM FMID(CCLXD00) REASON (DYNACT) DATE (20093) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 13.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF, including load module OPSAEX USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. This PTF updates load module OPSAEX, as well as the other load modules identified by the ++MOD statements contained in this PTF. APPLY of this PTF updates SMP/E Target	CA OPS/MVS Base	Version 13.0
CA OPS/MVS Base	Version 13.0		

Service	Details
	loadlib CCLXLOAD. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a STEPLIB used by the OPS/MVS main address space, a link listed loadlib, etc. 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent mechanism. 4. TSO users must get out of OPSVIEW. 5. Stop OPS/MVS. 6. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent mechanism. 7. Start OPS/MVS. 8. TSO users may access OPSVIEW. Depending on how OPSVIEW is accessed, this may require TSO logoff/logon.).

Service	Details		
SO12660	SO12660 M.C.S. ENTRIES = ++PTF (SO12660) POSSIBLE ABEND SOC4 AFTER INSTALLING IBM PTF UJ01558 PROBLEM DESCRIPTION: After UJ01558 is installed, 64-bit storage services (IARV64 and IARST64) may return with unpredictable values in access register 0, 1, 14, and 15. This may cause SOC4 ABENDS in various OPS/MVS modules that operate in AR mode. SYMPTOMS: Potential ABEND SOC4 in OPS/MVS modules OPSMMG, OPIIUASM, and OPMTCAUP. IMPACT: There are no known instances of actual ABENDS in OPS/MVS due to UJ01558. However, it is possible that an SOC4 might occur in a rare codepath, leading to loss of an automation event, or even total product shutdown. CIRCUMVENTION: NONE. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 13.0 CA OPS/MVS Base Version 13.5 Related Problem: OPSMVS 1673 Copyright (C) 2020 CA. All rights reserved. R00241-CLX130-SP1 DESC(POSSIBLE ABEND SOC4 AFTER INSTALLING IBM PTF UJ01558). ++VER (Z038) FMID (CCLXD00) PRE (R096478 R099262 S005676 S006934 S008413) SUP (ST12660) ++HOLD (SO12660) SYSTEM FMID(CCLXD00) REASON (DYNACT) DATE (20098) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 13.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF, including load module OPSAEX USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. This PTF updates load module OPSAEX, as well as the other	CA OPS/MVS Base	Version 13.0
CA OPS/MVS Base	Version 13.0		

Service	Details
	load modules identified by the ++MOD statements contained in this PTF. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a STEPLIB used by the OPS/MVS main address space, a link listed loadlib, etc. 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent mechanism. 4. TSO users must get out of OPSVIEW. 5. Stop OPS/MVS. 6. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent mechanism. 7. Start OPS/MVS. 8. TSO users may access OPSVIEW. Depending on how OPSVIEW is accessed, this may require TSO logoff/logon.).

Service	Details		
SO12671	SO12671 M.C.S. ENTRIES = ++PTF (SO12671) PASSWORD MASKING IGNORED FOR SECURITY EVENT PROBLEM DESCRIPTION: Password masking not working for SEC Events SYMPTOMS: Passwords are not masked in OPSLOG for SEC Events IMPACT: Potential password exposure CIRCUMVENTION: None PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 13.0 CA OPS/MVS Base Release 13.5 Related Problem: OPSMVS 1670 Copyright (C) 2020 CA. All rights reserved. R00242-CLX130-SP1 DESC(PASSWORD MASKING IGNORED FOR SECURITY EVENT). ++VER (Z038) FMID (CCLXD00) PRE (R096959) SUP (R099183 ST12671 TR99183) ++HOLD (SO12671) SYSTEM FMID(CCLXD00) REASON (DYNACT) DATE (20100) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 13.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF, including load module OPSAEX USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. This PTF updates load module OPSAEX, as well as the other load modules identified by the ++MOD statements contained in this PTF. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a STEPLIB	CA OPS/MVS Base	Version 13.0
CA OPS/MVS Base	Version 13.0		

Service	Details
	used by the OPS/MVS main address space, a link listed loadlib, etc. 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent mechanism. 4. TSO users must get out of OPSVIEW. 5. Stop OPS/MVS. 6. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent mechanism. 7. Start OPS/MVS. 8. TSO users may access OPSVIEW. Depending on how OPSVIEW is accessed, this may require TSO logoff/logon.).

Service	Details		
SO12827	SO12827 M.C.S. ENTRIES = ++PTF (SO12827) OPSJES2 NOT DISPLAYING REMOTE PRINTERS PROBLEM DESCRIPTION: The OPSJES2 function is not returning remote printer information after upgrading to z/OS 2.4. SYMPTOMS: The OPSJES2('I','PRTS','*','*') function returns only local printers. IMPACT: Automation using the OPSJES2 function to gather remote printer information will fail. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 13.0 CA OPS/MVS Base Version 13.5 Related Problem: OPSMVS 1675 Copyright (C) 2020 CA. All rights reserved. R00243-CLX130-SP1 DESC(OPSJES2 NOT DISPLAYING REMOTE PRINTERS). ++VER (Z038) FMID (CCLXD00) PRE (R098697) SUP (R095028 S006787 S011788 S012593 S012626 ST06787 ST11788 ST12593 ST12626 ST12827 TR95028) ++HOLD (SO12827) SYSTEM FMID(CCLXD00) REASON (DYNACT) DATE (20108) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 13.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF, including load module OPSAEX USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. This PTF updates load module OPSAEX, as well as the other load modules identified by the ++MOD statements contained in this PTF. APPLY of this PTF updates SMP/E Target	CA OPS/MVS Base	Version 13.0
CA OPS/MVS Base	Version 13.0		

Service	Details	
	loadlib CCLXLOAD. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a STEPLIB used by the OPS/MVS main address space, a link listed loadlib, etc. 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent mechanism. 4. TSO users must get out of OPSVIEW. 5. Stop OPS/MVS. 6. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent mechanism. 7. Start OPS/MVS. 8. TSO users may access OPSVIEW. Depending on how OPSVIEW is accessed, this may require TSO logoff/logon.).	
MCS	SO12493	STARTS ON PAGE 0002
MCS	SO12596	STARTS ON PAGE 0003
MCS	SO12626	STARTS ON PAGE 0005
MCS	SO12660	STARTS ON PAGE 0007
MCS	SO12671	STARTS ON PAGE 0008
MCS	SO12827	STARTS ON PAGE 0010

CA OPS/MVS for JES2 13.0
CA RS 2005 Product/Component Listing

15

Product Family	Product	Release
Systems Management	CA OPS/MVS BASE	13.00.00
The CA RS 2005 Product/Component Count for this release is 1		

CA RS Level	Service	FMID
CAR2005	S012827	CCLXD00
	S012671	CCLXD00
	S012660	CCLXD00
	S012626	CCLXD00
	S012596	CCLXD00
	S012493	CCLXD00
CAR2004	S012593	CCLXD00
	S012410	CCLXD00
CAR2003	S012095	CCLXD00
	S011956	CCLXD00
CAR2002	S011788	CCLXD00
	S011482	CCLXD00
CAR2001	S011245	CCLXD00
	S011111	CCLXD00
	S010838	CCLXD00
CAR1912	S010842	CCLXD00
CAR1911	S010591	CCLXD00
	S010458	CCLXD00
	S010420	CCLXD00
	S010407	CCLXD00
CAR1910	S010025	CCLXD00
	S009879	CCLXD00
	S009795	CCLXD00
	S009773	CCLXD00
	S008049	CCLXD00
CAR1909	S009842	CCLXD00
	S009697	CCLXD00
	S009638	CCLXD00
	S009490	CCLXD00
CAR1908	S009264	CCLXD00
	S009159	CCLXD00
CAR1907	S009018	CCLXD00
	S008875	CCLXD00
	S008824	CCLXD00
	S008718	CCLXD00
	S008711	CCLXD00
	S008252	CCLXD03
CAR1906	S008641	CCLXD00
	S008587	CCLXD00
	S008573	CCLXD00
	S008476	CCLXD00
	S008413	CCLXD00
	S008340	CCLXD00
	S008298	CCLXD00
	S008242	CCLXD00
CAR1905	S008133	CCLXD00
CAR1904	S007772	CCLXD00

CA RS Level	Service	FMID
	S007720	CCLXD00
	S007653	CCLXD00
CAR1903	S007229	CCLXD01
	S007074	CCLXD00
CAR1902	S007183	CCLXD01
	S007123	CCLXD00
	S006934	CCLXD00
	S006932	CCLXD00
	S006787	CCLXD00
CAR1901	S006683	CCLXD00
	S006578	CCLXD00
	S006538	CCLXD00
	S006488	CCLXD00
CAR1812	S006389	CCLXD00
	S006327	CCLXD01
	S006307	CCLXD00
	S006258	CCLXD00
	S006156	CCLXD00
	S005994	CCLXD01
CAR1811	S006103	CCLXD00
	S005982	CCLXD00
	S005726	CCLXD00
	S005709	CCLXD00
	S005692	CCLXD00
	S005657	CCLXD01
CAR1810	S005676	CCLXD00
	S005672	CCLXD00
	S005636	CCLXD01
	S005589	CCLXD00
	S005529	CCLXD01
	S005501	CCLXD00
	S005460	CCLXD00
	S005340	CCLXD00
	S005284	CCLXD00
	S005268	CCLXD00
CAR1809	S005193	CCLXD00
	S005089	CCLXD00
	S005046	CCLXD00
	S004984	CCLXD00
	S004937	CCLXD00
	S004902	CCLXD00
	S004899	CCLXD00
	S004780	CCLXD00
	S004605	CCLXD00
	S004137	CCLXD00
CAR1808	S004636	CCLXD00
	S004624	CCLXD00

CA RS Level	Service	FMID
	S004478	CCLXD00
	S004295	CCLXD01
CAR1807	S003936	CCLXD00
	S003909	CCLXD00
CAR1806	S003746	CCLXD00
	S003736	CCLXD00
	S003721	CCLXD01
	S003660	CCLXD00
	S003629	CCLXD00
	S001957	CCLXD00
	S001878	CCLXD00
	S001810	CCLXD00
	S001805	CCLXD00
	S001748	CCLXD00
CAR1805	S001582	CCLXD00
	S001318	CCLXD00
	S001269	CCLXD00
	S000892	CCLXD00
CAR1804	S001096	CCLXD00
	S001095	CCLXD00
	S001082	CCLXD01
	S000907	CCLXD00
	S000647	CCLXD00
	S000309	CCLXD00
CAR1803	S000659	CCLXD00
	S000639	CCLXD00
	S000534	CCLXD00
	S000407	CCLXD00
	S000392	CCLXD00
	S000300	CCLXD00
	R099262	CCLXD00
CAR1802	S000182	CCLXD00
	S000165	CCLXD00
	S000008	CCLXD00
	S000002	CCLXD00
	R099930	CCLXD00
CAR1801	R099603	CCLXD00
	R099549	CCLXD00
	R099351	CCLXD00
	R099017	CCLXD00
CAR1712	R099183	CCLXD00
	R099161	CCLXD00
	R099146	CCLXD00
	R099083	CCLXD00
	R099076	CCLXD00
	R098964	CCLXD00
CAR1711	R098820	CCLXD00

CA RS Level	Service	FMID
	R098697	CCLXD00
	R098686	CCLXD00
	R098596	CCLXD00
	R098522	CCLXD00
	R098459	CCLXD00
	R098339	CCLXD00
	R098292	CCLXD00
	R097912	CCLXD01
	R096479	CCLXD01
	R096478	CCLXD00
CAR1710	R098139	CCLXD00
	R097889	CCLXD00
	R097835	CCLXD00
CAR1709	R097665	CCLXD00
	R097620	CCLXD00
	R097559	CCLXD00
	R097551	CCLXD00
	R097465	CCLXD00
	R097449	CCLXD00
	R097420	CCLXD00
CAR1708	R097040	CCLXD00
	R097011	CCLXD00
	R097008	CCLXD00
	R097000	CCLXD01
	R096971	CCLXD00
	R096959	CCLXD00
	R096643	CCLXD00
CAR1707	R096446	CCLXD00
CAR1706	R096115	CCLXD00
	R095980	CCLXD00
	R095953	CCLXD00
	R095890	CCLXD00
	R095212	CCLXD00
CAR1705	R095660	CCLXD00
	R095391	CCLXD00
CAR1704	R095348	CCLXD00
	R095285	CCLXD00
	R095251	CCLXD00
	R095204	CCLXD00
	R095154	CCLXD00
	R095028	CCLXD00
	R094989	CCLXD00
	R094880	CCLXD00
	R094837	CCLXD00
	R094774	CCLXD00
	R094507	CCLXD00
	R094245	CCLXD00

CA RS Level	Service	FMID
CAR1703	R094721	CCLXD00
	R094704	CCLXD00
	R094652	CCLXD04
	R094625	CCLXD00
	R094613	CCLXD00
	R094603	CCLXD00
	R094474	CCLXD00
	R094359	CCLXD00
	R094323	CCLXD00
CAR1702	R094192	CCLXD03
	R094184	CCLXD00
	R094116	CCLXD00
	R094104	CCLXD00
	R094084	CCLXD03
	R094069	CCLXD00
	R094062	CCLXD00
	R093997	CCLXD00
	R093945	CCLXD00
	R093939	CCLXD00
	R093749	CCLXD00
CAR1701	R093685	CCLXD00
	R093591	CCLXD00
	R093549	CCLXD00
	R093524	CCLXD00