

CA OPS/MVS for JES3 14.0
CA RS 2009 Service List

1

Service	Description	Type
S014412	OPS7406E ERROR RUNNING STATESET	PTF
S014434	SMP/E APPLY OF A POST-14.0 RELEASE OF OPS/MVS MAY FAIL	PTF
S014477	COMPILER WORKSPACE OVERFLOW ERROR IN OPSVIEW 4.8	PTF
S014492	MTC-A DISPLAY SSM#MOVMOD FOR SSM RESOURCES	PTF
S014537	MSG.IMMEDACT INCORRECT IN AOFTEST	PTF
The CA RS 2009 service count for this release is 5		

CA OPS/MVS for JES3
CA RS 2009 Service List for CCLXE00

2

FMID	Service	Description	Type
CCLXE00	S014412	OPS7406E ERROR RUNNING STATESET	PTF
	S014477	COMPILER WORKSPACE OVERFLOW ERROR IN OPSVIEW 4.8	PTF
	S014537	MSG.IMMEDACT INCORRECT IN AOFTEST	PTF
The CA RS 2009 service count for this FMID is 3			

CA OPS/MVS for JES3
CA RS 2009 Service List for CCLXE01

3

FMID	Service	Description	Type
CCLXE01	SO14434	SMP/E APPLY OF A POST-14.0 RELEASE OF OPS/MVS MAY FAIL	PTF
	SO14492	MTC-A DISPLAY SSM#MOVMOD FOR SSM RESOURCES	PTF
The CA RS 2009 service count for this FMID is 2			

CA OPS/MVS for JES3 14.0
CA RS 2009 - PTF SO14412 Details

Service	Details				
SO14412	<p>SO14412 M.C.S. ENTRIES = ++PTF (SO14412)</p> <p>OPS7406E ERROR RUNNING STATESET</p> <p>PROBLEM DESCRIPTION:</p> <p>For customers running the SSMGA or SSMGAV2 application, the STATESET command will fail with a -7406 SQLCODE, if issued to a resource table that does not have an SSM#MOVMOD column.</p> <p>SYMPTOMS:</p> <p>Following error message issued for STATESET command:</p> <p>OPS0996I OPS7406E OPERATION FAILED. COLUMN SSM#MOVMOD IS NOT DEFINED IN TABLE</p> <p>IMPACT:</p> <p>STATESET command fails.</p> <p>CIRCUMVENTION:</p> <p>None.</p> <p>PRODUCT(S) AFFECTED:</p> <table> <tr> <td>CA OPS/MVS Base</td><td>Release 13.5</td></tr> <tr> <td>CA OPS/MVS Base</td><td>Release 14.0</td></tr> </table> <p>Related Problem:</p> <p>OPSMVS 1694</p> <p>Copyright (C) 2020 CA. All rights reserved. R00002-CLX140-SP0</p> <p>DESC(OPS7406E ERROR RUNNING STATESET).</p> <p>++VER (Z038)</p> <p>FMID (CCLXE00)</p> <p>SUP (ST14412)</p>	CA OPS/MVS Base	Release 13.5	CA OPS/MVS Base	Release 14.0
CA OPS/MVS Base	Release 13.5				
CA OPS/MVS Base	Release 14.0				

CA OPS/MVS for JES3 14.0
CA RS 2009 - PTF SO14434 Details

5

Service	Details
SO14434	<p>SO14434 M.C.S. ENTRIES = ++PTF (SO14434)</p> <p>SMP/E APPLY OF A POST-14.0 RELEASE OF OPS/MVS MAY FAIL</p> <p>PROBLEM DESCRIPTION:</p> <p>SMP/E installation of a CA OPS/MVS release higher than version 14.0 may fail during APPLY processing when installing into a CSI where CA OPS/MVS 14.0 Web Components FMID(CCLXE01) is installed.</p> <p>SYMPTOMS:</p> <p>The SYSLOG file for the APPLY step of the installation of a later release will contain the following message:</p> <p>GIM39311E ** SHELL SCRIPT OPSSHTAR PROCESSING TO DELETE HFS OPWBBRTR IN THE CCLXHFS LIBRARY FAILED FOR SYSMOD CCLXE00.</p> <p>IMPACT:</p> <p>A later release of CA OPS/MVS cannot be installed into the same CSI where CA OPS/MVS version 14.0 was installed.</p> <p>CIRCUMVENTION:</p> <p>None.</p> <p>PRODUCT(S) AFFECTED:</p> <p>CA OPS/MVS Base Release 14.0</p> <p>Related Problem:</p> <p>OPSMVS 1699</p> <p>Copyright (C) 2020 CA. All rights reserved. R00003-CLX140-SP0</p> <p>DESC(SMP/E APPLY OF A POST-14.0 RELEASE OF OPS/MVS MAY FAIL).</p> <p>++VER (Z038)</p> <p>FMID (CCLXE01)</p> <p>SUP (ST14434)</p> <p>TEXT</p> <p>LINK('.. /OPSSHTAR.sh')</p> <p>PARM(PATHMODE(0,7,5,5)) .</p>

CA OPS/MVS for JES3 14.0
CA RS 2009 - PTF SO14477 Details

6

Service	Details				
SO14477	<p>SO14477 M.C.S. ENTRIES = ++PTF (SO14477)</p> <p>COMPILER WORKSPACE OVERFLOW ERROR IN OPSVIEW 4.8</p> <p>PROBLEM DESCRIPTION:</p> <p>Selecting a SYSPLEX variable stem in OPSVIEW 4.8, that contains more variables than the REXX WORK SPACE can contain, causes many OPS0998E messages to be issued to the TSO session.</p> <p>SYMPTOMS:</p> <p>The following message is issued to the TSO session many times.</p> <p>RUNNING OPAODIGL LINE 300: COMPILER WORK SPACE OVERFLOW (1576928 1572864)</p> <p>IMPACT:</p> <p>Users must cancel out of their TSO session.</p> <p>CIRCUMVENTION:</p> <p>None.</p> <p>PRODUCT(S) AFFECTED:</p> <table> <tr> <td>CA OPS/MVS Base</td><td>Release 13.5</td></tr> <tr> <td>CA OPS/MVS Base</td><td>Release 14.0</td></tr> </table> <p>Related Problem:</p> <p>OPSMVS 1692</p> <p>Copyright (C) 2020 CA. All rights reserved. R00004-CLX140-SP0</p> <p>DESC (COMPILER WORKSPACE OVERFLOW ERROR IN OPSVIEW 4.8).</p> <p>++VER (Z038)</p> <p>FMID (CCLXE00)</p> <p>SUP (ST14477)</p>	CA OPS/MVS Base	Release 13.5	CA OPS/MVS Base	Release 14.0
CA OPS/MVS Base	Release 13.5				
CA OPS/MVS Base	Release 14.0				

Service	Details
S014492	<p>S014492 M.C.S. ENTRIES = ++PTF (S014492)</p> <p>MTC-A DISPLAY SSM#MOVMOD FOR SSM RESOURCES</p> <p>ENHANCEMENT DESCRIPTION:</p> <p>The MTC-A SSM Resource Detail page has been updated to include the value of resource table column SSM#MOVMOD (SSMGA Move Mode) for the selected resource. The value appears under the "Modes" section of the resource detail table in the column labeled "Move".</p> <p>PRODUCT(S) AFFECTED:</p> <p>CA OPS/MVS Web Components Version 14.0</p> <p>Related Problem:</p> <p>OPSMVS 1701</p> <p>Copyright (C) 2020 CA. All rights reserved. R00005-CLX140-SP0</p> <p>DESC(MTC-A DISPLAY SSM#MOVMOD FOR SSM RESOURCES).</p> <p>++VER (Z038)</p> <p>FMID (CCLXE01)</p> <p>SUP (ST14492)</p> <p>++HOLD (S014492) SYSTEM FMID(CCLXE01)</p> <p>REASON (ACTION) DATE (20240)</p> <p>COMMENT (</p> <pre> +-----+ CA OPS/MVS Web Components Version 14.0 +-----+-----+ SEQUENCE After APPLY +-----+-----+ PURPOSE To deploy a new version of Mainframe Team Center - Automation +-----+-----+ USERS All OPS/MVS MTC-A users AFFECTED +-----+-----+ KNOWLEDGE Basic z/OS systems programming skills and knowledge of REQUIRED your new or existing MTC-A installation and configuration +-----+-----+ ACCESS - Read/write access to the USS directories where your new REQUIRED or existing installation of MTC-A resides - Authority to STOP and START your MTC-A Web Application +-----+-----+ ***** * STEPS TO PERFORM * ***** Run The MTC-A Configuration Batch Job Sample JCL to execute the configuration script, mtcacfg.sh, is provided in yourHLQ.CCLXCNTL(OPMOIACG). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Set CCLXCLS0 to the fully qualified MVS dataset name of the SMP/E CLIST target library installed by FMID CCLXxr0 OPS/MVS Base. (eg. 'yourHLQ.CCLXCLS0') 3. Set CCLSHFSM to the USS mount point of the zFS installed by FMID CLXxr1 OPS/MVS OPSLOG WebView and Web Features. 4. Set TOMCATCONF to the USS path of your deployed Tomcat </pre>

Service	Details
	<p>server's "context" directory. Typically:</p> <pre><catalina_base>/conf/Catalina/localhost</pre> <p>5. Set MTCADeploy to the USS path where you wish to deploy the MTCA Web App. A new directory called '/mtca' will be created on this path and will contain the mtcaApp.war as well as '/conf' and '/log' sub-directories.</p> <p>The configuration script creates the MTC-A directory structure at your chosen deployment location and defines the context for MTC-A to your Tomcat installation.</p> <p>If a previous MTC-A installation exists, your current configuration is saved as 'MTCADeploy/mtca/conf/config.yaml.YY_MM_DD_hh_mm_ss'. Your configuration is then automatically merged and upgraded to the version supplied within this PTF. Verify the STDOUT of the configuration batch job for messages indicating the addition of fields to the 'conf.yaml' that must be set specifically for your site before MTC-A is restarted.</p> <p>If your '/mtca' directory is on path 'a/b/c/mtca' supply path '/a/b/c' as your value for the deploy location</p> <pre>). ++HOLD (SO14492) SYSTEM FMID(CCLXE01) REASON (ENH) DATE (20240) COMMENT (+-----+ CA OPS/MVS Web Components Version 14.0 +-----+-----+ SEQUENCE After APPLY and HOLD REASON(ACT) is followed +-----+-----+ PURPOSE Ability to display the value of SSM#MOVMOD for a SSM resource with MTC-A +-----+-----+ USERS All MTC-A users AFFECTED +-----+-----+ KNOWLEDGE Understanding of the function of SSM REQUIRED +-----+-----+ ACCESS Ability to log on to MTC-A REQUIRED +-----+-----+ ***** * STEPS TO PERFORM * ***** See section "View Resource Detail" in the CA OPS/MVS documentation set at http://techdocs.broadcom.com CA Mainframe Software > Automation > CA OPS/MVS). BINARY LINK(' ../conf.yaml') PARM(PATHMODE(0,7,5,5)) . TEXT LINK(' ../mtcacfg.sh') PARM(PATHMODE(0,7,5,5)) . BINARY</pre>

Service	Details
	LINK('.. /mtcaApp.war') PARM(PATHMODE(0,7,5,5)) .

Service	Details	
SO14537	SO14537	M.C.S. ENTRIES = ++PTF (SO14537)
	MSG.IMMEDACT INCORRECT IN AOFTEST	
	PROBLEM DESCRIPTION:	
	When testing a message rule in AOFTEST, the MSG.IMMEDACT environmental variable has a value of 1 even though DESC code 2 is not set.	
	SYMPTOMS:	
	MSG.IMMEDACT is set to 1 when DESC code 2 is not set.	
	IMPACT:	
	Incorrect rule test results.	
	CIRCUMVENTION:	
	None.	
	PRODUCT(S) AFFECTED:	
	CA OPS/MVS Base	Release 13.0
	CA OPS/MVS Base	Release 13.5
	CA OPS/MVS Base	Release 14.0
	Related Problem:	
	OPSMVS 1702	
	Copyright (C) 2020 CA. All rights reserved. R00006-CLX140-SP0	
DESC(MSG.IMMEDACT INCORRECT IN AOFTEST).		
++VER (Z038)		
FMID (CCLXE00)		
SUP (ST14537)		
MCS	SO14412	STARTS ON PAGE 0002
MCS	SO14434	STARTS ON PAGE 0002
MCS	SO14477	STARTS ON PAGE 0003
MCS	SO14492	STARTS ON PAGE 0004
MCS	SO14537	STARTS ON PAGE 0007

CA OPS/MVS for JES3 14.0
CA RS 2009 Product/Component Listing

11

Product Family	Product	Release
Systems Management	CA OPS/MVS BASE	14.00.00
The CA RS 2009 Product/Component Count for this release is 1		

CA RS Level	Service	FMID
CAR2009	S014537	CCLXE00
	S014492	CCLXE01
	S014477	CCLXE00
	S014434	CCLXE01
	S014412	CCLXE00