

CA OPS/MVS for JES3 14.0
CA RS 2107 Service List

1

Service	Description	Type
LU01140	OPSLOG WEBVIEW FAILS TO START: UNSIGNED BROWSER.JAR	PTF
LU01211	MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING	PTF
LU01212	MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING	PTF
LU01562	ABEND SOC4 IN OPSLOG WEBVIEW SERVER	PTF
LU01630	ABEND SOC4 IN OPSLOG WEBVIEW SERVER	PTF
LU01655	REMOTE SECURITY CHECK BYPASSED FOR CROSS SYSTEM SQL	PTF
LU01797	UPDATE SAMPLE JOB ARCHCRTE FOR MANUALLY ARCHIVING OPSLOG	PTF
LU01862	OPSGETVL MASK WILDCARD '*' FAILS FOR REMOTE SECURITY	PTF
LU01929	UNWANTED 'OPS9999T **OPAUCK ...' DEBUG WTOS IN OPSLOG	PTF
The CA RS 2107 service count for this release is 9		

CA OPS/MVS for JES3
CA RS 2107 Service List for CCLXE00

2

FMID	Service	Description	Type
CCLXE00	LU01211	MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING	PTF
	LU01630	ABEND SOC4 IN OPSLOG WEBVIEW SERVER	PTF
	LU01655	REMOTE SECURITY CHECK BYPASSED FOR CROSS SYSTEM SQL	PTF
	LU01797	UPDATE SAMPLE JOB ARHCRTS FOR MANUALLY ARCHIVING OPSLOG	PTF
	LU01862	OPSGETVL MASK WILDCARD '*' FAILS FOR REMOTE SECURITY	PTF
	LU01929	UNWANTED 'OPS9999T **OPAUCK ...' DEBUG WTOS IN OPSLOG	PTF
The CA RS 2107 service count for this FMID is 6			

CA OPS/MVS for JES3
CA RS 2107 Service List for CCLXE01

3

FMID	Service	Description	Type
CCLXE01	LU01140	OPSLOG WEBVIEW FAILS TO START: UNSIGNED BROWSER.JAR	PTF
	LU01212	MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING	PTF
	LU01562	ABEND SOC4 IN OPSLOG WEBVIEW SERVER	PTF
The CA RS 2107 service count for this FMID is 3			

Service	Details		
LU01140	LU01140 M.C.S. ENTRIES = ++PTF (LU01140) OPSLOG WEBVIEW FAILS TO START: UNSIGNED BROWSER.JAR PROBLEM DESCRIPTION: OPSLOG WebView is unable to complete initialization due to an unsigned certificate error. The OPSLOG WebView Browser.jar file has been resigned with an updated certificate and expiration date. SYMPTOMS: The following messages may be observed when starting OPSLOG WebView: Unsigned application requesting unrestricted access to system. Unsigned resource: Browser.jar IMPACT: Unable to use OPSLOG WebView. CIRCUMVENTION: none. PRODUCT(S) AFFECTED: CA OPS/MVS Web Features Release 14.0 Related Problem: OPSMVS 13594 Copyright (C) 2021 CA. All rights reserved. R00100-CLX140-SP0 DESC(OPSLOG WEBVIEW FAILS TO START: UNSIGNED BROWSER.JAR). ++VER (Z038) FMID (CCLXE01) PRE (LU00633 SO15821) SUP (LT01140) ++HOLD (LU01140) SYSTEM FMID(CCLXE01) REASON (ACTION) DATE (21158) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Web Components</td><td>Version 14.0</td></tr> </table> SEQUENCE After Apply PURPOSE To activate the fix USERS User's of the OPSLOG WebView component AFFECTED KNOWLEDGE Web servers and USS directories REQUIRED ACCESS USS directories for Tomcat Web Server REQUIRED ***** * STEPS TO PERFORM * ***** 1. Update your OPS/MVS WebView web server by copying the opslog.war file from the installation HFS to your runtime web server. See one of the following documents for detailed instructions on how to deploy the new modules. - How to Install and Configure OPSLOG WebView on Apache Tomcat - How to Install and Configure OPSLOG WebView on IBM HTTP Web	CA OPS/MVS Web Components	Version 14.0
CA OPS/MVS Web Components	Version 14.0		

Service	Details
	Server (IHS) 2. Recycle your web server so it recognizes and uses the newly updated opslog.war file.). BINARY LINK('..OPWBBRJR.tar') PARM(PATHMODE(0,7,5,5)) SHSCRIPT(OPSSHJAR,POST) . BINARY LINK('..OPWBBRTR.tar') PARM(PATHMODE(0,7,5,5)) SHSCRIPT(OPSSHTAR,POST) .

Service	Details
LU01211	LU01211 M.C.S. ENTRIES = ++PTF (LU01211) MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING ENHANCEMENT DESCRIPTION: This PTF introduces the ability for authorized users to edit a rules's status and auto-enabled setting using the MTC-A web application. Appropriate security checks ensure only users that have update privilege for the selected rule can perform a change to a rule s status or auto-enabled setting. PRODUCT(S) AFFECTED: CA OPS/MVS Base Release 14.0 CA OPS/MVS Web Components Release 14.0 Related Problem: OPSMVS 12872 Copyright (C) 2021 CA. All rights reserved. R00102-CLX140-SP0 DESC(MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING) . ++VER (Z038) FMID (CCLXE00) PRE (LU00067 LU00121 LU00442 LU00715 S015067 S015876) SUP (LT00113 LT01211 LU00113 ST14366) ++IF FMID(CCLXE01) REQ(LU01212) . ++HOLD (LU01211) SYSTEM FMID(CCLXE00) REASON (DEP) DATE (21161) COMMENT (<pre> +-----+ CA OPS/MVS Base Version 14.0 +-----+ SEQUENCE Before Apply +-----+ PURPOSE Upgrading the CCS Message Service Server (LU01507) is a prerequisite to the MTC-A Edit Rule Status and Auto-Enable Setting feature. +-----+ USERS All MTC-A Users AFFECTED +-----+ KNOWLEDGE CCS Message Service Server installations REQUIRED +-----+ ACCESS Ability to apply maintenance to and stop/start the CCS REQUIRED Message Service Server(s) +-----+ ***** * STEPS TO PERFORM * ***** 1. After applying the CCS PTF on all LPARs, restart the CCS Message Service Server(s) .). ++HOLD (LU01211) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (21161) </pre>

Service	Details
	COMMENT (<pre> +-----+ CA OPS/MVS Base Version 14.0 +-----+ SEQUENCE After APPLY +-----+ PURPOSE To activate load modules updated by this PTF +-----+ USERS All OPS/MVS users AFFECTED +-----+ KNOWLEDGE Basic z/OS systems programming skills REQUIRED +-----+ ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS +-----+ ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.). ++HOLD (LU01211) SYSTEM FMID(CCLXE00) REASON (ENH) DATE (21161) COMMENT (+-----+ CA OPS/MVS Base Version 14.0 +-----+ SEQUENCE After APPLY +-----+ PURPOSE To learn about this enhancement +-----+ </pre>

Service	Details
	USERS All CA OPS/MVS MTC-A users AFFECTED +-----+ KNOWLEDGE Knowledge of your CA OPS/MVS MTC-A installation REQUIRED +-----+ ACCESS Necessary CA OPS/MVS MTC-A specific authorization REQUIRED +-----+ ***** * PUBLICATION * ***** See section "Edit Rule Fields" in the CA OPS/MVS documentation set at http://techdocs.broadcom.com/opsmvs).

Service	Details		
LU01212	LU01212 M.C.S. ENTRIES = ++PTF (LU01212) MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING ENHANCEMENT DESCRIPTION: This PTF introduces the ability for authorized users to edit a rules's status and auto-enabled setting using the MTC-A web application. Appropriate security checks ensure only users that have update privilege for the selected rule can perform a change to a rule s status or auto-enabled setting. PRODUCT(S) AFFECTED: CA OPS/MVS Base Release 14.0 CA OPS/MVS Web Components Release 14.0 Related Problem: OPSMVS 12872 Copyright (C) 2021 CA. All rights reserved. R00102-CLX140-SP0 DESC(MTC-A EDIT RULE STATUS AND AUTO-ENABLED SETTING) . ++VER (Z038) FMID (CCLXE01) PRE (LU00044 LU00122 LU00462 LU00633 S014492 S014857 S015022 S015068 S015148 S015200 S015241 S015821 S015877) SUP (LT01162 LT01212 ST14979) ++IF FMID(CCLXE00) REQ(LU01211) . ++HOLD (LU01212) SYSTEM FMID(CCLXE01) REASON (DEP) DATE (21161) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Web Components</td><td>Version 14.0</td></tr> </table> SEQUENCE Before Apply PURPOSE Upgrading the CCS Message Service Server (LU01507) is a prerequisite to the MTC-A Edit Rule Status and Auto-Enable Setting feature. USERS All MTC-A Users AFFECTED KNOWLEDGE CCS Message Service Server installations REQUIRED ACCESS Ability to apply maintenance to and stop/start the CCS REQUIRED Message Service Server(s) ***** * STEPS TO PERFORM * ***** 1. After applying the CCS PTF on all LPARs, restart the CCS Message Service Server(s).).	CA OPS/MVS Web Components	Version 14.0
CA OPS/MVS Web Components	Version 14.0		

Service	Details
	<pre> ++HOLD (LU01212) SYSTEM FMID(CCLXE01) REASON (DYNACT) DATE (21161) COMMENT (+-----+ CA OPS/MVS Web Components Version 14.0 +-----+ SEQUENCE After APPLY +-----+ PURPOSE To deploy a new version of Mainframe Team Center - Automation +-----+ USERS All OPS/MVS MTC-A users AFFECTED +-----+ KNOWLEDGE Basic z/OS systems programming skills and knowledge of REQUIRED your new or existing MTC-A installation and configuration +-----+ ACCESS - Read/write access to the USS directories where your new REQUIRED or existing installation of MTC-A resides - Authority to STOP and START your MTC-A Web Application +-----+ ***** * STEPS TO PERFORM * ***** Run The MTC-A Configuration Batch Job Sample JCL to execute the configuration script, mtcacfg.sh, is provided in yourHLQ.CCLXCNTL(OPMOIACG). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Set CCLXCLS0 to the fully qualified MVS dataset name of the SMP/E CLIST target library installed by FMID CCLXxr0 OPS/MVS Base. (eg. 'yourHLQ.CCLXCLS0') 3. Set CCLSHFSM to the USS mount point of the zFS installed by FMID CLXxr1 OPS/MVS OPSLOG WebView and Web Features. 4. Set TOMCATCONF to the USS path of your deployed Tomcat server's "context" directory. Typically: <catalina_base>/conf/Catalina/localhost 5. Set MTCADepLOY to the USS path where you wish to deploy the MTCA Web App. A new directory called '/mtca' will be created on this path and will contain the mtcaApp.war as well as '/conf' and '/log' sub-directories. The configuration script creates the MTC-A directory structure at your chosen deployment location and defines the context for MTC-A to your Tomcat installation. If a previous MTC-A installation exists, your current configuration is saved as 'MTCADepLOY/mtca/conf/config.yaml.YY_MM_DD_hh_mm_ss'. Your configuration is then automatically merged and upgraded to the version supplied within this PTF. Verify the STDOUT of the configuration batch job for messages indicating the addition of fields to the 'conf.yaml' that must be set specifically for your site before MTC-A is restarted. If your '/mtca' directory is on path 'a/b/c/mtca' supply path '/a/b/c' as your value for the deploy location) </pre>

Service	Details
	<pre> ++HOLD (LU01212) SYSTEM FMID(CCLXE01) REASON (ENH) DATE (21161) COMMENT (+-----+ CA OPS/MVS Web Components Version 14.0 +-----+ SEQUENCE After APPLY +-----+ PURPOSE To learn about this enhancement +-----+ USERS All CA OPS/MVS MTC-A users AFFECTED +-----+ KNOWLEDGE Knowledge of your CA OPS/MVS MTC-A installation REQUIRED +-----+ ACCESS Necessary CA OPS/MVS MTC-A specific authorization REQUIRED +-----+ ***** * PUBLICATION * ***** See section "Edit Rule Fields" in the CA OPS/MVS documentation set http://techdocs.broadcom.com/opsmvs). BINARY LINK('../conf.yaml') PARM(PATHMODE(0,7,5,5)) . TEXT LINK('../mtcacfg.sh') PARM(PATHMODE(0,7,5,5)) . BINARY LINK('../mtcaApp.war') PARM(PATHMODE(0,7,5,5)) . </pre>

Service	Details
LU01562	LU01562 M.C.S. ENTRIES = ++PTF (LU01562) ABEND SOC4 IN OPSLOG WEBVIEW SERVER PROBLEM DESCRIPTION: The OPSLOG WebView Server takes a SOC4 abend when a client attempts to connect and selects a system and opslog to view. SYMPTOMS: Abend U422 in OPSLOGSV task following a SOC4 abend. IMPACT: Customer is unable to use OPSLOG WebView CIRCUMVENTION: None PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 14.0 Related Problem: OPSMVS 13906 Copyright (C) 2021 CA. All rights reserved. R00106-CLX140-SP0 DESC (ABEND SOC4 IN OPSLOG WEBVIEW SERVER) . ++VER (Z038) FMID (CCLXE01) PRE (LU00716) SUP (LT00535 LT00563 LT00641 LT00683 LT01562) ++IF FMID(CCLXE00) REQ(LU01630) .

Service	Details		
LU01630	LU01630 M.C.S. ENTRIES = ++PTF (LU01630) ABEND SOC4 IN OPSLOG WEBVIEW SERVER PROBLEM DESCRIPTION: The OPSLOG WebView Server takes a SOC4 abend when a client attempts to connect and selects a system and opslog to view. SYMPTOMS: Abend U422 in OPSLOGSV task following a SOC4 abend. IMPACT: Customer is unable to use OPSLOG WebView CIRCUMVENTION: None PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 14.0 Related Problem: OPSMVS 13906 Copyright (C) 2021 CA. All rights reserved. R00106-CLX140-SP0 DESC (ABEND SOC4 IN OPSLOG WEBVIEW SERVER). ++VER (Z038) FMID (CCLXE00) PRE (LU00715) SUP (LT01630) ++IF FMID(CCLXE01) REQ(LU01562) . ++HOLD (LU01630) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (21162) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib	CA OPS/MVS Base	Version 14.0
CA OPS/MVS Base	Version 14.0		

Service	Details
	in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details		
LU01655	LU01655 M.C.S. ENTRIES = ++PTF (LU01655) REMOTE SECURITY CHECK BYPASSED FOR CROSS SYSTEM SQL PROBLEM DESCRIPTION: Remote security check is bypassed for operations related to cross system SQL when parameters EXTSECURITY=ON and SECURITYSCOPE=REMOTE. SYMPTOMS: Remote security check is bypassed for operations related to cross system SQL. For example: 1. Remote resources can be started or stopped by local OPSVIEW panel 4.11.2 even though the user ID does not have the authority on the remote system. 2. Remote resource tables can be modified by ADDRESS SQL host environment commands with a remote system name for the SYSTEM keyword even though the user ID does not have the authority on the remote system. IMPACT: Security check failure through cross system SQL. CIRCUMVENTION: NONE. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 14.0 Related Problem: OPSMVS 13937 Copyright (C) 2021 CA. All rights reserved. R00107-CLX140-SP0 DESC (REMOTE SECURITY CHECK BYPASSED FOR CROSS SYSTEM SQL). ++VER (Z038) FMID (CCLXE00) PRE (S014801 S015876) SUP (LT01655) ++HOLD (LU01655) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (21165) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD.	CA OPS/MVS Base	Version 14.0
CA OPS/MVS Base	Version 14.0		

Service	Details
	Refer to GIM23903I messages in the SMPOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details
LU01797	LU01797 M.C.S. ENTRIES = ++PTF (LU01797) UPDATE SAMPLE JOB ARCHCRTE FOR MANUALLY ARCHIVING OPSLOG PROBLEM DESCRIPTION: Sample job ARCHCRTE in the CCLXCNTL data set uses deprecated load module OPARLGCR, which is not supported by, nor shipped with, OPS/MVS version 14.0. This PTF updates the sample to use load module OPARLGGE. SYMPTOMS: Attempt to use sample job ARCHCRTE results in ABEND S806: CSV003I REQUESTED MODULE OPARLGCR NOT FOUND CSV028I ABEND806-04 JOBNAME=SAMPJOBA STEPNAME=CREATEAR IMPACT: Manual OPSLOG archiving based on the sample ARCHCRTE in CCLXCNTL cannot be implemented. CIRCUMVENTION: Use OPSVIEW option 7.1.2 for manual OPSLOG archiving. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 14.0 Related Problem: OPSMVS 14013 Copyright (C) 2021 CA. All rights reserved. R00108-CLX140-SP0 DESC(UPDATE SAMPLE JOB ARCHCRTE FOR MANUALLY ARCHIVING OPSLOG). ++VER (Z038) FMID (CCLXE00) SUP (LT01797)

Service	Details		
LU01862	LU01862 M.C.S. ENTRIES = ++PTF (LU01862) OPSGETVL MASK WILDCARD '*' FAILS FOR REMOTE SECURITY PROBLEM DESCRIPTION: Authorization by the RACF generic profile fails for an OPSGETVL mask with trailing asterisk '*' when an OPSGETVL command is sent to a remote system. SYMPTOMS: ICH408I message appears indicating 'Profile not found', in which the profile name contains a trailing asterisk. IMPACT: Cannot use RACF generic profile for OPSGETVL mask authorization. CIRCUMVENTION: Define RACF profile exactly the same as the full OPSGETVL mask. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 14.0 Related Problem: OPSMVS 14088 Copyright (C) 2021 CA. All rights reserved. R00109-CLX140-SP0 DESC(OPSGETVL MASK WILDCARD '*' FAILS FOR REMOTE SECURITY). ++VER (Z038) FMID (CCLXE00) SUP (LT01862) ++HOLD (LU01862) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (21180) COMMENT (<table border="1"> <tr> <td>CA OPS/MVS Base</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST).	CA OPS/MVS Base	Version 14.0
CA OPS/MVS Base	Version 14.0		

Service	Details
	3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details
LU01929	LU01929 M.C.S. ENTRIES = ++PTF (LU01929) UNWANTED 'OPS9999T **OPAUCK ...' DEBUG WTOS IN OPSLOG PROBLEM DESCRIPTION: When using OPSLOG Browse cross-system, unwanted 'OPS9999T **OPAUCK ...' WTOS are issued regardless of the setting of parameter DEBUGEXTSEC. SYMPTOMS: OPS/MVS message 'OPS9999T **OPAUCK returns: RSEC: X'00' RC: 0' appears in OPSLOG each time cross-system OPSLOG Browse is used. IMPACT: Superfluous debug messages. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: CA OPS/MVS Base Version 14.0 Related Problem: OPSMVS 14087 Copyright (C) 2021 CA. All rights reserved. R00110-CLX140-SP0 DESC (UNWANTED 'OPS9999T **OPAUCK ...' DEBUG WTOS IN OPSLOG). ++VER (Z038) FMID (CCLXE00) SUP (LT01929) ++HOLD (LU01929) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (21181) COMMENT (<pre> +-----+ CA OPS/MVS Base Version 14.0 +-----+-----+ SEQUENCE After APPLY +-----+-----+ PURPOSE To activate load modules updated by this PTF +-----+-----+ USERS All OPS/MVS users AFFECTED +-----+-----+ KNOWLEDGE Basic z/OS systems programming skills REQUIRED +-----+-----+ ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS +-----+-----+ ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing </pre>

Service	Details	
	any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).	
MCS	LU01140	STARTS ON PAGE 0002
MCS	LU01211	STARTS ON PAGE 0003
MCS	LU01212	STARTS ON PAGE 0006
MCS	LU01562	STARTS ON PAGE 0009
MCS	LU01630	STARTS ON PAGE 0010
MCS	LU01655	STARTS ON PAGE 0018
MCS	LU01797	STARTS ON PAGE 0019
MCS	LU01862	STARTS ON PAGE 0020
MCS	LU01929	STARTS ON PAGE 0022

CA OPS/MVS for JES3 14.0
CA RS 2107 Product/Component Listing

22

Product Family	Product	Release
Systems Management	CA OPS/MVS BASE	14.00.00
The CA RS 2107 Product/Component Count for this release is 1		

CA RS Level	Service	FMID
CAR2107	LU01929	CCLXE00
	LU01862	CCLXE00
	LU01797	CCLXE00
	LU01655	CCLXE00
	LU01630	CCLXE00
	LU01562	CCLXE01
	LU01212	CCLXE01
	LU01211	CCLXE00
	LU01140	CCLXE01
CAR2106	LU01398	CCLXE00
	LU01310	CCLXE00
	LU01080	CCLXE00
	LU00913	CCLXE00
CAR2105	LU01117	CCLXE00
	LU01116	CCLXE00
	LU00998	CCLXE00
	LU00876	CCLXE00
	LU00741	CCLXE00
	LU00717	CCLXE00
	LU00679	CCLXE00
CAR2104	LU00716	CCLXE01
	LU00715	CCLXE00
	LU00677	CCLXE00
	LU00634	CCLXE00
	LU00633	CCLXE01
	LU00632	CCLXE00
	LU00610	CCLXE00
	LU00496	CCLXE00
	LU00477	CCLXE00
	LU00462	CCLXE01
	LU00442	CCLXE00
	LU00407	CCLXE00
	LU00361	CCLXE00
	LU00235	CCLXE00
CAR2103	LU00278	CCLXE00
	LU00210	CCLXE00
	LU00188	CCLXE00
	LU00122	CCLXE01
	LU00121	CCLXE00
CAR2102	SO15877	CCLXE01
	SO15876	CCLXE00
	LU00117	CCLXE00
	LU00113	CCLXE00
	LU00078	CCLXE00
	LU00077	CCLXE00
	LU00074	CCLXE00
	LU00067	CCLXE00

CA RS Level	Service	FMID
	LU00063	CCLXE00
	LU00060	CCLXE00
	LU00058	CCLXE00
	LU00057	CCLXE00
	LU00044	CCLXE01
	LU00040	CCLXE00
CAR2101	S015920	CCLXE00
	S015902	CCLXE00
	S015821	CCLXE01
	S015820	CCLXE00
	S015729	CCLXE00
	LU00028	CCLXE00
	LU00025	CCLXE00
CAR2012	S015758	CCLXE00
	S015662	CCLXE00
	S015610	CCLXE00
	S015578	CCLXE00
	S015569	CCLXE00
	S015565	CCLXE00
	S015526	CCLXE00
	S015515	CCLXE00
	S015505	CCLXE00
	S015502	CCLXE00
	S015497	CCLXE00
CAR2011	S015373	CCLXE00
	S015324	CCLXE00
	S015241	CCLXE01
	S015200	CCLXE01
	S015151	CCLXE00
	S015148	CCLXE01
	S015069	CCLXE00
	S015068	CCLXE01
	S015067	CCLXE00
	S014750	CCLXE00
CAR2010	S015022	CCLXE01
	S015018	CCLXE00
	S014993	CCLXE00
	S014932	CCLXE00
	S014903	CCLXE00
	S014875	CCLXE00
	S014871	CCLXE00
	S014857	CCLXE01
	S014824	CCLXE00
	S014801	CCLXE00
	S014646	CCLXE00
	S014644	CCLXE00
	S014609	CCLXE00

CA RS Level	Service	FMID
CAR2009	S014537	CCLXE00
	S014492	CCLXE01
	S014477	CCLXE00
	S014434	CCLXE01
	S014412	CCLXE00