

OPS/MVS for JES2/JES3 14.0
CA RS 2207 Service List

1

Service	Description	Type
LU05921	ADD UPDTYPE COMMAND TO SSMV3 POLICY MANAGER EDITOR.	PTF
LU06133	MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER	PTF
LU06134	MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER	PTF
LU06179	OPS/MVS WEB SERVICES FAILS TO LOG MESSAGES PROPERLY	PTF
LU06262	OPSJES2 FUNCTION SPOOL/LINE/MASI OPTIONS RETURNS BAD DATA	PTF
LU06342	MTC-A OPS/MVS REST API SERVER UPDATES	PTF
LU06343	MTC-A OPS/MVS REST API SERVER UPDATES	PTF
The CA RS 2207 service count for this release is 7		

OPS/MVS for JES2/JES3
CA RS 2207 Service List for CCLXE00

2

FMID	Service	Description	Type
CCLXE00	LU05921	ADD UPDTYPE COMMAND TO SSMV3 POLICY MANAGER EDITOR.	PTF
	LU06133	MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER	PTF
	LU06262	OPJSJES2 FUNCTION SPOOL/LINE/MASI OPTIONS RETURNS BAD DATA	PTF
	LU06342	MTC-A OPS/MVS REST API SERVER UPDATES	PTF
The CA RS 2207 service count for this FMID is 4			

OPS/MVS for JES2/JES3
CA RS 2207 Service List for CCLXE01

FMID	Service	Description	Type
CCLXE01	LU06134	MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER	PTF
	LU06179	OPS/MVS WEB SERVICES FAILS TO LOG MESSAGES PROPERLY	PTF
	LU06343	MTC-A OPS/MVS REST API SERVER UPDATES	PTF
The CA RS 2207 service count for this FMID is 3			

Service	Details																		
LU05921	LU05921 M.C.S. ENTRIES = ++PTF (LU05921) ADD UPDTYPE COMMAND TO SSMV3 POLICY MANAGER EDITOR. ENHANCEMENT DESCRIPTION: A new command (UPDTYPE) has been added to the SSMv3 policy manager. This command allows customers to copy changes to a user type definition to all resources in the policy that match that TYPE. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 16562 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00230-CLX140 DESC(ADD UPDTYPE COMMAND TO SSMV3 POLICY MANAGER EDITOR.). ++VER (Z038) FMID (CCLXE00) PRE (LU00677 LU00876 LU01398 LU02161 LU02417 LU02478 LU02545 LU02562 LU03011 LU03303 LU03790 LU04163 LU04341 LU04473 LU04575 LU04889 LU05260 S014412 S015151 S015578 S015610 S015662 S015902) SUP (LT02515 LT05921 LU02515) ++HOLD (LU05921) SYSTEM FMID(CCLXE00) REASON (ENH) DATE (22180) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> <tr> <td>SEQUENCE</td><td>After Apply</td></tr> <tr> <td>PURPOSE</td><td>Add UPDTYPE command to SSMV3 policy editor</td></tr> <tr> <td>USERS</td><td>All OPS/MVS users</td></tr> <tr> <td>AFFECTED</td><td></td></tr> <tr> <td>KNOWLEDGE</td><td>Knowledge of OPS/MVS installation</td></tr> <tr> <td>REQUIRED</td><td></td></tr> <tr> <td>ACCESS</td><td>Necessary OPS/MVS authorization</td></tr> <tr> <td>REQUIRED</td><td></td></tr> </table> ***** * STEPS TO PERFORM * ***** See the following topics in the OPS/MVS documentation set at http://techdoc.broadcom.com/opsmvs 'New UPDTYPE command added to SSMv3 Policy Resource Editor ' 'Primary Commands for the SSM Resource List Panel').	OPS/MVS	Version 14.0	SEQUENCE	After Apply	PURPOSE	Add UPDTYPE command to SSMV3 policy editor	USERS	All OPS/MVS users	AFFECTED		KNOWLEDGE	Knowledge of OPS/MVS installation	REQUIRED		ACCESS	Necessary OPS/MVS authorization	REQUIRED	
OPS/MVS	Version 14.0																		
SEQUENCE	After Apply																		
PURPOSE	Add UPDTYPE command to SSMV3 policy editor																		
USERS	All OPS/MVS users																		
AFFECTED																			
KNOWLEDGE	Knowledge of OPS/MVS installation																		
REQUIRED																			
ACCESS	Necessary OPS/MVS authorization																		
REQUIRED																			

Service	Details
LU06133	LU06133 M.C.S. ENTRIES = ++PTF (LU06133) MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER ENHANCEMENT DESCRIPTION: These PTFs deliver two enhancements: The new OPSLOG Manager component of Mainframe Team Center - Automation introduces the ability to view OPSLOG events from any OPS/MVS instance that is connected to MTC-A. This feature provides a modern web user interface that provides many of the same capabilities as OPSVIEW option 1 in ISPF, and replaces the OPSLOG WebView component. The new OPS/MVS REST API Server (OPSREST) acts as a broker to collect OPSLOG data from any OPS/MVS instance that is running on the same LPAR and return it to the REST requestor. The OPSLOG data provided by this new API server can be accessed using one of the following mechanisms: - OPSLOG Manager component of MTC-A - Alert Central REST API calls - User-written REST clients employing the OPS/MVS REST API protocol Related Problem: OPSMVS 16395 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00248-CLX140 DESC(MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER). ++VER (Z038) FMID (CCLXE00) PRE (LU00058 LU03513 LU03790 LU05807 S014824) SUP (LT02521 LT05470 LT06133 LU02521) ++IF FMID(CCLXE01) REQ(LU06134). ++HOLD (LU06133) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22168) COMMENT (<pre> +-----+ OPS/MVS Version 14.0 +-----+-----+ SEQUENCE After APPLY +-----+-----+ PURPOSE To activate load modules updated by this PTF +-----+-----+ USERS All OPS/MVS users AFFECTED +-----+-----+ KNOWLEDGE Basic z/OS systems programming skills REQUIRED +-----+-----+ ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS +-----+-----+ ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the </pre>

Service	Details
	specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details																
LU06134	M.C.S. ENTRIES = ++PTF (LU06134) MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER ENHANCEMENT DESCRIPTION: These PTFs deliver two enhancements: The new OPSLOG Manager component of Mainframe Team Center - Automation introduces the ability to view OPSLOG events from any OPS/MVS instance that is connected to MTC-A. This feature provides a modern web user interface that provides many of the same capabilities as OPSVIEW option 1 in ISPF, and replaces the OPSLOG WebView component. The new OPS/MVS REST API Server (OPSREST) acts as a broker to collect OPSLOG data from any OPS/MVS instance that is running on the same LPAR and return it to the REST requestor. The OPSLOG data provided by this new API server can be accessed using one of the following mechanisms: - OPSLOG Manager component of MTC-A - Alert Central REST API calls - User-written REST clients employing the OPS/MVS REST API protocol Related Problem: OPSMVS 16395 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved RO0248-CLX140 DESC (MTC-A OPSLOG MANAGER AND SUPPORTING OPS/MVS REST API SERVER) . ++VER (Z038) FMID (CCLXE01) PRE (LU00044 LU00122 LU00462 LU00633 LU01212 LU02570 LU03582 LU03791 LU03946 LU04002 LU04224 LU05148 LU05380 LU05432 LU05627 LU05691 LU06030 S014492 S014857 S015022 S015068 S015148 S015200 S015241 S015821 S015877) SUP (LT01162 LT05411 LT05452 LT05474 LT05480 LT05482 LT05838 LT06132 LT06134 ST14979) ++IF FMID(CCLXE00) REQ(LU06133) . ++HOLD (LU06134) SYSTEM FMID(CCLXE01) REASON (DOC) DATE (22168) COMMENT (***** * PUBLICATION * ***** <table><tr><td>SEQUENCE</td><td>Before implementing these new features</td></tr><tr><td>PURPOSE</td><td>To learn about these new features</td></tr><tr><td>USERS</td><td>All MTC-A users</td></tr><tr><td>AFFECTED</td><td></td></tr><tr><td>KNOWLEDGE</td><td>Knowledge of your OPS/MVS and MTC-A installations</td></tr><tr><td>REQUIRED</td><td></td></tr><tr><td>ACCESS</td><td>None</td></tr><tr><td>REQUIRED</td><td></td></tr></table> ***** * STEPS TO PERFORM *	SEQUENCE	Before implementing these new features	PURPOSE	To learn about these new features	USERS	All MTC-A users	AFFECTED		KNOWLEDGE	Knowledge of your OPS/MVS and MTC-A installations	REQUIRED		ACCESS	None	REQUIRED	
SEQUENCE	Before implementing these new features																
PURPOSE	To learn about these new features																
USERS	All MTC-A users																
AFFECTED																	
KNOWLEDGE	Knowledge of your OPS/MVS and MTC-A installations																
REQUIRED																	
ACCESS	None																
REQUIRED																	

Service	Details		
	***** For information about these enhancements, see the topic "New Features" in the OPS/MVS user documentation at https://techdocs.broadcom.com/opsmvs For information about installing the OPSREST server, see the topic "Deploy and Configure the OPS/MVS REST API". For information about using the OPS/MVS REST API, see the topic "Using the OPS/MVS REST API". For information about installing OPSLOG Manager, see the topic "Install OPSLOG Manager Prerequisites". For information about using OPSLOG Manager, see the topic "OPSLOG Manager".). ++HOLD (LU06134) SYSTEM FMID(CCLXE01) REASON (DYNACT) DATE (22168) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To deploy a new version of Mainframe Team Center - Automation USERS All OPS/MVS MTC-A users AFFECTED KNOWLEDGE Basic z/OS systems programming skills and knowledge of your new or existing MTC-A installation and configuration REQUIRED ACCESS - Read/write access to the USS directories where your new or existing installation of MTC-A resides REQUIRED - Authority to STOP and START your MTC-A Web Application ***** * STEPS TO PERFORM * ***** Step 1 - Run The MTC-A Configuration Batch Job Sample JCL to execute the configuration script, mtcacfg.sh, is provided in yourHLQ.CCLXCNTL(OPMOIACG). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Set CCLXCLS0 to the fully qualified MVS dataset name of the SMP/E CLIST target library installed by FMID CCLXxr0 OPS/MVS Base. (eg. 'yourHLQ.CCLXCLS0') 3. Set CCLSHFSM to the USS mount point of the zFS installed by FMID CLXxr1 OPS/MVS OPSLOG WebView and Web Features. 4. Set TOMCATCONF to the USS path of your deployed Tomcat server's "context" directory. Typically: <catalina_base>/conf/Catalina/localhost 5. Set MTCADepLOY to the USS path where you wish to deploy the MTCA Web App. A new directory called '/mtca' will be created on this path and will contain the mtcaApp.war as	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	well as '/conf' and '/log' sub-directories. The configuration script creates the MTC-A directory structure at your chosen deployment location and defines the context for MTC-A to your Tomcat installation. If a previous MTC-A installation exists, your current configuration is saved as 'MTCADeploy/mtca/conf/config.yaml.YY_MM_DD_hh_mm_ss'. Your configuration is then automatically merged and upgraded to the version supplied within this PTF. Verify the STDOUT of the configuration batch job for messages indicating the addition of fields to the 'conf.yaml' that must be set specifically for your site before MTC-A is restarted. If your '/mtca' directory is on path 'a/b/c/mtca' supply path '/a/b/c' as your value for the deploy location After executing the batch job, be sure to update the new OPSLOG Manager configuration section of the conf.yaml file if you wish to use the new OPSLOG Viewer functionality. Step 2 - Run The OPSREST ZFS Allocation Batch Job (first time only) Sample JCL to execute the configuration script is provided in yourHLQ.CCLXCNTL(CLXJSVZF). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Customize all the values in the JCL that are commented as "customize" 3. Submit the customized JCL Step 3 - Run The OPSREST Configuration Batch Job Sample JCL to execute the configuration script, opsRESTcfg.sh, is provided in yourHLQ.CCLXCNTL(CLXJSVCT). Before executing the batch job, make the following edits: 1. Include a valid job card 2. Customize all the values in the JCL that are commented as "customize" 3. Submit the customized JCL). ++HOLD (LU06134) SYSTEM FMID(CCLXE01) REASON (ENH) DATE (22168) COMMENT (<pre> +-----+ OPS/MVS Version 14.0 +-----+-----+ SEQUENCE Before implementing these new features +-----+-----+ PURPOSE To learn about these new features +-----+-----+ USERS All MTC-A users AFFECTED +-----+-----+ KNOWLEDGE Knowledge of your OPS/MVS and MTC-A installations REQUIRED +-----+-----+ ACCESS None REQUIRED +-----+-----+ ***** * STEPS TO PERFORM * ***** </pre>

Service	Details
	For information about these enhancements, see the cover letter of this PTF and the "New Features" topic in the OPS/MVS user documentation at https://techdocs.broadcom.com/opsmvs). LINK('..../opsREST.jar') PARM(PATHMODE(0,7,7,5)). LINK('..../opsRESTcfg.sh') PARM(PATHMODE(0,7,5,5)). LINK('..../application.yml') PARM(PATHMODE(0,7,7,5)). LINK('..../lib-opsmvs-le-31.so') PARM(PATHMODE(0,7,7,5)). LINK('..../libbcm-apisdk-security-31.so') PARM(PATHMODE(0,7,7,5)). LINK('..../libbcm-apisdk-attls-31.so') PARM(PATHMODE(0,7,7,5)). LINK('..../conf.yaml') PARM(PATHMODE(0,7,5,5)). LINK('..../mtcacfg.sh') PARM(PATHMODE(0,7,5,5)). LINK('..../mtcaApp.war') PARM(PATHMODE(0,7,5,5)).

Service	Details		
LU06179	LU06179 M.C.S. ENTRIES = ++PTF (LU06179) OPS/MVS WEB SERVICES FAILS TO LOG MESSAGES PROPERLY PROBLEM DESCRIPTION: The OPS/MVS Web Services fails to create an application log named webSvcListener.log under the log directory. SYMPTOMS: No application log. IMPACT: Customer cannot use the log for diagnostics because it is not created. CIRCUMVENTION: None PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 17181 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00249-CLX140 DESC(OPS/MVS WEB SERVICES FAILS TO LOG MESSAGES PROPERLY). ++VER (Z038) FMID (CCLXE01) PRE (LU00633 LU03791 LU04002 LU05148 LU05215 LU05380 S015821) SUP (CC15146 LT03165 LT03884 LT06179 LU03165 LU03884) ++HOLD (LU06179) SYSTEM FMID(CCLXE01) REASON (ACTION) DATE (22163) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After Apply PURPOSE To activate the fix USERS User's of the OPS/MVS Web Services AFFECTED KNOWLEDGE Web servers and USS directories REQUIRED ACCESS USS directories for Tomcat Web Server REQUIRED ***** * STEPS TO PERFORM * ***** 1. Update your OPS/MVS Web Services host server by copying the opsmvs.war file from the installation HFS to your runtime web server. See the following documentation for detailed instructions on how to deploy the new module. - Install and Configure CA OPS/MVS RESTful Web Services on Tomcat 2. Stop and restart your OPS/MVS web server STC so it recognizes	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	and uses the newly updated opsmvs.war file.). LINK('..../opwebsvc.config') PARM(PATHMODE(0,7,5,5)). LINK('..../opwscfg.sh') PARM(PATHMODE(0,7,5,5)). LINK('..../opwebsvc.env') PARM(PATHMODE(0,7,5,5)). LINK('..../opwebsvc.prop') PARM(PATHMODE(0,7,5,5)). LINK('..../OPWShttp.rex') PARM(PATHMODE(0,7,5,5)). LINK('..../opsmvs.war') PARM(PATHMODE(0,7,5,5)).

Service	Details		
LU06262	LU06262 M.C.S. ENTRIES = ++PTF (LU06262) OPSJES2 FUNCTION SPOOL/LINE/MASI OPTIONS RETURNS BAD DATA PROBLEM DESCRIPTION: OPS/REXX OPSJES2 function returns invalid data for the inquiries for SPOOL, LINE, and MASI (Multi-Access Spool Information). SYMPTOMS: Incorrect information is returned. IMPACT: Cannot use the OPSJES2 function to obtain information about SPOOL, LINE, and MASI. CIRCUMVENTION: Use z/OS JES2 commands to return corresponding information. PRODUCT(S) AFFECTED: OPS/MVS Release 13.5 OPS/MVS Version 14.0 Related Problem: OPSMVS 17023 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00251-CLX140 DESC(OPSJES2 FUNCTION SPOOL/LINE/MASI OPTIONS RETURNS BAD DATA). ++VER (Z038) FMID (CCLXE00) PRE (LU00442 LU03790) SUP (AL00442 LT05517 LT06262 LU05517) ++HOLD (LU06262) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22166) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To activate load modules updated by this PTF USERS All OPS/MVS users AFFECTED KNOWLEDGE Basic z/OS systems programming skills REQUIRED ACCESS - Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any REQUIRED deployed copies - Authority to issue MVS system commands - Authority to stop and start OPS/MVS ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD. Refer to GIM23903I messages in the SMPDOUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details
	CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details																						
LU06342	LU06342 M.C.S. ENTRIES = ++PTF (LU06342) MTC-A OPS/MVS REST API SERVER UPDATES PROBLEM DESCRIPTION: Updated code supporting the REST API Server: - Update ZOWE SDK to 2.2.0 - Remove extraneous trace messages in OPSLOG - Ensure FIND EVENT API works in all cases SYMPTOMS: - Extraneous trace messages in OPSLOG - FIND from OPSLOG Manager does not find API records IMPACT: Extraneous trace messages could obscure real problems. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 17514 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00252-CLX140 DESC (MTC-A OPS/MVS REST API SERVER UPDATES) . ++VER (Z038) FMID (CCLXE00) PRE (LU03513 LU03790 LU06133) SUP (LT06342) ++IF FMID(CCLXE01) REQ(LU06343) . ++HOLD (LU06342) SYSTEM FMID(CCLXE00) REASON (DYNACT) DATE (22179) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> -----+----- <table border="1"> <tr> <td>SEQUENCE</td><td>After APPLY</td></tr> </table> -----+----- <table border="1"> <tr> <td>PURPOSE</td><td>To activate load modules updated by this PTF</td></tr> </table> -----+----- <table border="1"> <tr> <td>USERS</td><td>All OPS/MVS users</td></tr> </table> <table border="1"> <tr> <td>AFFECTED</td><td></td></tr> </table> -----+----- <table border="1"> <tr> <td>KNOWLEDGE</td><td>Basic z/OS systems programming skills</td></tr> </table> <table border="1"> <tr> <td>REQUIRED</td><td></td></tr> </table> -----+----- <table border="1"> <tr> <td>ACCESS</td><td>- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any</td></tr> <tr> <td>REQUIRED</td><td>deployed copies</td></tr> <tr> <td></td><td>- Authority to issue MVS system commands</td></tr> <tr> <td></td><td>- Authority to stop and start OPS/MVS</td></tr> </table> -----+----- ***** * STEPS TO PERFORM * ***** 1. APPLY of this PTF updates SMP/E Target loadlib CCLXLOAD.	OPS/MVS	Version 14.0	SEQUENCE	After APPLY	PURPOSE	To activate load modules updated by this PTF	USERS	All OPS/MVS users	AFFECTED		KNOWLEDGE	Basic z/OS systems programming skills	REQUIRED		ACCESS	- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any	REQUIRED	deployed copies		- Authority to issue MVS system commands		- Authority to stop and start OPS/MVS
OPS/MVS	Version 14.0																						
SEQUENCE	After APPLY																						
PURPOSE	To activate load modules updated by this PTF																						
USERS	All OPS/MVS users																						
AFFECTED																							
KNOWLEDGE	Basic z/OS systems programming skills																						
REQUIRED																							
ACCESS	- Access to OPS/MVS SMP/E Target loadlib CCLXLOAD and any																						
REQUIRED	deployed copies																						
	- Authority to issue MVS system commands																						
	- Authority to stop and start OPS/MVS																						

Service	Details
	Refer to GIM23903I messages in the SMP/OUT to identify the specific load modules that are updated. 2. Copy the updated load modules from SMP/E Target loadlib CCLXLOAD to any other deployed copies, such as a loadlib in the OPSMAIN STEPLIB or the system link list (LNKLIST). 3. If the system library lookaside (LLA) program is managing any updated loadlib, you must refresh LLA by using MVS system command "F LLA,REFRESH" or some equivalent method. 4. If the system link pack area (LPA) contains any updated load module, you must refresh LPA by using MVS system command "SETPROG LPA" or some equivalent method. * Note that load module OPSAEX is commonly placed in LPA. 5. Stop and re-start OPS/MVS by using MVS system commands "P OPSS" and "S OPSS" or some equivalent method. * For possible alternatives to restarting OPS/MVS, see the topic "RELOAD Modules and RESTART Components" in the user documentation at https://techdocs.broadcom.com/opsmvs 6. TSO users must exit and re-enter OPSVIEW to activate any changes. Depending on how OPSVIEW is accessed, this may require a TSO logoff and logon.).

Service	Details		
LU06343	LU06343 M.C.S. ENTRIES = ++PTF (LU06343) MTC-A OPS/MVS REST API SERVER UPDATES PROBLEM DESCRIPTION: Updated code supporting the REST API Server: - Update ZOWE SDK to 2.2.0 - Remove extraneous trace messages in OPSLOG - Ensure FIND EVENT API works in all cases SYMPTOMS: - Extraneous trace messages in OPSLOG - FIND from OPSLOG Manager does not find API records IMPACT: Extraneous trace messages could obscure real problems. CIRCUMVENTION: None. PRODUCT(S) AFFECTED: OPS/MVS Version 14.0 Related Problem: OPSMVS 17514 (C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved R00252-CLX140 DESC (MTC-A OPS/MVS REST API SERVER UPDATES) . ++VER (Z038) FMID (CCLXE01) PRE (LU03791 LU06134) SUP (LT05411 LT05452 LT05474 LT05480 LT05482 LT06343) ++IF FMID(CCLXE00) REQ(LU06342) . ++HOLD (LU06343) SYSTEM FMID(CCLXE01) REASON (DYNACT) DATE (22179) COMMENT (<table border="1"> <tr> <td>OPS/MVS</td><td>Version 14.0</td></tr> </table> SEQUENCE After APPLY PURPOSE To deploy a new version of the OPS/MVS REST API server USERS All users of the OPS/MVS REST API, including users of AFFECTED MTC-A OPSLOG Viewer KNOWLEDGE Basic z/OS systems programming skills and knowledge of REQUIRED your OPS/MVS installation and configuration ACCESS - Read/write access to you OPS/MVS installation USS files REQUIRED and MVS data data sets - Authority to STOP and START your OPSREST server ***** * STEPS TO PERFORM * ***** To install the OPSREST server for the first time, see the topic	OPS/MVS	Version 14.0
OPS/MVS	Version 14.0		

Service	Details																					
	'Deploy and Configure the OPS/MVS REST API (OPSREST)' in the OPS/MVS user documentation at https://techdocs.broadcom.com/opsmvs To upgrade your existing OPSREST installation, follow these steps: (1) Stop the OPSREST server STC on z/OS using the STOP MVS console command: P OPSREST (2) Deploy the updated OPSREST server delivered by this PTF using the customized CLXJSVCT batch JCL that you used to first deploy the OPSREST server. The updated OPSREST directory structure is deployed to folder '<RESTMNT>/opsrest'. Your your current '<RESTMNT>/opsrest/application.yml' configuration file prior to the update is saved as file 'application.yml.YY_MM_DD_hh_mm_ss', then automatically merged with the updated version delivered by this PTF. (3) Examine the STDOUT of the CLXJSVCT configuration batch job. Look for messages indicating the addition of fields to the application.yml file that must be set specifically for your site before the OPSREST server is restarted. (4) Update the values of new fields that you identified in step 3. (5) Start the OPSREST server STC on z/OS using the START MVS console command: S OPSREST) . LINK('.../opsREST.jar') PARM(PATHMODE(0,7,7,5)). LINK('.../opsRESTcfg.sh') PARM(PATHMODE(0,7,5,5)). LINK('.../application.yml') PARM(PATHMODE(0,7,7,5)). LINK('.../lib-opsmvs-le-31.so') PARM(PATHMODE(0,7,7,5)). LINK('.../libbcm-apisdk-security-31.so') PARM(PATHMODE(0,7,7,5)). LINK('.../libbcm-apisdk-attls-31.so') PARM(PATHMODE(0,7,7,5)). <table><tr><td>MCS</td><td>LU05921</td><td>STARTS ON PAGE 0002</td></tr><tr><td>MCS</td><td>LU06133</td><td>STARTS ON PAGE 0003</td></tr><tr><td>MCS</td><td>LU06134</td><td>STARTS ON PAGE 0005</td></tr><tr><td>MCS</td><td>LU06179</td><td>STARTS ON PAGE 0009</td></tr><tr><td>MCS</td><td>LU06262</td><td>STARTS ON PAGE 0011</td></tr><tr><td>MCS</td><td>LU06342</td><td>STARTS ON PAGE 0013</td></tr><tr><td>MCS</td><td>LU06343</td><td>STARTS ON PAGE 0015</td></tr></table>	MCS	LU05921	STARTS ON PAGE 0002	MCS	LU06133	STARTS ON PAGE 0003	MCS	LU06134	STARTS ON PAGE 0005	MCS	LU06179	STARTS ON PAGE 0009	MCS	LU06262	STARTS ON PAGE 0011	MCS	LU06342	STARTS ON PAGE 0013	MCS	LU06343	STARTS ON PAGE 0015
MCS	LU05921	STARTS ON PAGE 0002																				
MCS	LU06133	STARTS ON PAGE 0003																				
MCS	LU06134	STARTS ON PAGE 0005																				
MCS	LU06179	STARTS ON PAGE 0009																				
MCS	LU06262	STARTS ON PAGE 0011																				
MCS	LU06342	STARTS ON PAGE 0013																				
MCS	LU06343	STARTS ON PAGE 0015																				

OPS/MVS for JES2/JES3 14.0
CA RS 2207 Product/Component Listing

19

Product Family	Product	Release
Systems Management	CA OPS/MVS BASE	14.00.00
The CA RS 2207 Product/Component Count for this release is 1		

CA RS Level	Service	FMID
CAR2207	LU06343	CCLXE01
	LU06342	CCLXE00
	LU06262	CCLXE00
	LU06179	CCLXE01
	LU06134	CCLXE01
	LU06133	CCLXE00
	LU05921	CCLXE00
CAR2206	LU06069	CCLXE00
	LU06030	CCLXE01
	LU05943	CCLXE01
	LU05807	CCLXE00
	LU05737	CCLXE00
	LU05612	CCLXE00
	LU05478	CCLXE00
CAR2205	LU05691	CCLXE01
	LU05627	CCLXE01
	LU05517	CCLXE00
	LU05432	CCLXE01
	LU05380	CCLXE01
	LU05358	CCLXE00
CAR2204	LU05306	CCLXE00
	LU05297	CCLXE00
	LU05260	CCLXE00
	LU05234	CCLXE00
	LU05216	CCLXE00
	LU05215	CCLXE01
	LU05214	CCLXE00
	LU05148	CCLXE01
	LU05096	CCLXE00
	LU05064	CCLXE00
	LU05045	CCLXE00
	LU05016	CCLXE00
	LU05009	CCLXE00
	LU04902	CCLXE00
	LU04793	CCLXE00
CAR2203	LU04913	CCLXE00
	LU04889	CCLXE00
	LU04888	CCLXE00
	LU04768	CCLXE00
	LU04738	CCLXE00
	LU04575	CCLXE00
	LU04473	CCLXE00
	LU03819	CCLXE00
CAR2202	LU04341	CCLXE00
	LU04292	CCLXE00
	LU04224	CCLXE01
	LU04194	CCLXE00

CA RS Level	Service	FMID
	LU04184	CCLXE00
	LU04168	CCLXE00
	LU04163	CCLXE00
	LU04106	CCLXE00
	LU03744	CCLXE00
	LU03513	CCLXE00
CAR2201	LU04002	CCLXE01
	LU03946	CCLXE01
	LU03884	CCLXE01
	LU03852	CCLXE00
	LU03792	CCLXE03
	LU03791	CCLXE01
	LU03790	CCLXE00
	LU03721	CCLXE00
	LU03582	CCLXE01
CAR2112	LU03548	CCLXE00
	LU03512	CCLXE03
	LU03481	CCLXE00
	LU03418	CCLXE00
	LU03387	CCLXE00
	LU03373	CCLXE01
	LU03334	CCLXE00
	LU03258	CCLXE00
CAR2111	LU03303	CCLXE00
	LU03179	CCLXE00
	LU03165	CCLXE01
	LU03149	CCLXE00
	LU03137	CCLXE00
	LU03119	CCLXE00
	LU03099	CCLXE00
	LU03084	CCLXE00
	LU03082	CCLXE00
	LU03072	CCLXE00
	LU03049	CCLXE00
	LU03011	CCLXE00
CAR2110	LU02790	CCLXE00
	LU02570	CCLXE01
	LU02514	CCLXE00
	LU02484	CCLXE00
	LU02253	CCLXE01
	LU02252	CCLXE00
CAR2109	LU02562	CCLXE00
	LU02545	CCLXE00
	LU02521	CCLXE00
	LU02515	CCLXE00
	LU02478	CCLXE00
	LU02417	CCLXE00

CA RS Level	Service	FMID
	LU02313	CCLXE00
	LU02285	CCLXE00
	LU02105	CCLXE00
CAR2108	LU02209	CCLXE00
	LU02161	CCLXE00
	LU02080	CCLXE00
	LU02046	CCLXE00
	LU02021	CCLXE00
	LU01967	CCLXE00
CAR2107	LU01929	CCLXE00
	LU01862	CCLXE00
	LU01797	CCLXE00
	LU01655	CCLXE00
	LU01630	CCLXE00
	LU01562	CCLXE01
	LU01212	CCLXE01
	LU01211	CCLXE00
	LU01140	CCLXE01
CAR2106	LU01398	CCLXE00
	LU01310	CCLXE00
	LU01080	CCLXE00
	LU00913	CCLXE00
CAR2105	LU01117	CCLXE00
	LU01116	CCLXE00
	LU00998	CCLXE00
	LU00876	CCLXE00
	LU00741	CCLXE00
	LU00717	CCLXE00
	LU00679	CCLXE00
CAR2104	LU00716	CCLXE01
	LU00715	CCLXE00
	LU00677	CCLXE00
	LU00634	CCLXE00
	LU00633	CCLXE01
	LU00632	CCLXE00
	LU00610	CCLXE00
	LU00496	CCLXE00
	LU00477	CCLXE00
	LU00462	CCLXE01
	LU00442	CCLXE00
	LU00407	CCLXE00
	LU00361	CCLXE00
	LU00235	CCLXE00
CAR2103	LU00278	CCLXE00
	LU00210	CCLXE00
	LU00188	CCLXE00
	LU00122	CCLXE01

CA RS Level	Service	FMID
	LU00121	CCLXE00
CAR2102	S015877	CCLXE01
	S015876	CCLXE00
	LU00117	CCLXE00
	LU00113	CCLXE00
	LU00078	CCLXE00
	LU00077	CCLXE00
	LU00074	CCLXE00
	LU00067	CCLXE00
	LU00063	CCLXE00
	LU00060	CCLXE00
	LU00058	CCLXE00
	LU00057	CCLXE00
	LU00044	CCLXE01
	LU00040	CCLXE00
CAR2101	S015920	CCLXE00
	S015902	CCLXE00
	S015821	CCLXE01
	S015820	CCLXE00
	S015729	CCLXE00
	LU00028	CCLXE00
	LU00025	CCLXE00
CAR2012	S015758	CCLXE00
	S015662	CCLXE00
	S015610	CCLXE00
	S015578	CCLXE00
	S015569	CCLXE00
	S015565	CCLXE00
	S015526	CCLXE00
	S015515	CCLXE00
	S015505	CCLXE00
	S015502	CCLXE00
	S015497	CCLXE00
CAR2011	S015373	CCLXE00
	S015324	CCLXE00
	S015241	CCLXE01
	S015200	CCLXE01
	S015151	CCLXE00
	S015148	CCLXE01
	S015069	CCLXE00
	S015068	CCLXE01
	S015067	CCLXE00
	S014750	CCLXE00
CAR2010	S015022	CCLXE01
	S015018	CCLXE00
	S014993	CCLXE00
	S014932	CCLXE00

CA RS Level	Service	FMID
	S014903	CCLXE00
	S014875	CCLXE00
	S014871	CCLXE00
	S014857	CCLXE01
	S014824	CCLXE00
	S014801	CCLXE00
	S014646	CCLXE00
	S014644	CCLXE00
	S014609	CCLXE00
CAR2009	S014537	CCLXE00
	S014492	CCLXE01
	S014477	CCLXE00
	S014434	CCLXE01
	S014412	CCLXE00