

MF SECURITY INSIGHTS PLATFORM 1.0
CA RS 2210 Service List

1

Service	Description	Type
LU07080	SIZCFG MINIFICATION AND ADDED SECONDARY LPAR MISSING FILES	PTF
The CA RS 2210 service count for this release is 1		

MF SECURITY INSIGHTS PLATFORM
CA RS 2210 Service List for CFIN100

FMID	Service	Description	Type
CFIN100	LU07080	SIZCFG MINIFICATION AND ADDED SECONDARY LPAR MISSING FILES	PTF
The CA RS 2210 service count for this FMID is 1			

Service	Details												
LU07080	<p>LU07080 M.C.S. ENTRIES = ++PTF (LU07080)</p> <p>SIZCFG MINIFICATION AND ADDED SECONDARY LPAR MISSING FILES</p> <p>PROBLEM DESCRIPTION:</p> <ol style="list-style-type: none"> Files are missing for a Secondary LPAR deployment and configuration. Re-use of configuration members (SIZCFGx) on Secondary LPARs is tedious due to an increasing number of variables. The Specified Resource Access Report might have a mismatch between the Entitlement Count and the list of users or groups returned in the report details drill-down. <p>SYMPTOMS:</p> <ol style="list-style-type: none"> Files are missing for a Secondary LPAR deployment and configuration. Edits of SIZCFGx on Secondary LPARs require the user to go through all the variables, but only a subset of the variables require modification (for example, definitions such as Host Name, Ports, and so on.) Mismatch between Entitlement Count and user/group lists in Specified Resource Access Report details. <p>IMPACT:</p> <ol style="list-style-type: none"> Users cannot start STC (SIZSRV2U) on Secondary LPARs. Overall Deployment and Configuration time increases across multiple LPARs. Users might see inconsistent counts for Entitlement Count versus user/group lists in the Specified Resource Access Report details. <p>CIRCUMVENTION:</p> <ol style="list-style-type: none"> NONE. NONE. <p>PRODUCT(S) AFFECTED:</p> <p>MF SECURITY INSIGHTS PLATFORM Version 1.0</p> <p>Related Problem:</p> <p>SECINS 18060</p> <p>(C) 2022 Broadcom Inc and/or its subsidiaries; All rights reserved</p> <p>R00050-SIN010</p> <p>DESC(SIZCFG MINIFICATION AND ADDED SECONDARY LPAR MISSING FILES).</p> <p>++VER (Z038)</p> <p>FMID (CFIN100)</p> <p>PRE (LU00579 LU02508 LU03001 LU05182 LU05479 LU06424 S015202 S016125)</p> <p>SUP (LT07032 LT07035 LT07080)</p> <p>++HOLD (LU07080) SYSTEM FMID(CFIN100)</p> <p>REASON (ACTION) DATE (22250)</p> <p>COMMENT (</p> <table border="1"> <tr> <td>MF SECURITY INSIGHTS PLATFORM</td><td>Version 1.0</td></tr> <tr> <td>SEQUENCE</td><td>After Apply</td></tr> <tr> <td>PURPOSE</td><td>Describe the steps required to fully implement this PTF</td></tr> <tr> <td>USERS</td><td>All Mainframe Security Insights Platform users</td></tr> <tr> <td>AFFECTED</td><td></td></tr> <tr> <td>KNOWLEDGE</td><td>ISPF edit and job submission experience</td></tr> </table> <p>)</p>	MF SECURITY INSIGHTS PLATFORM	Version 1.0	SEQUENCE	After Apply	PURPOSE	Describe the steps required to fully implement this PTF	USERS	All Mainframe Security Insights Platform users	AFFECTED		KNOWLEDGE	ISPF edit and job submission experience
MF SECURITY INSIGHTS PLATFORM	Version 1.0												
SEQUENCE	After Apply												
PURPOSE	Describe the steps required to fully implement this PTF												
USERS	All Mainframe Security Insights Platform users												
AFFECTED													
KNOWLEDGE	ISPF edit and job submission experience												

Service	Details
	<pre> REQUIRED +-----+-----+ ACCESS Access to Mainframe Security Insights Platform target REQUIRED and runtime libraries +-----+-----+ ***** * STEPS TO PERFORM * ***** Please Note: We have moved the configuration parameters with usable default values into a new member, SIZDFT. The configuration parameters that require modification remain in SIZCFGx members. For existing installations, the parameters in SIZDFT are duplicates of some parameters in your existing SIZCFG member. You do not need to edit SIZDFT. The product evaluates the values in SIZCFG over SIZDFT, so your values are not overwritten by SIZDFT. Review the online documentation for deploying maintenance to the runtime environment. 1. Stop the Primary LPAR started task (SIZSRVRD, by default). 2. Stop the Secondary LPAR started task (SIZSRV2D, by default) on each deployed secondary LPAR. 3. Start the Primary LPAR started task (SIZSRVRU, by default). 4. Start the Secondary LPAR started task (SIZSRV2U, by default) on each deployed secondary LPAR.). LINK('..lib/si_configurator.jar') PARM(PATHMODE(0,7,7,5)) SHSCRIPT(SIZMKDIR,PRE). LINK('..lib/si_orc.jar') PARM(PATHMODE(0,7,7,5)) SHSCRIPT(SIZMKDIR,PRE). LINK('..util/si_dep11.sh') PARM(PATHMODE(0,7,7,5)). LINK('..util/si_insights2.sh') PARM(PATHMODE(0,7,7,5)). MCS LU07080 STARTS ON PAGE 0002 </pre>

Product Family	Product	Release
Security	CA SECURITY INSIGHT	01.00.00
The CA RS 2210 Product/Component Count for this release is 1		

MF SECURITY INSIGHTS PLATFORM 1.0
All CA RS Levels Service List

CA RS Level	Service	FMID
CAR2210	LU07080	CFIN100
CAR2208	S016125	CFIN100
	S015202	CFIN100
	S015201	CFIN100
	LU06424	CFIN100
	LU05479	CFIN100
	LU05182	CFIN100
	LU03001	CFIN100
	LU02508	CFIN100
	LU00579	CFIN100