

CA Configuration Automation®

Message Reference Guide

r12.8



This Documentation, which includes embedded help systems and electronically distributed materials, (hereinafter referred to as the "Documentation") is for your informational purposes only and is subject to change or withdrawal by CA at any time.

This Documentation may not be copied, transferred, reproduced, disclosed, modified or duplicated, in whole or in part, without the prior written consent of CA. This Documentation is confidential and proprietary information of CA and may not be disclosed by you or used for any purpose other than as may be permitted in (i) a separate agreement between you and CA governing your use of the CA software to which the Documentation relates; or (ii) a separate confidentiality agreement between you and CA.

Notwithstanding the foregoing, if you are a licensed user of the software product(s) addressed in the Documentation, you may print or otherwise make available a reasonable number of copies of the Documentation for internal use by you and your employees in connection with that software, provided that all CA copyright notices and legends are affixed to each reproduced copy.

The right to print or otherwise make available copies of the Documentation is limited to the period during which the applicable license for such software remains in full force and effect. Should the license terminate for any reason, it is your responsibility to certify in writing to CA that all copies and partial copies of the Documentation have been returned to CA or destroyed.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CA PROVIDES THIS DOCUMENTATION "AS IS" WITHOUT WARRANTY OF ANY KIND, INCLUDING WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NONINFRINGEMENT. IN NO EVENT WILL CA BE LIABLE TO YOU OR ANY THIRD PARTY FOR ANY LOSS OR DAMAGE, DIRECT OR INDIRECT, FROM THE USE OF THIS DOCUMENTATION, INCLUDING WITHOUT LIMITATION, LOST PROFITS, LOST INVESTMENT, BUSINESS INTERRUPTION, GOODWILL, OR LOST DATA, EVEN IF CA IS EXPRESSLY ADVISED IN ADVANCE OF THE POSSIBILITY OF SUCH LOSS OR DAMAGE.

The use of any software product referenced in the Documentation is governed by the applicable license agreement and such license agreement is not modified in any way by the terms of this notice.

The manufacturer of this Documentation is CA.

Provided with "Restricted Rights." Use, duplication or disclosure by the United States Government is subject to the restrictions set forth in FAR Sections 12.212, 52.227-14, and 52.227-19(c)(1) - (2) and DFARS Section 252.227-7014(b)(3), as applicable, or their successors.

Copyright © 2013 CA. All rights reserved. All trademarks, trade names, service marks, and logos referenced herein belong to their respective companies.

CA Technologies Product References

This document references the following CA Technologies products:

- CA® Embedded Entitlements Manager (CA EEM)

Contact CA Technologies

Contact CA Support

For your convenience, CA Technologies provides one site where you can access the information that you need for your Home Office, Small Business, and Enterprise CA Technologies products. At <http://ca.com/support>, you can access the following resources:

- Online and telephone contact information for technical assistance and customer services
- Information about user communities and forums
- Product and documentation downloads
- CA Support policies and guidelines
- Other helpful resources appropriate for your product

Providing Feedback About Product Documentation

If you have comments or questions about CA Technologies product documentation, you can send a message to techpubs@ca.com.

To provide feedback about CA Technologies product documentation, complete our short customer survey which is available on the CA Support website at <http://ca.com/docs>.

Contents

Chapter 1: Introduction

9

Chapter 2: Error Messages

11

Agent Error Messages	11
Blueprint Error Messages	12
Blueprint Group Error Messages	37
Compliance Jobs Error Messages	38
Component Error Messages	42
Change Detection and Compare Error Messages	44
Catalyst Jobs Error Messages	59
Catalyst Profile Error Messages	62
Common Schedule Error Messages	63
Discovery and Refresh Error Messages	67
Data Migration Error Messages	78
Dashboard Error Messages	86
Export and Import Error Messages	89
Graph Error Messages	90
General Error Messages	94
Global Variable Error Messages	100
Notification Error Messages	102
NDG Error Messages	104
NDG Discovery Error Messages	105
Profile Error Messages	107
Property Error Messages	143
Rule Compliance Error Messages	145
Rules Error Messages	149
Rule Group Error Messages	150
Remediation Jobs Error Messages	151
Remediation Profile Error Messages	158
Remediation History Warning Messages	160
Remote Agent Installation Error Messages	160
Reports Error Messages	168
SDK Error Messages	181
Server Error Messages	185
Structure Class Error Messages	200
Server Groups Error Messages	206
Security Certificate Error Messages	209

Service Error Messages	219
Service Profile Error Messages	226
Snapshot Error Messages	226
Tenant Error Messages.....	230
Table View Error Messages	232
Task Wizard Error Messages	234

Chapter 3: Warning Messages 235

Agent Warning Messages.....	235
Blueprint Warning Messages	240
Blueprint Group Warning Messages	247
Compliance Jobs Warning Messages	247
Catalyst Jobs Warning Messages.....	248
Catalyst Profile Warning Messages	248
Change Detection and Compare Warning Messages	249
Common Schedule Warning Messages	252
Component Warning Messages	253
Discovery and Refresh Warning Messages	253
Data Migration Warning Messages	262
Global Variable Warning Messages.....	263
Graph Warning Messages	263
General Warning Messages.....	264
NDG Discovery Warning Messages	265
Network Scan Warning Messages	266
Profile Warning Messages.....	266
Remediation Jobs Warning Messages.....	276
Remediation Profile Warning Messages	277
Rules Warning Messages.....	280
Rule Compliance Warning Messages	280
Rule Group Warning Messages	281
Reports Warning Messages.....	282
Server Warning Messages	283
Server Groups Warning Messages	288
Structure Class Warning Messages	289
Security Certificate Warning Messages.....	291
Service Warning Messages.....	296
Service Profile Warning Messages	301
Snapshot Warning Messages	301
Storage Area Network Warning Messages.....	303
Property Warning messages	304
Tenant Warning Messages	304

Table View Warning Messages.....	305
Task Wizard Warning Messages.....	305
UI Export-Import of Profiles Warning Messages.....	306

Chapter 4: Information Messages 309

Blueprint Informational Messages	309
Blueprint Group Informational Messages	336
Compliance Jobs Informational Messages	338
Components Informational Messages	341
Catalyst Jobs Informational Messages	341
Catalyst Profile Informational Messages.....	344
Certificate Informational Messages	348
Component Informational Messages	349
Change Detection and Compare Informational Messages.....	350
Global Variable Informational Messages	355
Graph Informational Messages	357
General Informational Messages	360
Data Migration Informational Messages.....	363
Dashboard Informational Messages	381
Export and Import Informational Messages	383
Management Profiles informational Messages	384
NDG Informational Messages	384
NDG Discovery Informational Messages	386
Discovery and Refresh Informational Messages	387
Profile Informational Messages	397
Property Informational Messages.....	412
Rules informational Messages	413
Rule Compliance Informational Messages	414
Rule Group Informational Messages.....	419
Reports Informational Messages	422
Remediation Jobs Informational Messages	426
Remediation Profile Informational Messages.....	435
Remediation History Informational Messages.....	440
Remote Agent Installation Informational Messages.....	441
Server Informational Messages.....	443
Security Certificate Informational Messages	453
Structure Class Informational Messages	457
Server Groups Informational Messages	460
Service Information Messages	463
Service Profile informational Messages	469
Snapshot Information Messages.....	470

Storage Area Network Informational Messages	476
Table View Informational Messages	477
Tenant Information Messages	479
Task Wizard Informational Messages	479
Table View Informational Messages	480
UI Export-Import of Profiles Informational Messages	483

Chapter 1: Introduction

This guide explains the messages that CA Configuration Automation can display. The guide explains each message string, the reason for the message, and (where appropriate) the suggested solution.

The guide includes messages that are useful to resolve configuration issues, environment issues, and prerequisites. Messages that are internal to CA Configuration Automation are excluded. You require CA Technical Support Assistance to resolve internal messages.

Note: If the application displays a Security Violation error, log in as an Administrator or Architect to complete the operation.

CA Configuration Automation displays the following message types:

Error

 Informs you of a specific issue and how you can resolve it.

Warning

 Alerts you to a potential error and can require you to act to avoid the error.

Informational

 Displays information, but does not require you to act.

The messages are categorized depending on the operations CA Configuration Automation operations you perform.

Chapter 2: Error Messages

This section explains the error messages that you see while performing the change detection and compare operation. Error messages tell you that an error has occurred and the action you required to take to resolve the situation.

Agent Error Messages

This section explains the error messages that you see while performing the agent operations in CA Configuration Automation.

CCA-AG-5701

Server Connection : Failed

Reason:

The target computer might not be reachable.

Action:

Ensure that you can ping the target computer from the CA Configuration Automation Server.

CCA-AG-5702

Server Access : Not responding

Reason:

CA Configuration Automation Agent service might not be running on the target machine, or firewall is enabled and blocking incoming connections on the target machine.

Action:

Ensure that the CA Configuration Automation Agent service is running on the target server and the agent port is open and accepting incoming requests.

CCA-AG-5704

Agent Could not be contacted since End Point <end point url> is not available.

Reason:

The CA Configuration Automation Agent service might not be running on the target machine, or firewall is enabled and blocking incoming connections on the target machine.

Action:

Ensure that the CA Configuration Automation Agent service is running and responding to the test server.

CCA-AG-5729

WMI Remote execution failed: <error>

Reason:

Failed to execute a script on the remote server.

Action:

Ensure that the WMI services are running on the remote server and user has required permissions to execute the scripts. If necessary, contact CA Technologies Technical Support for further assistance.

Blueprint Error Messages

This section explains the error messages that you see while performing the blueprint operations in CA Configuration Automation.

CCA-BP-4051

Component Version Required.

Reason:

Component version is missing while creating or updating a blueprint.

Action:

Provide a component version.

CCA-BP-4052**Blueprint Version Required.****Reason:**

Blueprint version is missing while creating or updating a blueprint.

Action:

Provide a blueprint version.

CCA-BP-4053**Please choose one of the Component Grouping Options before continuing.****Reason:**

The Component Grouping Options (nesting) is not selected while creating or updating the blueprint.

Action:

Select one of the Component Grouping Options (Nesting).

CCA-BP-4055**Search From Required.****Reason:**

Search From is missing while creating or updating a blueprint.

Action:

Specify a value for the Search From.

CCA-BP-4056**Name is required.****Reason:**

Indicator Name is not provided while creating or updating the blueprint.

Action:

Specify the indicator Name.

CCA-BP-4057

Either the path or the depth must be specified.

Reason:

Missing the path, or the depth information while adding or updating an indicator.

Action:

Specify either the path, or the depth information.

CCA-BP-4058

Either the path or the depth can be specified.

Reason:

Both the path and depth information is specified while adding or updating an indicator.

Action:

Either the path or depth information is required.

CCA-BP-4059

Path Required.

Reason:

Missing path information while adding or updating an indicator.

Action:

Specify the path information.

CCA-BP-4060

Depth Required.

Reason:

Missing depth information while adding or updating an indicator.

Action:

Specify the depth information.

CCA-BP-4062**Indicator Name Invalid.****Reason:**

Indicator Name contains wildcards like * or *.*.

Action:

Specify other characters along with the provided wildcards.

CCA-BP-4063**Cannot add a name that already exists.****Reason:**

The specified name exists.

Action:

Provide a new name.

CCA-BP-4064**Primary Ports Required.****Reason:**

Primary ports information is not provided.

Action:

Provide primary ports information.

CCA-BP-4065**Name is required.****Reason:**

Name is not provided.

Action:

Provide a name.

CCA-BP-4066

Query Required.

Reason:

Query is not provided.

Action:

Provide a query.

CCA-BP-4067

Port Required.

Reason:

No port information is provided for the Network Probe directive type.

Action:

Provide a port number.

CCA-BP-4068

User ID Required.

Reason:

User ID is not provided for the Get LDAP directive type.

Action:

Provide User ID information.

CCA-BP-4069

Password Required.

Reason:

Password is not provided for the Get LDAP directive type.

Action:

Provide the password information.

CCA-BP-4070

Either the Parser or the Structure Class is required.

Reason:

The parser or structure class is not selected.

Action:

Select either the parser or structure class.

CCA-BP-4073

Only the Parser or the Structure Class can be specified.

Reason:

Both parser and structure class information are specified.

Action:

Select either the parser or structure class.

CCA-BP-4074

Version Required.

Reason:

Version is not specified.

Action:

Provide version information.

CCA-BP-4078

Name is required.

Reason:

Name is not provided.

Action:

Provide name.

CCA-BP-4079

Search Depth must be a positive integer less than 100.

Reason:

Search depth is not in the range between 0 to 99.

Action:

Provide a value within the range between 0 to 99.

CCA-BP-4080

Depth From Root must be a positive integer less than 100.

Reason:

Depth from the root value is not in the range between 0 to 99.

Action:

Provide a value in the range between 0 to 99.

CCA-BP-4081

Search From must be a path that begins at file or registry root. For example, \HKEY_LOCAL_MACHINE, /usr/local or C:\Program Files

Reason:

Incorrect Search From specified.

Action:

Search From must be a path that begins at the file or registry root. For example, \HKEY_LOCAL_MACHINE, /usr/local or C:\Program Files.

CCA-BP-4082

Managed Depth must be a positive integer less than 100.

Reason:

Managed Depth is not in the range between 0 to 99.

Action:

Provide a value in the range between 0 to 99.

CCA-BP-4083

Max Files must be an integer 0 or greater.

Reason:

Max Files value is not 0 or greater than 0.

Action:

Provide an integer value in the range between 0 or greater.

CCA-BP-4084

Max Elements must be an integer 0 or greater.

Reason:

Max Elements value is not 0 or greater than 0.

Action:

Provide an integer value in the range between 0 or greater.

CCA-BP-4085

Set the Blueprint Root before adding elements from the browser.

Reason:

Blueprint Root is not set in Browse Dialog while adding elements to the tree.

Action:

Set the Blueprint Root.

CCA-BP-4086

You must first add a database definition in the Data Management section.

Reason:

No database definition is added in the Data Management section.

Action:

Add a database definition in Data Management section.

CCA-BP-4102

Translation <translation> cannot be deleted. It is currently used by this or another blueprint.

Reason:

Translation <translation> is used by this blueprint or another blueprint.

Action:

Ensure that none of the blueprints are using the Translation <translation>, and perform the operation.

CCA-BP-4103

Translate From Required.

Reason:

Translate From value is not provided.

Action:

Either delete the row or provide the Translate From.

CCA-BP-4104

Duplicate Translate From.

Reason:

Translate From already exists.

Action:

Provide a new Translate From or delete the row.

CCA-BP-4121

Invalid blueprint name. The following characters are not allowed: < > ; : " ' * + = \ \ / | ?

Reason:

Blueprint name contains unsupported characters.

Action:

Provide a blueprint name without the unsupported special characters.

CCA-BP-4137

Blueprint already exists.

Reason:

The blueprint name already exists.

Action:

Provide a unique blueprint name.

CCA-BP-4138

Duplicate Option.

Reason:

The parser option name already exists.

Action:

Select other parser option names, or delete all the duplicate parser options.

CCA-BP-4141

Value must be an integer.

Reason:

The parser option value must be an integer.

Action:

Provide an integer value.

CCA-BP-4142

Value has a minimum of <n>.

Reason:

The parser option value is less than <n>.

Action:

Provide a parser option value which is either equal or greater than <n>.

CCA-BP-4143

Value has a maximum of <n>.

Reason:

The parser option value is greater than <n>.

Action:

Provide a parser option value which is either equal or lesser than <n>.

CCA-BP-4145

Invalid name. Must be valid regular expression.

Reason:

Invalid regular expression.

Action:

Correct the regular expression.

CCA-BP-4148

Export cannot be performed. User is not authorized to perform this operation.

Reason:

You do not have permission to perform this operation.

Action:

Log in to CA Configuration Automation as an administrator or architect.

CCA-BP-4149

Error while getting all blueprints

Reason:

An exception occurred while getting all the blueprints using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-BP-4160

Cannot delete database <database>. It is used in a configuration data definition.

Reason:

The database <database> is used in the Configuration Data Definition, and cannot be deleted.

Action:

Delete all the Configuration Data Definitions which uses this database, and try deleting the database <database>.

CCA-BP-4161

Import Failed. Could not delete Managed Databases of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Managed Database does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the Blueprint.

CCA-BP-4162

Import Failed. Could not delete Parameter Directive of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Parameter Directive does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4163

Import Failed. Could not delete Verification Directive of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Verification Directive does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4164

Import Failed. Could not delete Executable Directive of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Executable Directive does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4165

Import Failed. Could not delete Managed Database Table of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Managed Database does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4166

Import Failed. Could not delete Configuration Database Query of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Configuration Database does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4167

Import Failed. Could not delete Configuration File of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Configuration File does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4168

Blueprint already exists.

Reason:

Blueprint name already exists.

Action:

Provide a unique new blueprint name.

CCA-BP-4169

Cannot delete parameter because discovery data exists.

Reason:

Cannot delete the parameter because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the parameter.

CCA-BP-4170

Cannot delete filter because discovery data exists.

Reason:

Cannot delete the filter because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the filter.

CCA-BP-4171

Cannot delete group because discovery data exists.

Reason:

Cannot delete the group because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the group.

CCA-BP-4172

Cannot delete file because discovery data exists.

Reason:

Cannot delete the file because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the file.

CCA-BP-4173

Cannot delete database because discovery data exists.

Reason:

Cannot delete the database because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the database.

CCA-BP-4174

Cannot delete query because discovery data exists.

Reason:

Cannot delete the query because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the query.

CCA-BP-4175

Cannot delete blueprint because discovery data exists.

Reason:

Cannot delete the blueprint because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the blueprint.

CCA-BP-4176

Cannot delete blueprint because it is used in a Management Profile.

Reason:

Cannot delete the blueprint because it is used in a management profile.

Action:

Ensure that this blueprint is not used in any of the Management profiles, and delete the blueprint.

CCA-BP-4178

Invalid numeric value. The operation is applicable to numeric value only.

Reason:

Invalid numeric value is provided while creating or updating a Rule.

Action:

Provide a valid numeric value.

CCA-BP-4179

Invalid integer range. Both values must be positive integer or zero.

Reason:

Invalid integer range is provided while creating or updating a Rule.

Action:

The integer values must be equal to 0 or greater.

CCA-BP-4180

Cannot delete database table because discovery data exists.

Reason:

Cannot delete the database table because the corresponding discovery data exists.

Action:

Delete all the discovered components corresponding to this blueprint, and delete the database table.

CCA-BP-4181

Invalid translation name. The following characters are not allowed: < > ; : " ' * + = \ \ / | ?

Reason:

The following characters are not allowed as part of the translation name: < > ; : " ' * + = \ \ / | ?

Action:

Provide a translation name without containing the specified characters.

CCA-BP-4182

Invalid component version. The following characters are not allowed: < > ; : " " + = \\ / ?

Reason:

The following characters are not allowed as part of the component version: < > ; : " " + = \\ / ?

Action:

Provide a component version without containing the specified characters.

CCA-BP-4183

Invalid blueprint version. The following characters are not allowed: < > ; : " " + = \\ / ?

Reason:

The following characters are not allowed as part of the blueprint version: < > ; : " " + = \\ / ?

Action:

Provide a blueprint version without containing the specified characters.

CCA-BP-4203

Invalid Path: <path name>.

Reason:

The path <path name> is not valid.

Action:

Provide correct path <path name>, and perform the browse operation.

CCA-BP-4204

Import Failed. Could not delete Macros of the blueprint as they are in use.

Reason:

Cannot import the blueprint because the Macros does not exist in the JAR file but exists in the discovered components.

Action:

Delete all the discovered components corresponding to this blueprint, and import the blueprint.

CCA-BP-4205

Primary Ports value must be a single integer value in the valid range of TCP ports (1-65535), a comma-separated list of valid port numbers, or a range of ports specified as <port_number>-<port_number>. Comma separated-values and ranges can be combined, for example 21,22,30-40,100.

Reason:

Incorrect value is specified for the primary ports.

Action:

Specify the value as follows:

- a single integer value in the valid range of TCP ports (1-65535)
- a comma-separated list of valid port numbers,
- a range of ports that are specified as <port_number>-<port_number>

The comma separated-values and ranges can be combined, for example, 21,22,30-40,100.

CCA-BP-4206

Alternate Ports value must be a single integer value in the valid range of TCP ports (1-65535), a comma-separated list of valid port numbers, or a range of ports specified as <port_number>-<port_number>. Comma separated-values and ranges can be combined, for example 21,22,30-40,100.

Reason:

Incorrect value is specified for the alternate ports.

Action:

Specify the value as follows:

- a single integer value in the valid range of TCP ports (1-65535)
- a comma-separated list of valid port numbers,
- a range of ports that are specified as <port_number>-<port_number>

The comma separated-values and ranges can be combined, for example, 21,22,30-40,100.

CCA-BP-4210

Invalid parameter name. The following characters are not allowed: < > " &

Reason:

The parameter name has unsupported characters.

Action:

Provide a parameter name without the unsupported special characters.

CCA-BP-4213

Registry browsing is only available for Windows servers.

Reason:

Registry browsing is only available for the Windows Servers.

Action:

No action is required.

CCA-BP-4215

LOG Level

Relationship Type is required for relationship key 'yes'.

Reason:

Relationship Type is required when relationship key is selected as yes for value details in Directory Detail Panel or FSC Parameter Detail or Parameter Detail Panel.

Action:

Provide a Relationship Type.

CCA-BP-4216

Relationship Type is not applicable for relationship key 'no'.

Reason:

Relationship Type is not required when relationship key is selected as no for the value details in Directory Detail Panel or FSC Parameter Detail or Parameter Detail Panel.

Action:

Do not provide a Relationship Type.

CCA-BP-4220

Security violation error while exporting the blueprints.

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect.

CCA-BP-4222

Error while writing XML for the blueprint <blueprint name> into the file stream.

Reason:

Unable to write XML file for the blueprint <blueprint name> while exporting the blueprint

Action:

Do the following:

- You have the required permissions to write to file system.
- System has enough free disk space.

If necessary, contact CA Technologies Technical Support for further assistance.

CCA-BP-4225

Duplicate object exception while importing blueprint

Reason:

Parser already exists while importing the blueprint.

Action:

Ensure that you select Overwrite Existing blueprints to overwrite the existing blueprints.

CCA-BP-4227

Security violation while importing blueprint:

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect.

CCA-BP-4237

Security violation error while exporting the blueprint groups.

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect.

CCA-BP-4241

Security violation while importing translation: <translation name>

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect.

CCA-BP-4401

Fill the parameter name before adding a new row

Reason:

Parameter name is missing in the Response Parsing Options while creating, or updating a new row.

Action:

Provide a parameter name, or delete the row.

CCA-BP-4402

Fill the xpath before adding a new row

Reason:

xpath missing in Response Parsing Options while creating or updating a row.

Action:

Provide an xpath name.

CCA-BP-4403

WSDL load failed, check the WSDL URL

Reason:

Failed to connect to the server, or the Endpoint URL is not available.

Action:

Ensure that the server is reachable and the Endpoint URL is accessible using a browser. Verify exception stack trace in the cca.log file, and if the problem still exists contact CA Technologies Technical Support for further assistance.

CCA-BP-4404

Unable to retrieve the list of services in the WSDL

Reason:

An error occurred while retrieving the list of services in the WSDL.

Action:

Open the Endpoint URL in a browser, and verify a service available in the result. Verify exception stack trace in the cca.log file, and if the problem still exists contact CA Technologies Technical Support for further assistance.

CCA-BP-4405

Unable to retrieve the list of bindings for the service <service name>

Reason:

An error occurred while retrieving the list of bindings for the service <service name>.

Action:

Open the Endpoint URL in a browser and verify a binding available in the result. Verify exception stack trace in the cca.log file, and if the problem still exists contact CA Technologies Technical Support for further assistance.

CCA-BP-4406**Unable to retrieve the list of operations for the binding <binding name>****Reason:**

An error occurred while retrieving the list of operations for the binding <binding name>.

Action:

Open the Endpoint URL in a browser and verify operations available in the result for the binding <binding name>. Verify exception stack trace in the cca.log file, and if the problem still exists contact CA Technologies Technical Support for further assistance.

CCA-BP-4407**Unable to retrieve the default URL for the binding <binding name>****Reason:**

An error occurred while retrieving the default URL for the binding <binding name>.

Action:

Open the Endpoint URL in a browser and verify that the default URL is available in the result. Verify exception stack trace in the cca.log file, and if the problem still exists contact CA Technologies Technical Support for further assistance.

CCA-BP-4409**WSDL URL is required.****Reason:**

No WSDL URL is provided.

Action:

Provide a WSDL URL.

CCA-BP-4410**Step Name is required.****Reason:**

No step name is provided while creating or the updating a Step.

Action:

Provide a step name.

CCA-BP-4411

Service is required.

Reason:

No service name is provided.

Action:

Select a service from the available services.

CCA-BP-4412

Binding is required.

Reason:

No Binding information is provided.

Action:

Select a binding from the available bindings.

CCA-BP-4413

Operation is required.

Reason:

No operation information is provided.

Action:

Select an operation from the available operations.

CCA-BP-4414

Endpoint URL is required.

Reason:

No Endpoint URL is provided.

Action:

Provide an Endpoint URL.

CCA-BP-4415

SOAP Request XML is required.

Reason:

No SOAP Request URL is provided.

Action:

Provide a SOAP Request URL.

CCA-BP-4421

Step output parameter <parameter name> already exists.

Reason:

Step output parameter <parameter name> already exists.

Action:

Provide a new output parameter name, or delete the duplicate entries.

Blueprint Group Error Messages

This section explains the error messages that you see while performing the blueprint group operations in CA Configuration Automation.

CCA-BG-4505

Name is required.

Reason:

Name is not provided.

Action:

Provide Blueprint Group Name.

CCA-BG-4506

Blueprint Group <blueprint group> already exists.

Reason:

Blueprint group <blueprint group> already exists.

Action:

Provide a new Blueprint Group name.

CCA-BG-4509

Blueprint group cannot be deleted. It is used in one or more Management Profiles.

Reason:

Blueprint group cannot be deleted. The blueprint is used in one or more management profiles.

Action:

Ensure that none of the management profiles are using this Blueprint Group, and perform the operation.

CCA-BG-4511

Blueprint Group <blueprint group> already exists.

Reason:

The Blueprint Group <blueprint group> already exists.

Action:

Provide a new name.

Compliance Jobs Error Messages

This section explains the error messages that you see while performing the compliance jobs in CA Configuration Automation.

CCA-CM-9007

Compliance Job Name is required.

Reason:

Compliance Job name is not provided.

Action:

Provide a compliance job name.

CCA-CM-9008

Compliance Job <jobname> already exists.

Reason:

The compliance Job <jobname> already exists.

Action:

Provide a unique job name.

CCA-CM-9030

At least one Rule Group is required in a Compliance Job.

Reason:

No rule group is selected.

Action:

Select at least one Rule Group while creating or updating the compliance Job.

CCA-CM-9031

User is not authorized to schedule compliance job <jobname>, error message - <error>.

Reason:

User does not have permissions to run or schedule the compliance job.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to run or schedule the compliance job <jobname>.

CCA-CM-9032

Cannot create compliance job <jobname> because of scheduling failure, error message - <error>.

Reason:

The scheduling of the compliance job failed.

Action:

Verify the scheduling options.

CCA-CM-9033

Cannot update compliance job <jobname> because of scheduling failure, error message - <error>.

Reason:

The scheduling of the compliance job failed.

Action:

Verify the scheduling options.

CCA-CM-9034

Error while getting compliance job/compliance history.

Reason:

An exception occurred while retrieving the compliance job or the compliance history details using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CM-9035

Error while running compliance job <jobname>.

Reason:

An exception occurred while running the compliance job <jobname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CM-9036

Error while getting compliance result.

Reason:

An exception occurred while retrieving the compliance result using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CM-9037

Error while adding/updating compliance job <jobname>.

Reason:

An exception occurred while adding or updating the compliance job <jobname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CM-9038**Error while deleting compliance job <jobname>.****Reason:**

An exception occurred while deleting the compliance job <jobname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CM-9039**No Valid Rule Groups specified. At least one Rule Group is required in a Compliance Job.****Reason:**

No Valid Rule Groups specified.

Action:

Set at least one valid Rule Group while creating or updating the compliance Job.

CCA-CM-9040**No results found for the given result uuid.****Reason:**

No results available for a compliance job

Action:

Ensure that the result uuid is valid and exists in CCA Server. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CM-9041

Compliance Job Name is too long.

Reason:

The compliance Job Name is too long.

Action:

Ensure that job name length should not exceed 200.

Component Error Messages

This section explains the error messages that you see while performing the component operations in CA Configuration Automation.

CCA-CM-3560

This action applies to components in Inventoried or Managed state

Reason:

The components are not in managed state while performing the component refresh operation.

Action:

Ensure that the selected blueprints are available in discover and manage section of Blueprints tab in the management profile, so that all the components will be in manage state after the discovery operation.

CCA-CM-9307

Error while getting components for Server/Service/Snapshot with UUID < Server/Service/Snapshot uuid>

Reason:

An exception occurred while retrieving components for server through the SDK API.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CM-9308**Error while getting folders for component with UUID <componentuuid>****Reason:**

An exception occurred while getting the component folders with the component uuid.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CM-9311**Component <componentname> not found****Reason:**

Component is not present to open in the launch in context.

Action:

Check the component availability in CA Configuration Automation server.

CCA-CM-9313**Error while getting component with UUID <componentuuid>****Reason:**

An exception occurred while retrieving the component details from CA Configuration Automation DB.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CM-9314**Error while getting sub components for component with UUID <componentuuid>****Reason:**

An exception occurred while getting the sub components details from CA Configuration Automation DB.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CM-9321

Scheduled component refresh on server <servername> failed. User <username> is not authorized to perform this operation.

Reason:

You do not have permissions to perform the server component refresh operation.

Action:

Log in to CA Configuration Automation as an administration or architect to perform the server component refresh operation.

CCA-CM-9322

CCA-CM-9322: Scheduled component refresh on service <servicename> failed. User <username> is not authorized to perform this operation.

Reason:

You do not have permissions to perform service component refresh operation.

Action:

Log in to CA Configuration Automation as an administration or architect to perform the service component refresh operation.

Change Detection and Compare Error Messages

This section explains the error messages that you see while performing the change detection and compare operations in CA Configuration Automation.

CCA-DF-9101

Source date required.

Reason:

The source date is not provided.

Action:

Provide a source date.

CCA-DF-9102

Target date required.

Reason:

The target date was not provided.

Action:

Provide a target date.

CCA-DF-9103

One or more folders required.

Reason:

The selected folders field is empty.

Action:

Select the required folders.

CCA-DF-9104

One or more categories required.

Reason:

The selected categories field is empty.

Action:

Select the required categories.

CCA-DF-9105

One or more weights required.

Reason:

The selected weights field is empty.

Action:

Select the required weights.

CCA-DF-9107

Invalid type of change.

Reason:

An invalid type of change is provided while filtering the change detection or compare results in the flat table.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9109

Select source component.

Reason:

The source component value is not provided.

Action:

Provide a source component.

CCA-DF-9110

Select target components.

Reason:

The target component is not selected.

Action:

Select a target component.

CCA-DF-9111

Invalid source date. The date provided is not in the format MM/DD/YYYY.

Reason:

The source date is invalid.

Action:

Provide the source date in MM/DD/YYYY format.

CCA-DF-9112

Invalid target date. The date provided is not in the format MM/DD/YYYY.

Reason:

The target date is invalid.

Action:

Provide the target date in MM/DD/YYYY format.

CCA-DF-9113**Error while performing Server compare (source server <servername>).****Reason:**

An Exception occurred while performing the server compare operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DF-9114**Error while performing Service compare(source service <servicename>).****Reason:**

An exception occurred while performing the service compare operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DF-9115**Error while performing Server change detection (servers <servernamelist>).****Reason:**

An exception occurred while performing the server change detection operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DF-9116

Error while performing Service change detection (services <servicenamelist>).

Reason:

An exception occurred while performing the service change detection operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DF-9119

Service change detection failed, error message – <error>.

Reason:

The change detection operation failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9121

Server change detection failed, error message -<error>.

Reason:

The change detection operation failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9123

Invalid source service, no change detection and compare operations will be performed for service <servicename>.

Reason:

The source service <servicename> is not available.

Action:

Create the service, and discover service data.

CCA-DF-9124

Missing service snapshot or no server in the snapshot, no change detection and compare operations will be performed for service <servicename>.

Reason:

The service snapshot is missing to perform the change detection and compare operations.

Action:

Create a snapshot for service <servicename>.

CCA-DF-9125

Invalid target service, no change detection and compare operations will be performed for service <servicename>.

Reason:

The target service <servicename> is not available.

Action:

Create <servicename> service to discover the service data.

CCA-DF-9126

Invalid source server, no change detection and compare operations will be performed for server <servername>.

Reason:

The source server <servername> is not available.

Action:

Create a server <servername> to discover the server data.

CCA-DF-9127

Missing server snapshot, no change detection and compare operations will be performed for server <servername>.

Reason:

The server snapshot is missing.

Action:

Create a snapshot for the server <servername>.

CCA-DF-9128

Invalid target server, no change detection and compare operations will be performed for server <servername>.

Reason:

The target server <servername> is not available.

Action:

Create a server <servername> to discover the server data.

CCA-DF-9134

Found inconsistent file data. A difference detected in object UUID <uuid> but it does not exist in directory hierarchy.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9136

Found inconsistent registry value data. A difference detected in object UUID <uuid> but it does not exist in registry hierarchy.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9139

Found inconsistent configuration group in file data. A difference detected in object UUID <uuid> but it does not exist in group hierarchy.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9141

Found inconsistent configuration parameter in file data. A difference detected in object UUID <uuid> but it does not exist in group hierarchy.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9143

Found inconsistent configuration parameter in executable data. A difference detected in object UUID <uuid> but it does not exist in directive hierarchy.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9149

Cannot find data for registry key, UUID=<uuid>.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9151

Cannot find data for configuration group key, UUID=<uuid>.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9165

For both source and target data, server snapshots are missing, no change detection or compare operations will be performed for server <servername>.

Reason:

Server snapshots are missing for the selected source and target data.

Action:

Create snapshot for both the source and target data in the server <servername>.

CCA-DF-9166

For both source and target data, service snapshots or servers are missing, no change detection or compare operations will be performed for service <servicename>.

Reason:

The service snapshots are missing for both selected source and target data.

Action:

Create snapshot for the source and target data in the service <servicename>.

CCA-DF-9167

For both source and target data, server snapshots are missing, no change detection or compare operations will be performed for servers <servername1> and <servername2>.

Reason:

The server snapshots are missing for both selected source and target data.

Action:

Create snapshot for server <servername1>, and the server <servername2> for source and target data.

CCA-DF-9168

For both source and target data, service snapshots or servers are missing, no change detection or compare operations will be performed for services <servicename1> and <servicename2>.

Reason:

For both selected source and target data, service snapshots are missing.

Action:

Create snapshot for the service <servicename1> and the service <servicename2> for source and target data.

CCA-DF-9179

Server <servername> is in unmanaged state, no change detection or compare operation will be performed.

Reason:

The server <servername> is in unmanaged state.

Action:

Change the server <servername> state to managed.

CCA-DF-9180

Both source server <servername1> and target server <servername2> are in unmanaged state, no change detection or compare operation will be performed.

Reason:

The source server <servername1>, and target server <servername2> are in unmanaged state

Action:

Change the state of source server <servername1> and target server <servername2> to managed.

CCA-DF-9181

Source server <servername> is in unmanaged state, no change detection or compare operation will be performed.

Reason:

The source server <servername> is in unmanaged state.

Action:

Change the source server <servername> state to managed.

CCA-DF-9182

Target server <servername> is in unmanaged state, no change detection or compare operation will be performed.

Reason:

The target server <servername> is in unmanaged state.

Action:

Change the target server <servername> state to managed.

CCA-DF-9189

Missing hash values in keys of managed registry. Change detection and compare operation cannot be performed.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9191

Cannot find directory UUID for file object <objectname>. Change detection and compare operation cannot be performed.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9193

Value is null in directory UUID mapping. Change detection and compare operation cannot be performed.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9195

Value is null in registry UUID mapping. Change detection and compare operation cannot be performed.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9197

Change detection on server <servername> between <servicename1> and <servicename2> completed with error.

Reason:

The change detection operation failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9199

Compare server <servername1> snapshot <snapshotname1> to server <servname2> snapshot <snapshotname2> completed with error.

Reason:

The change detection operation failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9201

Change detection on service <servicename> between <snapshotname1> and <snapshotname2> completed with error.

Reason:

The change detection operation failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9203

Compare service <servicename1> snapshot <snapshotname1> to service <servicename2> snapshot <snapshotname2> completed with error.

Reason:

The compare operation failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9206

Cannot find data for configuration executable, executable UUID=<uuid>.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-DF-9207

Invalid server <servername> in service <servicename>, no change detection operations will be performed for server.

Reason:

The server <servername> is not available to perform the change detection operation.

Action:

Create the server <servername> as part of the service <servicename>, then rediscover the service data.

CCA-DF-9208

For both source and target data, server snapshots are missing, no change detection operations will be performed for server <servername> in service <servicename>.

Reason:

The components of the server <servername> are not available as part of the selected source data and target data in the service <servicename>.

Action:

Ensure that the components of the server <servername> are available as part of the selected source data and target data in the service <servicename>.

CCA-DF-9211

Invalid source server, no compare operations will be performed for server <servername> in service <servicename>.

Reason:

The server <servername> is not available.

Action:

Create Server <servername> as part of the service <servicename>, then rediscover the service data.

CCA-DF-9212

Invalid target server, no compare operations will be performed for server <servername> in service <servicename>.

Reason:

The server <servername> is not available to perform the compare operation.

Action:

Create the server <servername> as part of the service <servicename>, then rediscover the service data.

CCA-DF-9213

For both source and target data, server snapshots are missing, no compare operations will be performed between server <servername1> in service <servicename1> and server <servername2> in service <servicename2>.

Reason:

The components of the server <servername1> and <servername2> are not available as part of the corresponding selected source and target data.

Action:

Ensure that the components of the server <servername1> and <servername2> are available as part of the corresponding selected source and target data.

CCA-DF-9214

Identical snapshots are used for server change detection.

Reason:

The selected snapshots for the change detection operation are same.

Action:

Select different snapshot types for the change detection operation.

CCA-DF-9218

Identical snapshots are used for service change detection.

Reason:

The selected snapshots for the change detection operation are same.

Action:

Select different snapshot types for the change detection operation.

CCA-DF-9177

No source snapshot selected.

Reason:

The source snapshot is not provided.

Action:

Provide a valid source snapshot.

CCA-DF-9178

No target snapshot selected.

Reason:

The target snapshot is not provided.

Action:

Provide a valid target snapshot.

CCA-DF-9204

Missing hash value in configuration file <file>. Change detection and compare operation cannot be performed.

Reason:

The discovered data is inconsistent.

Action:

Contact CA Technologies Technical Support for further assistance.

Catalyst Jobs Error Messages

This section explains the error messages that you see while performing the catalyst jobs in CA Configuration Automation.

CCA-CJ-9904

Name is required.

Reason:

No name value is required.

Action:

Provide a name.

CCA-CJ-9908

Catalyst Job <job name> already exists.

Reason:

The <job name> already exists.

Action:

Provide another <job name>.

CCA-CJ-9910

Please select at least one service or server group or server.

Reason:

No services or servers or server groups are selected while saving the catalyst job.

Action:

Select any one or more servers, services, server groups.

CCA-CJ-9913

Name is too long.

Reason:

Name length is greater than 200 characters.

Action:

Ensure that the name length is not greater than 200 characters.

CCA-CJ-9915

Opening Catalyst Web View failed. Please configure property <catalyst.server.name> and <catalyst.server.httpport> in Administration > Configuration > Properties.

Reason:

Either or both the catalyst server name or server port is not provided.

Action:

Provide both the <catalyst.server.name> and <catalyst.server.httpport> values in Administration, Configuration, Properties.

CCA-CJ-9931

Catalyst User Name required

Reason:

The catalyst username is not provided during the testing of the connector status.

Action:

Provide a valid catalyst user name.

CCA-CJ-9932

Password Required

Reason:

Catalyst password is not provided during the testing of the connector status.

Action:

Provide the catalyst password.

CCA-CJ-9934

The node <node name> seems to be unreachable

Reason:

The application could not connect to the Catalyst container server to test the connector status.

Action:

Verify the Catalyst server container connectivity through a server ping. Contact CA Technologies Technical Support for further assistance.

CCA-CJ-9935

Operation failed for the node <nodename> : <reason>

Reason:

The <reason> describes why the operation failed.

Action:

Respond according to the reported the reason. If the reason is *unauthorized*, ensure that you provide valid credentials during the connector status testing.

CCA-CJ-9936

No Connectors connected to CCA Server

Reason:

No connectors are installed for the CCA Server. To verify whether the connectors are installed, view the CCA Integrations tab under the Administrator, Diagnostics tab.

Action:

Install CCA Connector for the CCA Server. Contact CA Technologies Technical Support for further assistance.

Catalyst Profile Error Messages

This section explains the error messages that you see while performing the catalyst profile operations in CA Configuration Automation.

CCA-PL-3915

Cannot create Catalyst Job <job name> because of scheduling failure, error message - <error>

Reason:

Scheduling error occurred while creating a catalyst job.

Action:

If the error message is similar to "The specified time has already passed. Schedule will never trigger", correct the schedule and finish creating the catalyst job <job name>. For any other errors, contact CA Technologies Technical Support for further assistance.

CCA-PL-3904

Catalyst Attributes Profile <profile name> already exists.

Reason:

The profile <profile name> already exists.

Action:

Provide a new name.

CCA-PL-3918

Cannot update Catalyst Job <job name> because of scheduling failure, error message - <error>.

Reason:

A scheduling error occurred while updating the catalyst job.

Action:

If the error message is similar to "The specified time has already passed. Schedule will never trigger", correct the schedule and finish updating the catalyst job <job name>. For other errors, contact CA Technologies Technical Support for further assistance.

Common Schedule Error Messages

This section explains the error messages that you see while performing the common schedule operations in CA Configuration Automation.

CCA-SH-9001

Schedule Time should be greater than current time.

Reason:

Schedule time is less than CCA server time.

Action:

The schedule time must be greater than the CCA server time.

CCA-SH-9002

Schedule End Date should be greater than or equal to Begin Date.

Reason:

Schedule End Date less than the begin Date.

Action:

The schedule end date must be greater than or equal to the begin date.

CCA-SH-9003

The time provided is not in the format DD/MM/YYYY HH:mm:ssAM.

Reason:

The time is not in the DD/MM/YYYY HH:mm:ssAM format.

Action:

Provide time in DD/MM/YYYY HH:mm:ssAM format.

CCA-SH-9004

The begin date provided is not in the format DD/MM/YYYY.

Reason:

The begin date is not in the DD/MM/YYYY format.

Action:

Provide the begin date in DD/MM/YYYY format.

CCA-SH-9005

The end date provided is not in the format DD/MM/YYYY.

Reason:

The end date is not in the DD/MM/YYYY format.

Action:

Provide end date in DD/MM/YYYY format.

CCA-SH-9006

Days is required.

Reason:

Days are not selected after selecting frequency.

Action:

Select days for the given frequency.

CCA-SH-9007

Frequency is required. The task is not scheduled.

Reason:

Frequency is not selected.

Action:

Select the frequency while scheduling the tasks later in the Tasks tab.

CCA-SH-9009

Job name supply is empty!

Reason:

The job name is empty.

Action:

Provide the job name.

CCA-SH-9010

Based on configured schedule, the given trigger will never fire.

Reason:

Based on the configured schedule days for frequency, the given trigger will never fire.

Action:

Provide the correct days for the given frequency. The select days should be less than or equal to the end date, and greater than the begin date.

CCA-SH-9011

No days specified for trigger.

Reason:

No days are selected.

Action:

Specify days for trigger.

CCA-SH-9012

No dates specified for trigger.

Reason:

No dates are selected.

Action:

Specify dates for trigger.

CCA-SH-9013

Invalid end date. Schedule will never trigger.

Reason:

The end date is not valid.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-SH-9016

The specified time has already passed. Schedule will never trigger.

Reason:

Schedule time is less than the current time.

Action:

The schedule time must be greater than the current time.

Discovery and Refresh Error Messages

This section explains the error messages that you see while performing the discovery and refresh operations in CA Configuration Automation.

CCA-DIS-8633

Invalid SSH Username

Reason:

SSH Username is not valid.

Action:

Provide a valid SSH username.

CCA-DIS-8510

Blueprint <blueprintname> is not found.

Reason:

The Blueprint name <blueprintname> in the URL does not exist in CA Configuration Automation server.

Action:

Provide a valid blueprint name in the URL.

CCA-DIS-8511

Component <componentname> is not found for refresh.

Reason:

The Component <componentname> in the URL does not exist in the given server.

Action:

Provide a valid component name in the URL.

CCA-DIS-8515

**Discovery cannot communicate with the <accessmode> on server <servername>.
Discovery has been terminated, Error message=<error>**

Reason:

The possible reasons are as follows:

- Invalid details (for example, access mode, port) are provided in the access profile that is assigned to the server
- The service (Agent/SSH/Telnet/WMI) is not responding or running.

Action:

Do the following:

- Ensure that the service (Agent/SSH/Telnet) corresponding to the assigned access mode is running on the target server <servername>.
- Provide the correct details in the access profile which is assigned to the server <servername>.
- Verify that the test server action is successful.

CCA-DIS-8518

Discovery failed on Server <servername>, Error message=<error>.

Reason:

The possible reasons are as follows:

- Invalid platform is set to the server.
- Communication to the server <servername> is lost while doing the discovery operation.
- The service (Agent/SSH/Telnet/WMI) is not responding.

Action:

Do the following:

- Provide a valid platform and ensure that the test server operation is successful.
- Use the latest CA Configuration Automation agent version if the access mode type is agent.
- Verify the log data in the cca.log file. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8523

Refresh failed on Server <servername>, error message - <error>.

Reason:

Possible reasons are as follows:

- The communication to the server <servername> is lost while performing the refresh operation.
- The service (Agent/SSH/Telnet/WMI) is not responding.

Action:

Do the following:

- Ensure that the test server operation is successful.
- Verify the log data in the cca.log file. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8547

Component discovery failed on Server <servername>, Component root <rootpath> and blueprint name <blueprintname>, Error message = <error>.

Reason:

The communication to the server <servername> is lost while performing the discovery operation.

Action:

Do one of the following:

- Ensure that the service (Agent/SSH/Telnet/WMI) corresponding to the assigned access mode is running on the target server <servername>.
- Verify that the test server operation is successful.

CCA-DIS-8548

Component refresh failed on Server <servername>, Component root <rootpath> and blueprint name <blueprintname>, Error message = <error>.

Reason:

The communication to the server <servername> is lost while performing the refresh operation.

Action:

Ensure that the service (Agent/SSH/Telnet/WMI) corresponding to the assigned access mode is running on the target server <servername>. Verify that the test server operation is successful.

CCA-DIS-8563

Caught 'Parser' exception during component discovery on Server <servername>, Component Root: <rootpath>, File Name: <file>, Error Message: <error>, Parser:<parsername>, Lexer: <lexername>, Blueprint Name: <blueprintname>. See CCA log file on <hostname> for stream content that was passed to parser.

Reason:

An exception occurred while parsing file <file> is using a specified parser class.

Action:

View the CA Configuration log file on the <hostname> for the stream content that is provided to the parser. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8564

Caught 'Parser' exception during component refresh on Server <servername>, Component root <rootpath> and filename <file>, Error message = <error>.

Reason:

An exception occurred while parsing file <file> using a specified parser class.

Action:

See CA Configuration Automation log file on the <hostname> for the stream content that is provided to the parser. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8569

Discovery canceled for Server <servername> because it reaches time limit of <minutes> minutes.

Reason:

The discovery operation exceeds the time limit configured in the management profile assigned to the server <servername>.

Action:

Increase the Discovery Time Limit value in the management profile assigned to the server <servername>.

CCA-DIS-8583

Refresh failed on Service <servicename>, error message - <error>.

Reason:

The management profile that is assigned to service <servicename> is disabled.

Action:

Ensure that the management profile that is assigned to the service <servicename> is enabled. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8584

Discovery failed on Service <servicename>, error message - <error>.

Reason:

The management profile that is assigned to the service <servicename> is disabled.

Action:

Ensure that the management profile that is assigned to the service <servicename> is enabled. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8588

Server test failed for Server <servername>. No Access Profile Assigned to the Server

Reason:

Access Profile is not assigned to the server <servername>.

Action:

Assign access profile with proper access mode to the server <servername>.

CCA-DIS-8589

Server test failed for Server <servername>. Agent connection cannot be established

Reason:

The possible reasons are as follows:

- Either that the CA Configuration Automation agent service is not running or using the old CA Configuration Automation agent.
- Invalid ports are assigned in the access profile.

Action:

Do the following:

- Ensure that the CA Configuration Automation agent service is running on the server <servername> and set the valid port in the assigned access profile.
- Use the latest CA Configuration Automation agent version.

CCA-DIS-8590

Server test failed for Server <servername>. SSH username and password are wrong, or SSH connection cannot be established

Reason:

The possible reasons are as follows:

- Invalid SSH user name and password are provided in the access profile that is assigned to the server<servername>.
- The SSH service is not running on Server <servername>

Action:

Provide a correct SSH username and password in the assigned access profile and ensure that the SSH service is running on the server <servername>.

CCA-DIS-8591

Cannot communicate with the <accessmode> on server <servername>. Discovery has been terminated.

Reason:

The possible reasons are as follows:

- Invalid details (for example, access mode, port) are provided in the access profile assigned to the server
- The service (Agent/SSH/Telnet) is not responding or running.

Action:

Do the following:

- Ensure service (Agent/SSH/Telnet/ WMI) corresponding to assigned access mode is running on the target server <servername>.
- Provide valid details in the access profile which is assigned to the server <servername>.
- Verify that the status of the test server action is successful.

CCA-DIS-8592

Cannot communicate with the <accessmode> on server <servername>. Refresh has been terminated, Error message=<error>.

Reason:

The possible reasons are as follows:

- Invalid details (for example, access mode, port) are provided in the access profile that is assigned to the server
- The service (Agent/SSH/Telnet) is not responding or running.

Action:

Do the following:

- Ensure service (Agent/SSH/Telnet) corresponding to assigned access mode is running on the target server <servername>.
- Provide valid details in the access profile that is assigned to server <servername>.
- Verify that the status of the test server action is successful.

CCA-DIS-8593

Cannot communicate with the <accessmode> on server <servername>. Refresh has been terminated.

Reason:

The possible reasons are as follows:

- Invalid details (for example, access mode, port) are provided in the access profile that is assigned to the server.
- The service (Agent/SSH/Telnet) is not responding or running.

Action:

Do the following:

- Ensure the service (Agent/SSH/Telnet/ WMI) corresponding to assigned access mode is running on the target server <servername>.
- Provide valid details in the access profile that is assigned to the server<servername>.
- Verify that status of the test server action is successful.

CCA-DIS-8594

No access profile is assigned to server <servername>. Refresh has been terminated.

Reason:

Access profile is not assigned to the server <servername>.

Action:

Assign access profile with proper access mode to the server <servername>.

CCA-DIS-8595

No access profile is assigned to server <servername>. Discovery has been terminated.

Reason:

Access profile is not assigned to the server <servername>.

Action:

Assign access profile with proper access mode to the server <servername>.

CCA-DIS-8596

Discovery failed for Service <servicename>

Reason:

No servers exist in service or cannot communicate to the servers in the service <servicename> using corresponding assigned access profile. So discovery failed for all servers.

Action:

Do the following:

- Ensure that the servers exist in service and assign the access profile with proper access mode and other required details to all servers in the service <servicename>.
- Verify that the status of the test server operation is successful for all servers in service.

CCA-DIS-8597

Refresh failed for Service <servicename>

Reason:

There are no servers in service <servicename> or cannot communicate to the servers in service <servicename> using corresponding assigned access profile. So, refresh failed for all servers.

Action:

Do the following:

- Ensure that the servers exist in the service <servicename>.
- Assign access profile with proper access mode and other required details to all servers in service <servicename>
- Verify that the status of the test server operation is successful for all servers in service.

CCA-DIS-8609

The Server Properties blueprint is missing.

Reason:

The Server Properties blueprint is deleted.

Action:

Get the Server Properties blueprint from the following location and import it to the CA Configuration Automation server:

http://techweb.ca.com/r11ImpCD/CCA_Updates/CCA_Frame.htm

CCA-DIS-8616

Verification Directive failed for the component

Reason:

The verification that is defined in the blueprint failed.

Action:

Correct the verification rule that is defined in the blueprint. If necessary, Contact CA Technologies Technical Support for further assistance.

CCA-DIS-8622**UnknownHostException****Reason:**

Target Server is not responding during discovery operation using SSH or WMI.

Action:

Ensure target server is up and running. Also ensure service (SSH or WMI) is running on the target server.

CCA-DIS-8627

Timeout error occurred in remote execution of directive <directivename> on target server <servername> for blueprint <blueprintname>. To customize the timeout value, increase current timeout setting of <timeout> seconds in the blueprint then rerun discovery/refresh.

Reason:

The timeout error occurred while remote execution of the directive <directivename> on the target server <servername> for a blueprint <blueprintname>.

Action:

Increase current timeout setting <timeout> seconds for the directive <directivename> in the blueprint and rerun discovery or refresh.

CCA-DIS-8629

Timeout error occurred in remote execution of command on target server <servername>. Current timeout setting is <timeout>. See CCA log for command content.

Reason:

The timeout error occurred while remote execution of the command on the target server <servername>. Current timeout setting is <timeout>.

Action:

Increase the current timeout setting <timeout> seconds in the blueprint and rerun discovery or refresh.

CCA-DIS-8630

Operation timed out.

Reason:

Time out error is thrown during the discovery or refresh operation of a server. Usually this error is thrown with SSH, Telnet, WMI access mode of operation.

Action:

Based on the access profile, increase the timeout for the following properties in administration configuration. These properties are used to increase the session time.

- `ssh.rexec.timeout.sec`
- `wmi.script.exec.timeout.sec`
- `directive.netprobe.timeout.msec`
- `directive.rexec.timeout.sec`

The common for the access modes of discovery and refresh operation is as follows. The property is used to wait the specified time for the execution of the remote command:

- `directive.rexec.timeout.sec`

If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8632

Error while performing stop discovery

Reason:

An exception occurred while performing the stop discovery operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

Data Migration Error Messages

This section explains the error messages that you see while performing the data migration operations in CA Configuration Automation.

CCA-DM-7501

Select an Archive File.

Reason:

Archive File is not provided while importing the cohesion data to the CA Configuration Automation database using archive file.

Action:

Provide Archive File which is exported from CA Configuration Automation.

CCA-DM-7502

Server Name is required.

Reason:

Database server name is not provided in the Cohesion Database Details tab while exporting cohesion data to Archive File or importing cohesion data into the CA Configuration Automation database.

Action:

Provide a cohesion database server name.

CCA-DM-7503

Database Name is required.

Reason:

The database name is not provided in the Cohesion Database Details tab while exporting the cohesion data to Archive File or importing the cohesion data into the CA Configuration Automation database.

Action:

Provide the cohesion database name.

CCA-DM-7504

Database user is required.

Reason:

The database user name is not provided in the Cohesion Database Details tab while exporting the cohesion data to archive file or the CA Configuration database.

Action:

Provide a cohesion database user name.

CCA-DM-7505

Database Password is required.

Reason:

The database password is not provided in the Cohesion Database Details tab while exporting cohesion data to archive File or importing cohesion data into the CA Configuration Automation database.

Action:

Provide the cohesion database password.

CCA-DM-7507

Failed to connect database. Please verify database details and try again.

Reason:

Failed to connect the database while exporting the CA Cohesion data to archive file or import the CA Cohesion data into the CA Configuration Automation database. The possible reasons are as follows:

- Database details provided in the Cohesion Database Details tab are not correct.
- The database server service is down.
- The database server is not reachable with the server name

Action:

Verify the provided database details. Ensure that the database server service is up and running and connect to the database server with the IP address.

CCA-DM-7508

File Name is required.

Reason:

File name is not provided while exporting the cohesion data to archive File.

Action:

Provide a file name to create the archive file.

CCA-DM-7509

File Path is required.

Reason:

File path is not provided while exporting the cohesion data to archive File.

Action:

Provide file path where the archive file are copied after exporting data from cohesion.

CCA-DM-7512

Port Number is Required.

Reason:

The database server port is not provided in the Cohesion Database Details tab while exporting the cohesion data to Archive File or importing the cohesion data into the CA Configuration Automation database.

Action:

Provide cohesion database server port.

CCA-DM-7513

Please Select KeyStore File.

Reason:

The Key Store File is not selected while importing the cohesion security certificates into CA Configuration Automation.

Action:

Select Key Store File from the cohesion server. The file can be found at the following location:

COHESION-INSTALLATION-HOME\server\lib

CCA-DM-7514

Please Select TrustStore File.

Reason:

The Trust Store File is not selected while importing the cohesion security certificates into CA Configuration Automation.

Action:

Select Trust Store File from the cohesion server. The file can be found in at the following location:

COHESION-INSTALLATION-HOME\server\lib

CCA-DM-7519

Import Certificates Failed.

Reason:

The possible reasons are as follows:

- The Certificate Authority is not created in CA Configuration Automation
- Invalid CA Cohesion data or CA Configuration Automation data is provided while importing certificates.

Action:

Ensure that the Certificate Authority is created in CA Configuration Automation, and provide a valid Cohesion data and CA Configuration Automation data while importing certificates. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DM-7521

Cohesion Server Certificate Password is required.

Reason:

Cohesion Server Certificate Password is not provided while importing Cohesion security certificates into CCA.

Action:

Provide a cohesion server certificate password.

CCA-DM-7522**CCA Server Certificate Password is required.****Reason:**

The CA Configuration Automation server certificate password is not provided while importing the cohesion security certificates into CA Configuration Automation.

Action:

Provide a CA Configuration Automation server certificate password.

CCA-DM-7523**Cohesion Server Name is required.****Reason:**

The cohesion server name is not provided while importing the cohesion security certificates into CA Configuration Automation.

Action:

Provide a cohesion server name.

CCA-DM-7556**<objectname> not imported. <errormessage>.****Reason:**

The object <objectname> already exists.

Action:

No action is required if the object exists. Verify the <errormessage> and if necessary, contact CA Technologies Technical Support for further assistance.

CCA-DM-7607**Database server cannot be resolved****Reason:**

The database server provided in the Cohesion Database Details tab cannot be resolved.

Action:

Provide a valid database server name. Ensure that the server is up and running, and then connect to the database server with the IP address.

CCA-DM-7608

Database driver not found.

Reason:

The database driver is not found while connecting to the Cohesion Sybase Database.

Action:

Get driver from the Sybase database or web, and copy to the following directory:

<CAInstalledDirectory>\tomcat\webapps\ROOT\WEB-INF\lib.

CCA-DM-7609

Could not connect to the given database.

Reason:

The database server is not reachable with the server name while exporting the cohesion data to Archive File or importing cohesion data into the CA Configuration Automation database.

Possible reasons are as follows:

- The database details provided in the Cohesion Database Details tab are not correct.
- The database server service is down.

Action:

Verify the database details and ensure that the database server service is up and running and then connect to database server with the IP address.

CCA-DM-7631

Connection to the Database Server was successful, but either the user is not authorized to access the database or the database is not a valid Cohesion database.

Reason:

The cohesion database details are not valid.

Action:

Ensure to provide valid user and cohesion database details.

CCA-DM-7632

Database Connected successfully, but migrating data from Cohesion Database with version <version> is not supported.

Reason:

Data Migration is not supported for the cohesion Version <version>.

Action:

Ensure that the cohesion version is r5.0 or r5.0 sp1 for data migration.

CCA-DM-7638

Given file path does not exists, please give existing file path.

Reason:

The file path given in Archive File Details section does not exist.

Action:

Provide an existing file path.

CCA-DM-7639

Given path [<path>] is not a valid directory path.

Reason:

The file Path given in the Archive File Details section is not a valid directory path.

Action:

Provide a valid directory path.

CCA-DM-7567

Validation of JAR file failed.

Reason:

An invalid jar file is provided while importing the cohesion data into the CA Configuration Automation database using the archive file.

Action:

Provide a valid JAR file which is created from CA Configuration Automation application.

CCA-DM-7598

Import Security Certificates Failed. <errormessage>

Reason:

The possible reasons are as follows:

- The Certificate Authority is not created in CA Configuration Automation
- Invalid CA Cohesion data or CA Configuration Automation data is provided while importing the certificates.

Action:

Ensure that the Certificate Authority is created in CA Configuration Automation, and provide a valid CA Cohesion data and CA Configuration Automation data while importing certificates. If necessary, contact CA Technologies Technical Support for further assistance.

Dashboard Error Messages

This section explains the error messages that you see while performing the dashboard operations in CA Configuration Automation.

CCA-DB-9704

You are not the owner of dashboard <Dashboard Name>. You cannot update it.

Reason:

You cannot save changes to the dashboards created by another user.

Action:

To perform changes to the dashboard, log in as the owner of the dashboard.

CCA-DB-9705

You are not the owner of dashboard <Dashboard Name>. You cannot delete it.

Reason:

You cannot delete the dashboards created by another user.

Action:

To perform delete operations, log in as the dashboard owner.

CCA-DB-9712

Dashboard <Dashboard Name> already exists.

Reason:

The dashboard with the same name exists.

Action:

Create a dashboard with a unique name.

CCA-DB-9713

You are not the owner of the dashboard. You cannot update it.

Reason:

You are trying to overwrite an existing dashboard that is created by a different user.

Action:

Log in as the owner of the dashboard to update the existing dashboard.

CCA-DB-9714

Please select at least one dashboard to perform this operation.

Reason:

No dashboards are selected while importing the dashboards using the Import On Selection option.

Action:

Select at least one dashboard from the available dashboards for a successful import.

CCA-DB-9715

Select at least one virtualization filter.

Reason:

The virtualization filter is not selected. The virtualization filter is commonly available in most of the dashboard charts.

Action:

Ensure that you select at least one virtualization filter.

CCA-DB-9716

Select at least one severity filter.

Reason:

None of following severity filters are selected in the Management Profile Rule Violations Over time and Compliance Profile Rule Violations Over time dashboards charts.

- Information
- Warning
- Error
- Critical

Action:

Select at least one severity filter in the dashboard charts.

CCA-DB-9718

Dashboard <Dashboard Name> cannot be imported. A Dashboard with the same name already created by another user but not shared.

Reason:

You are trying to import an existing unshared dashboard that is created by another user.

Action:

Log in as the owner of the dashboard.

CCA-DB-9719

Dashboard <Dashboard Name> cannot be saved. A Dashboard with the same name already created by another user but not shared.

Reason:

You are trying to create an already existing unshared dashboard that is created by another user.

Action:

Create a dashboard with a different name.

Export and Import Error Messages

This section explains the error messages that you see while performing the export and import operations in CA Configuration Automation.

CCA-EX-5804

Export cannot be performed. User is not authorized to perform this operation.

Reason:

You do not have permissions to export selected objects.

Action:

Log in to CA Configuration Automation as an administrator or architect to export the profiles.

CCA-IM-5901

Select a JAR file to import.

Reason:

Jar file is not selected for the import operation.

Action:

Select the jar file for the import operation.

CCA-IM-5907

Error during import. Not a valid JAR file.

Reason:

JAR file is not valid, or the value is empty, or the object type mismatch.

Action:

Provide a valid jar file.

CCA-IM-5917

Import cannot be performed. User is not authorized to perform this operation.

Reason:

You do not have permissions to perform the import operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect to perform the import operation.

CCA-IM-5923

<objectType> not imported, Cause<incorrecttype>.

Reason:

The JAR file type is mismatched with the object type while importing the objects using SDK and Command-Line utility.

Action:

Provide a valid JAR file type. For example, to import blueprints provide the exported blueprint.jar and not the accessprofile.jar.

CCA-IM-5925

Select a CSV file to import.

Reason:

CSV File is not selected during Import Services.

Action:

Select the CSV File which has valid service definition.

Graph Error Messages

This section explains the error messages that you see while performing the graph operations in CA Configuration Automation.

CCA-GR-9804

You are not the owner of graph <graphname>. You cannot update it.

Reason:

Graph owner can only update the graph.

Action:

Log in as the graph owner to update the graph.

CCA-GR-9805

You are not the owner of graph <graphname>. You cannot delete it.

Reason:

Graph owner can only delete the graph. Current user is not the graph owner.

Action:

Log in as a graph owner to delete the graph.

CCA-GR-9807

Cannot delete default graph.

Reason:

Selected graph is a default graph.

Action:

Default graph cannot be deleted. Make the other graph as a default before you delete the selected default graph.

CCA-GR-9812

Graph <graphname> already exists.

Reason:

Importing an already existing graph without selecting the overwrite flag.

Action:

Select the overwrite flag while importing the already available graph.

CCA-GR-9813

You are not the owner of the graph. You cannot update it.

Reason:

Graph owner can only update the graph. Current user is not the graph owner while importing the graph.

Action:

Log in as the graph owner to update the graph.

CCA-GR-9818

Graph Folder <graphfoldername> already exists.

Reason:

Graph Folder with this name is already available.

Action:

Provide a unique graph folder name.

CCA-GR-9819

You are not the owner of folder <graphfoldername>. You cannot delete it.

Reason:

Graph folder owner can only delete the graph. Current user is not the graph folder owner.

Action:

Log in with graph folder owner credentials to delete the graph folder.

CCA-GR-9820

You cannot share a graph residing in an unshared folder. Please share folder first.

Reason:

Trying to share the graph when the graph folder is not shared.

Action:

Share the graph folder before sharing the graph inside the graph folder.

CCA-GR-9821

You cannot delete folder <graphfoldername> because graphs exist. Please delete the graphs first.

Reason:

Graph folder contains graphs.

Action:

Delete all the graphs before deleting graph folder.

CCA-GR-9822

You are not the owner of folder <graphfoldername>. You cannot update it.

Reason:

Graph folder owner can only update the graph. Current user is not the graph folder owner.

Action:

Log in as the graph folder owner to update the graph folder.

CCA-GR-9825

Cannot stop sharing folder <graphfoldername> because it contains shared graphs you do not own.

Reason:

Graph folder contains shared graphs that you do not own.

Action:

Log in as the graph owner and stop sharing the graphs that you do not own.

CCA-GR-9826

Cannot delete default graph.

Reason:

Selected graph is a default graph.

Action:

Default graph cannot be deleted. Make other graph as the default before you delete the select default graph.

CCA-GR-9829

Graph <graphname/id> not found.

Reason:

Graph name provided in launch in context not found in CA Configuration Automation, or the graph name is invalid or incorrect.

Action:

Provide the correct graph name or ID.

CCA-GR-9833

Security Violation while exporting the graph.

Reason:

You do not have permission to export a graph.

Action:

Log in to CA Configuration Automation as an Administration or an Architect to export the property.

General Error Messages

This section explains the error messages that you see while performing the general tasks in CA Configuration Automation.

CCA-GM-0008

Name is required.

Reason:

No name is provided while copying any one of the following:

- Management profile
- Access Profile
- Network Profile
- Credential Vault
- Network Scan Policies
- Notification profile.
- Catalyst profile.

Action:

Provide appropriate name while making a copy of the Management profile, Access profile, Network profile, Credential vault, Network Scan Policies, Notification profile, Catalyst profile.

CCA-AA-0000

Login failed, please check credentials

Reason:

Unable to authenticate the user from SDK.

Action:

Provide valid user credentials to log in to CA Configuration Automation.

CCA-GM-0010

Server connection exception, message = <Exception Message>

Reason:

Exception occurred due to connectivity issues between CA Configuration Automation server and agent.

Action:

Restart the agent and verify the agent communication by performing Test Servers. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-GM-0011

exceptionClassMsg=CCA-GM-0011: Command execution failed on host <Server Name>, exception class is <Exception Class>, message is "<Error Message>". See CCA log for command content.

Reason:

Time out error is thrown during the discovery or refresh operation of a server in SSH, Telnet, and WMI access mode of operation.

Action:

For SSH-based discovery or refresh operation, do the following:

- Increase the timeout for the following configuration:

`ssh.rexec.timeout.sec` property

- Set the file transfer as SCP in the SSH access profile.

For WMI-based discovery or refresh operation, do the following:

- Increase the timeout for the following configuration:

`wmi.script.exec.timeout.sec` property

If necessary, contact CA Technologies Technical Support for further assistance.

CCA-GM-0014

Retry of database connection failed; SQL Exception: <Exception message>

Reason:

Database service may not be running or shutdown.

Action:

Verify if the database is up and running. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-GM-0015

Invalid database password.

Reason:

The database password is null.

Action:

Provide the correct password in the `cca.properties` file.

CCA-GM-0020

Unknown database type:

Reason:

SQL exception occurred as the driver information is not specified.

Action:

Verify whether the database driver information is correct in the cca.properties file is valid or not. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-GM-0021

Database context not found

Reason:

SQL exception occurred as the database context information is not specified in the respective relational database blueprint.

Action:

Verify the User Input section of the respective relational database blueprint being used for discovery. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-AA-9201

User Authentication Failed.

Reason:

Unable to authenticate the user.

Action:

Provide valid user credentials to log in to CA Configuration Automation.

CCA-AA-9204

The password needs to be changed

Reason:

The password has expired.

Action:

Change the password.

CCA-AA-9206

The SDK login cache has reached its maximum capacity. No new SDK session can be created.

Reason:

The SDK login cache has reached the maximum capacity.

Action:

Configure the property "sdk.session.cache.size" in Administration, Configuration, Properties with a higher value, and restart the CA Configuration Automation server. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-AA-9207

Password already used, please provide different password.

Reason:

The password policy in CA EEM restricts you to use the already used password.

Action:

Provide a password that you have not used previously.

CCA-GD-0047

wrong execution server, intended is uuid <execution server uuid>, actual is <server uuid>

Reason:

Possible reason is CCA Server machine might be blocking the incoming requests on the port specified.

Action:

Ensure that the port is open and accepting incoming requests.

Example:

If the CA Configuration Automation server is running on Linux platform, configure iptables for the specific port. If the CA Configuration Automation server is running on Windows platform, configure firewall to allow incoming request through the specified port. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-1000

Security Violation: <error>

Reason:

User does not have privilege to run the operation.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to run the operation.

CCA-MS-1001

Your user login session has expired. Please Log in again.

Reason:

The session has timed out.

Action:

Log in again.

Global Variable Error Messages

This section describes the error messages that you get while performing the global variable operations.

CCA-GV-5507

Name is required

Reason:

Name is not provided while creating a global variable.

Action:

Provide a name while creating a global variable.

CCA-GV-5511

Select an XML OR CSV file to import.

Reason:

The possible reasons are as follows:

- File name is not selected while importing the global Variables.
- Invalid file is selected to import the global Variables.

Action:

Select a valid XML, or CSV file to import the global Variables.

CCA-GV-5513

Global Variable <variablename> already exists.

Reason:

The global variable <variable name> already exists.

Action:

Provide a unique global variable name.

CCA-GV-5514

Invalid input characters for name <name>. Do not use space and below characters <characterlist>.

Reason:

Name contains invalid characters.

Action:

Provide valid characters for Name while creating a global variable.

CCA-GV-5515

File has no Global Variables

Reason:

The XML file provided to import the global variables does not contain global variables.

Action:

No action is required.

CCA-GV-5516

Provide a unique name for the global sub-variable and try adding it again.

Reason:

Global sub-variable name already exists.

Action:

Provide a unique global sub-variable and perform the addition task.

CCA-GV-5517

Invalid file.

Reason:

The XML file that is provided to import Global Variables does not contain valid start tag <GlobalRegistry> or end tag </GlobalRegistry>.

Action:

XML file should have a start tag <GlobalRegistry>, and an end tag </GlobalRegistry>.

CCA-GV-5518

File contains invalid characters.

Reason:

The XML file that is provided to import the global variables contains invalid character '&'.

Action:

Remove invalid characters from the XML file and import it.

Notification Error Messages

This section describes the error messages that you get while sending notifications to users.

CCA-NF-5602

Sending notification failed. Mail Server not configured, Please configure property "mail.server" in Administration > Configuration > Properties.

Reason:

Sending notification failed. The Mail Server is not configured.

Action:

Configure property "mail.server" in Administration > Configuration > Properties.

CCA-NF-5603

Sending notification failed. "From" mail address not configured, Please configure property "mail.from" in Administration > Configuration > Properties.

Reason:

Sending of the notification failed. "From" mail address is not configured

Action:

Configure property "mail.from" in Administration, Configuration, Properties.

CCA-NF-5604

Sending notification failed. "To" mail address missing. Please set a valid mail address in the "Send Email To" parameter in the Notification Profile.

Reason:

Sending notification failed. "To" mail address is not configured

Action:

Configure property "mail.to" in Administration, Configuration, Properties.

CCA-NF-5605

Sending notification failed. Mail address provided is invalid.

Reason:

"To" and/or "From" mail addresses are not configured with valid mail addresses.

Action:

Configure property "mail.to" and/or "mail.from" in Administration, Configuration, Properties with valid mail addresses.

CCA-NF-5607

Sending notification failed. User <username> is not authorized to perform this operation.

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administrator or Architect.

CCA-NF-5608

Formatting notification message failed. User <username> is not authorized to perform this operation.

Reason:

You do not have permissions to perform the operation.

Action:

Log in to CA Configuration Automation as an Administrator or Architect.

CCA-NF-5609

Formatting notification message failed. Exception occurred - <error>.

Reason:

An error occurred while formatting the notification message.

Action:

Verify the properties "mail.to", "mail.from" and "mail.server" in Administration, Configuration, Properties for correctness. If the issue still exists, Contact CA Technologies Technical Support for further assistance.

NDG Error Messages

This section explains the error messages that you see while performing the NDG operations in CA Configuration Automation.

CCA-NR-1708

Failed to delete existing schedule of network scan job <jobname> error message - <errormessage>

Reason:

A job is currently running, or an exception occurred while deleting the scheduled job.

Action:

Try after the job completes. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-NR-1709

Network Discovery Gateway is required

Reason:

Network Discovery Gateway server name is not provided while creating the network discovery gateway.

Action:

Provide the NDG server name while creating the network discovery gateway.

CCA-NR-1710**Network Discovery Gateway port number is required****Reason:**

Network discovery gateway port number is not provided while creating the network discovery gateway.

Action:

Provide the NDG server port number while creating the network discovery gateway.

CCA-NR-1711**Failed to connect to the Network Discovery Gateway****Reason:**

NDG test connection failed while creating the network profile.

Action:

Verify the NDG server connectivity with a ping, if necessary contact CA Technologies Technical Support for further assistance.

NDG Discovery Error Messages

This section explains the error messages that you see while performing the NDG discovery operations in CA Configuration Automation.

CCA-ND-8053**Host <hostname> does not respond to Network Discovery Gateway on node <NDGservername> for reconciling server IP****Reason:**

Hostname is not getting resolved while reconciling the server IP.

Action:

Verify whether the server is up and running; if necessary contact CA Technologies technical support for further assistance.

CCA-ND-8054

Server Name,<servername>, cannot be reconciled due to unknown host name

Reason:

Unknown host exception occurred while reconciling the server IP.

Action:

Ensure that the target server with hostname is pingable.

CCA-ND-8056

Network Discovery Gateway connection error: <errormessage>.

Reason:

Incompatible version of the network discovery gateway is detected.

Action:

Install the NDG which is available in CA Configuration Automation image along with the corresponding CA Configuration Automation server.

CCA-ND-8057

Network Discovery Gateway <servername> already exists

Reason:

The network discovery gateway with the server name already exists.

Action:

No action is required.

CCA-ND-8058

Server Name, <servername> cannot be reconciled because it is not responding to requests

Reason:

The server is not responding for the reconciliation operation.

Action:

Verify whether the target server is up and running.

CCA-ND-8059

SNMP Gateway IP address must be in either IPV4 or IPV6 format. No wildcards allowed

Reason:

The SNMP gateway IP address contains wildcards.

Action:

Add SNMP gateway IP address without wildcards.

CCA-ND-8063

Communication error. Please validate that NDG is a compatible version and confirm that Network Discovery Gateway service on node <servername> is running

Reason:

CA Configuration Automation server is unable to communicate with NDG.

Action:

Validate that the NDG is a compatible version, and confirm that the network discovery gateway service on the node <servername> is running.

CCA-ND-8064

The Scan Policy used for this NDG scan contains invalid parameters. Please re-check the values in your Scan Policy and try again

Reason:

An Axis fault exception occurred while running the network scan policy with invalid parameters.

Action:

Re-check the values in the scan policy and try again.

Profile Error Messages

This section explains the error messages that you see while performing the profile operations in CA Configuration Automation.

CCA-PL-3517

Profile name is required

Reason:

The profile name is not provided while creating the management, or notification, or access, or network, or credential vault profile creation.

Action:

Provide a profile name.

CCA-PL-3522

<proxyserver/SSHserverhost> is required

Reason:

The proxy server or SSH server host details are not provided while adding or updating the proxy details of the access profile.

Action:

Provide proxy server or SSH server host details while adding or updating the proxy details of the access profile.

CCA-PL-3523

Enter a valid port number

Reason:

The port number contains invalid characters while creating or updating the access profile.

Action:

Provide valid characters as the port number.

CCA-PL-3524**Enter server account****Reason:**

The SSH server host account details are not provided while adding or updating the proxy details of the access profile.

Action:

Provide SSH server host account details while adding or updating the proxy details of access profile.

CCA-PL-3525**SSH password is required****Reason:**

The SSH server host account password is not provided while adding or updating the proxy details of the access profile.

Action:

Provide SSH server host account password while adding or updating the proxy details of the access profile.

CCA-PL-3526**SSH retype password is required****Reason:**

The SSH server host account retype password is not provided while adding, or updating the proxy details of the access profile.

Action:

Provide the SSH server host account retype password while adding, or updating the proxy details of the access profile.

CCA-PL-3527

Enter a valid connection timeout

Reason:

The connection timeout contains alphabets while updating or adding the SSH access profile.

Action:

Provide numeric values for the connection timeout field.

CCA-PL-3530

Invalid email address

Reason:

The email address is not provided or an invalid email address is provided while adding or updating the notification profile.

Action:

Provide a valid email address while adding or updating the notification profile.

CCA-PL-3533

The default profile cannot be deleted. A new default profile must be assigned before the selected profiles can be deleted

Reason:

One of the selected profiles is marked as default. You cannot delete a default profile.

Action:

Assign a new default profile before you delete the existing default profile or exclude the default profile and delete the other profiles.

CCA-PL-3534

The passwords you entered do not match. Re-enter your passwords again in both password fields

Reason:

The password and Re type password text varies.

Action:

Provide same value for the password and retype password fields.

CCA-PL-3538**Management Profile <managementprofilename> already exists****Reason:**

The management profile with this name already exists.

Action:

Provide a unique name to the management profile.

CCA-PL-3539**Access Profile <accessprofilename> already exists****Reason:**

The access profile with this name already exists.

Action:

Provide a unique name to the access profile.

CCA-PL-3540**Notification Profile <Notificationprofilename> already exists****Reason:**

The notification profile with this name exists.

Action:

Provide a unique name to the notification profile.

CCA-MP-3549**Scheduled Management Profile <jobname> execution failed. User <username> is not authorized to perform this operation****Reason:**

You do not have permissions to execute the schedule management profile, or refresh operation, or scheduled server or service discovery operation.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to execute the schedule management profile or refresh operation or scheduled server or service discovery.

CCA-PL-3556

Management Profile <managementprofileuuid> does not exist

Reason:

The access profile or the management profile is not available in the CA Configuration Automation while importing the server in data migration operation.

Action:

Create or import the access profile or management profiles before importing the server in data migration operation.

CCA-PL-3558

Selection contains Self Registered Access Profile. Cannot perform delete operation

Reason:

You cannot delete a Self Registered Access Profile.

Action:

Remove the Self Registered Access Profile from the selection list, and delete the access profile.

CCA-PL-3559

Cannot edit <accessprofilename> Self Registered Access Profile.

Reason:

The details are auto populated so the Self Registered Access Profile cannot be edited.

Action:

Copy the profile and edit the access profile.

CCA-PL-3565

Cannot update management profile <managementprofilename> because of scheduling failure, error message - <errormessage>

Reason:

Invalid days or time is provided for the selected frequency.

Action:

Provide valid days or time for the selected frequency.

CCA-PL-3570**Enter a valid file search depth****Reason:**

The file search depth entered in the management profile discovery options is not numeric value.

Action:

Enter a numeric value for the file search depth field.

CCA-PL-3574**Required fields are missing.****Reason:**

The required fields in the access modes tab of the access profile are not provided.

Action:

Provide all the details in the access modes tab while creating or updating the access profile.

CCA-PL-3577**Invalid IP Address found: <ipaddress>****Reason:**

The IP address that is provided while adding the server is invalid IPv4 or IPv6 address.

Action:

Provide a valid IPv4 or IPv6 address while adding the server.

CCA-PL-3582**An IP Address is a required field. Please provide a valid IP Address.****Reason:**

The IPv4 or IPv6 address is empty.

Action:

Provide a valid IPv4 or IPv6 address while adding or updating the server.

CCA-PL-3587

Invalid IP Address Mask found: <IPaddressrange>

Reason:

IP address is not IPv4 or IPv6.

Action:

Provide a valid IP address

CCA-PL-3589

Profile name is too long.

Reason:

The profile name contains more than 200 characters while creating or updating the management profile or network profile.

Action:

Provide a profile name that is less than or equal to 200 characters.

CCA-PL-3590

Invalid profile name. The following characters are not allowed: " "

Reason:

Invalid characters (" , ') found in the management profile name while creating the management profile.

Action:

Provide the management profile name without the double or single quotes.

CCA-PL-3599

Management Profile is not enabled

Reason:

The management profile is disabled.

Action:

Enable the management profile and re run the operation.

CCA-PL-3605

Network Scan Policy <policyname> already exists.

Reason:

The network scan Policy with the same name exists.

Action:

Provide a unique network scan policy name while creating a policy.

CCA-PL-3611

The selected policies cannot be deleted. One or more of the selected policies are assigned to a Network Profile.

Reason:

Selected policies are assigned to the network profile.

Action:

Ensure that the selected network scan policies are not assigned to any other network profile before you delete the selected policies.

CCA-PL-3615

CCA pre-built Network Scan Policies cannot be deleted.

Reason:

You cannot delete CCA pre-built Network Scan Policies.

Action:

No action is required.

CCA-PL-3631

Network Profile <profilename> already exists.

Reason:

The network profile with the same name exists.

Action:

Provide a unique network profile name while creating a network profile.

CCA-PL-3620

Failed to import

Reason:

An exception occurred while importing the policy. The exceptions are SQLException, SecurityViolation, and XMLStream Exception.

Action:

If it is a security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3621

Inclusion and Exclusion list cannot have similar ports <list of ports>

Reason:

You have selected similar inclusion and exclusion ports.

Action:

Provide different ports in the inclusion or exclusion list.

CCA-PL-3639

Failed to communicate with the Network Discovery Gateway on port CA Portal on node <servername>

Reason:

RemoteException occurred while connecting from NDG.

Action:

Check the NDG server status whether it is properly responding.

CCA-PL-3641

Could not find host <servername>. Please correct the host name or select a different Network Discovery Gateway and try again.

Reason:

An unknown Host exception occurred while resolving new server.

Action:

Provide a valid host name or select a different Network Discovery Gateway.

CCA-PL-3642

Could not find host <servername>. Please correct the host name and try again.

Reason:

Unknown Host exception occurred while resolving new server.

Action:

Provide a valid host name.

CCA-PL-3643

IP address <ipv4/ipv6> was not detected as a valid address for host <servername>. Please correct the IP address and try again.

Reason:

The address that you specified is not available in the resolved address list.

Action:

Provide a valid IP address.

CCA-PL-3650

Scan type required.

Reason:

Scan type is not selected while creating or updating network profile.

Action:

Select IPV4 or IPV6 as the scan type.

CCA-PL-3651

Invalid characters found in hostname <hostname>

Reason:

Hostname contains invalid characters.

Action:

Provide a valid hostname.

CCA-PL-3652

Invalid characters found in TCP port.

Reason:

The TCP port contains invalid characters.

Action:

Provide a valid(numeric value) TCP port.

CCA-PL-3653

A target host name or IP address is required when engine type is Pingsweep.

Reason:

Target host name or IP address is not provided while creating network profile with the pingsweep engine type.

Action:

Provide a target host name or IP address in the inclusion list of the network profile while creating the profile with the pingsweep engine type.

CCA-PL-3654

Global Routing Prefix length has a min value of <minvalue>

Reason:

Global Routing Prefix length value is less than the <minvalue>.

Action:

Ensure that the Global Routing Prefix length value is equal or greater than the <minvalue>.

CCA-PL-3655

Global Routing Prefix length has a max value of <maxvalue>

Reason:

Global Routing Prefix length value is greater than the <maxvalue>.

Action:

Ensure that the Global Routing Prefix length value is equal or less than the <maxvalue>.

CCA-PL-3656

Global Routing Prefix length is required.

Reason:

Global Routing Prefix length is not provided while creating the network profile.

Action:

Provide the Global Routing Prefix length while creating the network profile.

CCA-PL-3660

The sum of all levels in Subnet Hierarchy cannot exceed 64 - Global Routing Prefix length: <value>

Reason:

The sum of all levels in Subnet Hierarchy is more than 64 <value>.

Action:

Ensure that the sum of all levels in Subnet Hierarchy is less than or equal to 64 <value>.

CCA-PL-3661

Subnet Hierarchy level has a min value of <minvalue>

Reason:

Subnet Hierarchy level value is less than <minvalue>.

Action:

Ensure that the Subnet Hierarchy level value is equal or greater than <minvalue>.

CCA-PL-3662

Subnet Hierarchy lower bound has a min value of <minvalue>

Reason:

The Subnet Hierarchy lower bound value is less than <minvalue>.

Action:

Ensure that the Subnet Hierarchy lower bound value is equal or greater than <minvalue>.

CCA-PL-3663

Subnet Hierarchy lower bound has a max value of (2 to the power of Bits value) - 1

Reason:

Subnet Hierarchy lower bound value is greater than <maxvalue>.

Action:

Ensure that the Subnet Hierarchy lower bound value is equal or less than <maxvalue>.

CCA-PL-3664

Subnet Hierarchy upper bound has a min value of specified lower bound value

Reason:

The Subnet Hierarchy upper bound value is less than <minvalue>.

Action:

Ensure that the Subnet Hierarchy upper bound value is equal or greater than <minvalue>.

CCA-PL-3665

Subnet Hierarchy upper bound has a max value of (2 to the power of Bits value) - 1

Reason:

Subnet Hierarchy upper bound value is greater than <maxvalue>.

Action:

Ensure that the Subnet Hierarchy upper bound value is equal or less than <maxvalue>.

CCA-PL-3666

A target host name or IP address is required when engine type is TCP Connect Scan.

Reason:

Hostname or IP address is not provided in the inclusion tab while creating a network profile with a TCP connect scan.

Action:

Provide Hostname or IP address in the inclusion tab while creating a network profile with a TCP connect scan.

CCA-PL-3667

An IP address inclusion filter is required for this engine type.

Reason:

The IP address is not provided in the inclusion tab while creating network profile with a netflow scan.

Action:

Provide IP address in the inclusion tab while creating a network profile with a netflow scan.

CCA-PL-3668

SNMP Retries has a min value of <minvalue>

Reason:

SNMP Retries value less is than the <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Retries value is equal or greater than the <minvalue>.

CCA-PL-3669

SNMP Retries has a max value of <maxvalue>

Reason:

SNMP Retries value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Retries value is equal or less than the <maxvalue>.

CCA-PL-3670

SNMP Timeout has a min value of <minvalue>

Reason:

SNMP Timeout value is less than the <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Timeout value is equal or greater than the <minvalue>.

CCA-PL-3671

SNMP Timeout has a max value of <maxvalue>

Reason:

SNMP Timeout value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Timeout value is equal or less than <maxvalue>.

CCA-PL-3672

SNMP Engines has a min value of <minvalue>

Reason:

SNMP Engines value less than <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Engines value is equal or greater than the <minvalue>.

CCA-PL-3673

SNMP Engines has a max value of <maxvalue>

Reason:

SNMP Engines value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Engines value is equal or less than the <maxvalue>.

CCA-PL-3674**DNS Server IP Address required.****Reason:**

The DNS Server IP Address is not provided while adding or updating network profile with DNS scan policy.

Action:

Provide DNS Server IP Address while adding or updating network profile with the DNS scan policy.

CCA-PL-3675**CIDR (slash) notation not valid.****Reason:**

Invalid CIDR (slash) notation.

Action:

Provide valid CIDR (slash) notation.

CCA-PL-3676**Invalid characters found in IP address.****Reason:**

IP address is not valid.

Action:

Provide valid IP address.

CCA-PL-3677**DNS Domain required.****Reason:**

DNS domain is not provided in DNS scan policy.

Action:

Provide DNS domain in DNS scan policy.

CCA-PL-3678

Execution days has a min value of {0}

Reason:

The Execution days value is less than <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the Execution days value is equal or greater than the <minvalue>.

CCA-PL-3679

Execution days has a max value of {0}

Reason:

The Execution days value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Execution days value is equal or less than the <maxvalue>.

CCA-PL-3680

Execution hours has a min value of {0}

Reason:

The execution hours value is less than the <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the Execution hours value is equal or greater than the <minvalue>.

CCA-PL-3681

Execution hours has a max value of {0}

Reason:

The Execution hours value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Execution hours value is equal or less than the <maxvalue>.

CCA-PL-3682

Execution minutes has a min value of {0}

Reason:

The Execution minutes value is less than the <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the Execution minutes value is equal or greater than <minvalue>.

CCA-PL-3683

Execution minutes has a max value of {0}

Reason:

The Execution minutes value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Ensure that the SNMP Execution minutes value is equal or less than <maxvalue>.

CCA-PL-3684

Statistics reporting interval has a min value of {0}

Reason:

The Statistics reporting interval value is less than <minvalue> while creating or updating the network scan policy.

Action:

Ensure that the Statistics reporting interval value is equal or greater than the <minvalue>.

CCA-PL-3685

Statistics reporting interval has a max value of <n>

Reason:

The Statistics reporting interval value is greater than the max value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3686

Cache Purge Frequency has a min value of <n>

Reason:

Cache Purge Frequency is less than the min value <n> while creating or updating the network scan policy.

Action:

Provide a value which is greater than or equal to <n>.

CCA-PL-3687

Cache Purge Frequency has a max value of <n>

Reason:

Cache Purge Frequency is greater than the max value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3688

Relationship Packet Threshold Count has a min value of <n>

Reason:

Relationship Packet Threshold Count is less than the min value <n> while creating or updating the network scan policy.

Action:

Provide a value which is greater than or equal to <n>.

CCA-PL-3689

Relationship Packet Threshold Count has a max value of <n>

Reason:

Relationship Packet Threshold Count is greater than the max value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3690**Port must be a numeric value****Reason:**

Either no port value is provided or a non-numeric value is provided for Port while creating or updating the network scan policy.

Action:

Provide a valid port value.

CCA-PL-3691**Aggregation Interval has a min value of <n>****Reason:**

Aggregation Interval is less than the minimum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is greater than or equal to <n>.

CCA-PL-3692**Aggregation Interval has a max value of <n>****Reason:**

Aggregation Interval is greater than the maximum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3693**Pingsweep Retries has a min value of <n>****Reason:**

The Retries value is less than the minimum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is greater than or equal to <n>.

CCA-PL-3694

Pingsweep Retries has a max value of <n>

Reason:

Retries is greater than the maximum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3695

Pingsweep Timeout has a min value of <n>

Reason:

Timeout is less than the minimum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is greater than or equal to <n>.

CCA-PL-3696

Pingsweep Timeout has a max value of <n>

Reason:

Timeout is greater than the maximum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3697

Pingsweep Engines has a min value of <n>

Reason:

Pingsweep Engines value is less than the minimum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is greater than or equal to <n>.

CCA-PL-3698

Pingsweep Engines has a max value of <n>

Reason:

Pingsweep Engines value is greater than the maximum value <n> while creating or updating the network scan policy.

Action:

Provide a value which is less than or equal to <n>.

CCA-PL-3699

A target IP address is required when engine type is Pingsweep.

Reason:

No target IP address is provided in the inclusions page.

Action:

Provide a valid target IP address.

CCA-PL-3700

A target IP address is required when engine type is TCP Connect Scan.

Reason:

No target IP address is provided in the inclusions page.

Action:

Provide a valid target IP address.

CCA-PL-3701

Error while adding <profilename> profile

Reason:

An exception occurred while adding a profile using SDK or command line utility. The exceptions are SecurityViolation, DuplicateObjectException, SQLException, and SDKException.

Action:

If it is security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3702

Error while getting <profilename> profile

Reason:

An exception occurred while retrieving a profile using SDK or command line utility. The exceptions are SecurityViolation and SQLException.

Action:

If it is security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3704

Profile by UUID <profileuuid> not found

Reason:

Provided a wrong or invalid UUID for profile details fetch through SDK.

Action:

Provide a valid profile UUID.

CCA-PL-3705

Error while getting all Profiles

Reason:

An exception occurred while retrieving a profile using SDK or command line utility. The exceptions are SecurityViolation and SQLException.

Action:

If it is security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3706

Error while updating profile having id <profileuuid> and name <profilename>

Error:

An exception occurred while updating a profile using SDK or command line utility. The exceptions are SecurityViolation, DuplicateObjectException, SQLException, and SDKExceptionException.

Action:

If it is security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3707

Error while setting profile attribute (type=<profiletype>, name=<profilename>, attribute name=<attributename>)

Error:

An exception occurred while updating a profile attribute using SDK or command line utility. The exceptions are SecurityViolation, DuplicateObjectException, SQLException, and SDKExceptionException.

Action:

If it is security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3708

Error while getting profile attribute (type=<profiletype>, name=<profilename>, attribute name=<attributename>)

Reason:

An exception occurred while getting a profile attribute using SDK or command line utility. The exceptions are SecurityViolation and SQLException.

Action:

If it is security violation exception, then verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3712

Port is a required value.

Reason:

Port is not provided while creating a communication mapping.

Action:

Provide port value while creating a communication mapping.

CCA-PL-3713

Communication Name is a required value.

Reason:

Communication Type is not provided while creating a communication mapping.

Action:

Provide a communication Type while creating communication.

CCA-PL-3715

Communication Mapping already exists.

Reason:

The communication mapping exists.

Action:

Provide a unique value for communication type.

CCA-PL-3718

The valid range for port is 1 - 65535.

Reason:

The Port value that is provided is not in the range 1-65535 while adding a communication mapping.

Action:

Provide a valid port value.

CCA-PL-3719

An Application Mapping with this application path already exists.

Reason:

The application mapping with this application path exists.

Action:

Provide a unique application path value while creating the application mapping.

CCA-PL-3720

Application Name is a required value.

Reason:

The application name is not provided while adding application mapping.

Action:

Provide an application name while adding application mapping.

CCA-PL-3721

Application Path is a required value.

Reason:

The application path is not provided while adding application mapping.

Action:

Provide application path while adding application mapping.

CCA-PL-3726

Application Mapping with the same application path already exists.

Reason:

Application Mapping with the same application path exists.

Action:

Select Overwrite existing Application Mappings flag while importing the existing application mapping.

CCA-PL-3734

Error while adding <profilename> Credential Vault

Reason:

An exception occurred while adding credential vault using SDK or command line utility. The exceptions are SecurityViolation, DuplicateObjectException, SQLException, and SDKExceptionException.

Action:

If it is security violation exception, verify the user privileges. Contact CA Technologies Technical Support for further assistance.

CCA-PL-3736

Port must be a numeric value.

Reason:

The Port value entered in communication type or NDG server detail is not numeric value.

Action:

Provide a valid port number.

CCA-PL-3737

The length of account must be less than 20 characters.

Reason:

The length of agent or ssh or proxy account is more than 20 characters.

Action:

Ensure that the length of agent or ssh or proxy account is less than 20 characters.

CCA-PL-3740

Invalid target IP address - specify too many targets for a single scan: <n>

Reason:

The IP addresses with CIDR notation or wild-card characters comprises of too many targets.

Action:

Ensure that the IP address comprises of lower number of targets when using CIDR notation or wild-card characters.

CCA-PL-3741 (r12.8)

Exclusion List Entry value of "*" is not allowed for Selected IP Addresses.

Reason:

When you specify the Exclusion List Entry value, the wildcard character * can be used only as a part of a string such as 10.144.37.*. When you set the Exclusion List Entry value to an independent *, the NDG network scan excludes all the discovered results.

Action:

Do not provide an independent * value for the Exclusion List Entry for the selected IP addresses.

CCA-PL-3742

Exclusion List Entry value of "*" is not allowed for Selected Ports.

Reason:

When you specify the Exclusion List Entry value, the wildcard character * can be used only as a part of a string such as 801*. When you set the Exclusion List Entry value to an independent *, the NDG network scan excludes all the discovered results.

Action:

Do not provide an independent * value for the Exclusion List Entry for the selected ports.

CCA-PL-3800

Pingsweep Burst Size has a min value of <minvalue>

Reason:

The Pingsweep Burst Size value is less than the <minvalue> while creating or updating the Network Scan Policy.

Action:

Provide Pingsweep Burst Size value equal greater than the <minvalue> value while creating or updating the network scan policy.

CCA-PL-3801

Pingsweep Burst Size has a max value of <maxvalue>

Reason:

The Pingsweep Burst Size value greater is than the <maxvalue> while creating or updating the network scan policy.

Action:

Provide Pingsweep Burst Size value equal or less than the < maxvalue> while creating or updating the network scan policy.

CCA-PL-3802

Local Link Retries has a min value of <minvalue>

Reason:

Local Link Retries value is less than the <minvalue> while creating or updating the network scan policy.

Action:

Provide Local Link Retries value equal or greater than the <minvalue> while creating or updating the network scan policy.

CCA-PL-3803

Local Link Retries has a max value of <maxvalue>

Reason:

You are updating the Local Link Retries value greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Provide Local Link Retries value equal or less than the <maxvalue> while creating or updating the network scan policy.

CCA-PL-3804

Local Link Timeout has a min value of <minvalue>

Reason:

Local Link Timeout value is less than the <minvalue> while creating or updating the network scan policy.

Action:

Provide Local Link Timeout value equal or greater than the <minvalue> while creating or updating the network scan policy.

CCA-PL-3805

Local Link Timeout has a max value of <maxvalue>

Reason:

The Local Link Timeout value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Provide Local Link Timeout value equal or less than the <maxvalue> while creating or updating the network scan policy.

CCA-PL-3806

Gateway IP Address required.

Reason:

Gateway IP address is not provided.

Action:

Provide the valid gateway IP address.

CCA-PL-3807

TCP Connect Scan Engines has a min value of <minvalue>

Reason:

TCP Connect Scan Engines value is less than the <minvalue> while creating or updating the network scan policy.

Action:

Provide TCP Connect Scan Engines value that is equal or greater than the <minvalue> while creating or updating the network scan policy.

CCA-PL-3808

TCP Connect Scan Engines has a max value of <maxvalue>

Reason:

Local Link Timeout value is greater than the <maxvalue> while creating or updating the network scan policy.

Action:

Provide a Local Link Timeout value that is equal or less than the <maxvalue> while creating or updating the network scan policy.

CCA-PL-3809

Specified file does not contain the expected file header <servername/ipaddress>

Reason:

File header does not contain the header.

Action:

Ensure that the file is in the proper format.

CCA-PL-3811

Error occurred reading from the specified file.

Reason:

An Input Output exception occurred while adding the hosts from a file.

Action:

Check the file format and accessibility.

CCA-PL-3817

Invalid Install Directory.

Reason:

Invalid Install Directory is provided while creating or updating the access profile.

Action:

Provide a valid installation directory.

CCA-PL-3818

Access Profile <profilename> not found.

Reason:

The access profile is not found to display in the launch in context.

Action:

Verify the access profile availability in CA Configuration Automation server.

CCA-PL-3819

Management Profile <profilename> not found.

Reason:

Management Profile is not found to display in the launch in context.

Action:

Check the management profile availability in CA Configuration Automation server.

CCA-PL-3824

Domain is required.

Reason:

Domain is not provided while creating the credential vault profile.

Action:

Provide a Domain name.

CCA-PL-3828

Invalid port value. The valid range for a port is 1-65535

Reason:

The SSH port value that you provided is not in the 1 to 65535 range.

Action:

Provide a valid port value.

CCA-PL-3855

Credential Vault Profile <profilename> already exists.

Reason:

The credential vault profile with the same name exists.

Action:

Provide a unique Credential vault profile name while creating a credential vault.

CCA-PL-3856

The selected profiles cannot be deleted. One or more of the selected profiles are assigned to a Network Profile.

Reason:

One or more of the selected profiles are assigned to a network profile.

Action:

Ensure that the selected profiles are not assigned to any network profile before you delete them.

CCA-PL-3858

User Id with the same credentials already exists (see highlighted row below).

Reason:

User Id with the same credentials exists.

Action:

Provide a unique user ID and password combination.

CCA-PL-3920

Enter WMI account.

Reason:

The account information of the WMI proxy server is not provided.

Action:

Provide the account information of the WMI proxy server.

CCCA-PL-3921

WMI password is required

Reason:

The password for the WMI proxy server is not provided.

Action:

Provide a valid password for the WMI proxy server.

CCA-PL-3922

WMI retype password is required

Reason:

No value is provided in the Retype Password field, or the value that is entered does not match the password.

Action:

Confirm the password that you have provided in the Password field.

CCA-PL-3923

Enter FTP account

Reason:

The account information of the FTP server is not provided.

Action:

Provide the account details of the FTP server.

CCA-PL-3924

FTP Root is required

Reason:

The home directory information of the FTP server is not provided.

Action:

Provide the home directory details of the FTP server.

CCA-PL-3925

FTP password is required

Reason:

The password for the FTP server is not provided.

Action:

Provide a password for the FTP server.

CCA-PL-3926

FTP retype password is required

Reason:

The retype password value is not provided for the FTP server.

Action:

Confirm the password for the FTP server.

CCA-PL-3927**Cannot access FTP Root provided in Access Profile****Reason:**

Unable to access the FTP home directory on the proxy machine.

Action:

Verify that the FTP home directory exists on the FTP server. Also, ensure that the FTP home directory is similar to the user's FTP home directory that is provided in an access profile.

Property Error Messages

This section explains the error messages that you see while performing the property operations in CA Configuration Automation.

CCA-PY-6504**Value <value> is not numeric for Property <propertyname>.****Reason:**

The value <value> is not numeric.

Action:

Provide a numeric value for the property <propertyname>.

CCA-PY-6505**Value <value> is not in range <min> through <max> for Property <propertyname>.****Reason:**

The value <value> is not in the range between <min> and <max>.

Action:

Provide the value between <min> and <max> range.

CCA-PY-6506

Value <value> not in list <allowableValues> for Property <propertyname>.

Reason:

The value <value> is not in the <allowableValues> list.

Action:

Provide a value as one of the <allowableValues>.

CCA-PY-6507

The passwords you entered do not match.

Reason:

The password and the confirm password are not matching.

Action:

Ensure that the value of the password and the confirm password match.

CCA-PY-6510

Security violation error while exporting the property.

Reason:

You do not have permissions to export the property.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to export the property.

CCA-PY-6511

Property <propertyname> already exists.

Reason:

You are importing already existing property without selecting the overwrite flag.

Action:

Select the overwrite flag while importing the already available properties.

Rule Compliance Error Messages

This section explains the error messages that you see while performing the rule compliance operations in CA Configuration Automation.

CCA-RC-8102

Date required.

Reason:

The date field is empty.

Action:

Provide date value, as it is mandatory for the selected rule compliance operation.

CCA-RC-8103

Error while populating rule compliance request.

Reason:

An exception occurred while populating the rule compliance request using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RC-8104

Error while running Server rule compliance request.

Reason:

An exception occurred while running the server rule compliance operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RC-8105

Error while running Service rule compliance request.

Reason:

An exception occurred while running the service rule compliance operation using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RC-8107

Error while running rule compliance.

Reason:

An exception occurred while processing the rule compliance results using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RC-8108

Error while adding failed rule to results.

Reason:

An exception occurred while adding the failed rule to results using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RC-8109

Missing service snapshot or no server in the snapshot, no rule compliance operation will be performed for service <servicename>.

Reason:

The service snapshot is missing.

Action:

Create the required snapshot for the service <servicename>.

CCA-RC-8110

Invalid service name, no rule compliance operation will be performed for service <servicename>.

Reason:

The service <servicename> is not available.

Action:

Create the service <servicename>.

CCA-RC-8111

Missing server snapshot, no rule compliance operation will be performed for server <servername>.

Reason:

The server snapshot is missing.

Action:

Create the required snapshot for the server <servername>.

CCA-RC-8112

Invalid server name, no rule compliance operation will be performed for server <servername>.

Reason:

The server <servername> is not available.

Action:

Create server <servername>

CCA-RC-8114

Service rule compliance failed, error message - <error>.

Reason:

An exception occurred during the rule compliance operation.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-RC-8125

Server <servername> is in unmanaged state, no rule compliance operation will be performed.

Reason:

The server <servername> is in unmanaged state.

Action:

Change the state of the server <servername> to managed.

CCA-RC-8126

Invalid server name, no rule compliance operation will be performed for server <servername> in service <servicename>.

Reason:

Server <servername> is not available.

Action:

Create the server <servername> as part of the service <servicename>.

CCA-RC-8127

Missing server snapshot, no rule compliance operation will be performed for server <servername> in service <servicename>.

Reason:

Components of the server <servername> are not available as part of the service data.

Action:

Ensure that the components of the server <servername> are available as part of the service data.

CCA-RE-1625

Rule Exception with rule <rulename> on blueprint <blueprint name with version> already exists.

Reason:

The rule exception with the same rule name and blueprint name exists in the CCA server.

Action:

Remove the existing rule from the selection list, and add the other rules.

CCA-RE-1634

Rule Exception with rule <rulename> on file structure class <filestructureclass name> already exists.

Reason:

Rule exception with the same rule name and the File structure class name exists in the CCA server.

Action:

Remove the existing rule from the selection list and add the other rules.

CCA-RE-1641

At least one Server or Service is required in a Rule Exception.

Reason:

Select a server or a service to create a rule.

Action:

Ensure that a server or service is added in a rule exception.

Rules Error Messages

This section explains the error messages that you see while performing the rule operations in CA Configuration Automation.

CCA-RL-2509

Failed to get the Rules defined by blueprint <blueprintname>

Reason:

Exception occurred while retrieving the rules defined in blueprint using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

Rule Group Error Messages

This section explains the error messages that you see while performing the rule group operations in CA Configuration Automation.

CCA-RG-1604

Rule Group <groupname> already exists.

Reason:

The rule group already exists with the same <groupname> name.

Action:

Ensure that the rule group name is unique. Provide a different name while adding or updating the rule group.

CCA-RG-1606

Name is required.

Reason:

The rule group name is not provided while creating or updating the server group.

Action:

Provide a rule group name.

CCA-RG-1619

Rule Group cannot be deleted. It is used in one or more Management Profiles.

Reason:

The rule group is used in one or more Management Profiles.

Action:

Ensure that the rule group does not use any management profile before the run rule groups delete operation.

CCA-RG-1620

Rule Group cannot be deleted. It is used in one or more Compliance Jobs.

Reason:

The rule group is used in one or more compliance jobs.

Action:

Ensure that the rule group does not use any compliance job before the run rule group delete operation.

CCA-RG-1622

Rule <rulename> already exists.

Reason:

The rule already exists with the same name <rulename >.

Action:

Ensure that the rule name is unique. Provide different name while adding or updating the rule.

Remediation Jobs Error Messages

This section explains the error messages that you see while performing the remediation jobs in CA Configuration Automation.

CCA-RJ-8002

Remediation Job Name is required

Reason:

Remediation job name is not provided.

Action:

Provide a remediation job name.

CCA-RJ-8003

Please select at least one Remediation Job to perform this operation

Reason:

No remediation job is selected to perform run/delete remediation job operation.

Action:

Select at least one remediation job.

CCA-RJ-8014

Remediation Job <jobname> already exists.

Reason:

Remediation job <jobname> already exists.

Action:

Provide a new name for the remediation job <jobname>.

CCA-RJ-8020

Server <server> already exists in remediation job <jobname>

Reason:

The <server> already exists in the remediation job.

Action:

As this <server> already exists in the remediation job, do not include this <server> again.

CCA-RJ-8022

Server group <servergroup> already exists in remediation job <jobname>

Reason:

The <servergroup> already exists in remediation job.

Action:

As this <servergroup> already exists in the remediation job, do not include this <servergroup> again.

CCA-RJ-8024

Service <service> already exists in remediation job <jobname>

Reason:

The <service> already exists in the remediation job.

Action:

As the <service> already exists in the remediation job, do not include the <service> again.

CCA-RJ-8026

Fail to remove servers from remediation job <jobname>, error message - <error>

Reason:

An error occurred while removing the <server> from the remediation job.

Action:

Log in to CA Configuration Automation as a CCA Administration or CCA Architect to do the operation. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8027

Fail to remove server groups from remediation job <jobname>, error message - <error>

Reason:

An error occurred while removing <servergroup> from the remediation job.

Action:

Log in to CA Configuration Automation as a CCA Administration or CCA Architect to do the operation. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8028

Fail to remove services from remediation job <jobname>, error message - <error>

Reason:

An error occurred while removing the <services> from the remediation job.

Action:

Log in to CA Configuration Automation as a CCA Administration or CCA Architect to do the operation. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8029

User is not authorized to delete existing schedule of remediation job <jobname> error message - <error>

Reason:

You do not have permissions to delete the existing schedule of the remediation job.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to delete the existing schedule of the remediation job <jobname>.

CCA-RJ-8031

User is not authorized to schedule remediation job <jobname>, error message - <error>

Reason:

You do not have permissions to run or schedule the remediation job.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to run or schedule the remediation job <jobname>.

CCA-RJ-8057

Notification for remediation job <jobname> failed, error message - <error>

Reason:

An error occurred while sending notification after running the remediation job.

Action:

Ensure the "mail.to", "mail.from" and "mail.server" properties are configured correctly in the Administration, Configuration, Properties page. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8058

Notification for undo remediation history <jobname> failed, error message - <error>

Reason:

An error occurred while sending notification after running undo remediation job.

Action:

Ensure the "mail.to", "mail.from" and "mail.server" properties are configured correctly in the Administration, Configuration, Properties page. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8059

Notification for rerun remediation history <jobname> failed, error message - <error>

Reason:

An error occurred while sending notification after rerunning the remediation job.

Action:

Ensure the "mail.to", "mail.from" and "mail.server" properties are configured correctly in the Administration, Configuration, Properties page. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8067

Error while getting remediation job/remediation history.

Reason:

An error occurred while getting remediation jobs or history using SDK.

Action:

Verify the exception stack trace and the corresponding operation log details in the Log tab. If security violation exception occurs, verify the login user privileges; or contact CA Technologies Technical Support for further assistance.

CCA-RJ-8071

Remediation job finished with failure.

Reason:

Remediation job <jobname> finished with failure.

Action:

Verify the corresponding operation log details in the Log tab which caused the failure.

CCA-RJ-8075

Cannot create remediation job <jobname> because of scheduling failure, error message - <error>

Reason:

A scheduling error occurred while creating the remediation job.

Action:

If the error message is similar to "The specified time has already passed. Schedule will never trigger", correct the schedule and finish creating the remediation job <jobname>. For other errors, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8076

Cannot update remedaition job <jobname> because of scheduling failure, error message - <error>

Reason:

A scheduling error occurred while updating the remediation job.

Action:

If the error message is similar to "The specified time has already passed. Schedule will never trigger", correct the schedule and finish updating the remediation job <jobname>. For other errors, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8084

Error while adding/updating remediation job.

Reason:

An exception occurred while adding or updating the remediation job <jobname> using SDK.

Action:

Verify the SDK exception stack trace, and the corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8085

Remediation Profile UUID is required.

Reason:

Remediation Profile UUID is required to add or update the remediation job using SDK.

Action:

Use the remediation profile UUID while creating or updating the remediation job using SDK.

CCA-RJ-8086

Error while deleting remediation jobs.

Reason:

An exception occurred while deleting the remediation job <jobname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RJ-8087

Cannot delete profile because it is used in one or more remediation jobs.

Reason:

Remediation profile cannot be deleted, because it is used in one or more remediation jobs.

Action:

Update the remediation jobs to use any other remediation profile and then delete the profile.

CCA-RJ-8088

Remediation Job Name is too long.

Reason:

Job name exceeded the job name column length.

Action:

Ensure that the job name length should not be greater than 200.

Remediation Profile Error Messages

This section explains the error messages that you see while performing the remediation profile operations in CA Configuration Automation.

CCA-RP-1003

Remediation Profile <profilename> already exists.

Reason:

The remediation profile <profilename> already available.

Action:

Provide a unique remediation profile name.

CCA-RP-1010

Remediation Profile Step <stepname> already exists.

Reason:

The remediation profile step <profilestep> already available.

Action:

Provide a unique remediation profile step name.

CCA-RP-1028

New Registry Name required.

Reason:

New Registry name is required while adding the job step.

Action:

Provide a new registry name.

CCA-RP-1035

Remediation Profile <profilename> not found.

Reason:

While doing the context launch for remediation profile, the <profilename> does not exist. Profile might be deleted or incorrect Profile name is provided.

Action:

Provide a profile name which should exist in CCA.

Remediation History Warning Messages

This section explains the warning messages that you see while performing the remediation history operations in CA Configuration Automation.

CCA-RH-1001

Please select at least one Remediation History record to perform this operation.

Reason:

No Remediation History is selected.

Action:

Select at least one Remediation History.

Remote Agent Installation Error Messages

This section explains the error messages that you see while performing the remote agent installation in CA Configuration Automation.

CCA-RI-1411

Remote Agent Install Failed. Error Message: Remote Agent Installation is timed out. Install process is not responding.

Reason:

Possible reasons are as follows:

- Communication to the target server is lost while performing the remote agent installation
- Due to the network latency, the agent build is taking time to copy at the target server and the response did not reach the CA Configuration Automation server within the specified time.

Action:

Verify that the network settings. Ensure that the communication is properly happening between the CA Configuration Automation server and the target machine where the agent has to be installed.

CCA-RI-1412

Remote Agent Install Failed. Error Message: Remote installation process timed out. One possible cause is the absence of a Java VM on the remote system. Try repeating the installation with the 'Install JVM' option set to 'Yes' in the Access Profile.

Reason:

Either the Java virtual machine is unavailable on the target machine, or is not included in the "PATH" environment variable.

Action:

Add the JAVA_HOME\bin directory to the System PATH variable, if it is not already added. Ensure that the JAVA_HOME variable points to a valid Java virtual machine.

CCA-RI-1413

Remote Agent Install Failed. Error Message: OS Platform not supported by Remote Agent Installation.

Reason:

CA Configuration Automation does not support the operating system platform of the target machine where the remote agent installation is attempted.

Action:

Ensure that CA Configuration Automation supports the operating system of the target machine. For more information about the supported agent platforms, see the *Release Notes*.

CCA-RI-1416

The Access Profile <AccessProfileName> does not have a 'System Account' specified. 'System Account' is required for the Remote Agent Install.

Reason:

The System Account field in the access profile that is assigned to the target server is empty.

Action:

Verify the System Account field. Provide a valid user name for the target machine in the System Account field in the access profile, and retry the installation.

CCA-RI-1417

The Access Profile <AccessProfileName> does not have a 'System Password' specified. 'System Password' is required for the Remote Agent Install.

Reason:

The System Password field in the access profile that is assigned to the target server is empty.

Action:

Verify the System Password text field in the access profile. Provide a valid password for the target machine and retry the installation.

CCA-RI-1418

Remote Agent Install Failed. Error Message: No Java VM was found from the PATH environment variable on the remote system. Make sure the Java VM can be found on the remote system from the PATH environment variable for the user specified in the Access Profile.

Reason:

Either Java virtual machine is not available on the target machine, or it is not included in the PATH environment variable.

Action:

Add the JAVA_HOME\bin directory to the System PATH variable, if not already added. Ensure that the JAVA_HOME variable points to a valid Java Virtual machine.

CCA-RI-1419

Remote Agent Install Failed. Error Message: Java VM version <version> was found on the remote system, but does not meet the minimum requirements. Try repeating the installation with the 'Install JVM' option set to 'Yes' in the Access Profile.

Reason:

The remote agent installation requires a java version of 1.4.2 or higher. If the java version on the target machine is less than 1.4.2, this error message is thrown.

Action:

Install a Java virtual machine of 1.4.2 or higher version on the target machine and retry the remote agent installation.

CCA-RI-1420

Remote Agent Install Failed. Error Message : Cannot find Agent Installer <InstallerFileName> for <PlatformName> platform on Grid Node <Grid Node Name>. An invalid or inaccessible directory may have been provided for the Agent Installers during the Server/Grid Node install.

Reason:

Possible reasons are as follows:

- The agent Installers directory is not specified during the CA Configuration Automation server installation.
- Agent installers directory is currently not accessible.

Action:

Verify the <CCA Server Install path>\Agent_Installers directory on the CA Configuration Automation server. Ensure whether the respective platform's agent installer is available or accessible. The <CCA Server Install path>\Agent_Installers directory must have all the agent installers for the remote agent installation to work.

CCA-RI-1421

Cannot install Agent remotely. Unable to put Agent installer on target server

Reason:

Issue while establishing an SFTP session due to insufficient privileges to the user or any problem in the SFTP subsystem on the target machine.

Action:

Ensure that the user specified in the access profile can copy files to the target machine through SFTP.

CCA-RI-1422

Cannot install Agent remotely. Unable to establish SSH connection to the target server

Reason:

The SSH connection from the CA Configuration Automation server to the target server is not working.

Action:

Ensure that the user specified in the access profile can connect to the target machine using SSH.

CCA-RI-1423

Cannot Uninstall Agent remotely. Unable to execute Agent Uninstall on target server

Reason:

Issue while establishing an SFTP session due to insufficient permissions to the user, or any problem in the SFTP subsystem on the target machine.

Action:

Ensure that the user specified in the access profile can copy files to the target machine through SFTP.

CCA-RI-1424

Cannot Uninstall Agent remotely. Unable to establish SSH connection to the target server

Reason:

The SSH connection from CCA Server to the target server is not working.

Action:

Ensure that the user specified in the access profile can connect to the target machine using SSH.

CCA-RI-1425

Install completed successfully, but test server failed for server <ServerName> during Remote Agent Installation.

Reason:

The port specified in the agent access profile is in use or a firewall is running on the target machine blocking the incoming request to an agent.

Action:

Verify the firewall. Ensure that the agent port is configured properly in the firewall settings.

CCA-RI-1426

Remote Agent Uninstall Failed on Server <ServerName>. Error: No Agent has been detected on the remote system.

Reason:

No agent is installed on the target machine, or if an incorrect access profile is assigned to the server while performing the remote agent installation.

Action:

Ensure that the access profile is properly assigned to the server where the agent is being uninstalled.

CCA-RI-1427

Remote Agent Install Failed on Server <ServerName>. Logon failure: unknown user name or bad password.

Reason:

Incorrect username or password specified in the access profile is assigned to the target server.

Action:

Provide a valid username or password in the access profile and retry the operation.

CCA-RI-1428

Remote Agent Install Failed on Server <ServerName>. Port number is already in use.

Reason:

Port number specified in the access profile is already in use on the target machine.

Action:

Change the port number to a different value in the access profile and retry the operation.

CCA-RI-1429

Remote Agent Install Failed on Server <ServerName> Invalid port number.

Reason:

Port number specified in the access profile is invalid.

Action:

Change the port number in the access profile to a valid number. The available port number must be greater than 1024.

CCA-RI-1430

Remote Agent Install Failed on Server <ServerName>. A newer version of the Agent is already installed. To install an older version, uninstall the existing version first.

Reason:

A newer version of the agent exists on the target machine.

Action:

Uninstall the older version manually and then retry the operation.

CCA-RI-1431

Remote Agent Install Failed on Server <ServerName>. Invalid installation location.

Reason:

The installation location specified in the access profile does not exist on the target machine.

Action:

Provide a valid installation location which is available and accessible on the target machine.

CCA-RI-1432

Remote Agent Install Failed on Server <ServerName>. Insufficient disk space at: <Install Location>

Reason:

Not enough free space on the installation directory that is specified in the access profile.

Action:

Ensure that the installation directory specified in the access profile has enough free space for the agent installation.

CCA-RI-1433

Remote Agent Install Failed. Error Message: A Java VM was found on the remote system, but does not meet the installer requirements. Try repeating the installation with the 'Install JVM' option set to 'Yes' in the Access Profile.

Reason:

The agent installer check for a Java virtual machine version which is compatible with installAnywhere. If it finds a Java virtual machine incompatibility with the installAnywhere, the error is thrown.

Action:

Change the Java virtual machine version on the target machine to a valid Java virtual machine which is compatible with the agent installer. The Java virtual machine version must be higher than 1.4.2.

CCA-RI-1434

Could not authenticate <username> with provided password on host

Reason:

The user password specified in the access profile is incorrect.

Action:

Provide the correct password and retry the operation.

CCA-RI-1435

The Access Profile <Access Profile Name> has environment variable <Variable name> specified in install directory. But this variable value could not be resolved on Server <Target Server Name>.

Please make sure that the environment variable is defined on target server.

Reason:

Before installing the remote agent on the target server, the environment variables that are mentioned in the access profile are resolved. If the environment variable is not defined on the target machine, the remote agent installation fails.

Action

Ensure that the environment variable mentioned in the access profile is defined on the target server, and available for remote agent installation process.

Reports Error Messages

This section describes the error messages that you get while performing the report operations.

CCA-RT-6011

Report name required.

Reason:

Report name is not provided while creating or updating or running the report.

Action:

Provide a report name.

CCA-RT-6019

User does not have the permissions to perform the operation : <operation>.

Reason:

Only instance owner can share or unshare the report instance.

Action:

Log in to CA Configuration Automation as the owner of report instance to share or unshare the report instance.

CCA-RT-6020

Can not view a report instance with current status : <currentstatus>.

Reason:

Cannot view a report instance with failed as the current status.

Action:

Click the report instance with complete as the status.

CCA-RT-6023

Report parameters are invalid. Please contact the administrator.

Reason:

Invalid parameters are provided in launch in context URL.

Action:

Provide a valid report instance ID, and format.

CCA-RT-6025

Task submission failed for some of the selected reports. See Log tab for further details.

Reason:

The possible exception is security violation.

Action:

Log in to CA Configuration Automation as an Administrator or Architect to run the saved report.

CCA-RT-6031

Invalid Date Range.

Reason:

The date range field is empty.

Action:

Provide a numeric value in the date range field.

CCA-RT-6032

Service is required

Reason:

The service data is not provided while creating or updating or running the report.

Action:

Provide a service data.

CCA-RT-6033

Server is required.

Reason:

The server data is not provided while creating, or updating, or running the report.

Action:

Provide a server data.

CCA-RT-6034

Search text is required.

Reason:

Search text is not provided while creating or updating or running the Pattern search service report.

Action:

Provide a search text.

CCA-RT-6035

Blueprint is required.

Reason:

Blueprint name is not provided while creating or updating or running the Rule Definition Blueprint Report.

Action:

Provide the blueprint name.

CCA-RT-6037

Password and Retype Password must be equal.

Reason:

Password and retype password value does not match in the destination folder.

Action:

Ensure that the password and retype password value match.

CCA-RT-6038

Server is required.

Reason:

Server data is not provided either in the target tab or destination tab while creating, or updating, or running report.

Action:

Provide a server name.

CCA-RT-6039

Path is Required

Reason:

Path field is empty in the destination tab.

Action:

Provide path where the report result file has to be copied.

CCA-RT-6040

File Name is Required

Reason:

File name field is empty in the destination tab.

Action:

Provide file name that is used to create a report result file.

CCA-RT-6042

Password required.

Reason:

Password is not provided in the Destination tab while running, or saving a report.

Action:

Provide a password.

CCA-RT-6041

User or Login is required.

Reason:

The User or Login field is empty in the destination tab.

Action:

Provide a user name.

CCA-RT-6043

Password and Retype Password must be equal.

Reason:

Password and Retype Password does not match in the destination folder.

Action:

Ensure that the value of the password and retype password values match.

CCA-RT-6046

Report <reportname> already exists.

Reason:

The <reportname> already exists.

Action:

Provide different report name while creating a new saved report.

CCA-RT-6047

Failed to get the report instances. - <errormessage>

Reason:

Possible reasons are as follows:

- Invalid values are configured for the following properties in the BO group in the CCA Properties tab:
 - http.port
 - http.server
 - admin.user
 - admin.password
- Services under Central Configuration Manager are not running where the CABI server is installed.
- Connection from CA Configuration Automation to the CABI server is not established.

Action:

- Ensure configured correct values to the following properties:
 - http.port
 - http.server
 - admin.user
 - admin.password
- Ensure all the services under Central Configuration Manager are running.
- Also verify the test connection from CCA to CABI server from Universe Designer, ensure that the server is responding for CCA application. If the server is not responding, contact CABI administrator.

CCA-RT-6052

Snapshot is required

Reason:

Snapshot is not selected in the Target tab while creating, or updating, or running report.

Action:

Select a snapshot in the Target tab.

CCA-RT-6053

Execution of report <reportname> failed. - <errormessage>

Reason:

Possible reasons are:

- Invalid values are configured for the following properties:
 - http.port
 - http.server
 - admin.user
 - admin.password
- Services under Central Configuration Manager are not running where the CABI server is installed.
- Connection from CCA to the CABI server is not established.

Action:

- Ensure that you configured correct values to the following properties:
 - http.port
 - http.server
 - admin.user
 - admin.password
- Ensure all the services under Central Configuration Manager are running.
- Verify the test connection from the CA Configuration Automation to CABI server from Universe Designer.
- Ensure that the server is responding to the CA Configuration Automation application. If the server is not responding, contact the CABI administrator.

CCA-RT-6058

Report <reportname> has been saved. But scheduling of report failed. - <errormessage>

Reason:

The specified schedule time is over. Schedule will never trigger

Action:

Change the schedule time, ensure that the schedule time is greater than current time.

CCA-RT-6061

Source Server is required.

Reason:

Source server is not selected in the target tab while running, or creating, or updating the report.

Action:

Select source server in the target tab.

CCA-RT-6063

Target Server is required.

Reason:

Target server is not selected in the Target tab while running or creating or updating the report.

Action:

Select target server in the target tab.

CCA-RT-6066

Error while adding report <reportname> of type <reporttype>

Reason:

An exception occurred while adding report using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RT-6067

Error while deleting report <reportname>

Reason:

An exception occurred while deleting the saved report <reportname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RT-6068

Error while getting report <reportname>

Reason:

An exception occurred while getting the saved report <reportname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RT-6069

Error while getting reports

Reason:

An exception occurred while getting the saved report <reportname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RT-6070

Error while updating report <reportname>

Reason:

An exception occurred while updating the saved report <reportname> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-RT-6071**Remediation Job is Required.****Reason:**

Remediation job is not selected or provided while creating or updating or running the remediation Jobs (Service) report.

Action:

Provide or select a remediation job.

CCA-RT-6072**Server or Server Group is required.****Reason:**

Server or server group is not selected or provided while creating or updating or running rule compliance server report.

Action:

Provide or select a server or server group.

CCA-RT-6073**Domain Name is required.****Reason:**

Domain name is not selected or provided while creating or updating or running Server Domain Membership Report.

Action:

Provide or select the domain name.

CCA-RT-6074**Patch Name is required.****Reason:**

Patch name is not selected or provided while creating, or updating, or running the Server Patch Distribution Report.

Action:

Provide or select a patch name.

CCA-RT-6078

Execution of scheduled report <reportname> failed. - <errormessage>.

Reason:

Possible reasons are:

- Invalid values are configured for the following properties in the BO group in the CCA Properties tab:
 - http.port
 - http.server
 - admin.user
 - admin.password
- Services in the Central Configuration Manager are not running where the CABI server is installed.
- Connection from CA Configuration Automation to the CABI server is not established.

Action:

- Ensure configured valid values to the following properties:
 - http.port
 - http.server
 - admin.user
 - admin.password
- Ensure all the services under Central Configuration Manager are running.
- Also verify the test connection from CA Configuration Automation to CABI server from Universe Designer.
- Ensure that the server is responding to the CA Configuration Automation application. If the server is not responding, contact the CABI administrator.

CCA-RT-6082

"If 'From date' is entered then 'To date' is required."

Reason:

The From date is provided, but "To date" is not provided while creating or updating or running report using SDK.

Action:

Provide From Date and To Date.

CCA-RT-6083

"If 'To date' is entered then 'From date' is required."

Reason:

The To date value is provided, but the From date value is not provided while creating or updating or running report using SDK.

Action:

Provide To date and From date values.

CCA-RT-6084

"To Date should be greater than or equal to From Date"

Reason:

The To date value is less than the From date value while creating, or updating, or running the report using SDK.

Action:

Ensure that the To Date value is greater than, or equal to the From Date value.

CCA-RT-6088

Component is required.

Reason:

Component is not provided, or selected while creating, or updating, or running the Component Details Server or Component Details Service report.

Action:

Provide or select the component data.

CCA-RT-6089

Report name is too long.

Reason:

Length of the Report name is greater than 200.

Action:

Ensure that the length of the report name is less than, or equal to 200.

CCA-RT-6090

Component is missing or does not exist.

Reason:

The component is deleted or does not exist while running the Component Details Server, or Service report.

Action:

Ensure that the provided component exists in the corresponding server or service.

CCA-RT-6091

Blueprint or Blueprint Category or Blueprint Group is required.

Reason:

The Blueprint or Blueprint Category or Blueprint Group is not selected while creating, or updating, or running the Blueprint Source Details Report.

Action:

Select Blueprint, or Blueprint Category, or Blueprint Group.

CCA-RT-6097

There is a problem with the selected report, it can not be loaded. Please select a another report.

Reason:

The selected report cannot be loaded.

Action:

Select another report.

CCA-RT-6098

Retype Password required.

Reason:

No password is provided in the Retype Password field of the Destination tab while running, or a saving report.

Action:

Confirm the password in the Retype Password field.

SDK Error Messages

This section explains the error messages that you see while performing the SDK operations in CA Configuration Automation.

CCA-AU-9681

Error while scheduling ccautil job

Reason:

An exception occurred while scheduling job with the SDK scheduleAcmutilJob API.

Action:

If it is a security violation, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CI-9621

Error while getting item of type <Cltype>

Reason:

Exception occurred while retrieving the Configuration Item(CI) details from CCA with SDK API or command-line Utility.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CI-9622

Error while deleting item of type <Cltype>

Reason:

Exception occurred while deleting the Configuration Item(CI) details from CCA with SDK API or command-line Utility.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CI-9624

Error while updating CI

Reason:

Exception occurred while updating the Configuration Item(server/serverGroup/service) details with SDK API or command-line Utility.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CI-9625

value passed is null or invalid

Reason:

Values sent to the SDK API or command-line Utility for invoking APIs are null or empty.

Action:

Provide the valid arguments for the SDK and command-line utility APIs.

CCA-CI-9626

Invalid server state, only New or Managed is allowed while adding Server

Reason:

Server is not in New or Managed State while adding the target server with SDK.

Action:

While adding a target server using the SDK, provide or set the target server state to NEW or Managed.

CCA-OP-9644

SDK feature is not enabled

Reason:

In the Administration properties tab Sdk.enabled flag is set to false.

Action:

Set the sdk.enabled flag value in the Administration properties tab to true to enable the SDK API.

CCA-OP-9645

The <discovery/management/refresh> operation can be performed on servers in Managed state only

Reason:

Running discovery, or refresh, or management operation on a server which is not in managed state.

Action:

Change the server state as managed and run the discovery, or refresh, or management operation.

CCA-RT-9651

Report target details are required

Reason:

Report Target details are not provided while adding or updating the customized report.

Action:

Provide the target (server or service) details while calling the addcustomizedreport API or the updatecustomizedreport API through the SDK.

CCA-RT-9652

Snapshot date is required

Reason:

For the snapshot type Most recent snapshot on the specified date, source or target snapshot date is not provided while adding or updating the customized report with SDK.

Action:

Provide a source or target snapshot date while calling the add or updatecustomizedreport API through SDK for the snapshot type *Most recent* snapshot on the specified date.

CCA-RT-9653

Invalid date <date>. The date provided is not in the format MM/DD/YYYY

Reason:

For the snapshot type *Most recent snapshot* on the specified date, the source or target snapshot date is not provided in MM/DD/YYYY format while adding or updating the customized report with the SDK or command-line utility API.

Action:

Provide a source or target snapshot date in the MM/DD/YYYY format while calling the add or updatecustomizedreport API through SDK or command-line utility API for the snapshot type *Most recent snapshot* on the specified date.

CCA-RT-9654

Invalid date <date>. The date provided is not in the format MM/DD/YYYY HH:MM:SS

Reason:

The date range (fromDate or toDate) is not provided in MM/DD/YYYY HH:MM:SS format while adding or updating the customized report with SDK or command-line utility API.

Action:

Provide a date range in MM/DD/YYYY HH:MM:SS format while calling the add or updatecustomizedreport API through the SDK or command-line utility API.

CCA-CR-9671

Error while getting relationships

Reason:

An exception occurred while retrieving the communication or configuration relationships with the SDK or command-line utility API.

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CR-9672**Error while getting public IP addresses for server <servername>****Reason:**

An exception occurred while retrieving the public IP addresses for the given server with SDK API .

Action:

If it is security violation exception, verify the user permissions; or contact CA Technologies Technical Support for further assistance.

CCA-CR-9673**Error while getting storage system managers****Reason:**

Exception occurred while retrieving the storage system managers with SDK.

Action:

If it is security violation exception, then check the user privileges. Contact CA Technologies Technical Support for further assistance.

Server Error Messages

This section explains the error messages that you see while performing the server operations in CA Configuration Automation.

CCA-SR-1009**Server <servername> already exists.****Reason:**

The server <servername> already available.

Action:

No action is.

CCA-SR-1011**Server cannot be deleted. It exists in a Service.**

Reason:

Server exists in one or more services.

Action:

Remove the server from the services before you delete the server.

CCA-SR-1013

Name or IP Address is required.

Reason:

The Name or IP value is not provided.

Action:

Provide the server name or IP Address.

CCA-SR-1017

Select CSV file to add servers.

Reason:

The CSV file is not provided.

Action:

Select the CSV file to add servers.

CCA-SR-1024

A server with the same name or IP address already exists in the database.

Reason:

The server is already available in the database.

Action:

No action is required.

CCA-SR-1047

Execution of Management profile for Server <servername> failed.

Reason:

Connection to the server <servername> cannot be established using the assigned access profile.

Action:

Ensure to set the correct access mode and other required values in the assigned access profile. Verify that status of the test server action is successful.

CCA-SR-1049**File has invalid format for servers add.****Reason:**

The CSV file has invalid format.

Action:

Provide a valid CSV file.

CCA-SR-1053**One or more selected servers are part of services and cannot be unmanaged.****Reason:**

One or more selected servers are part of the services.

Action:

Remove the servers from the services before performing the unmanaged operation.

CCA-SR-1054**One or more selected servers are part of server groups and cannot be unmanaged.****Reason:**

One or more selected servers are part of the server group.

Action:

Remove the servers from server groups before unmanaged.

CCA-SR-1060**Server cannot be deleted. It is used in one or more Management Profiles.**

Reason:

The server is used in one or more management profiles.

Action:

Remove the server from management profiles before deleting it.

CCA-SR-1061

Server cannot be deleted. It is used in one or more Access Profiles.

Reason:

The server is used in one or more Access Profiles.

Action:

Remove the server from the Access Profiles before deleting it.

CCA-SR-1067

Connection to host <hostname> failed

Reason:

Not able to connect the host <hostname>.

Action:

Ensure that the host <hostname> is pingable.

CCA-SR-1068

Access mode <accessmode> for <hostname > is not responding.

Reason:

Notable to access the host <hostname> using the assigned access mode <accessmode>.

Action:

Ensure to set the correct access mode and other required values in the assigned access profile. Verify that the status of the test server action is successful.

CCA-SR-1069

Error while trying to test host <hostname>.

Reason:

Notable to access the host <hostname> using the assigned access mode <accessmode>.

Action:

Ensure that the host <hostname> is pingable. Set the correct access mode and other required values in the assigned access profile. Verify that the status of the test server action is successful.

CCA-SR-1070**Error while updating managed status of server.****Reason:**

An exception occurred while updating the managed status of the server using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1071**Error while assigning profile of type <profile type> to <CI type>.****Reason:**

An exception occurred while assigning profile of type <profile type> to <CI type> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1072**Error while adding server <servername>.****Reason:**

An exception occurred while adding the server <servername> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1073

Error while getting all servers.

Reason:

An exception occurred while retrieving all the servers using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1074

Error while getting server <server>.

Reason:

Exception occurred while retrieving the server <servername> by server name or IP Address using SDK.

Action:

Ensure that the server name or IP address is valid and exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1075

Error while getting server by UUID <uuid>.

Reason:

An exception occurred while retrieving a server by UUID <uuid> using SDK.

Action:

Ensure that the server UUID <uuid> is valid and exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1076

Server by UUID <uuid> not found.

Reason:

The server <uuid> does not exist in CCA.

Action:

Provide a valid server UUID.

CCA-SR-1077**Error while getting server snapshots by UUID <uuid>.****Reason:**

An exception occurred while retrieving the server snapshots using the server UUID <uuid>.

Action:

Ensure that the server UUID <uuid> is valid and exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1078**Error while getting server activity for server <servername>.****Reason:**

An exception occurred while getting server activity for the server <servername>.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1079**Error while securing agents.****Reason:**

Exception occurred while securing the agents.

Action:

Ensure that the access mode type Agent or Secure Agent is assigned to the selected servers and set the required values in the assigned access profile. Verify that the status of the test server action is successful. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1088**Invalid OS family.**

Reason:

Found invalid operating system while installing the remote agent.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-SR-1094

Server cannot be deleted. It is used in one or more Network Profiles.

Reason:

Server is used in one or more network profiles.

Action:

Remove the server from network profiles.

CCA-SR-1098

Error creating Network Discovery Gateway: <error>.

Reason:

The Network Discovery Gateway service is not running, or incompatible version of Network Discovery Gateway is detected.

Action:

Ensure that the compatible version of Network Discovery Gateway service is running. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SR-1102

Malformed export file - Server Name not found.

Reason:

The corrupted JAR file is used to import the servers.

Action:

Use the original JAR file which is exported from CA Configuration Automation to import the servers.

CCA-SR-1109

Network Discovery Gateway <ndgservername> is currently assigned to at least one server.

Reason:

Trying to delete the Network Discovery Gateway <ndgservernam> which is assigned to one or more servers.

Action:

Ensure that the Network Discovery Gateway <ndgservername> is not assigned to any of the servers. Assign other Network Discovery Gateways to all the servers before you delete the Network Discovery Gateway <ndgservername>.

CCA-SR-1110

Network Discovery Gateway <ndgservername> is currently assigned to at least one network profile.

Reason:

Trying to delete the Network Discovery Gateway <ndgservername> which is assigned to one or more network profiles.

Action:

Ensure that the Network Discovery Gateway <ndgservername> is not assigned to any network profile. Create and assign different Network Discovery Gateway to all the network profiles before you delete the Network Discovery Gateway <ndgservername>.

CCA-SR-1111

The last Network Discovery Gateway cannot be removed.

Reason:

Only one Network Discovery Gateway exists and you cannot delete it.

Action:

Create and use a new Network Discovery Gateway, and delete the old Network Discovery Gateway.

CCA-SR-1112

Network Discovery Gateway cannot be assigned to itself.

Reason:

A Network Discovery Gateway cannot be assigned to itself.

Action:

Assign another Network Discovery Gateway.

CCA-SR-1124

Enter a valid port number.

Reason:

The agent port value that you provided while performing an auto locate operation is either negative or a nonnumeric.

Action:

Provide a valid agent port value.

CCA-SR-1125

Server <servername> / <ipaddress> not found.

Reason:

An error occurred in launch in context operation. Server <servername> or <ipaddress> is not available in CCA.

Action:

Provide a valid <servername> or <IPaddress> in the launch in context URL.

CCA-SR-1130

Remote Agent Install Failed. Error Message : Cannot install Windows agent from a non-Windows server.

Reason:

You are installing windows CCA agent from a CCA Server where the CCA Server is installed on a non-windows server.

Action:

Install the windows CCA agent from a CCA server where the CCA server is installed on the windows server.

CCA-SR-1131

Server <servername1> is associated with IP <ipaddress> that is already being used by server <servername2>. Please perform IP Reconciliation or Delete Server action on server <servername2>, then retry Create Server operation.

Reason:

The server <servername1> is associated with IP <ipaddress> that is used by the server <servername2>.

Action:

Perform IP Reconciliation or Delete Server action on server <servername2>, then retry the Create Server operation.

CCA-SR-1132

Invalid job name.

Reason:

Job name is invalid.

Action:

Provide valid job name.

CCA-SR-1134

Found duplicate IP address <ipaddress> in network realm <realmname>. Fail to set network realm for server <servername>.

Reason:

Network realm <realmname> already has one server with same the IP address <ipaddress>.

Action:

Set another network realm for the server <servername>.

CCA-SR-1135

Found duplicate IP address <ipaddress> in network realm <realmname>. Fail to add server <servername>.

Reason:

The network realm <realmname> already has one server with the same IP address <ipaddress>.

Action:

Set another network realm for the server <servername>.

CCA-SR-1136

Found duplicate IP address <ipaddress> in network realm <realmname>.

Reason:

The network realm <realmname> already has one server with the same IP address <ipaddress>.

Action:

Set another network realm for the server <ipaddress >.

CCA-SR-1140

Out-of-box self registered access profile is not available.

Reason:

The access profile Self Registered is not available.

Action:

Create access profile Self Registered with agent mode as Self Registered Agent, and enable the Agent Logging and Server Ping options in it.

CCA-SR-1142

Discovery failed for Server <servername>, skip management option job execution.

Reason:

Connection to the server <servername> cannot be established using the assigned access profile.

Action:

Ensure that the access profile with proper access mode is assigned to the server <servername>. Verify that the status of test servers operation is successful for the server <servername>.

CCA-SR-1143

Refresh failed for Server <servername>, skip management option job execution.

Reason:

Connection to the server <servername> cannot be established using the assigned access profile.

Action:

Ensure that the access profile with proper access mode is assigned to the server <servername>. Verify that the status of test servers operation is successful for the server <<servername>.

CCA-SR-1144

Discovery failed for Service <servicename>, skip management option job execution.

Reason:

Connection to one or more servers in the service <servicename> cannot be established using assigned access profile to the servers.

Action:

Ensure that the access profile with proper access mode is assigned to the servers in the service <servicename>. Verify that the status of test servers operation is successful for the servers in the service <servicename>.

CCA-SR-1145

Refresh failed for Service <servicename>, skip management option job execution.

Reason:

Connection to one or more servers in the service <servicename> cannot be established using the assigned access profile to the servers.

Action:

Ensure that the access profile with proper access mode is assigned to the servers in the service <servicename>. Verify that the status of test servers operation is successful for the servers in the service <servicename>.

CCA-SR-1148

Change Detection/Compare/Rule Compliance failed for Server <servername>, skip snapshot creation.

Reason:

Change Detection/Compare/Rule Compliance failed for Server <servername>.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-SR-1153

Server by UUID <uuid> cannot be deleted.

Reason:

The server UUID is not part of the service.

Action:

Ensure that the server <uuid> is part of the service.

CCA-SR-1154

Server cannot be deleted. It is part of a remediation job.

Reason:

Server is part of a remediation job.

Action:

Remove the server from the remediation job.

CCA-SR-1158

Job name is required.

Reason:

The job name is not provided.

Action:

Provide the job Name.

CCA-SR-1159

Job name is too long.

Reason:

SDK validation error, Job name longer than job name column length.

Action:

Ensure that the job name length should not be greater than 200.

CCA-SR-1162

Reconciliation failed for server <servername>.

Reason:

Network Discovery Gateway is not responding.

Action:

Ensure that the Network Discovery Gateway service is running. Verify that the status of test Network Discovery Gateway is responding.

CCA-SR-1163

OS Name is a required field. Please select a valid OS Name.

Reason:

Operating System Is not selected while adding server.

Action:

Select a valid operating system.

CC-SR-1171

Server <ServerName> is already added in CCA Server with the alias name <Alias hostname>. Please delete the existing alias host from server table to manage the server with desired hostname.

Reason:

You are adding an existing server with the different alias names while creating a server using the NDG option.

Action:

Do *one* of the following:

- Delete the existing server which is available with the alias name, and add a server with the actual host name.
- Use the existing server with the alias name as it is already available in the server table.

Structure Class Error Messages

This section explains the error messages that you see while performing the structure class operations in CA Configuration Automation.

CCA-SC-5007

Name is required.

Reason:

File structure class name is not provided while creating a structure class.

Action:

Provide a file structure class name.

CCA-SC-5012

Cannot delete File Structure Class <fscname>. It is used in this blueprint.

Reason:

File structure class <fscname> is used in the blueprint.

Action:

Update the blueprint to use another FSC, or stop using the file structure class <fscname>, and then delete the <fscname>.

CCA-SC-5014

Cannot delete the selected File Structure Classes because it is used in one or more blueprints.

Reason:

The file structure class <fscname> is used in one or more blueprints.

Action:

Update all the blueprints to use another file structure class, or stop using the file structure class <fscname>, and then delete the <fscname>.

CCA-SC-5015

CCA pre-built File Structure Classes cannot be deleted.

Reason:

You cannot delete the pre-build file structure class.

Action:

No action is required.

CCA-SC-5020

Please save Structure Class before continuing. Or click "Cancel" to cancel without making any changes.

Reason:

Save the structure class first before you click the Finish button.

Action:

Save the structure class before you select Finish.

CCA-SC-5022

Invalid enumeration values. Valid values should be comma separated (for example: 1, 4, 3).

Reason:

Invalid enumeration values are provided. The values should be comma-separated integers.

Action:

Provide a valid enumeration value.

CCA-SC-5023

Invalid integer range. Minimum and maximum valid values should be separated by a dash (for example: 1-11).

Reason:

Integer range should be provided as Minimum and maximum valid values are separated by a dash.

Action:

Provide a valid integer range.

CCA-SC-5026

Version is required.

Reason:

The structure class version is not provided.

Action:

Provide a structure class version.

CCA-SC-5027

Name is required.

Reason:

Structure class name is not provided.

Action:

Provide a structure class name.

CCA-SC-5028

Structure Class already exists. [Name, version] and [display name, version] must be unique.

Reason:

Structure already class exists.

Action:

Use a different name or version, and save the structure class.

CCA-SC-5032

Structure Class already exists.

Reason:

Structure class already exists.

Action:

Select *Overwrite Existing Structure Classes* while importing the structure classes to overwrite an already existing structure class.

CCA-SC-5034

No Parser specified in selected File Structure Class.

Reason:

Missing parser information in the file structure class.

Action:

Close the Browse Server dialog window. Select a parser and browse it.

CCA-SC-5035

Invalid structure class name. The following characters are not allowed: < > ; : " ' = \ \ | ?

Reason:

Structure class name should not contain these special characters: < > ; : " ' = \ \ | ?.

Action:

Avoid invalid characters in the structure class.

CCA-SC-5036

Invalid version. The following characters are not allowed: < > ; : " ' + = \ \ / | ?

Reason:

Version should not contain these special characters: < > ; : " ' + = \ \ / | ?.

Action:

Avoid invalid characters in the version.

CCA-SC-5037

Cannot move parameter <parametername> up. It is already the first parameter.

Reason:

<parametername> is already the first parameter.

Action:

No action is required.

CCA-SC-5038

Cannot move group <groupname> up. It is already the first group.

Reason:

<groupname> is already the first group.

Action:

No action is required.

CCA-SC-5039

Cannot move parameter <parametername> down. It is already the last parameter.

Reason:

<parametername> is already the last parameter.

Action:

No action is required.

CCA-SC-5040

Cannot move group <groupname> down. It is already the last group.

Reason:

<groupname> is already the last group.

Action:

No action is required.

CCA-SC-5051

Security violation while importing FSC: <fsc name>

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect.

CCA-SC-5052

Duplicate object exception while importing FSC: <fsc name>

Reason:

File structure class already exists.

Action:

Ensure that you select Overwrite Existing Structure Classes to overwrite the existing FSCs.

CCA-SC-5056

Error while writing XML for the parser <parser name> into the file stream.

Reason:

An error occurred while writing XML for the parser <parser name> into the file stream

Action:

Do the following:

Ensure that you required permissions to write to file system.

System has enough free disk space.

If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SC-5057

Parser already exists

Reason:

Parser already exists while importing the Parser.

Action:

Ensure to select Overwrite Existing Structure Classes to overwrite the existing Parsers.

CCA-SC-5058

Duplicate object exception while importing parser: <parser name>

Reason:

Parser already exists.

Ensure:

Ensure that the Overwrite Existing Structure Classes to overwrite the existing Parsers.

CCA-SC-5060

Security violation while importing parser:

Reason:

You do not have permissions to perform this operation.

Action:

Log in to CA Configuration Automation as an Administration or Architect.

Server Groups Error Messages

This section describes the error messages that you get while performing the server groups operations.

CCA-SG-1504

ServerGroup <groupname> already exists.

Reason:

The server group already exists with the same name <groupname>.

Action:

The server group name should be unique. Provide a different name while adding or updating the server group.

CCA-SG-1506

Name is required.

Reason:

The server group name is not provided while creating or updating the server group.

Action:

Provide a server group name.

CCA-SG-1510

Error while adding server group <groupname>.

Reason:

A duplicate exception occurred while creating the server group using SDK.

Action:

The server group name should be unique. Provide different server group name. Verify the SDK exception stack trace, If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SG-1515

Filter is required for Dynamic Server Group.

Reason:

The filter is not selected while creating the dynamic server group.

Action:

Select filter to create a dynamic server group.

CCA-SG-1517

Server Group by UUID <groupuuid> not found

Reason:

Invalid server group UUID <groupuuid> is provided while adding the server group to service using SDK.

Action:

Provide a valid server group UUID available in CA Configuration Automation.

CCA-SG-1518

Server Group by UUID <groupuuid> can not be deleted.

Reason:

Invalid server group UUID <groupuuid> is provided while deleting the server group from service using SDK.

Action:

Provide a valid server group UUID available in CA Configuration Automation.

CCA-SG-1519

Failed to add a Server specified in the input to ServerGroup <groupuuid>. Server does not exist.

Reason:

Adding invalid server object to the server group <groupuuid> using SDK.

Action:

Ensure to set valid server objects to the server group while updating the server group.

CCA-SG-1520

Failed to add a Server <servername> specified in the input to Server Group <groupuuid>. Server does not exist.

Reason:

You are adding the server <servername> with the rejected state, or new server to the group <groupid>. Server group only allows servers with managed state.

Action:

Change the state of the servers to managed before adding to the server group.

CCA-SG-1521

Server group cannot be deleted. It is part of a Service.

Reason:

The server group is part of service.

Action:

Remove the server group from service before you delete the server group.

CCA-SG-1524

Security violation error while exporting the server groups.

Reason:

You are not authorized to run the export operation.

Action:

Log in to CA Configuration Automation as an administration or architect to run export operation.

Security Certificate Error Messages

This section explains the error messages that you see while performing the security certificate operations in CA Configuration Automation.

CCA-CT-9409

Server is required**Reason:**

The server name is not provided to create a certificate.

Action:

Provide a server name to create a certificate.

CCA-CT-9410

Certificate Password is required**Reason:**

Certificate password is not provided to create a certificate.

Action:

Provide certificate password to create a certificate.

CCA-CT-9412

Certificate Authority Password is required**Reason:**

Certificate authority password is not provided to create a certificate.

Action:

Provide certificate authority password to create a certificate.

CCA-CT-9413

Password is required**Reason:**

Password is not provided.

Action:

Provide the password.

CCA-CT-9414

Password must be at least 6 characters

Reason:

Password length is less than six characters.

Action:

Provide password with six or more characters.

CCA-CT-9415

Agent Certificate Password is required

Reason:

The agent certificate password is not provided.

Action:

Provide the agent certificate password.

CCA-CT-9427

Server Certificate Password is required

Reason:

The server certificate password is not provided.

Action:

Provide the server certificate password.

CCA-CT-9428

HTTPS Certificate Password is required

Reason:

The HTTPS Certificate Password is not provided.

Action:

Provide HTTPS certificate password.

CCA-CT-9434

Could not send certificate data to agent.

Reason:

An exception occurred while creating the certificate authority.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9436

Invalid certificate purpose.

Reason:

The certificate purpose is not valid.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9438

Could not create agent certificate files. <errormessage>.

Reason:

An exception occurred while creating the agent certificate file.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9440

Failed to create some files in the certificate authority directory <CADirectoryname>.

Reason:

An exception occurred while creating the CA Directories.

Action:

Contact CA Technologies Technical Support for further assistance

CCA-CT-9441

Operation failed. Check certificate authority password

Reason:

The certificate authority password is not valid.

Action:

Provide a valid certificate authority password.

CCA-CT-9443

Failed to run openssl operation.

Reason:

An exception occurred while running the OpenSSL operation.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9446

Keytool failed to run.

Reason:

The Keytool run failed.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9448

Keytool executable <executablenamewithpath> not present in installation

Reason:

The keytool executable is missing.

Action:

Copy the keytool.exe file from the available JRE library.

CCA-CT-9450

Failed to update Tomcat configuration file <configurationfilenamewithpath>.

Reason:

An exception occurred while updating the Tomcat configuration file.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9453

Failed to generate configuration file for OpenSSL.

Reason:

An exception occurred while creating the configuration file for OpenSSL executable.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9454

Certificate file <certificatefilenamewithpath> not available anymore. Please regenerate

Reason:

The certificate file <configurationfilenamewithpath> is not available.

Action:

Regenerate the certificate file.

CCA-CT-9456

OpenSSL executable <OpenSSLExecutableNameWithPath> missing from server installation.

Reason:

The OpenSSL executable is not available in the path <OpenSSLExecutableNameWithPath>.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9457

Failed to complete operation. Please make sure your Solaris installation supports /dev/random. See <http://sunsolve.sun.com/search/document.do?assetkey=1-25-27606-1> for details.

Reason:

Solaris installation is not supporting /dev/random.

Action:

Ensure that the Solaris installation supports /dev/random. For more information about the Solaris installation, see the Solaris installation documentation.

CCA-CT-9458

Operation failed. Check certificate password

Reason:

The https password or trust store password is not provided.

Action:

Provide values for https or trust store password.

CCA-CT-9461

Reason:

Exception occurred while destroying Certificate Authority.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9462

Certificate Authority does not exists

Reason:

Certificate authority is not available and you are trying to create certificate.

Action:

Create a certificate authority before you create a certificate or enable https.

CCA-CT-9463

Failed to delete directory <content>

Reason:

Failed to delete the directory while destroying the certificate authority.

Action:

Delete the directory manually.

CCA-CT-9464

Failed to delete file <content>

Reason:

Failed to delete the file while destroying the certificate authority.

Action:

Delete the file manually.

CCA-CT-9465

<certificatepurpose> Certificate for Server <servername> already exists

Reason:

The <certificatepurpose> certificate already exists for the server <servername>.

Action:

As the same certificate already exists, do not create new Certificate with the same purpose.

CCA-CT-9466

The passwords you entered do not match

Reason:

The password and confirm password does not match.

Action:

Provide a same value for the password and confirm password.

CCA-CT-9468

Error while reading the file.

Reason:

An exception occurred while reading the keystore or truststore content.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9470

Failed to secure <failurecount> agents

Reason:

The agent is not reachable or the agent is already secured .

Action:

Ensure that the agent is reachable and the agent is not secured. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-CT-9472**Invalid arguments****Reason:**

ca or server password is not valid

Action:

Provide valid ca or server passwords.

CCA-CT-9474**Failed to load CCA Security certificates.****Reason:**

Not able to find the required certificates in the installation folder. There might be an issue with the certificates which you are trying to create or retrieve.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-CT-9487**EEM Admin Username is required****Reason:**

Username is not provided.

Action:

Provide EEM Admin username.

CCA-CT-9488**EEM Admin Password is required****Reason:**

Password is not provided.

Action:

Provide EEM Admin password.

CCA-CT-9489

Invalid EEM Admin credentials. <errormessage>

Reason:

The EEM admin username or password is not valid.

Action:

Provide a valid EEM admin username and password.

CCA-CT-9490

Please select certificate of purpose "Client Authentication".

Reason:

The selected certificate purpose is not Client Authentication.

Action:

Select certificate purpose as Client Authentication.

CCA-CT-9492

Client Authentication is not supported with the EEM server. Please upgrade to the latest EEM (version 12 or higher)

Reason:

The EEM server version is not 12.0 or higher.

Action:

Upgrade the EEM server to the latest EEM version (12 or higher).

CCA-CT-9493

Client Authentication is not supported with the EEM SDK API. Please upgrade to the latest EEM SDK API (version 12 or higher)

Reason:

The EEM SDK API version is not 12.0 or higher.

Action:

Upgrade the EEM SDK API to the latest EEM SDK API version (12 or higher).

CCA-CT-9495

User <username> does not exist in user store or user is not assigned to application instance CCA, please verify application user details

Reason:

The user <username> does not exist in user store, or the user is not assigned to application instance in CA Configuration Automation.

Action:

Create the user in EEM and provide the application instance as CCA for the user.

CCA-CT-9497

<certificatepurpose> Certificate for User <username> already exists

Reason:

The <certificatepurpose> certificate already exists for the server <servername>.

Action:

As same certificate already exists, do not create a certificate with the same purpose.

Service Error Messages

This section explains the error messages that you see while performing the service operations in CA Configuration Automation.

CCA-SV-2008

Service <servicename> already exists.

Reason:

The possible reasons are:

- Trying to import service <servicename> from CA Cohesion that exists in CCA Server.
- Trying to create new service <servicename> that exists in CCA Server.

Action:

Do one of the following actions:

- Delete the existing service <servicename> or update the existing service name <servicename> before you import the service <servicename>.
- Use a different name while creating the service.

CCA-SV-2012

Name is required.

Reason:

Service name is not provided.

Action:

Provide a service name.

CCA-SV-2027

No servers assigned to service <servicename>.

Reason:

Trying to run discovery, or refresh the service <servicename> when there are no servers are added.

Action:

Add servers to the service <servicename>.

CCA-SV-2029

Cannot perform discovery. Discovery is disabled on service <servicename>.

Reason:

Discovery is disabled for the service <servicename>.

Action:

Enable the discovery option for the service <servicename>.

CCA-SV-2030

Cannot perform management operations. Management is disabled on service <servicename>.

Reason:

Management option is disabled for service <servicename>.

Action:

Enable management option for the service <servicename>.

CCA-SV-2034

Service cannot be deleted. It is used in one or more Management Profiles.

Reason:

One or more selected services are used in one or more management profiles.

Action:

Remove the selected services from management profiles before deleting a service.

CCA-SV-2040

Error while adding service <servicename>.

Reason:

An exception occurred while adding the service<servicename> using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2041

Error while getting service <servicename>.

Reason:

An exception occurred while retrieving service by service name <servicename> using SDK.

Action:

Ensure that the service exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2042

Error while getting all services.

Reason:

An exception occurred while retrieving all the services using the SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2043

Error while getting service by UUID <uuid>.

Reason:

An exception occurred while retrieving the service by UUID <uuid> using the SDK.

Action:

Ensure that the Service UUID <uuid> exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2044

Service by UUID <uuid> not found.

Reason:

Invalid service UUID <uuid> which does not exist in CCA Server.

Action:

Provide valid Service UUID <uuid> which exists in CCA Server.

CCA-SV-2045

Error while getting servers in service snapshot by UUID <uuid>.

Reason:

An exception occurred while retrieving the servers in the service snapshot by service snapshot UUID <uuid> using the SDK.

Action:

Ensure that the service snapshot UUID <uuid> exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2046

Error while getting service <servicename> servers.

Reason:

An exception occurred while retrieving all the servers in <servicename> using SDK.

Action:

Ensure that the service <servicename> exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2047**Error while getting service snapshots by UUID <uuid>.****Reason:**

An exception occurred while retrieving the service snapshots by service UUID <uuid> using SDK.

Action:

Ensure that the service UUID <uuid> exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2048**Error while adding Servers to Service.****Reason:**

An exception occurred while adding servers to service using the SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2051**Failed to unlock the Service <servicename>. Error occurred: <error>.****Reason:**

An exception occurred while running management operations using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary contact, CA Technologies Technical Support for further assistance.

CCA-SV-2058

Malformed export file - Service Name not found.

Reason:

The corrupted JAR file is used to import the services.

Action:

Use the original JAR file which is exported from CA Configuration Automation.

CCA-SV-2061

Service <servicename>..not found.

Reason:

Provided the wrong service <servicename> in launch in context URL, which does not exist in CA Configuration Automation.

Action:

Provide a valid service <servicename> in launch in context URL.

CCA-SV-2064

Execution of Management profile for Service <servicename> failed.

Reason:

No servers exist in the service, or connection to the server <servername> cannot be established using the assigned access profile.

Action:

Ensure that the servers exist in the service, and assign proper access mode to the access profile. Verify that the status of test servers operation is successful.

CCA-SV-2065

Error while adding ServerGroups to Service.

Reason:

An exception occurred while adding the ServerGroups to Service using SDK.

Action:

Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2066

Error while getting service <servicename> server groups.

Reason:

An exception occurred while getting the server groups of service <servicename> using SDK.

Action:

Ensure Service <servicename> exists in CCA. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-SV-2067

Servers in Service <servicename> can not be removed, <currentactiity>.

Reason:

Discovery or Management operations are running on Service <servicename>.

Action:

Wait until the activity <currentactivity> is complete on the service <servicename>.

CCA-SV-2068

Servers Groups in Service <servicename> can not be removed, <currentactiity>.

Reason:

The discovery, or management operations are running on the service <servicename>.

Action:

Wait until the activity <currentactivity> is completed on the service <servicename>.

CCA-SV-2073

File has invalid format for services import.

Reason:

The Services.csv file which is being imported does not contain any data.

Action:

Ensure that the Services.csv file contains valid service definition data.

CCA-SV-2074

CSV File has invalid format for services import.

Reason:

The Services.csv file which is being imported contains more than the required column headers.

Action:

Ensure that the Services.csv file contains valid column list.

CCA-SV-2078

Service name is too long.

Reason:

The service name has exceeded the maximum characters.

Action:

Ensure that the service name must not exceed 200 characters.

Service Profile Error Messages

This section explains the error messages that you see while performing the service profile operations in CA Configuration Automation.

CCA-SVCP-1004

Please select filter criteria other than Virtualization Filter and Server State

Reason:

Only Virtualization And Server State Filters are selected.

Action:

Select filters other than Virtualization And Server State Filters.

Snapshot Error Messages

This section explains the error messages that you see while performing the snapshot operations in CA Configuration Automation.

CCA-ST-3023

Please enter value for Snapshot Name.

Reason:

No value is entered in the snapshot name field.

Action:

Enter a valid snapshot name.

CCA-ST-3031

Error while taking <snaptype> snapshot by name <snapshotname>.

Reason:

An exception occurred while taking the server or service snapshot using SDK.

Action:

Ensure that the server or service has discovered components. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-ST-3032

Error while getting <snaptype> snapshot by UUID <uuid>.

Reason:

An exception occurred while retrieving the snapshot by the snapshot UUID <uuid> using SDK.

Action:

Ensure that the provided snapshot UUID <uuid> exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-ST-3033

Error while updating designation status of <snaptype> snapshot with UUID <uuid> to <designation>

Reason:

An exception occurred while updating the designation of snapshot with the UUID <uuid> using SDK.

Action:

Ensure that the snapshot with UUID <uuid> exists in CCA Server. Verify the SDK exception stack trace, and corresponding operation log details in the Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-ST-3035

Snapshot cannot be imported. Server <servername> does not exist.

Reason:

The server <servername> does not exist.

Action:

Create the server <servername>.

CCA-ST-3037

Snapshot cannot be imported. Service <servicename> does not exist.

Reason:

The service <servicename> does not exist.

Action:

Create the service <servicename>.

CCA-ST-3041

Unable to take snapshot on this Service <servicename> as another conflicting operation is running on the Server.

Reason:

The service <servicename > is locked by another operation.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-ST-3043

Unable to take snapshot- Attempt to get a lock on Service <servicename> failed. Error occurred: <error>.

Reason:

Unable to lock the service <servicename > because of a time-out or SQL exception.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-ST-3045

Failed to submit snapshot job on Server <servername>. Error occurred: <error>.

Reason:

An exception occurred during the snapshot creation.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-ST-3050

Import Failed. Blueprint of the Component <componentname> is not in sync.

Reason:

Blueprint of the Component <componentname> is updated, and the updates are not in sync with the component in the snapshot.

Action:

Use the old blueprint, or reset the blueprint changes.

CCA-ST-3058

Failed to submit snapshot delete job on Service <servicename>. Error occurred: <error>.

Reason:

An exception occurred while deleting the snapshot.

Action:

Contact CA Technologies Technical Support for further assistance.

CCA-ST-3082

Selected snapshot "<snapshotname>" of Server "<servername>" has a designation and cannot be deleted.\n Remove the designation and try delete.

Reason:

Error occurred while deleting the snapshot which has designation like gold standard, baseline, silver standard, bronze standard.

Action:

Remove the designation of the snapshot before initiating the snapshot delete action.

CCA-ST-3083

Selected snapshot "<snapshotname>" of Service "<servicename>" has a designation and cannot be deleted.\n Remove the designation and try delete.

Reason:

Error occurred while deleting the snapshot which has designation like gold standard, baseline, silver standard, bronze standard.

Action:

Remove the designation of the snapshot before initiating the snapshot delete action.

Tenant Error Messages

This section describes the error messages that you get while performing the tenant operations.

CCA-TN-9971

Select at least one tenant.

Reason:

No tenant is selected.

Action:

Select one or more tenants.

CCA-TN-9980

Tenant alias <alias name> for product <product name> already exists.

Reason:

Tenant alias <alias name> for product already exists.

Action:

Provide a new tenant alias name.

CCA-TN-9983

Tenant alias name <alias name> for product <product name> not found.

Reason:

Unable to delete the tenant alias name.

Action:

Ensure that the tenant alias name exists, and perform the operation.

CCA-TN-9984

Tenant UUID <tenant uuid> not found.

Reason:

The Tenant UUID does not exist. It is either deleted or an invalid tenant UUID is provided.

Action:

Ensure that the tenant exists, and perform the operation.

CCA-TN-9985

Tenant <tenant name> already exists.

Reason:

The Tenant <tenant name> already exists.

Action:

Provide a unique tenant name.

CCA-TN-9987

Tenant Group name <group name> cannot be the same as a user name.

Reason:

The Tenant Group name and the user name cannot be the same.

Action:

Provide a new Tenant Group name.

Table View Error Messages

This section explains the error messages that you see while performing the Table view operations in CA Configuration Automation.

CCA-TV-7003

Table View <viewname> already exists.

Reason:

Table View with this name already exists

Action:

Provide a unique table view name.

CCA-TV-7010

Sort column is not a selected column.

Reason:

Selected column for Sort is not available in the table view

Action:

Add sort column to the table view or use another column for the sort column.

CCA-TV-7011

Name is required.

Reason:

Table view name is not provided.

Action:

Provide table view name.

CCA-TV-7012

Table view is a default view. It cannot be deleted.

Reason:

Table view is a current view.

Action:

Ensure that the table view is not default or current view before you delete the table view.

CCA-TV-7015

Table View <viewname> already exists.

Reason:

Table View with this name already available.

Action:

Select the Overwrite existing Table Views flag while importing the existing table view Information.

CCA-TV-7018

Invalid table view name. The following characters are not allowed: < > ; : " ' * + = \ \ / | ?.

Reason:

Table view name has invalid characters.

Action:

Provide the table view name without using these characters < > ; : " ' * + = \ \ / | ?.

CCA-TV-7021

Security violation error while exporting the table views.

Reason:

You do not have permissions to export Table Views.

Action:

Log in to CA Configuration Automation as an administrator or Architect to export the Table Views.

Task Wizard Error Messages

This section explains the error messages that you see while performing the task wizard operations in CA Configuration Automation.

CCA-TW-1011

Job Completed with Errors

Reason:

Error occurred while running the compliance job/discover network/discover service in the task wizard.

Action:

Verify the error details in the corresponding operation Log tab. If necessary, contact CA Technologies Technical Support for further assistance.

Chapter 3: Warning Messages

You may encounter the following warning messages while performing with CA Configuration Automation. Warning messages warn you of a potential error situation and may require you to take some action.

Agent Warning Messages

This section describes the warning messages that you get while performing the agent operations.

CCA-AG-5707

Agent unable to establish a database connection. TNS-listener does not currently know of SID given in connect descriptor. Component Blueprint <blueprintname>. Server <servername>

Reason:

Error occurred while connecting to the Oracle database. The related error in Oracle is as follows:

ORA-12505: TNS listener does not currently know of SID given in connect descriptor

Action:

For more information about the Oracle database connection errors, see the Oracle documentation.

CCA-AG-5708

Agent unable to establish a database connection. TNS-no listener. Component Blueprint <blueprintname>. Server <servername>

Reason:

Error occurred while connecting to the Oracle database. The related message in Oracle is as follows:

ORA-12541: TNS no listener

Action:

For more information about the Oracle database connection errors, see the Oracle documentation.

CCA-AG-5709

Agent unable to establish a database connection. Invalid username or password, logon denied. Component Blueprint <blueprintname>. Server <servername>

Reason:

Error occurred while connecting to the database. The related database error is as follows:

Invalid username or password, logon denied.

Action:

Ensure that you have permissions to make database connections.

CCA-AG-5710

Agent unable to establish a database connection. Invalid username or password, logon denied. Component Blueprint <blueprintname>. Server <servername>

Reason:

Error occurred while connecting to the database. The related database error is as follows:

Invalid username or password, logon denied.

Action:

Ensure that you have permissions to make database connections.

CCA-AG-5711

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>

Reason:

Unable to establish a database connection.

Action:

Ensure that you are able to connect to the database from an ODBC database client.

CCA-AG-5712

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>. Provide correct Database Context value

Reason:

Incorrect Database context value is provided in the Component Parameters section.

Action:

Provide correct Database Context Value. If the problem still persists contact CA Technologies Technical Support for further assistance.

CCA-AG-5717

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>. Could not connect or no database running

Reason:

Unable to establish a database connection.

Action:

Ensure that sure you are able to connect to the database from an ODBC database client.

CCA-AG-5719

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>. TNS:could not resolve the connect identifier specified

Reason:

Error occurred while connecting to the Oracle database. The related database error in Oracle is as follows:

ORA-12514: TNS:listener does not currently know of service requested in connect descriptor.

Action:

For more information about the Oracle database errors, see the Oracle documentation.

CCA-AG-5720

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>. TNS:listener does not currently know of service requested in connect descriptor

Reason:

Error occurred while connecting to the Oracle database. The related database error in Oracle is as follows:

ORA-12514: TNS:listener does not currently know of service requested in connect descriptor

Action:

For more information about the Oracle database errors, see the Oracle documentation.

CCA-AG-5721

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>. Oracle immediate shutdown in progress - no operations are permitted

Reason:

Error occurred while connecting to the Oracle database. The related database error in Oracle is as follows:

ORA-01089: immediate shutdown in progress - no operations are permitted

Action:

For more information about the Oracle database errors, see the Oracle documentation.

CCA-AG-5722

Agent connected to database for blueprint <blueprintname> on server <servername>. Managed tables are missing, or character case (upper/lower) of table names not matched

Reason:

Missing database tables on the target server.

Action:

If the discovered component is for the pre-build CA Configuration Automation blueprint, then contact CA Technologies Technical Support for further assistance. Else, ensure that the tables are present in the database on the target server.

CCA-AG-5723

**Agent connected to database for blueprint <blueprintname> on server <servername>.
One or more queries were not executed**

Reason:

Failed to execute the query.

Action:

If the discovered component is for the pre-build CA Configuration Automation blueprint, then contact CA Technologies Technical Support for further assistance. Else, ensure that the queries are executed using an ODBC database client on the target server.

CCA-AG-5724

**Agent connected to database for blueprint <blueprintname> on server <servername>.
No or partial results returned from Agent**

Reason:

Unable to fetch some of the data from the database.

Action:

If the discovered component is for the pre-build CA Configuration Automation blueprint, then contact CA Technologies Technical Support for further assistance. Else, ensure that the queries are executed and the data is fetched using an ODBC database client on the target server.

CCA-AG-5725

**Agent connected to database for blueprint <blueprintname> on server <servername>.
The user account is locked**

Reason:

Error occurred while connecting to the Oracle database. The related database error in Oracle is as follows:

ORA-28000: the account is locked

Action:

For more information about the Oracle database errors, see the Oracle documentation.

CCA-AG-5726

Agent unable to establish a database connection for blueprint <blueprintname> on server <servername>. TNS:protocol adapter not loadable

Reason:

Error occurred while connecting to the Oracle database. The related database error in Oracle is as follows:

ORA-12557: TNS:protocol adapter not loadable when access Designer

Action:

For more information about the Oracle database errors, see the Oracle documentation.

CCA-AG-5727

Agent connected to database for blueprint <blueprintname> on server <servername>. Cannot access NLS data files or invalid environment specified. No data returned

Reason:

Error occurred while connecting to the Oracle database. The related database error in Oracle is as follows:

ORA-12705: Cannot access NLS data files or invalid environment specified.

Action:

For more information about the Oracle database errors, see the Oracle documentation.

Blueprint Warning Messages

This section describes the warning messages that you get while performing on the blueprint operations.

CCA-BP-4048

Please select at least one blueprint to perform this operation.

Reason:

No blueprint is selected to perform the following operations:

- Import
- Delete
- Enable
- Disable
- Export

Action:

Select at least one blueprint to perform the operations.

CCA-BP-4049

Please select a blueprint to perform this operation.

Reason:

No blueprint is selected to perform the copy operation.

Action:

Select a blueprint to perform the copy operation.

CCA-BP-4050

Please select only one blueprint to perform this operation.

Reason:

Multiple blueprints are selected to perform the copy operation.

Action:

Select only one blueprint to perform the copy operation.

CCA-BP-4184

Cannot move file <file name> up. It is already the first file.

Reason:

The file <file name> is already at the first row.

Action:

No action is required.

CCA-BP-4185

Cannot move directory <directory> up. It is already the first directory.

Reason:

The directory <directory> is already at the first row.

Action:

No action is required.

CCA-BP-4186

Cannot move value <value> up. It is already the first value.

Reason:

The value <value> is already at first row.

Action:

No action is required.

CCA-BP-4187

Cannot move key <key name> up. It is already the first key.

Reason:

The key <key name> is already at the first row.

Action:

No action is required.

CCA-BP-4188

Cannot move file <file name> down. It is already the last file.

Reason:

The file <file name> is already at the last row.

Action:

No action is required.

CCA-BP-4189

Cannot move directory <directory> down. It is already the last directory.

Reason:

The directory <directory> is already at the last row.

Action:

No action is required.

CCA-BP-4190

Cannot move value <value> down. It is already the last value.

Reason:

The value <value> is already at the last row.

Action:

No action is required.

CCA-BP-4191

Cannot move key <key name> down. It is already the last key.

Reason:

The key <key name> is already at the last row.

Action:

No action is required.

CCA-BP-4196

Please select one or more filter to reorder.

Reason:

No filters are selected.

Action:

Select one or more filters, and perform the reorder (Move up or Move down) operation.

CCA-BP-4197

Please select one or more groups to reorder.

Reason:

No filters are selected.

Action:

Select one or more filters, and perform the reorder (Move up, or Move down) operation.

CCA-BP-4198

Please select one or more parameters to reorder.

Reason:

No filters are selected.

Action:

Select one or more filters, and perform the reorder (Move up, or Move down) operation.

CCA-BP-4207

This is a product controlled blueprint. Copying this blueprint is not allowed.

Reason:

Copying this blueprint is not allowed as this is a product controlled blueprint.

Action:

No action is required.

CCA-BP-4416

Please select a step to delete.

Reason:

No step is selected.

Action:

Select a step to delete.

CCA-BP-4417

Please select a step to edit.

Reason:

No step is selected.

Action:

Select a step to edit.

CCA-BP-4418

Please select a parameter to delete.

Reason:

No parameter is selected.

Action:

Select a parameter to delete the parameter.

CCA-BP-4422

Please select one blueprint to perform this operation.

Reason:

Either multiple blueprints or no blueprint is selected to perform the blueprint search operation.

Action:

Select only one blueprint to perform blueprint search operation.

CCA-BP-4426

Discovery/Refresh job is in progress for this Component, blueprint references can not be deleted.

Reason:

You cannot delete blueprint references when the discovery or refresh job is in progress for a Component.

Action:

Delete blueprint references after completion of the discovery or refresh job.

CCA-BP-4425

Please select at least one blueprint reference to perform this operation.

Reason:

No blueprint is selected while deleting the blueprint references operation.

Action:

Select at least one blueprint to perform the delete operation on blueprint references.

CCA-BP-4427

Test Discovery data found, please close the test discovery browser window and perform Refresh.

Reason:

Test Discovery data found. Close the test discovery browser window.

Action:

Delete the blueprint references after closing the test discovery browser window.

Blueprint Group Warning Messages

This section describes the warning messages that you get while performing on the blueprint group operations.

CCA-BG-4512

Blueprint <blueprint name> not found during import of Blueprint Group <blueprint group>.

Reason:

The blueprint <blueprint name> which is available in the JAR file does not exist in CA Configuration Automation application.

Action:

If a pre built CA Configuration Automation blueprint is missing. Download the blueprint from the following location and import the blueprint:

http://techweb.ca.com/r11impcd/cca_updates/cca_frame.htm

CCA-BG-4508

Please select at least one Blueprint Group to perform this operation.

Reason:

No Blueprint Group is selected.

Action:

Select one or more Blueprint Groups, and perform the operation.

Compliance Jobs Warning Messages

This section describes the warning messages that you get while performing the compliance jobs.

CCA-CM-9000

Please select at least one Compliance Job to perform this operation.

Reason:

No compliance job is selected.

Action:

Select at least one compliance job.

CCA-CM-9026

Please select at least one History record to perform this operation.

Reason:

No History record is selected.

Action:

Select at least one History record.

Catalyst Jobs Warning Messages

This section explains the error messages that you see while performing the rule catalyst jobs in CA Configuration Automation.

CCA-CJ-9900

Please select at least one catalyst job to perform this operation.

Reason:

No catalyst job is selected while performing the delete or run catalyst job operation.

Action:

Select one catalyst job and perform the operation.

Catalyst Profile Warning Messages

This section describes the warning messages that you get while performing the catalyst profile operations.

CCA-PL-3908

Catalyst Attributes Profile already exists.

Reason:

The profile <profile name> already exists.

Action:

Select overwrite option, to replace the profile <profile name>.

CCA-PL-3909

Please select at least one Catalyst Attributes Profile to perform this operation.

Reason:

No Catalyst Attributes Profile is selected while importing the selected Catalyst Attributes Profile operation.

Action:

Select one or more Catalyst Attributes Profiles.

CCA-PL-3910

Selected profiles cannot be deleted. One or more of the selected profiles are assigned to a management profile or catalyst job.

Reason:

The selected profiles cannot be deleted as one or more of the selected profiles are assigned to a management profile or catalyst job.

Action:

Ensure that none of the management profiles or catalyst jobs are using the selected profiles, and delete the profile.

Change Detection and Compare Warning Messages

This section describes the warning messages that you get while performing the change detection and compare operations.

CCA-DF-9145

Identical snapshots are used for service change detection. No difference detected for service <servicename>.

Reason:

Identical snapshots are used for service change detection.

Action:

No action is required.

CCA-DF-9146

Identical snapshots are used for service comparison. No difference found between service <servicename1> and <servicename2>.

Reason:

Identical snapshots are used for the service comparison.

Action:

No action is required.

CCA-DF-9147

Identical snapshots are used for server change detection. No difference detected for server <servername>.

Reason:

Identical snapshots are used for the server change detection.

Action:

No action is required.

CCA-DF-9148

Identical snapshots are used for server comparison. No difference found between server <servername1> and <servername2>.

Reason:

Identical snapshots are used for server comparison.

Action:

No action is required.

CCA-DF-9183

There is no managed component or all components are excluded from change detection. No difference found for server <servername>.

Reason:

There is no discovered component in the selected source data and target data.

Action:

No action is required.

CCA-DF-9184

There is no managed component or all components are excluded from compare. No difference found between server <servername1> and <servername2>.

Reason:

There is no discovered component in the selected source data and target data.

Action:

No action is required.

CCA-DF-9185

There is no managed component or all components are excluded on source snapshot for server <Servername>.

Reason:

There is no discovered component in the selected source data.

Action:

No action is required.

CCA-DF-9186

There is no managed component or all components are excluded on target snapshot for server <Servername>.

Reason:

There is no discovered component in the selected target data.

Action:

No action is required.

Common Schedule Warning Messages

This section describes the warning messages that you get while performing the common schedule operations.

CCA-SH-9008

The current schedule is shown below.Changes to the schedule will be reflected in the profile.

Reason:

Frequency is not selected. Updating the current schedule..

Action:

No action is required.

CCA-SH-9017

Scheduled job <jobname> in group <jobgroup> on <nextfiretime> was skipped because an instance of that job was already running.

Reason:

An instance of that job was already running.

Action:

No action is required.

CCA-SH-9018

Scheduled job <jobname> in group <jobgroup> on <nextfiretime> missed a scheduled fire-time and was launched now.

Reason:

No reason.

Action:

No action is required.

Component Warning Messages

This section explains the warning messages that you see while performing the component operations in CA Configuration Automation.

CCA-CM-9301

Please select at least one Component to perform this operation

Reason:

No component is selected to delete, or view, or refresh the component operation.

Action:

Select at least one component to perform the delete, or view, or refresh the component operation.

CCA-CM-9310

Unable to remove component <componentname,versionand currentactivity>

Reason:

Component refresh is going on.

Action:

After the refresh operation, delete the component.

Discovery and Refresh Warning Messages

This section describes the warning messages that you get while performing the discovery and refresh operations.

CCA-DIS-8543

Failed to unlock on server <servername>

Reason:

An exception occurred while unlocking the server <servername>.

Action:

No action is required. The lock clears automatically after timeout is configured in the "discover.lock.timeout" property.

CCA-DIS-8545

Failed to unlock on service <servicename>

Reason:

An exception occurred while unlocking the service <serviename>.

Action:

No action is required. The lock will clear automatically after the timeout is configured in the "discover.lock.timeout" property.

CCA-DIS-8555

Discovery completed with errors for Server <servername> - <0> components discovered.

Reason:

Possible reasons are:

- An invalid platform is set to the server.
- The communication to the server <servername> is lost while performing the discovery operation.
- The service (Agent/SSH/Telnet/WMI) is not responding or running.

Action:

Do the following:

- Ensure that the correct platform is set to the server <servername>
- Ensure that the service (Agent/SSH/Telnet/WMI) corresponding to the assigned access mode is running on the target server <servername>.
- Use the latest CA Configuration Automation agent version if the access mode type is agent.
- Verify that the test server operation is successful.

CCA-DIS-8556

Refresh completed with errors for Server <servername> - <0> components Refreshed.

Reason:

Possible reasons are as follows:

- The communication to the server <servername> is lost while performing the refresh operation
- The service (Agent/SSH/Telnet/WMI) is not responding or running.

Action:

Do the following:

- Ensure that the service (Agent/SSH/Telnet/WMI) corresponding to assigned access mode is running on the target server <servername>.
- Use the latest CCA agent version if the access mode type is agent.
- Verify the test server operation is successful.

CCA-DIS-8577

Discovery of component blueprint <blueprintname> on server <servername> requires the JDBC driver <drivename>. Please install this driver.

Reason:

The JDBC driver <drivename> is not available in following location:

<CCAIInstalledDirectory>\tomcat\webapps\ROOT\WEB-INF\lib

Action:

Get the JDBC driver <drivename> from actual product or web, and copy to the following location:

<CCAIInstalledDirectory>\tomcat\webapps\ROOT\WEB-INF\lib.

CCA-DIS-8578

Refresh of component blueprint <blueprintname> on server <servername> requires the JDBC driver <drivename>. Please install this driver.

Reason:

The JDBC driver <drivename> is not available in the following location:

<CCAIstalledDirectory>\tomcat\webapps\ROOT\WEB-INF\lib.

Action:

Get the JDBC driver <drivename> from the actual product or web, and copy to the following location:

<CCAIstalledDirectory>\tomcat\webapps\ROOT\WEB-INF\lib.

CCA-DIS-8579

Failed to connect to remote database during discovery of the component blueprint <blueprintname> on server <servername>, error message-<error>.

Reason:

The possible reasons are as follows:

- The Server <servername> could not be pingable.
- The database service is down.
- Invalid details like database server name, database name, user name and password are provided to connect to the database.

Action:

Do the following:

- Ensure the server <servername> is pingable and database server service is running.
- Ensure that the database server name, database name, user name and password are valid and re-run the discovery operation.

CCA-DIS-8580

Failed to connect to remote database during refresh of the component blueprint <blueprintname> on server <servername>, error message-<error>.

Reason:

The possible reasons are as follows:

- The Server <servername> could not be pingable.
- The database service is down.
- The details like database server name, database name, user name and password are invalid to connect to the database.

Action:

Ensure that the Server <servername> is pingable and database server service is running. Verify that the database server name, database name, user name and password are valid and run refresh operation.

CCA-DIS-8581

Failed to execute query on remote database during discovery of the component blueprint <blueprintname> on server <servername>, error message-<error>.

Reason:

The query data or syntax is invalid.

Action:

Verify the syntax of added queries in the blueprint if the customized blueprint is used. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8582

Failed to execute query on remote database during refresh of the component blueprint <blueprintname> on server <servername>, error message-<error>.

Reason:

The query data or syntax is incorrect.

Action:

Verify that the query string is using the customized blueprint. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8587

Component refresh completed with errors for server <servername> - <0> components Refreshed.

Reason:

The possible reasons are as follows:

- The communication to the server <servername> is lost while performing the component refresh operation
- The service (Agent/SSH/Telnet) is not responding or running.

Action:

Do the following:

- Ensure that the service (Agent/SSH/Telnet/ WMI) corresponding to assigned access mode is running on target server <servername>.
- Verify that the status of the test server action is successful.
- Use the latest CA Configuration Automation agent, If the access mode type as agent. If necessary, contact CA Technologies Technical Support for further assistance.

CCA-DIS-8600

The blueprint <blueprintname> was managed by other server/service management profiles. Discovery will bypass the component <blueprintname>(<path>) on server <servername>.

Reason:

The blueprint <blueprintname> was managed by the other server/service management profile.

Action:

No action is required.

CCA-DIS-8606

sudo is not available on server <servername>. sudo will not be used.

Reason:

Sudo is not available on server <servername>.

Action:

Ensure sudo is available and properly configured on server <servername>. For more information about the how to configure sudo, see the Configuring sudo for UNIX and Linux Softagent Discovery section in the CA Configuration Automation documentation.

CCA-DIS-8610

Component discovery unable to resolve the server <IPAddress> while populating the relationship data.

Reason:

The server is not responding because the name may be changed, or server is not available.

Action

No action is required.

CCA-DIS-8611

Component discovery found relationship with ambiguous IP reference. IP address <ipaddress>, has been found on the following servers: <serverlist>.

Reason:

Duplicate IP address are found on the servers <serverlist>

Action:

Run reconcile operation on the servers <serverlist>.

CCA-DIS-8612

Component discovery found relationship with ambiguous IP reference within Network Realm <networkrealm>. IP address <ipaddress>, has been found on the following servers: <serverlist>.

Reason:

Duplicate IP address found on servers <serverlist> within Network Realm <networkrealm>

Action:

Run reconcile operation on servers <serverlist> within the Network Realm <networkrealm>.

CCA-DIS-8643

Component Blueprint <Blueprint Name> will be discarded from current discovery job as ambiguous File and Registry roots are found. Please modify this blueprint to define either File Indicator or Registry Indicator but not both.

Reason:

The logs specify that a blueprint has ambiguous root and the discovery operation discarded it.

Action:

Modify the blueprints to have either the File or Registry indicators.

CCA-DIS-8644

Discovery job could not find File Indicator <File Indicator Name> for the Blueprint(s) (<Blueprint names>) on the management server <Server Name>

Reason:

The log specify that the file indicator is not found. Either the component is not available on the target machine, or one of the blueprint indicators is not found.

Action:

Install the software which discovers the blueprints, or update the blueprints.

CCA-DIS-8645

Discovery job could not find Registry Indicator <Registry Indicator Name> for the Blueprint(s) (<Blueprint names>) on the management server <Server Name>

Reason:

The logs specify that the registry indicator is not found. Either the component is not available on the target machine, or one of the blueprint indicators is not found.

Action:

Install the software which discovers the blueprints, or update the blueprints.

CCA-DIS-8654

Cannot communicate with the <Access Mode> on the server <Server Name>". The specified user name and the password in Access Profile may be incorrect or if Access Profile is WMI with the Proxy action verify the specified Proxy/FTP Server credentials in Access Profile. Refresh is terminated.

Reason:

The server refresh operation could not connect to a target server with the specified access profile details.

Action:

Verify the following details:

- Valid access profile credentials are provided in the access profile.
- The Proxy, and FTP server credentials if the access profile is for WMI-Proxy.
- The FTP home directory exists on the FTP server.
- The FTP home directory is similar to the FTP home directory that is provided in an access profile.

CCA-DIS-8655

Cannot communicate with the <Access Mode> on the server <Server Name>". The specified user name and the password in Access Profile may be incorrect or if Access Profile is WMI with the the Proxy action verify the specified Proxy/FTP Server credentials that are in Access Profile. Discovery is terminated.

Reason:

The Server Discovery operation could not connect to a target server with the specified access profile details.

Action:

Verify the following details:

- Valid access profile credentials are provided in the access profile.
- The Proxy, and FTP server credentials if the access profile is for WMI-Proxy.
- The FTP home directory exists on the FTP server.
- The FTP home directory is similar to the FTP home directory that is provided in an access profile.

CCA-DIS-8653

No indicators found for the Blueprint(s) (<Blueprint Names>) on the management server <Server Name> in the current discovery job.

Log statement indicating there were no indicators (File/Registry) found for the specified blueprints in the current discovery job

Reason:

The logs specify the File or /Registry indicators are not found for a specified blueprint in a discovery operation.

Action:

Verify whether the blueprint specified indicators are available in the discovered target servers. If the indicators are available, verify the blueprint and update it.

Data Migration Warning Messages

This section describes the warning messages that you get while performing the data migration operations.

CCA-DM-7537

Blueprint <blueprintname> Version [<blueprintversion>] Component Version <componentvesrion> not imported. Blueprint already exists.

Reason:

The blueprint <blueprintname>, Version <blueprintversion>, and the Component Version <componentvesrion> already exists.

Action:

No action is required.

CCA-DM-7576

Global Variable <globalvariable> already exists.

Reason:

The global variable <globalvariable> already exists in CA Configuration Automation.

Action:

No action is required.

Global Variable Warning Messages

This section describes the warning messages that you get while performing the global variable operations.

CCA-GV-5505

Select one or more Variables to delete.

Reason:

No global variable is selected.

Action:

Select at least one global variable to perform the delete operation.

Graph Warning Messages

This section describes the warning messages that you get while performing the graph operations.

CCA-GR-9814

Please select at least one graph to perform this operation.

Reason:

Graph is not selected from the available graphs in the JAR while importing the selected operation.

Action:

Select at least one graph to perform the import on selection operation.

General Warning Messages

This section explains the warning messages that you see while performing the general tasks in CA Configuration Automation.

CCA-LN-1002

No converter found for the server <servername> for converting the results to UTF-8 encoding. Decoding the results using UTF-8 by default. Please check whether the operating system details set for this server is correct.

Reason:

The operating system details that are set for this server is incorrect.

Action:

Set the correct operating system details in the Server tab manually. If necessary, contact CA technologies technical support for further assistance.

CCA-LA-1002

Please select at least one log archive to perform this operation.

Reason:

No archive files are selected to perform the delete operation.

Action:

Select an achieved file and perform the delete operation.

CCA-LA-1006

Log Archive <archive file name> can not be deleted, file is in use.

Reason:

The <archive file name> is in use, and cannot be the deleted.

Action:

Close the archive file that is in use, and perform the delete operation.

CCA-LA-1008

Selected log archives were deleted except files are in use.

Reason:

One or more log archives are in use, and you cannot perform the delete operation.

Action:

Close all the archive files to delete them.

NDG Discovery Warning Messages

This section explains the warning messages that you see while performing the NDG discovery operations in CA Configuration Automation.

CCA-ND-8066

Network Discovery Gateway on node <NDGservername> discovered the following servers with IP address conflict: <serverIP>

Reason:

Two servers with the same IP addresses are detected.

Action:

Reconcile the servers.

CCA-ND-8067

Network Discovery Gateway on node <NDGservername> discovered the following servers with IP address conflict in network realm <networkrealm>: <serverIP>

Reason:

Two servers with same IP addresses are detected in a network realm.

Action:

By using different network realms, separate the conflicting IP addresses.

CCA-ND-8069

Network Discovery Gateway on node <NDGservername> found a Realm Integrity problem. The following server(s) are already in network realm(s) that do not match Network Profile Realm <networkrealm> in Network Profile<networkprofilename>: <servermultirealm>

Reason:

Target server already present in one network realm and trying to add the same server with other network realm.

Action:

Make sure one server available in one network realm.

Network Scan Warning Messages

This section explains the warning messages that you see while performing the network scan operations in CA Configuration Automation.

CCA-NS-7304

Please select one policy to perform this operation

Reason:

No policy is selected to perform delete ,or copy ,or export network scan policy.

Action:

Select at least one policy to perform the delete, or copy, or export network scan policy.

Profile Warning Messages

This section describes the warning messages that you get while performing the profile operations.

CCA-PL-3514

Select one or more profiles to delete

Reason:

No profile is selected to perform the delete operation.

Action:

Select one or more profiles.

CCA-PL-3515

Select one profile to set as default

Reason:

No profile is selected to set as default.

Action:

Select one profile to set as default.

CCA-PL-3516

Please select only one profile to set as default

Reason:

More than one profile is selected to set as default.

Action:

Select only one profile to set as default.

CCA-PL-3520

Selected profile <profilename> cannot be deleted. It is assigned to one or more servers

Reason:

The selected profile is assigned to one or more servers.

Action:

Identify the servers to which the profile <profilename> is assigned, and change the server profile, and delete the profile.

CCA-PL-3521

Selected profiles cannot be deleted. One or more of the selected profiles are assigned to a server

Reason:

One or more selected profiles are assigned to a server.

Action:

Identify the server to which the profile is assigned, and change the server profile, and delete the profile.

CCA-PL-3528

Select one or more profiles to enable

Reason:

The management profiles or network profiles are not selected for the enable profile operation.

Action:

Select one or more management profiles or network profiles to perform the enable profiles operation.

CCA-PL-3529

Select one or more profiles to disable

Reason:

The management profiles or network profiles are not selected for the disable profile operation.

Action:

Select one or more management profiles or network profiles to perform the disable profiles operation.

CCA-PL-3542

Selected profiles cannot be deleted. One or more of the selected profiles is assigned

Reason:

The selected notification profile is assigned to one or more servers or operations.

Action:

Ensure that the selected notification profile is not assigned to any server or operation before you perform the delete operation.

CCA-PL-3552

Please select at least one profile to perform this operation

Reason:

No profile is selected to perform the delete or import or selection operations while importing profiles.

Action:

Select a profile to execute delete credential vault or import or selection operations while importing profiles.

CCA-PL-3557

Please select a profile

Reason:

The management or access or notification or network Profile is not selected to run the discover network, discover service task wizard and remediation operations.

Action:

Select the corresponding profiles to run the discover network, discover service and remediation operations.

CCA-PL-3562

Updated successfully. Please check the Agent port. Changes need to be made on agent end as well otherwise the communication does not work.

Reason:

The port numbers in both profiles are varies while changing the server assigned access profile from self-registered to not self-registered agent.

Action:

Verify the agent port. Change either on the agent end or in the new assigned access profile for the communication to work.

CCA-PL-3572

Please select one profile to perform this operation.

Reason:

More than one profile is selected for the copy operation.

Action:

Select one profile to perform the copy profile operation.

CCA-PL-3573

This action applies only to enabled profiles.

Reason:

The selected management profile is disabled.

Action:

Ensure that the selected management profile is enabled before you run the management profile.

CCA-PL-3575

Selected Network Profile, <profilename> must be enabled before it can be run.

Reason:

The network profile is disabled.

Action:

Ensure that the selected network profile is in enabled state before you run it.

CCA-PL-3576

Only one network profile can be run at a time

Reason:

More than one network profiles are selected to run the network profile operation.

Action:

Select one network profile at a time to run this operation.

CCA-PL-3579

Selected profile <profilename> cannot be deleted. It is assigned to one or more network profiles.

Reason:

The selected access profile is assigned to one or more network profiles.

Action:

Ensure that the selected access profile is not assigned to any network profile before you delete the selected access profiles.

CCA-PL-3580

Selected profiles cannot be deleted. One or more of the selected profiles are assigned to network profile.

Reason:

One or more of the selected management or access profiles are assigned to the network profile.

Action:

Ensure that the selected management or access profiles are not assigned to any network profile before you delete the selected management or access profiles.

CCA-PL-3581

Selected profiles cannot be deleted. One or more of the selected profiles are assigned to a server or service.

Reason:

One or more of the selected management profiles are assigned to a server or service.

Action:

Ensure that the selected management profiles are not assigned to any server or service before you delete the selected management profiles.

CCA-PL-3585

One or more selected profiles are disabled and cannot be run.

Reason:

One or more selected management profiles are disabled.

Action:

Enable the selected management profile and then execute the run management profile.

CCA-PL-3588

Selected profiles cannot be run. One or more selected profiles are not assigned to a server or service.

Reason:

One or more selected profiles are not assigned to a server or service.

Action:

Assign the selected profile to a server or service before you run the management profile discovery or refresh operation.

CCA-PL-3622

This action is only applicable to profiles having scan policies with soft agent.

Reason:

You are performing the rerun profiles action without the soft agent scan policies.

Action:

Select a soft agent scan policy profile before you rerun the network discovery.

CCA-PL-3919

The dynamic profile cannot be deleted. A new dynamic profile must be assigned before the selected profiles can be deleted.

Reason:

The dynamic profile cannot be deleted.

Action:

Set a new dynamic profile and try deleting this profile.

CCA-PL-3606

Select one or more policies to delete.

Reason:

No network scan policy is selected for the delete operation.

Action:

Select one or more policies to perform the delete operation.

CCA-PL-3612

Please select at least one network scan policy to perform this operation.

Reason:

No network scan policy is selected to perform the import.

Action:

Select at least one network scan policy to perform the import.

CCA-PL-3614

Please select only one policy to copy.

Reason:

More than one policy is selected.

Action:

Select only one policy to perform the copy operation.

CCA-PL-3709

Please select one communication mappings to perform this operation.

Reason:

Communication mappings are not selected to perform the delete operation.

Action:

Select one or more communication mappings to perform the delete operation.

CCA-PL-3725

Please select at least one Application Mapping to perform this operation.

Reason:

Application mapping is not selected for delete or export operation.

Action:

Select at least one application mapping to perform delete or export operation.

CCA-PL-3730

Please select one or more application mappings to reorder.

Reason:

No application is selected.

Action:

Select one or more application mappings.

CCA-PL-3731

Cannot move application mapping <applicationname> up. It is already the first application mapping.

Reason:

Selected application mapping is the first application mapping.

Action:

No action is required.

CCA-PL-3732

Cannot move application mapping <applicationname> down. It is already the last application mapping.

Reason:

The selected application mapping is the last application mapping.

Action:

No action is required.

CCA-PL-3649

Please select one Network Profile for cancellation.

Reason:

The network profile is not selected to cancel a job.

Action:

Select the network profile to cancel a job.

CCA-PL-3657

At least one subnet hierarchy level is required if Global Routing Prefix less than 64.

Reason:

You are removing all the levels when Global Routing Prefix Length is less than 64.

Action:

If Global Routing Prefix length value is less than 64 <value>, then there should be at least one level in subnet filtering panel. You cannot delete the same.

CCA-PL-3658

The total number of levels in Subnet Hierarchy cannot exceed 64 - Global Routing Prefix length: <value>

Reason:

You are adding more levels in the Subnet hierarchy than the default 64-<value>.

Action:

Ensure that the total number of levels in Subnet Hierarchy are less than or equal to 64 <value>.

CCA-PL-3659

The value for each level in Subnet Hierarchy cannot exceed 64 - Global Routing Prefix length: <value>

Reason:

You are adding value of each level in Subnet Hierarchy that is more than 64-<value>.

Action:

Ensure that the value for each level in Subnet Hierarchy is less than or equal to 64 <value>.

CCA-BP-4423

Are you sure you want to delete the selected blueprint references?

Reason:

Confirming the delete operation.

Action:

Your confirmation is required.

CCA-PL-3814

Please select only one Profile to copy.

Reason:

More than one profile is selected.

Action:

Select only one Profile to perform copy operation.

CCA-PL-3823

Notification profile already exists.

Reason:

Notification profile with the same name exists.

Action:

Select overwrite option to update the existing notification profile.

Remediation Jobs Warning Messages

This section describes the warning messages that you get while performing the remediation jobs.

CCA-RJ-8003

Please select at least one Remediation Job to perform this operation

Reason:

No remediation job is selected to perform run/delete remediation job operation.

Action:

Select at least one remediation job.

CCA-RJ-8064

Remediation Profile is required.

Reason:

Remediation profile is not provided while creating the remediation job.

Action:

Select an existing profile, or create a new remediation profile and select the same while creating the new remediation job.

CCA-RJ-8069

No servers assigned to remediation job.

Reason:

No servers are selected while performing the Adhoc Remediation Job.

Action:

Select one or more servers and perform the Adhoc Remediation Job.

Remediation Profile Warning Messages

This section describes the warning messages that you get while performing the remediation profile operations.

CCA-RP-1013

Please select one or more steps to delete.

Reason:

No remediation steps are selected.

Action:

Select at least one remediation step.

CCA-RP-1020

Please select one or more steps to reorder.

Reason:

No remediation steps are selected to reorder.

Action:

Select at least one remediation step to reorder.

CCA-RP-1021

Cannot move step <stepname> up. It is already the first step.

Reason:

The remediation step is already the first step.

Action:

No action is required.

CCA-RP-1022

Cannot move step <stepname> down. It is already the last step.

Reason:

The remediation step is already the last step.

Action:

No action is required.

CCA-RP-1039

Cant find blueprint for component name: <component>; version: <version> during import of Remediation Profile <profilename>: Step <stepname>. Step was not imported.

Reason:

The Blueprint used for discover the <componentname> does not exist. The remediation step is skipped while importing the remediation profile.

Action:

If a pre-built CCA blueprint is missing, download the same from the following location and import the Remediation Profile:

http://techweb.ca.com/r11impcd/cca_updates/cca_frame.htm

CCA-RP-1040

Cant find macro: <macro> during import of Remediation Profile <profilename>: Step <stepname>. Step was not imported.

Reason:

Cannot find the macro <macro> during an import of the remediation profile. The remediation step is skipped while importing the remediation profile.

Action:

If a pre-built CCA blueprint is missing, download the same from the following location and import the Remediation Profile:

http://techweb.ca.com/r11impcd/cca_updates/cca_frame.htm

CCA-RP-1041

Cant find file structure class parameter for parameter name: <parametername>; class name: <classname> during import of Remediation Profile <profilename>: Step <stepname>. Step was not imported.

Reason:

The file structure class used to discover the <componentname> does not exist. The remediation step is skipped while importing the remediation profile.

Action:

If a pre-built CCA blueprint is missing, download the same from the following location and import the Remediation Profile:

http://techweb.ca.com/r11impcd/cca_updates/cca_frame.htm

CCA-RP-1042

Cant find overlay: <overlay> during import of Remediation Profile <profilename>: Step <stepname>. Step was not imported.

Reason:

Cannot find the overlay <overlay> during an import of the remediation profile. The remediation step is skipped while importing the remediation profile.

Action:

If a pre-built CCA blueprint is missing, download the same from following location and import the Remediation Profile:
http://techweb.ca.com/r11impcd/cca_updates/cca_frame.htm

Rules Warning Messages

This section explains the messages that you see while performing the rules operations in CA Configuration Automation.

CCA-RL-2508

Please select at least one rule to perform this operation.

Reason:

No rule is selected.

Action:

Select one or more rules to perform the delete operation.

Rule Compliance Warning Messages

This section explains the warning messages that you see while performing the rules operations in CA Configuration Automation.

CCA-RE-1628

Please select at least one Rule Exception to perform this operation.

Reason:

No rule is selected to delete or manage a rule exception.

Action:

Select at least one rule to delete or manage the rule exception.

CCA-RE-1630

No server and service selected to add in rule exception.

Reason:

No server or service is selected to add a rule exception.

Action:

Select a server or service to add the rule exception.

Rule Group Warning Messages

This section describes the warning messages that you get while performing the rule group operations.

CCA-RG-1609

Please select at least one Rule Group to perform this operation.

Reason:

No rule group is selected while exporting or importing or deleting the rule groups.

Action:

Select one or more rule groups and run export or import or delete operation.

CCA-RG-1617

Rule <rulename> not found during import of Rule Group <groupname>.

Reason:

The rule <rulename> is not created or rule <rulename> is deleted.

Action:

No action is required.

CCA-RG-1621

No rules selected to add.

Reason:

The category is selected, but no rules are selected while creating a rule group.

Action:

Select at least one rule.

CCA-RG-1623

<count> rules have been added to Rule Group <groupname> but <dupcount> duplicate rules have been skipped.

Reason:

Some rules are skipped because the rules exist in the rule group <rulegroup>.

Action:

No action is required.

Reports Warning Messages

This section describes the warning messages that you get while performing the reports operations.

CCA-RT-6017

At least one instance should be selected.

Reason:

No instance is selected to delete, or share, or unshare the report instance.

Action:

Select at least one instance to delete, or share, or unshare the report instance.

CCA-RT-6044

At least one report selection is required to perform this action.

Reason:

No report is selected to perform the run or delete report operation.

Action:

Select at least one report to perform run or delete the report operation.

CCA-RT-6096

Report as an attachment is not supported for format <formattype>

Reason:

Attachment is not supported for format Crystal report.

Action:

Select format other than crystal report to attach the report.

Server Warning Messages

This section describes the warning messages that you get while working the server operations.

CCA-SR-1012

Please select at least one server to perform this operation.

Reason:

No server is selected.

Action:

Select at least one server.

CCA-SR-1016

Please select two or more servers to perform this operation.

Reason:

At least two or more servers are required to perform the compare operation.

Action:

Select two or more servers to perform the compare operation.

CCA-SR-1023

This action applies to servers in Managed state.

Reason:

One or more selected servers are in unmanaged state.

Action:

Change the state of selected servers to managed.

CCA-SR-1048

Snapshot cannot be created for servers with no components.

Reason:

One or more selected servers have no discovered components.

Action:

Discover components for the servers.

CCA-SR-1055

The Agent Install Command does not apply to servers in access mode other than type Agent.

Reason:

The access mode type of one or more selected servers is not Agent.

Action:

Change the access mode type to Agent for the selected servers.

CCA-SR-1057

Discovery cannot be performed on Server <servername>. No Management Profile assigned to the server.

Reason:

Management profile is not assigned to the server <servername>.

Action:

Assign management profile to the server <servername>.

CCA-SR-1058

Management Profile cannot be run on Server <server>. No Management Profile assigned to the server.

Reason:

Management profile is not assigned to the server <servername>.

Action:

Assign management profile to the server<servername>.

CCA-SR-1059

Refresh cannot be performed on Server <servername>. No Management Profile assigned to the server.

Reason:

Management profile is not assigned to the server <servername>.

Action:

Assign management profile to the server <servername>.

CCA-SR-1062

Discovery cannot be performed on Server <servername>. Assigned Management Profile is disabled.

Reason:

Management profile which is assigned to Server <servername> is disabled.

Action:

Enable management profile which is assigned to Server <servername>.

CCA-SR-1065

Secure Agents command only applies to servers with access mode "Agent" or "Secure Agent".

Reason:

The access mode type of one or more selected servers is not Agent or Secure Agent.

Action:

Ensure that the access mode of selected servers is Agent or Secure Agent.

CCA-SR-1082

This action cannot be performed on server <servername> because it is not in Managed state.

Reason:

The server <servername> is not in managed state.

Action:

Change the state of the server <servernamne> to managed.

CCA-SR-1091

This action cannot be performed on servers that are not in Managed state.

Reason:

The selected servers are not in Managed state.

Action:

Change the state of selected servers to Managed.

CCA-SR-1096

Refresh cannot be performed on Server <servername>. Assigned Management Profile is disabled.

Reason:

Management profile assigned to the server <servername> is disabled.

Action:

Enable the management profile assigned to the server <servername>.

CCA-SR-1097

Management Profile cannot be run on Server <servername>. Assigned Management Profile is disabled.

Reason:

Management profile assigned to the server <servername> is disabled.

Action:

Enable the management profile assigned to the server <servername>

CCA-SR-1114

Discovery cannot be performed on Server <servername>. Server is not in "Managed" state.

Reason:

The server <servername> is not in managed state.

Action:

Change state of the server <servername> to managed.

CCA-SR-1115

Management Profile cannot be run on Server <servername>. The server is not in Managed state.

Reason:

The server <servername> is not in managed state.

Action:

Change the state of the server <servername> to Managed.

CCA-SR-1146

Refresh cannot be performed on Server <servername>. Server is not in "Managed" state.

Reason:

The server is not in the Managed state.

Action:

Change the state of the server to Managed.

CCA-SR-1155

Please select only one server for this operation.

Reason:

Selected more than one server.

Action:

Select only one server.

CCA-SR-1156

Please select only one application for this operation.

Reason:

More than one application is selected.

Action:

Select only one application to perform this operation.

CCA-SR-1157

Please select a server to perform this operation.

Reason:

Server is not selected.

Action:

Select a server.

CCA-SR-1164

Cannot communicate with the agent on server <servername> at IP address <ipaddress>; however an agent running at IP address <newipaddress> is detected, thus server discovery communication is set to that IP address.

Reason:

The Server <servername> cannot communicate with the agent on the specified IP address <ipaddress>.

Action:

Now the server discovery communication is set to a new IP address <newipaddress>, so rerun the discovery operation.

Server Groups Warning Messages

This section describes the warning messages that you get while performing the server groups operations.

CCA-SG-1509

Please select at least one Server Group to perform this operation.

Reason:

No server group is selected while exporting or importing or deleting the server groups.

Action:

Select one or more server groups to export or import or delete operation.

Structure Class Warning Messages

This section describes the warning messages that you get while performing the structure class operations.

CCA-SC-5004

Please select a structure class to perform this operation.

Reason:

No structure class is selected while performing the delete, export, copy, or import operation.

Action:

Select at least one structure class.

CCA-SC-5005

Please select only one structure class to perform this operation.

Reason:

Multiple structure classes are selected to perform the copy operation.

Action:

Select only one structure class to perform the copy operation.

CCA-SC-5024

Please select a structure class to perform this operation.

Reason:

No structure class is selected while performing the copy operation.

Action:

Select one structure class and perform the copy operation.

CCA-SC-5025

Please select only one structure class to perform this operation.

Reason:

Multiple structure classes are selected to perform the copy operation.

Action:

Select only one structure class to perform the copy operation.

CCA-SC-5043

Cannot move parameter ".*" up. It must remain as lowest precedence.

Reason:

Parameter .* must always remain as lowest precedence.

Action:

No action is required.

CCA-SC-5044

Cannot move group ".*" up. It must remain as lowest precedence.

Reason:

Group .* must always remain as lowest precedence.

Action:

No action is required.

CCA-SC-5045

Cannot move parameter <paramtername> down. Parameter ".*" must remain as lowest precedence.

Reason:

Parameter .* must always remain as lowest precedence.

Action:

No action is required.

CCA-SC-5046

Cannot move group <groupname> down. Group ".*" must remain as lowest precedence.

Reason:

Group .* must always remain as lowest precedence.

Action:

No action is required.

Security Certificate Warning Messages

This section explains the warning messages that you see while performing the security certificate operations in CA Configuration Automation.

CCA-CT-9416

Please select only one certificate

Reason:

More than one certificate is selected.

Action:

Select only one certificate.

CCA-CT-9417

Please select one or more certificates to delete

Reason:

No certificate is selected.

Action:

select one or more certificates to perform the delete action.

CCA-CT-9421

HTTPS enabled already

Reason:

You are trying to enable an already enabled HTTPS.

Action:

No action is required.

CCA-CT-9422

HTTPS disabled already

Reason:

You are disabling an already disabled HTTPS.

Action:

No action is required.

CCA-CT-9423

There is no certificate authority set up in this installation

Reason:

Certificate Authority is not created.

Action:

Create a Certificate Authority.

CCA-CT-9424

Certificate authority has already been set up in this installation

Reason:

Certificate Authority has already been set up during the installation process.

Action:

No action is required.

CCA-CT-9425

HTTPS disabled already, requires server restart

Reason:

HTTPS disabled already.

Action:

Restart the CA Configuration Automation server to login in with with HTTP.

CCA-CT-9426

HTTPS enabled already, requires server restart

Reason:

HTTPS is already enabled.

Action:

Restart the CA Configuration server to login with HTTPS.

CCA-CT-9429

Please select certificate of purpose "CCA Agent"

Reason:

Selected certificate purpose is not a CA Configuration Automation Agent.

Action:

Select certificate which is having a purpose as CA Configuration Automation Agent.

CCA-CT-9430

Please select certificate of purpose "CCA Server"

Reason:

Selected certificate purpose is not CA Configuration Automation server.

Action:

Select a certificate which is having a purpose as CA Configuration Automation server.

CCA-CT-9431

Please select certificate of purpose "HTTPS"

Reason:

Selected certificate purpose is not HTTPS.

Action:

Select a certificate which is having purpose as HTTPS.

CCA-CT-9478

Client Authentication enabled already

Reason:

You are trying to enable an already enabled client authentication.

Action:

No action is required.

CCA-CT-9479

Client Authentication disabled already

Reason:

You are disabling an already disabled client authentication.

Action:

No action is required.

CCA-CT-9481

Client Authentication disabled already, requires server restart

Reason:

The client authentication is already disabled.

Action:

Restart the CA Configuration Automation server to login without client authentication.

CCA-CT-9482

Client Authentication enabled already, requires server restart

Reason:

The client authentication is already enabled.

Action:

Restart the CA Configuration Automation server to login with client authentication.

CCA-CT-9483

HTTPS enabled is required for client authentication

Reason:

HTTPS is disabled.

Action:

Enable HTTPS before enabling the client authentication.

CCA-CT-9490

Please select certificate of purpose "Client Authentication"

Reason:

The selected certificate purpose is not client authentication.

Action:

Select a certificate purpose as client authentication.

Service Warning Messages

This section describes the warning messages that you get while performing the service operations.

CCA-SV-2010

Please select at least one service to perform this operation.

Reason:

At least one Service is required to perform the change detection operation.

Action:

Select at least one service to perform the change detection operation.

CCA-SV-2016

Please select two services to perform this operation.

Reason:

Two services are required to perform the compare operation.

Action:

Select two services to perform the compare operation.

CCA-SV-2021

This action does not apply to services with discovery disabled.

Reason:

The discovery operation is disabled for one or more selected services.

Action:

Enable the discovery option for selected services.

CCA-SV-2022

This action does not apply to services with management disabled.

Reason:

The Management option is disabled for one or more selected services.

Action:

Enable the management option for selected services.

CCA-SV-2023

Snapshot cannot be created for services with no components.

Reason:

One or more selected services have no components.

Action:

Discover the service components before creating a service snapshot.

CCA-SV-2028

This action does not apply to services without any server added to it.

Reason:

No servers are added to one or more selected services.

Action:

Ensure that the selected service has one or more servers added to it.

CCA-SV-2031

Discovery cannot be performed on Service <servicename>. No Management Profile assigned to the service.

Reason:

The management profile is not assigned to the service <servicename>.

Action:

Assign the management profile to the service <servicename>.

CCA-SV-2032

Management Profile cannot be run on Service <servicename>. No Management Profile assigned to the service.

Reason:

The management profile is not assigned to the service <servicename>.

Action:

Assign the management profile to the service <servicename>.

CCA-SV-2033

Refresh cannot be performed on Service <servicename>. No Management Profile assigned to the service.

Reason:

The management profile is not assigned to the service <servicename>.

Action:

Assign the management profile to the service <servicename>.

CCA-SV-2035

Discovery cannot be performed on Service <servicename>. Assigned Management Profile is disabled.

Reason:

The management profile assigned to the service <servicename> is disabled.

Action:

Enable the management profile which is assigned to the service <servicename>.

CCA-SV-2036

Refresh cannot be performed on Service <servicename>. Assigned Management Profile is disabled.

Reason:

The management profile assigned to the service <servicename> is disabled.

Action:

Enable the management profile which is assigned to Service <servicename>.

CCA-SV-2037

Management Profile cannot be run on Service <servicename>. Assigned Management Profile is disabled.

Reason:

Management profile assigned to the service <servicename> is disabled.

Action:

Enable management profile which is assigned to the service <servicename>.

CCA-SV-2038

Please select one service to perform this operation.

Reason:

No service is selected.

Action:

Select one service to perform this operation.

CCA-SV-2070

Management Profile <Management profile name> not found during import of Service <Service Name> Default management profile set to Service <Service Name>.

Reason:

The imported service does not have the assigned management profile.

Action:

No action is required.

CCA-SV-2071

Server <Hostname> not found or not in managed state during import of Service <Service Name>.

Reason:

The imported service contains servers which are either unmanaged or do not exist in CA Configuration Automation.

Action:

Do one of the following tasks:

- Update the state of corresponding servers to Managed and import the service.
- Create servers which are not present and import the service.

CCA-SV-2072

Server Group <ServerGroupName> not found during import of Service <ServiceName>.

Reason:

The server group which is part of the service definition does not exist in CA Configuration Automation.

Action:

No action is required.

CCA-SV-2075

A service with the same name already exists in the database.

Reason:

Service definition with the same name exists.

Action:

Use the overwrite existing service option if require to update the existing service definition.

CCA-SV-2076

Service <Service Name> cannot be imported, <Current Activity>.

Reason:

The service cannot be imported as some current activity is in progress for it.

Action:

Import the service after the current activity gets completed.

Service Profile Warning Messages

This section describes the warning messages that you get when you perform the service profile operations.

CCA-SVCP-1005

There are selections already in the list, please reselect.

Reason:

Duplicate selections in the list.

Action:

Ensure that the selected list is unique.

Snapshot Warning Messages

This section describes the warning messages that you get while performing the snapshot operations.

CCA-ST-3013

Selected snapshots has a designation and cannot be deleted. Remove the designation and try delete.

Reason:

Selected snapshots has a designation.

Action:

Remove the designation to delete the snapshot.

CCA-ST-3017

Select at least one snapshot to perform this operation.

Reason:

Snapshot information is not provided.

Action:

Select at least one snapshot.

CCA-ST-3018

Please select only one snapshot to set as <snapshotdesignation>.

Reason:

More than one snapshot is selected.

Action:

Select only one snapshot.

CCA-ST-3020

Selected snapshot already designated as <snapshotdesignation>.

Reason:

The designated snapshot already exists.

Action:

No action is required.

CCA-ST-3046

Selecting more than two snapshots is not supported to perform this operation.

Reason:

Two or more snapshots are selected.

Action:

Select only two snapshots to perform change detection operation.

CCA-ST-3052

Blueprint name <blueprintname> blueprint version <version> and component version <version> not exists to import component.

Reason:

Blueprint does not exist.

Action:

No action is required.

CCA-ST-3053

Parameter <paramtername> not exists in the blueprint <blueprintname> to import.

Reason:

Parameter <paramtername> does not exist in the blueprint <blueprintname>.

Action:

No action is required.

CCA-ST-3054

Configuration file <file> not exists in component <componentname> configuration bucket blueprint to import.

Reason:

Configuration file <file> does not exist in blueprint <blueprintname>.

Action:

No action is required.

Storage Area Network Warning Messages

This section describes the warning messages that you get while performing the storage area networks operations.

CCA-SS-1001

Please select at least one storage system to perform this operation.

Reason:

No storage systems are selected and you are trying to run either the Export Storage Systems or Delete Storage Systems operations.

Action:

Select at least one storage system to perform export or delete operations.

Property Warning messages

This section describes the warning messages that you get while performing the property operations in CA Configuration Automation.

Please select at least one property to perform this operation.

Reason:

No property is selected.

Action:

Select at least one property to export the properties.

Tenant Warning Messages

This section describes the warning messages that you get while performing the tenant operations.

CCA-TN-9964

Please select at least one tenant to perform this operation.

Reason:

No tenant is selected while performing the view tenants, or delete tenants operation.

Action:

Select at least one tenant to perform this operation.

CCA-TN-9969

Please select at least one tenant group to perform this operation.

Reason:

No tenant group is selected while performing the delete tenant groups operation.

Action:

Select at least one tenant group to perform this operation.

Table View Warning Messages

This section describes the warning messages that you get while performing the table view operations.

CCA-TV-7006

Please select at least one Table View to perform this operation.

Reason:

Table view is not selected.

Action:

Select at least one table view to perform the delete or export operation.

CCA-TV-7007

Please select only one Table View to perform this operation.

Reason:

More than one table views are selected to set as the current view.

Action:

Select only one table view to set as a current view.

Task Wizard Warning Messages

This section explains the warning messages that you see while performing the task wizard operations in CA Configuration Automation.

CCA-TW-1004

Please select a policy

Reason:

The network scan policy is not selected.

Action:

Select a network scan policy.

CCA-TW-1015

No Network Discover Gateway was found. Please add one to continue

Reason:

Network discovery gateway is not available.

Action:

Add network discover gateway.

CCA-TW-1017

At least one server is required

Reason:

No server is available to perform operations like assign access profile, run compliance job, and discover service and discover network.

Action:

Add at least one server to perform operations like assign access profile, run compliance job, and discover service and discover network.

UI Export-Import of Profiles Warning Messages

This section describes the warning messages that you get while performing the UI export and import of profile operations.

CCA-MP-5604

Catalyst Attributes Profile <profilename> does not exists. It is not assigned to the Management Profile <managementprofilename>. Please update the management profile manually if it is required.

Reason:

The Catalyst Attributes Profile is available in the exported management profile JAR file, and it is not available in CA Configuration Automation server during the import operation.

Action:

If necessary, create the catalyst attribute profile, and update the management profile manually.

CCA-MP-5605

Rule Group(s) <rulegrouplist> not found during import of Management Profile <managementprofilename >.

Reason:

Rule Groups are available in the exported JAR file, but not available in the CA Configuration Automation server during the import operation.

Action:

If necessary, create Rule Groups and update the management profile manually.

Chapter 4: Information Messages

You may encounter the following information messages while performing with CA Configuration Automation. Information messages display information and usually do not require you to take any action.

Blueprint Informational Messages

This section describes the information messages that you get when you perform the blueprint operations.

CCA-BP-4001

Blueprint <blueprintname> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4002

Blueprint <blueprintname> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4003

Blueprint <blueprintname> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4005

Search Options <searchoptions> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4006

Search Options <searchoptions> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4007

Search Options <searchoptions> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4008

Network Probe <networkprobe> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4009

Network Probe <networkprobe> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4010

Network Probe <networkprobe> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4011

Discovery Verification Rule <verification rule> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4012

Discovery Verification Rule <verification rule> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4013

Discovery Verification Rule <verification rule> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4016

Discovery successfully enabled for <blueprint name>.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4017

Discovery successfully disabled for <blueprint name>.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4018

File <file name> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4019

File <file name> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4020

File <file name> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4021

Value <value> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4022

Value <value> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4023

Value <value> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4024

Key <key name> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4025

Key <key name> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4026

Key <key name> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4027

Directory <directory> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4028

Directory <directory> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4029

Directory <directory> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4030

File System Root updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4031

Registry Root updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4032

Parameter <parameter> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4033

Parameter <parameter> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4034

Parameter <parameter> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4036

Executable <executable> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4037

Executable <executable> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4038

Executable <executable> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4039

Database <database> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4040

Table <table> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4041

Database <database> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4042

Table <table> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4043

Database <database> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4044

Table <table> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4045

Query <query> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4046

Query <query> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4047

Query <query> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4087

Blueprint details changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4088

Indicator changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4089

Network Probe changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4090

Directive changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4091

File Management changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4092

Registry Management changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4093

Data Management changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4094

Parameter changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4095

File changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4096

Executable changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4097

Configuration Data changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4098

Grouping Options changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4099

Translation <translation> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4100

Translation <translation> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4101

Translation <translation> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4108

Discovery on Server <server> started.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4110

File <file name> added in tree. Please review and save to add to blueprint.

Reason:

The file <file name> is added in the tree from Browse Dialog.

Action:

Review and save the contents in the blueprint.

CCA-BP-4111

Directory <directory name> added in tree. Please review and save to add to blueprint.

Reason:

The directory <directory name> is added in the tree from Browse Dialog.

Action:

Review and save the contents in the blueprint.

CCA-BP-4112

Key <key name> added in tree. Please review and save to add to blueprint.

Reason:

The key <key name> is added in the tree from Browse Dialog.

Action:

Review and save the contents in the blueprint.

CCA-BP-4113

Value <value name> added in tree. Please review and save to add to blueprint.

Reason:

The value <value name> is added in the tree from Browse Dialog.

Action:

Review and save the contents in the blueprint.

CCA-BP-4114

Search Option <search option> added in tree. Please review and save to add to blueprint.

Reason:

The search option <search option> is added in the tree from Browse Dialog.

Action:

Review and save the contents in the blueprint.

CCA-BP-4115

File <file name> updated in tree. Please review and save to update in blueprint.

Reason:

The file <file name> is updated in the tree from Browse Dialog.

Action:

Review and save the contents to update in the blueprint.

CCA-BP-4116

Directory <directory name> updated in tree. Please review and save to update in blueprint.

Reason:

The directory <directory name> is updated in the tree from Browse Dialog.

Action:

Review and save the contents to update in the blueprint.

CCA-BP-4117

Key <key name> updated in tree. Please review and save to update in blueprint.

Reason:

The key <key name> is updated in the tree from Browse Dialog.

Action:

Review and save the contents to update in the blueprint.

CCA-BP-4118

Value <value name> updated in tree. Please review and save to update in blueprint.

Reason:

The value <value name> is updated in the tree from Browse Dialog.

Action:

Review and save the contents to update in the blueprint.

CCA-BP-4119

Search Option <search option> updated in tree. Please review and save to update in blueprint.

Reason:

The search option <search option> is updated in the tree from Browse Dialog.

Action:

Review and save the contents to update in the blueprint.

CCA-BP-4122

Selected blueprints were enabled.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4123

Selected blueprints were disabled.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4124

Selected blueprints were deleted.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4147

Selected Blueprints were exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4150

Macro changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4151

Macro <macro> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4152

Macro <macro> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4153

Macro <macro> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4154

Step changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4155

Step <step> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4156

Step <step> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4157

Step <step> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4158

Step <step> moved successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4159

Blueprint <blueprint> imported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4177

File <file name> parsed and contents added in tree. Please review and save to add to blueprint.

Reason:

The file <file name> is parsed and the content is added in the tree from Browse Dialog.

Action:

Review and save the contents in the blueprint.

CCA-BP-4192

Files were successfully reordered.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4193

Directories were successfully reordered.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4194

Values were successfully reordered.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4195

Keys were successfully reordered.

Reason:

Information only.

Action:

No action is required.

CCA-BP-4200

No components found.

Reason:

Test Discovery operation is completed successfully, but no components found.

Action:

No action is required.

CCA-BP-4201

Test Discovery canceled.

Reason:

Test Discovery action is successfully canceled.

Action:

No action is required.

CCA-BP-4209

Blueprint already exists. Cannot overwrite with a Cohesion blueprint.

Reason:

Cannot overwrite the existing blueprint with Cohesion blueprint.

Action:

No action is required.

CCA-BP-4211

Items added in tree. Please review and save to add to blueprint.

Reason:

Items are added using the Browse Dialog.

Action:

Review and save the items added to the blueprint.

CCA-BP-4424

Selected blueprint references successfully deleted.

Blueprint Group Informational Messages

This section describes the information messages that you get when you perform the blueprint group operations.

CCA-BG-4501

Blueprint Group <blueprint group> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BG-4502

Blueprint Group <blueprint group> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BG-4503

Blueprint Group <blueprint group> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BG-4504

Selected blueprint groups were deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-BG-4510

Blueprint Group <blueprint group> was exported.

Reason:

Information only.

Action:

No action is required.

CCA-BG-4513

Blueprint Group <blueprint group> was imported.

Reason:

Information only.

Action:

No action is required.

CCA-BG-4514

Successfully removed the Blueprint "<Blueprintname>" references from Blueprint Group "<Blueprintgroupname>".

Reason:

Information only.

Action:

No action is required.

CCA-BG-4515

Failed to remove the Blueprint <blueprint name> references from Blueprint Group <blueprint group>.

Reason:

Information only. Either a previous error has caused this information message or 0 blueprint references got deleted.

Action:

If there are any previous error messages in the log which are related to deletion of blueprint references, search this document for the same. Otherwise no action is required.

Compliance Jobs Informational Messages

This section describes the information messages that you get when you perform the compliance jobs.

CCA-CM-9002

Selected Compliance jobs deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9003

Compliance job <jobname> deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9004

Compliance job <jobname> created.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9005

Compliance job <jobname> updated.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9006

Compliance Job changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9009

Execution of compliance job <jobname> started.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9010

Execution of compliance job <jobname> finished.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9020

Compliance Jobs started successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9021

Compliance job <jobname> started.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9022

Compliance job <jobname> finished successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9025

Compliance Job <jobname> was saved.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9028

Selected Compliance history deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9029

Compliance History Job <jobname> deleted.

Reason:

Informational only.

Action:

No action is required.

Components Informational Messages

This section describes the information messages that you get when you perform the components operations.

CCA-CM-9316

Component "<compname>" is successfully deleted for Server "<servername>" from Service "<servicename>".

Reason:

Informational only.

Action:

No action is required.

Catalyst Jobs Informational Messages

This section explains the error messages that you see while performing the rule catalyst jobs in CA Configuration Automation.

CCA-CJ-9901

Selected catalyst jobs were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9902

Catalyst Job \"{0}\" deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9903

Catalyst jobs started successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9906

Catalyst job changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9907

Catalyst Job <job name> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9909

Catalyst Job <job name> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9911

Catalyst Job <job name> started.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9912

Catalyst Job <job name> finished.

Reason:

Informational only.

Action:

No action is required.

CCA-CJ-9916

Clearing the CIs exported by the Catalyst job For Republishing started.

Reason:

Informational only.

Action:

No action is required.

Catalyst Profile Informational Messages

This section describes the information messages that you get when you perform the catalyst profile operations.

CCA-PL-3900

Catalyst Attributes Profile <profile name> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-PL-3905

Catalyst Attributes Profile <profile name> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-PL-3906

Catalyst Attributes Profile changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-PL-3907

Catalyst Attributes Profile <profile name> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-PL-3911

Catalyst Attributes Profile <profile name> imported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-PL-3912

Catalyst Attributes Profile <profile name> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-PL-3913

Catalyst Job <job name> created successfully

Reason:

Information only.

Action:

No action is required.

CCA-PL-3916

Catalyst Job <job name> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9951

Tenant <tenant name> added successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9952

Tenant <tenant name> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9960

Tenant Group <group name> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9961

Tenant Group <group name> added successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9962

Tenant Group <group name> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9966

Selected tenants were deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9968

Selected tenant groups were deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9972

Tenant Administrator list successfully updated.

Reason:

Information only.

Action:

No action is required.

CCA-TN-9973

Tenant Viewer list successfully updated.

Reason:

Information only.

Action:

No action is required.

Certificate Informational Messages

This section explains the error messages that you see while performing the certificate operations in CA Configuration Automation.

CCA-CT-9498

<certificatepurpose> Certificate deleted for User <username>.

Reason:

Informational only.

Action:

No action is required.

Component Informational Messages

This section explains the informational messages that you see while performing the component operations in CA Configuration Automation.

CCA-CM-9302

Selected components deleted

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9304

Component <componentname> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9306

Component <componentname> is in Service <servicename>, and cannot be deleted from Server <servername>

Reason:

Informational only.

Action:

No action is required.

CCA-CM-9309

Component refresh job submitted for selected components

Reason:

Informational only.

Action:

No action is required.

Change Detection and Compare Informational Messages

This section describes the information messages that you get when you perform the change detection and compare operations.

CCA-DF-9152

Change detection on server <servername> between <snapshotdesignation1> and <snapshotdesignation2> started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9153

Change detection on server <servername> between <snapshotdesignation1> and <snapshotdesignation2> completed. <resultURL>.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9155

Change detection on service <servicename> between <snapshotdesignation1> and <snapshotdesignantion2> started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9157

Change detection on service <servicename> between <snapshotdesignation1> and <snapshotdesignation1> completed. <resultURL>

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9158

Compare server <servername1> snapshot <snapshotname1> to server <servername2> snapshot <snapshotname2> started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9160

Compare server <servername1> snapshot <snapshotname1> to server <servername2> snapshot <snapshotname2> completed. <resultURL>.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9161

Compare service <servicename1> snapshot <snapshotname1> to service <servicename2> snapshot <snapshotname2> started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9163

Compare service <servicename1> snapshot <snapshot1> to service <servicename2> snapshot <snapshotname3> completed. <resultURL>.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9164

The cleanup task found <1> compare/change detection records older than <1> days.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9169

Change detection task of <1> servers started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9170

Change detection task of <1> services started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9171

Compare task of server <servername> to <1> servers started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9172

Compare task between service <servicename1> and service <servicename2> started.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9173

Change detection task of <1> servers completed. <1> differences found.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9174

Change detection task of <1> services completed. <1> differences found.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9175

Compare task of server <servername> to <1> servers completed. <1> differences found.

Reason:

Informational only.

Action:

No action is required.

CCA-DF-9176

Compare task between service <servicename1> and service <servicename2> completed. <1> differences found

Reason:

Informational only.

Action:

No action is required.

Global Variable Informational Messages

This section describes the information messages that you get when you perform the global variables operations.

CCA-GV-5501

Global Variable <variablename> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-GV-5502

Global Variable <variablename> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-GV-5503

Global Variable <variablename> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-GV-5504

Selected global variables were deleted.

Reason:

Information only.

Action:

No action is required.

CCA-GV-5509

Imported global variables successfully.

Reason:

Information only.

Action:

No action is required.

CCA-GV-5512

Global Variable changes have been discarded.

Reason:

Information only.

Action:

No action is required.

Graph Informational Messages

This section describes the information messages that you get when you perform the graph operations.

CCA-GR-9801

Graph <graphname> deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9802

Graph <graphname> created.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9803

Graph <graphname> updated.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9806

Default graph set to <graphname>.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9808

Graph <currentname> renamed to <newname>.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9809

Graph <graphname> exported.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9810

Graph <graphname> imported.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9816

Folder <graphfoldername> created.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9817

Folder <graphfoldername> deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9823

Folder <graphfoldername> updated.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9830

Selected clusters were deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-GR-9806

Default graph set to <graphname>.

Reason:

Informational only.

Action:

No action is required.

General Informational Messages

This section describes the information messages that you get when you perform the general tasks in CA Configuration Automation.

CCA-GM-0031

Heap Dump started on all Grid servers

Reason:

Information only.

Action:

No action is required.

CCA-GM-0032

Heap Dump started on CCA Server <Hostname>

Reason:

Information only.

Action:

No action is required.

CCA-GM-0033

Heap Dump started on Grid Server <Hostname> (process id <id>)

Reason:

Information only.

Action:

No action is required.

CCA-GM-0035

Heap Dump for CCA Server <Hostname> created and zipped to file <output file>

Reason:

Information only.

Action:

No action is required.

CCA-GM-0036

Heap Dump for Grid Server <Hostname> (process id <id>) created and zipped to file <output file>

Reason:

Information only.

Action:

No action is required.

CCA-LA-1004

Selected log archives were deleted.

Reason:

Information only.

Action:

No action is required.

CCA-LA-1005

Log Archive <archive file name> deleted successfully

Reason:

Information only.

Action:

No action is required.

CCA-LA-1007

<number1> log entries and <number2> network discovery detail logs are archived in file <archived file name>.

Reason:

Information only.

Action:

No action is required.

CCA-LOG-8202

Auto-Refresh was successfully turned on.

Reason:

Information only.

Action:

No action is required.

CCA-LOG-8203

Auto-Refresh was successfully turned off.

Reason:

Information only.

Action:

No action is required.

Data Migration Informational Messages

This section describes the information messages that you get when you perform the data migration operations.

CCA-DM-7506

Database connected successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7510

Data Migration successfully completed.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7515

Certificates Imported Successfully, requires server restart.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7524

Starting Data Migration from Cohesion database to CCA database.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7525

Data Migration from Cohesion database to CCA database completed.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7526

Starting Data Migration from Cohesion database to archive file.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7527

Data Migration from Cohesion database to archive file completed.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7528

Creating a jar file...

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7529

Jar file creation completed.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7530

Started exporting data from Cohesion database to common file format.

Reason:

Informational only.

Action:

No action is required.

CCA-DM-7531

Exporting data to common file format completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7532

Loading the data into CCA database started.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7533

Loading the data into CCA database completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7534

Importing blueprints...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7535

Importing blueprints completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7536

No blueprints to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7538

Blueprint <blueprintname> Version [<blueprintversion>] Component Version <componentvesrion> imported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7541

Importing access profiles...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7542

Importing access profiles completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7543

No access profiles to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7544

Importing management profiles...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7545

Importing management profiles completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7546

No management profiles to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7547

Importing servers...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7548

Importing servers completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7549

No servers to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7550

Importing server groups...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7551

Importing server groups completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7552

No server groups to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7553

Importing services...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7554

Importing services completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7555

No Services to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7557

<objectname> imported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7558

<number> Blueprints selected for export using the filter criteria.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7561

Total: <totalcount> Success: <successcount> Failed: <failedcount>

Reason:

Information only.

Action:

No action is required.

CCA-DM-7562

**Importing Blueprint <blueprintname> Version [<blueprintversion>] Component
Version <componentversion>**

Reason:

Information only.

Action:

No action is required.

CCA-DM-7566

Data migration from an archive file to CCA Database completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7568

Validation of JAR file succeeded.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7569

Extracting JAR file.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7573

Importing global variables completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7575

Exporting global variables completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7577

Total: <totalcount> Success: <successcount> Failed: <failedcount>

Reason:

Information only.

Action:

No action is required.

CCA-DM-7579

**Blueprint <blueprintname> Version(<blueprintversion>) Component
Version(<componentversion>) exported successfully.**

Reason:

Information only.

Action:

No action is required.

CCA-DM-7582

<Count> Servers selected for export using the filter criteria.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7583

< Count> Services selected for export using the filter criteria.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7584

< Count> Server Groups selected for export.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7585

Service <servicename> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7586

Server <servername> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7587

Server Group <servergroupname> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7588

Access Profile <profilename> export started for Server Id <serverid>

Reason:

Information only.

Action:

No action is required.

CCA-DM-7589

Access Profile <profilename> exported successfully for Server Id <serverid>.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7590

Management Profile <profilename> export started.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7591

Management Profile <profilename> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7592

Notification Profile <profilename> export started.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7593

Notification Profile <profilename> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7596

Management Profile schedule export started.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7597

Management Profile schedule exported Successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7599

Import Security Certificates Successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7604

Importing global variables...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7605

No global variables to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7619

Importing Server Snapshots...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7620

No Server Snapshots to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7621

Importing Server Snapshots Completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7622

Importing Service Snapshots...

Reason:

Information only.

Action:

No action is required.

CCA-DM-7623

No Service Snapshots to import.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7624

Importing Service Snapshots Completed.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7625

<count> Server Snapshots selected for export using the filter criteria.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7626

Server Snapshot <snapshotname> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7627

Service Snapshot <snapshotname> exported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7628

<Count> Service Snapshots selected for export using the filter criteria.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7633

Invalid File search depth value <value>, It should be an integer.

Reason:

Information only.

Action:

No action is required.

CCA-DM-7641

Could not find host with the given name

Reason:

The server that is exported from the CA cohesion database is not resolved and is not imported to CA Configuration Automation.

Action:

No action is required.

Dashboard Informational Messages

This section describes the information messages that you get when you perform the dashboard operations.

CCA-DB-9701

Dashboard <Dashboard Name> deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9702

Dashboard <Dashboard Name> created.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9703

Dashboard <Dashboard Name> updated.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9706

Default dashboard set to <Dashboard name>.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9707

Cannot delete default dashboard.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9708

Dashboard <Old Name> renamed to <New Name>.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9709

Dashboard <Dashboard name> exported.

Reason:

Informational only.

Action:

No action is required.

CCA-DB-9710

Dashboard <Dashboard name> imported.

Reason:

Informational only.

Action:

No action is required.

Export and Import Informational Messages

This section describes the information messages that you get when you perform the export and import operations.

CCA-EX-5805

Export operation initiated.

Reason:

Informational only.

Action:

No action is required.

CCA-EX-5806

Export operation initiated for selected objects.

Reason:

Informational only.

Action:

No action is required.

CCA-IM-5924

<objectname> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-IM-5926

CSV File processed successfully.

Reason:

Informational only.

Action:

No action is required.

Management Profiles informational Messages

This section describes the information messages that you get when you perform the management profile operations.

CCA-PL-3812

Successfully removed the Blueprint "<Blueprintname>" references from Management Profile "<profilename>".

Reason:

Informational only.

Action:

No action is required.

NDG Informational Messages

This section explains the informational messages that you see while performing the NDG operations in CA Configuration Automation.

CCA-NR-1701

Network Discovery Gateway <NDGservername> added successfully

Reason:

Informational only.

Action:

No action is required.

CCA-NR-1702

Network Discovery Gateway <NDGservername> updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-NR-1703

Network Discovery Gateway <NDGservername> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-NR-1704

Network Discovery Gateway changes have been discarded

Reason:

Informational only.

Action:

No action is required.

CCA-NR-1707

Selected Network Discovery Gateways were deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-NR-1712

The Network Discovery Gateway for the selected servers has been updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-NR-1713

The Network Realm for the selected servers has been updated successfully

Reason:

Informational only.

Action:

No action is required.

NDG Discovery Informational Messages

This section explains the informational messages that you see while performing the NDG discovery operations in CA Configuration Automation.

CCA-ND-8050

Added Host <servername> discovered by Network Discovery Gateway on node <NDGservername>

Reason:

Informational only.

Action:

No action is required.

CCA-ND-8051

Updated Host <servername> discovered by Network Discovery Gateway on node <NDGservername>

Reason:

Informational only.

Action:

No action is required.

CCA-ND-8068

Network discovery with the following network profile is cancelled:

Reason:

Informational only.

Action:

No action is required.

Discovery and Refresh Informational Messages

This section describes the information messages that you get when you perform the discovery and refresh operations.

CCA-DIS-8516

Discovery started for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8519

Discovery completed for Server <servername> - <0> components discovered.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8521

<0> new components found. <1> components missing. <2> components deleted on the server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8522

Refresh started for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8524

Refresh completed for Server <servername> - <0> components Refreshed.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8525

Discovery started for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8526

Discovery completed on Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8527

Refresh started for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8528

Refresh completed on Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8553

Discovery on Server <servername> interrupted.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8565

Length <length> of parameter <parametername> in file <file> exceeded maximum.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8568

Discovery Options: [discoveryoptions]

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8574

Default Discovery Time Limit (No Wait) taken for Management Profile <profilename>

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8575

Default Inventory Pruning Mode (Mark Missing Keep Inventory) taken for <profilename>

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8576

OS Family not set for the Server <servername>, blueprints chosen will be irrespective of platform

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8585

Component refresh started for server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8586

Component refresh completed for server <servername> - <1> components Refreshed.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8598

<1> components are currently in use solely by services and stay intact on the server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8599

No changes found in the discovered data. Discovery will bypass the component <blueprintname> (<path>) on server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8601

The component <blueprintname> <path> is not discovered in the server <servername>. The component state will be marked as missing.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8602

The component <blueprintname> <path> is not discovered in the server <servername>. The component will be deleted from CCA inventory.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8603

The <serverproperties> grid job started for server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8604

The <serverproperties> grid job completed for server <servername> - <1> component created.

Reason:

Informational only.

Action:

No action is required.

CCA-DIS-8634

Server components <Hardware, Network, Storage> are discovered for server <ServerName>

Reason:

The logs display the discovered server components.

Action:

No action is required.

CCA-DIS-8635

Blueprints part of current discovery job are : <Blueprint Name + Version>

Reason:

The Blueprints that are selected in the server management profile are logged during the discovery operation.

Action:

No action is required.

CCA-DIS-8636

File Indicators part of current discovery job are : <File Indicators of Blueprints>

Reason:

The logs display the comma-separated list of the File indicators that are part of the discovery job.

Action:

No action is required.

CCA-DIS-8637

Directories excluded from discovery job are : <Excluded Directories specified in Administration properties>

Reason:

The logs specify the directories in the administration properties that are excluded from the discovery job.

Action:

No action is required.

CCA-DIS-8638

Files excluded from discovery job are : < Excluded files specified in Administration properties >

Reason:

The logs specify the files in the administration properties that are excluded from the discovery job.

Action:

No action is required.

CCA-DIS-8639

Discovery job will start the indicators search from : <Search From path> to the search depth <Search Depth Value>

Reason:

The logs specify the starting point and the depth level of the indicator search.

Action:

No action is required.

CCA-DIS-8640

Registry Indicators part of current discovery job are : <Registry Indicators of Blueprints>

Reason:

The logs specify the comma-separated list of file indicators that are part of the discovery operation.

Action:

No action is required.

CCA-DIS-8641

Discovery job will start registry indicators search from : <Search From Key> to the Search depth <Search Depth Value>

Reason:

The logs specify the registry indicators search, and the depth of the search during a discover operation.

Action:

No action is required.

CCA-DIS-8642

No indicators found for the server <Server Name> in the current discovery job.

Reason:

The logs specify that no indicators are found for a server during a discovery operation.

Action:

No action is required.

CCA-DIS-8646

File Search Roots found for the Indicator <File Indicator Name> during Discovery are : <File Search Roots>

Reason:

The logs specify that the File search roots are found for a file indicator.

Action:

No action is required.

CCA-DIS-8647

Registry Search Roots found for the Indicator <Registry Indicator Name> during Discovery are : <Registry Search Roots>

Reason:

The logs specify that the registry search roots are found for a file indicator.

Action:

No action is required.

CCA-DIS-8648

Effective Component Roots determined for the component blueprint <Blueprint Name> are : <Effective component roots>

Reason:

The logs specify that the effective search roots are found for the file indicator. The search roots are the qualifiers of the discovered component.

Action:

No action is required.

CCA-DIS-8649

Verification directive failed for blueprint <Blueprint name >, <component root> , on server <Server Name>, therefore this component will be discarded from the Discovery

Reason:

The logs specify that a verification rule failed for a component, and the discovery operation excludes it.

Action:

Update the component version. Ignore this message if the new component version is available.

CCA-DIS-8650**Server Properties component is discovered for server : <Server Name>**

Log statement indicating that the Server properties component is discovered

Reason:

The logs specify that the server properties component is discovered for a server.

Action:

No action is required.

CCA-DIS-8651**Time taken for discovery on server <Server Name> is : <Number of Seconds>****Reason:**

The logs specify the total time that is taken for discovering a server.

Action:

No action is required.

CCA-DIS-8652**Test Discovery started on server <Server Name>****Reason:**

The logs specify the start of the test discovery.

Action:

No action is required.

Profile Informational Messages

This section describes the information messages that you get when you perform the profile operations.

CCA-PL-3501

Management Profile <managementprofilename> created successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3502

Management Profile <managementprofilename> updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3503

Management Profile <managementprofilename> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3504

Access Profile <accessprofilename> created successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3505

Access Profile <accessprofilename> updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3506

Access Profile <accessprofilename> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3507

Notification Profile <notificationprofilename> created successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3508

Notification Profile <notificationprofilename> updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3509

Notification Profile <notificationprofilename> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3510

<profilename> was set as default profile

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3511

Selected profiles were deleted

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3512

Selected profiles were enabled

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3513

Selected profiles were disabled

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3532

Profile <profilename>updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3535

Management Profile changes have been discarded

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3536

Access Profile changes have been discarded

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3537

Notification Profile changes have been discarded

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3543

Assigned profiles to the selected servers

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3544

Assigned profiles to the selected services

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3555

Selected profiles were run

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3568

<n> Snapshots of Service <servicename> older than <maxAge> were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3569

<n> Snapshots of Service <servicename> exceeding the maximum count <maxcount> were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3578

Run action initiated for Management Profile <profilename>.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3578

Run action initiated for Management Profile <profilename>.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3583

<snapsdeleted> Snapshots of Server <servername> older than <maxage.agequalifier > and exceeding the maximum count <maxcount> were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3584

<snapsDeleted> Snapshots of Service <servicename> older than <maxage.agequalifier> and exceeding the maximum count <maxcount> were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3586

Job submitted for selected management profiles.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3601

Network Scan Policy <polycyname> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3602

Network Scan Policy <polycyname> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3603

Network Scan Policy <polycyname> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3604

Network Scan Policy changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3608

Selected policies were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3616

Selected Network Scan Policies were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3617

Network Scan Policy <policyname> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3850

Credential Vault Profile <profilename > created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3851

Credential Vault Profile <profilename > updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3852

Credential Vault Profile <profilename > deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3854

Credential Vault Profile changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3853

Credential Vault Profile <profilename > was set as the default profile.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3711

Communication Mapping deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3714

Communication Mapping created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3733

Application Mappings were successfully reordered.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3735

A request to validate credentials for User Id <username> on Server <servername> has been issued.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3626

Network Profile <profilename> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3627

Network Profile <profilename> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3628

Network Profile <profilename> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3630

Network Profile changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3636

Network Profile <profilename> job started.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3637

Network Profile <profilename> job finished. Click for details. <url>

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3722

Application Mapping created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3728

Application Mapping <applicationname> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3727

Application Mapping <applicationname> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3724

Application Mappings deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3816

Cancellation message successfully sent to Network Discovery Gateway.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3821

Notification profile <profilename> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3822

Notification profile <profilename> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3825

<n> Snapshots of Server <servername> older than <maxage> were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-3826

<n> Snapshots of Server <servername> exceeding the maximum count <maxcount> were deleted.

Reason:

Informational only.

Action:

No action is required.

Property Informational Messages

This section describes the information messages that you get when you perform the property operations.

CCA-PY-6501

Property <propertyname> saved successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PY-6502

Property <propertyname> for host <servername> was deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-PY-6503

Property <propertyname> for host <servername> was saved.

Reason:

Informational only.

Action:

No action is required.

Rules informational Messages

This section explains the error messages that you see while performing the rules operations in CA Configuration Automation.

CCA-RL-2501

Rule <rulename> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RL-2502

Rule <rulename> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RL-2503

Selected rules were deleted successfully.

Reason:

Informational only.

Action:

No action is required.

Rule Compliance Informational Messages

This section describes the information messages that you get when you perform the rule compliance operations.

CCA-RC-8115

Rule compliance on server <servername> snapshot <snapshotdesignation> started.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8117

Rule compliance on server <servername> snapshot <snapshotdesignation> completed. <resultURL>.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8118

Rule compliance on service <servicename> snapshot <snapshotdesignation> started.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8119

Rule compliance on service <servicename> snapshot <snapshotdesignation> completed. <resultURL>.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8120

The cleanup task found <1> rule compliance records older than <1> days.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8121

Rule compliance task of <1> servers started.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8122

Rule compliance task of <1> servers completed. <0> failures found.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8123

Rule compliance task of <1> services started.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8124

Rule compliance task of <1> services completed. <0> failures found.

Reason:

Informational only.

Action:

No action is required.

CCA-RE-1627

Rule Exception with Rule <rulename> on blueprint <blueprint name with version> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-RE-1631

Rule Exception with <rulename> on blueprint <blueprint name with version> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RE-1632

Rule Exception with <rulename> on file structure class <filestructureclass name> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RE-1633

Rule Exception with Rule <rulename> on file structure class <filestructureclass name> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-RE-1635

Rule Exception with rule <rulename> on blueprint <blueprintname with version> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RE-1636

Rule Exception with rule <rulename> on file structure class <filestructureclass name> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8132

The cleanup task found <Exceptions Count> rule compliance exceptions which does not have any servers/services associated.

Reason:

Informational only.

Action:

No action is required.

CCA-RC-8133

The cleanup task found <Number of rules> rule compliance exception rules which no longer exists.

Reason:

Informational only.

Action:

No action is required.

Rule Group Informational Messages

This section describes the information messages that you get when you perform the rule group operations.

CCA-RG-1601

Rule Group <groupname> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1602

Rule Group <groupname> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1603

Rule Group <groupname> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1605

Selected rule groups were deleted.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1608

Rule Group changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1610

<count> rules have been added to Rule Group <groupname>.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1611

Rules have been updated in Rule Group <groupname>.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1612

Rules have been deleted from Rule Group <groupname>.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1614

Rule Group <groupname> already exists.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1615

Rule Group <groupname> exported.

Reason:

Information only.

Action:

No action is required.

CCA-RG-1616

Rule Group <groupname> imported successfully.

Reason:

Information only.

Action:

No action is required.

Reports Informational Messages

This section describes the information messages that you get when you perform the reports operations.

CCA-RT-6001

Report <reportname> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6002

Report <reportname> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6003

Report <reportname> deleted successfully

Reason:

Information only.

Action:

No action is required.

CCA-RT-6004

Report <reportname> was run.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6005

Report <reportname> of this template created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6007

<instancename> Report Instance deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6009

<instancename> Report Instance share removed.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6010

<instancename> Report instance is shared.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6013

Selected instances were deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6014

Selected reports were deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6015

Selected instances were shared.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6016

Selected instances share removed.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6024

Selected reports tasks submitted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6045

Report changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6086

Run report task submitted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6087

Report Template <reporttemplatename> is saved as <reportname>.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6093

Report <reportname> execution started.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6094

Report <reportname> execution completed.

Reason:

Information only.

Action:

No action is required.

CCA-RT-6095

Report <reportname> attachment file size exceeds the default attachment configuration property "mail.server.attachment.size". By default the report result will be sent as hyper link in the notification.

Reason:

Information only.

Action:

No action is required.

Remediation Jobs Informational Messages

This section describes the information messages that you get when you perform the remediation operations.

CCA-RJ-8001

Remediation Job changes have been discarded

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8005

Selected remediation jobs deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8006

Remediation Job <jobname> was created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8008

Remediation Job Step <jobstep> was saved.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8009

Remediation Job <jobname> was saved.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8015

Remediation Job <jobname> was updated.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8016

Remediation Job <jobname> was deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8036

The cleanup task found <n> remediation history records older than <n> days.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8037

Server <server> was added to remediation job <jobname>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8038

Server group <servergroup> was added to remediation job <jobname>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8039

Service <service> was added to remediation job <jobname>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8040

<n> servers removed from remediation job <jobname>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8041

<n> server groups removed from remediation job <jobname>.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8042

<n> services removed from remediation job <jobname>.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8044

Remediation Jobs started successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8045

Remediation job <jobname> started at <time>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8046

Remediation job <jobname> finished successfully at <time>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8047

Remediation job <jobname> finished with failure at <time>

Reason:

The remediation job <jobname> failed.

Action:

Verify the corresponding operation log details in the Log tab which caused the failure.

CCA-RJ-8049

Undo remediation history <jobname> started.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8050

Undo remediation history <jobname> finished successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8051

Undo remediation history <jobname> finished with failure.

Reason:

Informational only.

Action:

Undo the remediation history <jobname> failed with failures. Verify the corresponding operation log details in the Log tab which caused the failure.

CCA-RJ-8052

Rerun remediation history <jobname> started.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8053

Rerun remediation history <jobname> finished successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8054

Rerun remediation history <jobname> finished with failure.

Reason:

Informational only.

Action:

Rerun the remediation history <jobname> failed with failures. Verify the corresponding operation log details in the Log tab which caused the failure.

CCA-RJ-8055

<n> remediation history of job <jobname> were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8060

Execute macro <macro> of component <component> started on server <server>

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8061

Execute macro <macro> of component <component> finished successfully on server <server>

Reason:

Informational only.

Action:

No action is required.

.

CCA-RJ-8070

Remediation job finished successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8072

Remediation Jobs scheduled successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8073

Remediation job started.

Reason:

Informational only.

Action:

No action is required.

CCA-RJ-8074

Remediation Job Step changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

Remediation Profile Informational Messages

This section describes the information messages that you get when you perform the remediation profile operations.

CCA-RP-1002

Remediation Profile <profilename> was created.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1004

Remediation Profile <profilename> was updated.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1005

Remediation Profile <profilename> was deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1006

Remediation Profile changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1014

Selected steps were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1017

Remediation Profile Step <stepname> was created.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1018

Remediation Profile Step <stepname> was updated.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1019

Remediation Profile Step <stepname> was deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1023

Remediation Profile Steps were successfully reordered.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1025

Steps were reordered for Remediation Profile <profilename>.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1026

<n> Remediation Profile Steps deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1027

**A Remediation Profile Step is specified more than once in the request to be deleted.
The duplicate one will be ignored.**

Reason:

Informational only.

Action:

No action is required.

CCA-RP-1031

<n> Remediation Profiles deleted.

Reason:

Informational only

Action:

No action is required

CCA-RP-1034

Remediation Profile Step <stepname> was added to Profile <profilename>

Reason:

Informational only

Action:

No action is required

CCA-RP-1036

Remediation profile <profilename> imported successfully.

Reason:

Informational only

Action:

No action is required.

CCA-RP-1037

Remediation profile <profilename> updated successfully.

Reason:

Informational only

Action:

No action is required.

CCA-RP-1038

Remediation profile already exists.

Reason:

The remediation profile <profilename> is already available.

Action:

No action is required.

Remediation History Informational Messages

This section describes the information messages that you get when you perform the remediation history operations.

CCA-RH-1003

Selected Remediation History records were deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-RH-1007

Jobs for the selected Remediation History records were successfully ran again.

Reason:

Informational only.

Action:

No action is required.

CCA-RH-1008

Jobs for the selected Remediation History records were successfully submitted.

Reason:

Informational only.

Action:

No action is required.

Remote Agent Installation Informational Messages

This section describes the information messages that you get when you perform the remote agent installation.

CCA-RI-1401

Remote Agent Install Started for Server <servername>.

Reason:

Informational only

Action:

No action is required.

CCA-RI-1402

Remote Agent Uninstall Started for Server <servername>.

Reason:

Informational only

Action:

No action is required.

CCA-RI-1403

Remote Agent Installed Successfully on Server <servername>.

Reason:

Informational only

Action:

No action is required.

CCA-RI-1404

Remote Agent Uninstalled Successfully on Server <servername>.

Reason:

Informational only

Action:

No action is required.

CCA-RI-1408

Remote Agent Installation Job is not posted for Server <Server Name>

Reason:

Informational only

Action:

No action is required.

CCA-RI-1410

Remote Agent Uninstallation Job is not posted for Server <Server Name>

Reason:

Informational only

Action:

No action is required.

Server Informational Messages

This section describes the information messages that you get when you perform the server operations.

CCA-SR-1001

Server <servername> added successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1002

User provided server name <servername1> was resolved to <servername2> and added successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1003

Server <servername> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1004

Server <servername> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1005

Run Management Profile action initiated for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1007

Stop Discovery action initiated for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1008

Refresh Server action initiated for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1010

Selected servers were deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1015

Server changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1018

Servers added successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1021

Stop Discover Servers job submitted.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1022

Management Profile job submitted for selected servers.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1027

Selected servers state changed to "Managed".

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1028

Selected servers state changed to "Unmanaged".

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1044

Execution of Management profile for Server <servername> started.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1045

Execution of Management profile for Server <servername> completed.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1052

Reconcile servers successful.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1056

Operation <operation> is not allowed.

Reason:

Except the add command, no other command is supported while adding servers using the CSV file.

Action:

No action is required.

CCA-SR-1063

File processed successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1064

Agent secured for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1066

Discovery canceled for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1080

Currently no adhoc discovery operation is running on Server <servername>. Stop Discovery is only applicable to adhoc discovery.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1081

Server <servername> can not be deleted, <currentactivity>.

Reason:

Operation <currentactivity> is running on the server <servername>.

Action:

No action is required.

CCA-SR-1084

Server <servername> added to Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1085

Server <servername> deleted from Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1086

Management Options: [<selectedmanagementoptions>]

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1087

Server <servername> does not exist.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1089

Install Agents action is initiated for Server <servername>

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1090

Uninstall Agents action is initiated for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1100

Discovery job submitted for selected servers.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1101

Refresh job submitted for selected servers.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1116

Agent Installation job submitted for selected servers.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1117

Agent Uninstallation job submitted for selected servers.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1118

Snapshot job submitted for selected servers.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1121

Snapshot action initiated for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1123

Could not resolve host <servername>, IP address <ipaddress>. Server creation allowed by user.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1126

No snapshot on server <servername> to perform change detection operation for profile <managementprofilename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1127

No snapshot (snapshotdesignation) on target server <servername> to compare for profile <managementprofile>

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1137

Server <servername> has been removed from CCA database.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1138

Successfully added the server <servername> through self registration agent request.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1152

Selected servers were updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1160

Reconciliation started for server <servername>

Reason:

Informational only.

Action:

No action is required.

CCA-SR-1161

Reconciliation for server <servername> completed successfully

Reason:

Informational only.

Action:

No action is required.

Security Certificate Informational Messages

This section explains the informational messages that you see while performing the security certificate operations in CA Configuration Automation.

CCA-CT-9401

Certificate Authority destroyed

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9402

HTTPS support disabled

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9403

HTTPS support enabled

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9404

<certificatepurpose> Certificate created for Server <servername>

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9405

Certificate Authority created successfully. The CCA Server must be restarted for this Certificate Authority to become activated

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9407

Selected Certificates were deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9408

Selected Server Agents were secured successfully

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9432

<certificatepurpose> Certificate deleted for Server <servername>

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9475

<certificatepurpose> Certificate created for Server <servername>. Perform \"Enable HTTPS\" action to enable https

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9476

Client Authentication enabled

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9477

Client Authentication disabled

Reason:

Informational only.

Action:

No action is required.

CCA-CT-9496

<certificatepurpose> Certificate created for User <username>

Reason:

Informational only.

Action:

No action is required.

Structure Class Informational Messages

This section describes the information messages that you get while performing the structure class operations.

CCA-SC-5001

File Structure Class <fscname> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5002

File Structure Class <fscname> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5003

File Structure Class <fscname> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5008

File Structure Class changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5009

Group <groupname> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5010

Group <groupname> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5011

Group <groupname> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5016

Parameter <parametername> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5017

Parameter <parametername> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5018

Parameter <parametername> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5029

Structure Classes exported successfully

Reason:

Information only.

Action:

No action is required.

CCA-SC-5031

Structure Class <structureclass> imported successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5033

The selected File Structure Classes were deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5041

Parameters were successfully reordered.

Reason:

Information only.

Action:

No action is required.

CCA-SC-5042

Groups were successfully reordered.

Reason:

Information only.

Action:

No action is required.

Server Groups Informational Messages

This section describes the information messages that you get when you perform the server groups operations.

CCA-SG-1501

Server Group <groupname> created successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1502

Server Group <groupname> updated successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1503

Server Group <groupname> deleted successfully.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1505

Selected server groups were deleted.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1508

Server Group changes have been discarded.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1511

Server Group <groupname> was exported.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1512

Server Group <groupname> already exists.

Reason:

Information only.

Action:

No action is required.

CCA-SG-1514

Server Group <groupname> was imported.

Reason:

Information only.

Action:

No action is required.

Service Information Messages

This section describes the information messages that you get when you perform the service operations.

CCA-SV-2001

Service <servicename> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2002

Service <servicename> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2003

Service <servicename> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2004

Run Management Profile action initiated for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2005

Run Discovery action initiated for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2006

Stop Discovery action initiated for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2007

Refresh Server action initiated for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2009

Selected services were deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2014

Service changes have been discarded successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2015

Service Snapshot changes have been discarded successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2019

Stop Discover Services job submitted.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2020

Management Profile job submitted for selected services.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2024

Execution of Management profile for Service <servicename> started.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2025

Execution of Management profile for Service <servicename> completed.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2039

Discovery canceled for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2049

Currently no discovery operation is running on Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2050

Service <servicename> can not be deleted, <currentactivity>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2052

Server <servername> added to Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2053

Server <servername> deleted from Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2056

Discovery job submitted for selected services.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2057

Refresh job submitted for selected services.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2059

Snapshot job submitted for selected services.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2060

Snapshot action initiated for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2063

No snapshot <designatedsnapshot> on target service <servicename> to compare for profile <managementprofile>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2062

No snapshot on service <servicename> to perform change detection operation for profile <managementprofile>.

Reason:

Informational only.

Action:

No action is required.

CCA-SV-2077

Service <Service Name> imported successfully.

Reason:

Informational only.

Action:

No action is required.

Service Profile informational Messages

This section describes the information messages that you get when you perform the service profile operations.

CCA-SVCP-1001

Service Profile <Profile Name> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SVCP-1002

Service Profile <Profile Name> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SVCP-1003

Service Profile <Profile Name> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

Snapshot Information Messages

This section describes the information messages that you get when you perform the snapshot operations.

CCA-ST-3002

Snapshot <snapshotname> of Service <servicename> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3003

Service Snapshot <snapshotname> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3004

Service Snapshot <snapshotname> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3005

Service Snapshot <snapshotname> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3007

Snapshot <snapshotname> of Server <servername> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3008

Server Snapshot <snapshotname> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3009

Server Snapshot <snapshotname> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3010

Server Snapshot <snapshotname> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3011

Snapshot <snapshotname> saved successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3019

Snapshot <snapshotname> is designated as <snapshotdesignation>.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3025

Server Snapshot changes have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3028

Removed snapshots <snapshotdesignation> designation.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3047

Server Snapshot <snapshotname> of Server <servername> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3048

Service Snapshot <snapshotname> of Service <servicename> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3051

Snapshot already exists.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3055

Server Snapshot <snapshotname> started.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3056

Snapshot delete operation initiated, check log for details.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3059

Snapshot <snapshotname> of Service <servicename> delete started.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3060

Snapshot <snapshotname> of Server <servername> delete started.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3061

Snapshot delete operation initiated for Server <servername>.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3062

Snapshot delete operation initiated for Service <servicename>.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3063

Snapshot <snapshotname> of Server <servername> already deleted.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3064

Service Snapshot <snapshotname> started.

Reason:

Informational only.

Action:

No action is required.

CCA-ST-3081

Snapshot "<snapshotname>" of Service "<servicename>" already deleted.

Reason:

Informational only.

Action:

No action is required.

Storage Area Network Informational Messages

This section describes the information messages that you get when you perform the storage area network operations.

CCA-SS-1002

The selected storage systems were deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-SS-1003

Storage system <Storage System Name> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

Table View Informational Messages

This section explains the informational messages that you see while performing the table view operations in CA Configuration Automation.

CCA-TV-7001

Table View <viewname> updated successfully

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7002

Table View <viewname> created successfully

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7004

Selected table views were deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7005

Changes to the Table View have been discarded

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7013

Table View <viewname> deleted successfully

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7014

Table View <viewname> was exported

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7016

Table View <viewname> was imported

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7017

Number of records returned exceeded the allowed maximum. Please use a filter to limit the number of records

Reason:

Informational only.

Action:

No action is required.

Tenant Information Messages

This section describes the information messages that you get when you perform the tenant operations.

CCA-TN-9950

Tenant <tenant name> updated successfully.

Reason:

Information only.

Action:

No action is required.

Task Wizard Informational Messages

This section explains the informational messages that you see while performing the task wizard operations in CA Configuration Automation.

CCA-TW-1006

Network Discovery has been started

Reason:

Informational only.

Action:

No action is required.

CCA-TW-1007

Service Discovery has been started

Reason:

Informational only.

Action:

No action is required.

CCA-TW-1010

Job Complete

Reason:

Informational only.

Action:

No action is required.

CCA-TW-1012

Network Discovery was scheduled successfully

Reason:

Informational only.

Action:

No action is required.

CCA-TW-1013

Agent installation was scheduled successfully

Reason:

Informational only.

Action:

No action is required.

Table View Informational Messages

This section describes the information messages that you get when you perform the table view operations.

CCA-TV-7001

Table View <viewname> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7002

Table View <viewname> created successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7004

Selected table views were deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7005

Changes to the Table View have been discarded.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7013

Table View <viewname> deleted successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7014

Table View <viewname> was exported.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7016

Table View <viewname> was imported.

Reason:

Informational only.

Action:

No action is required.

CCA-TV-7017

Number of records returned exceeded the allowed maximum. Please use a filter to limit the number of records.

Reason:

Informational only.

Action:

No action is required.

UI Export-Import of Profiles Informational Messages

This section describes the information messages that you get when you perform the UI export and import operations.

CCA-MP-5601

Management profile already exists.

Reason:

Informational only.

Action:

No action is required.

CCA-MP-5602

Management profile <managementprofilename> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-MP-5603

Management profile <managementprofilename> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-AP-5604

Access profile <accessprofilename> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-AP-5605

Access profile <accessprofilename> updated successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-PL-5611

Access profile already exists.

Reason:

Informational only.

Action:

No action is required.

CCA-NP-5613

Network profile already exists.

Reason:

Informational only.

Action:

No action is required.

CCA-NP-5614

Network profile <networkprofilename> imported successfully.

Reason:

Informational only.

Action:

No action is required.

CCA-NP-5615

Network profile <networkprofilename> updated successfully.

Reason:

Informational only.

Action:

No action is required.