

CA View[®]

Message Guide

Release 12.1



This Documentation, which includes embedded help systems and electronically distributed materials, (hereinafter referred to as the "Documentation") is for your informational purposes only and is subject to change or withdrawal by CA at any time.

This Documentation may not be copied, transferred, reproduced, disclosed, modified or duplicated, in whole or in part, without the prior written consent of CA. This Documentation is confidential and proprietary information of CA and may not be disclosed by you or used for any purpose other than as may be permitted in (i) a separate agreement between you and CA governing your use of the CA software to which the Documentation relates; or (ii) a separate confidentiality agreement between you and CA.

Notwithstanding the foregoing, if you are a licensed user of the software product(s) addressed in the Documentation, you may print or otherwise make available a reasonable number of copies of the Documentation for internal use by you and your employees in connection with that software, provided that all CA copyright notices and legends are affixed to each reproduced copy.

The right to print or otherwise make available copies of the Documentation is limited to the period during which the applicable license for such software remains in full force and effect. Should the license terminate for any reason, it is your responsibility to certify in writing to CA that all copies and partial copies of the Documentation have been returned to CA or destroyed.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CA PROVIDES THIS DOCUMENTATION "AS IS" WITHOUT WARRANTY OF ANY KIND, INCLUDING WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NONINFRINGEMENT. IN NO EVENT WILL CA BE LIABLE TO YOU OR ANY THIRD PARTY FOR ANY LOSS OR DAMAGE, DIRECT OR INDIRECT, FROM THE USE OF THIS DOCUMENTATION, INCLUDING WITHOUT LIMITATION, LOST PROFITS, LOST INVESTMENT, BUSINESS INTERRUPTION, GOODWILL, OR LOST DATA, EVEN IF CA IS EXPRESSLY ADVISED IN ADVANCE OF THE POSSIBILITY OF SUCH LOSS OR DAMAGE.

The use of any software product referenced in the Documentation is governed by the applicable license agreement and such license agreement is not modified in any way by the terms of this notice.

The manufacturer of this Documentation is CA.

Provided with "Restricted Rights." Use, duplication or disclosure by the United States Government is subject to the restrictions set forth in FAR Sections 12.212, 52.227-14, and 52.227-19(c)(1) - (2) and DFARS Section 252.227-7014(b)(3), as applicable, or their successors.

Copyright © 2013 CA. All rights reserved. All trademarks, trade names, service marks, and logos referenced herein belong to their respective companies.

Contact CA Technologies

Contact CA Support

For your convenience, CA Technologies provides one site where you can access the information that you need for your Home Office, Small Business, and Enterprise CA Technologies products. At <http://ca.com/support>, you can access the following resources:

- Online and telephone contact information for technical assistance and customer services
- Information about user communities and forums
- Product and documentation downloads
- CA Support policies and guidelines
- Other helpful resources appropriate for your product

Providing Feedback About Product Documentation

If you have comments or questions about CA Technologies product documentation, you can send a message to techpubs@ca.com.

To provide feedback about CA Technologies product documentation, complete our short customer survey which is available on the CA Support website at <http://ca.com/docs>.

Contents

Chapter 1: Overview	7
New Features and Enhancements in this Release.....	7
Audience	7
Chapter 2: Common Component Error Messages	9
Diagnostic and Error Messages	9
Chapter 3: Error Messages	99
System Error Messages	99
Chapter 4: Cross-Memory Services Messages	583
Error Messages.....	583
Chapter 5: Abends	599
User Abends	599
System Abends	607

Chapter 1: Overview

Welcome to CA View, a SYSOUT archival, and retrieval system that stores the computer output on either DASD or tape and retrieves that output upon demand.

This section contains the following topics:

[New Features and Enhancements in this Release](#) (see page 7)

[Audience](#) (see page 7)

New Features and Enhancements in this Release

For information about new features and enhancements, see the *Release Notes*.

Audience

This guide is targeted at system administrators who are responsible for managing a report storage (archival) and subsequent report retrieval.

This guide provides the user abend codes and routine error messages that CA View generates and provides procedures to respond to the messages. This guide assumes that you are familiar with IBM computer system terms and concepts and that you have a basic working knowledge of IBM JCL.

Chapter 2: Common Component Error Messages

This chapter discusses the Common Component error messages.

This section contains the following topics:

[Diagnostic and Error Messages](#) (see page 9)

Diagnostic and Error Messages

EBCCIE01

NON-MVS/XA EXECUTION NOT ALLOWED

Reason:

The CICS Cross Memory online interface must be executed on a system that runs MVS/XA or higher.

Action:

Run the Cross Memory task on a MVS/XA system or higher.

EBCCIE02

NON-CICS/XA EXECUTION NOT ALLOWED

Reason:

The DFHPPT or RDO definition for the EC1CIEND program is wrong. The comment indicates the specific error. You are possibly not using Version 4.1 or a later version of CICS. EC1CEND requires Version 4.1 or a later version of CICS to work.

Action:

Correct the EC1CIEND definition.

EBCCIE03

XMS SUPPORT SUBTASK STOP FAILED

Reason:

The EC1XSTSK has not shut down after waiting 10 seconds. The termination program stops with this error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCCIE10

EC1XSTSK SUBTASK TERMINATE REQUESTED

Reason:

The subtask termination program has requested that the MVS subtask terminate; this occurs when CICS is being shut down and the PLTSD program is executed, or when a terminal operator requests that the subtask be shut down through the operator interface (CICS OP20 transaction).

Action:

None. This message is informational.

EBCCIE99

XMS SUPPORT TASK STOPPED

Reason:

EC1CIEND has terminated the subtask for EC1XSTSK.

Action:

None. This message is informational.

EBCCIN01

NON-MVS/XA EXECUTION NOT ALLOWED

Reason:

The CICS Cross Memory online interface must be executed on a system that runs MVS/XA or higher.

Action:

Run the Cross Memory task on an MVS/XA system or higher.

EBCCIN02

NON-CICS/XA EXECUTION NOT ALLOWED

Reason:

The DFHPPT or RDO definition for the EC1CINIT program is wrong. The comment indicates what specifically is found to be in error. You are possibly not using Version 4.1 or a later version of CICS. EC1CINIT requires Version 4.1 or a later version of CICS to work.

Action:

Correct the EC1CIEND definition.

EBCCIN03

USER SUB-POOL GETMAIN FAILURE

Reason:

EC1CINIT could not get enough storage to initialize. The MAXUSER parameter in EC1XMCTR is used to determine the initial storage requirements.

Action:

Reduce the value that is assigned to MAXUSER or increase the storage available above the 31-bit line in the region.

EBCCIN04

SERVICE TRANSACTION TRANID ERROR

Reason:

EC1CINIT could not start the service transaction defined in the EC1XMCTR table. This transaction is required. The subtask is terminated.

Action:

Try to execute EC1CINIT again.

EBCCIN05

EBCXSTSK ATTACH FAILURE

Reason:

EC1CINIT could not start the EC1XSTSK subtask. The system cannot be initialized.

Action:

Try to execute EC1CINIT again.

EBCCIN06

EBCXSTSK ALREADY ACTIVE, CONTROL TABLE (EC1XMCTR) RELOADED

Reason:

The subtask is active when EC1CINIT was executed. The control table was reloaded and no other changes were made. Some initialization options (MAXUSER, MSGVLV) are ignored.

Action:

None. This message is informational.

EBCCIN07

WAITLIST GETMAIN FAILURE

Reason:

EC1CINIT requires more storage above the 24-bit line to be initialized.

Action:

Increase the line storage by increasing the region size of CICS or TSO.

EBCCIN08

CICS RELEASE DEPENDENT MISSING

Reason:

EC1CINIT could not find the correct version of the CICS release-dependent program.

Action:

Review the Installation Guide and see <http://ca.com/support> for the most latest requirements for CICS.

EBCCIN09

REQUIRED PROGRAMS MISSING FROM STEPLIB/DFHRPL

Reason:

The EC1CINIT program has checked and found one or more required programs cannot be loaded from the STEPLIB or DFHRPL.

Action:

Review the CICS JOBLOG for EBCCIN10 or EBCCIN11 error messages indicating the specific programs that are not found. Copy the required programs to the STEPLIB/DFHRPL and restart the initialization process.

EBCCIN10

pgm-name NOT IN STEPLIB

Reason:

The listed program is not found in the STEPLIB and is required for normal operation.

Action:

Move the program to the CICS STEPLIB.

Note: This program cannot be loaded from the CICS DFHRPL libraries.

EBCCIN11

pgm-name NOT IN DFHRPL

Reason:

The listed program is not found in the DFHRPL and is required for normal operation.

Action:

Move the program to the CICS DFHRPL.

Note: The program cannot be loaded from the CICS STEPLIB or linklist.

EBCCIN99

XMS SUPPORT TASK READY (XMC1)

Reason:

EC1CINIT finished initializing without error.

Action:

None. This message is informational.

EBCCIS01

NON-MVS/XA EXECUTION NOT ALLOWED

Reason:

You are not using MVS/ESA. EC1CISRV requires MVS/ESA to work.

Action:

Use MVS/ESA, and then try again.

EBCCIS02

NON-CICS/XA EXECUTION NOT ALLOWED

Reason:

The DFHPPT or RDO definition for the EC1CISRV program is wrong. The comment indicates what specifically was in the error. You are possibly not using Version 4.1 or a later version of CICS. EC1CISRV requires Version 4.1 or a later version.

Action:

Correct the EC1CISRV definition.

EBCCIS03

EC1XSTSK NOT ACTIVE

Reason:

The EC1XSTSK program is not executing. EC1CISRV requires the EC1XSTSK to work. EC1CISRV ends. EC1CINIT, which starts the subtask, was not executing. The subtask stopped.

Action:

See your operations administrator for more information.

EBCCIS04

INVALID EBCXSCTL BLOCK FOUND

Reason:

An internal error occurred in EC1CISRV.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCCIS05

EC1CISRV PROGRAM IS NOT A TERMINAL PROGRAM

Reason:

EC1CISRV is not designed to be attached to a terminal. EC1CISRV ends.

Action:

Refrain from executing EC1CISRV from a terminal.

EBCCIS06

EC1CISRV PROGRAM HAS ABENDED

Reason:

The service program has abended and shut down.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCCIS98

XXXXXXXXXXXXXXXXXXXXXXXXXXXX

Reason:

This is an informational message response that is written to the terminal.

Action:

Review the associated message text for further information. Also review error messages that are displayed before this about the cause. For assistance, contact Technical Support at <http://ca.com/support> if necessary.

EBCCIS99

SRVC TRAN EC1CISRV STOPPED

Reason:

The EC1CISRV service transaction has been stopped.

Action:

Review the error messages that are displayed before this message about the cause. For assistance, contact Technical Support at <http://ca.com/support> if necessary.

EBCC0x01

LENGTH ERROR ON CICS SEND FUNCTION

Reason:

VIEW received a CICS LENGERR condition when doing a screen send to a terminal where 'x' indicates the CICS release level being used and 4 = CICS Release 4 or above.

Action:

Retry VIEW command. For assistance, contact Technical Support at <http://ca.com/support>.

EBCDBI00 through EBCDBI13

EBCDBI00 xxxxx does not exist
EBCDBI01 allocation failed for xxxxx - ERROR=XXXX INFO=XXXX DS=
EBCDBI02 I/O error on xxxx - DCCB=XXXXXXXXX ECB=
EBCDBI03 block out of range on xxxxx - DCCB=
EBCDBI04 Data set rename failed - REQ=XXXXXXXXX RC=XXXX
REASON=XXXXXXXXX
EBCDBI05 Unsupported device type - BLKS/CYL=XXXXX
EBCDBI06 Maximum of 255 extents defined to xxxxx
EBCDBI07 No more space in database
EBCDBI08 Missing high-level index name of database
EBCDBI09 logical I/O error XXXX on xxxxx - DCCB=
EBCDBI10 Unexpected end of data
EBCDBI11 Record not found
EBCDBI12 Lock file for xxxxx already exists
EBCDBI13 Lock file for xxxxx does not exist

Reason:

An allocation error, access error, or I/O error occurred with the CA View database as described by the text of the message where:

database

Identifies the high-level prefix of the database.

dccb

Represents a hexadecimal string identifying the data set, relative cylinder, and relative block in the database.

Function

Identifies the type of catalog function that failed for a RENAME.

ccc

Indicates the internal control block being accessed (SFB, IFB, or XFB).

eeee

Identifies the internal error code of the logical I/O error.

Kkkkkkkkkkkkkkkk

Specifies the key of the record in hex (if the key is longer than 16 bytes, only the first 16 bytes are shown).

nnn

Represents a number to identify a data set number, number of blocks, return code, or error code.

xxxx or xxxxxxxx

Represents a hexadecimal number for an error code, information code, or reason code.

Action:

Correct the problem with the database. This can require copying the database with the SARDBASE utility or, in the extreme case, recovering the database.

Note: For more information about database utilities, see the chapters "Database Utilities" and "Backing Up and Recovering the Database" in the *Reference Guide*.

EBCDBI16

Database xxxxx at incorrect release level

Reason:

The software release level does not match the database release level.

Action:

Verify that you are using the correct steplib (loadlib). If it is correct, run the SARDBASE utility to version the database to the correct level.

EBCDBI17

Database space for file deleted or reused

Reason:

A report was deleted from the disk while it was being viewed.

Action:

Verify that the report is no longer on the disk, and then reload it back to disk.

EBCDBI18

No MVS support for Compression Services

Reason:

A report was compressed and archived to disk using MVS Compression Services, but your current operating system does not support MVS Compression Services.

Action:

If the report is archived to tape, delete the disk copy and reload the report from tape. If the report is not archived to tape, access the report from the same machine that archived it.

EBCDBL01

SAR DATABASE dbase-name action id status

Reason:

During XMS initialization CA View provides information on the databases in use. The Dbase-name indicates the database name. The 'action' field shows ADDED or RESET. The 'id' field indicates the relative database # in the EBCXMCTR table for XMS. The 'status' field shows AVAILABLE or SUSPENDED.

Action:

None. This message is informational.

EBCDBL02

DATABASE CONTROL TABLE READY

Reason:

During XMS initialization, CA View clears the use counts and allocation flag bit for each table listed in the EBCXMCTR table. The EBCDBL02 message is displayed after this process is completed.

Action:

None. This message is informational.

EBCDBP01

CRITICAL ERROR. PROGRAM TERMINATED WITH DUMP. INVALID blk

Reason:

A CA View program has terminated, and a dump was generated. In this message blk specifies the control block CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It is suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart the program that was terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

EBCDRV00

SYSIN DATA=parameter=value
PARM DATA=parameters

Reason:

The EBCDRV00 message is informational and displays both the parameters in the SYSIN dataset and in the execute statement PARM Field.

Action:

None

EBCDRV01

pgm-name SUBTASK ATTACHED

Reason:

The operator communication subtask has attached and is ready to accept operator commands. This message has a MSGLVL of NORM.

Action:

None.

EBCDRV02

pgm-name SUBTASK ATTACHED

Reason:

The cross-memory login subtask has attached and is ready to except cross-memory logon requests. This message has a MSGLVL of NORM.

Action:

None.

EBCDRV03

pgm-name SUBTASK ATTACHED APPLID=applid

Reason:

The VTAM login subtask has attached to open the VTAM ACB and attach VTAM exits. This message has a MSGLVL of NORM.

Action:

Correct the input parameters, and then restart the region.

EBCDRV04

pgm-name CANNOT BE USED WITH parm-name=value

Reason:

Initialization has detected incompatible input parameters. These parameters cannot be used together. For example, LGNFMT= cannot be specified when SARVTDB= is used because LGNFMT= specifies the FORMAT of the VTAM logon data. And SARVTDB= indicates that the specific qualifier replaces the logon data. You cannot do both at the same time.

Action:

Correct the input parameters, and then restart the region.

EBCDRV05

XXXXXX= MUST BE SPECIFIED WITH YYYY=ZZZZ

Reason:

Initialization has detected that an input parameter requires a missing input parameter. For instance SARAPPL= must be specified when SARVTDB= is used. SARAPPL= specifies that the VTAM interface is used, and SARVTDB= is only valid when VTAM is initialized.

Action:

Correct the input parameters, and then restart the region.

EBCDRV06

VTAMPASS=YES IS SPECIFIED, BUT NO VTAM INTERFACE IS ACTIVE

Reason:

Initialization has detected that an input parameter that specifies the VTAM logon processing occurs, but none of the VTAM interfaces (SARAPPL=, RMOAPPL= INBAPPL=) were specified.

Action:

Correct the input parameters, and then restart the region.

EBCDRV07

VTMSAA=YES IS SPECIFIED, BUT NO VTAM INTERFACE IS ACTIVE

Reason:

Initialization has detected that an input parameter that specifies how a VTAM logon processing occurs, but none of the VTAM interfaces (SARAPPL=, RMOAPPL= INBAPPL=) were specified.

Action:

Correct the input parameters, and then restart the region.

EBCDRV08

VTMQUERY= IS SPECIFIED, BUT NO VTAM INTERFACE IS ACTIVE

Reason:

Initialization has detected that an input parameter that specifies how a VTAM logon processing occurs, but none of the VTAM interfaces (SARAPPL=, RMOAPPL= INBAPPL=) were specified.

Action:

Correct the input parameters, and then restart the region.

EBCDRV09

VTAM INTERFACES ARE STARTED BY SARAPPL=, RMOAPPL= OR INBAPPL= SPECIFICATIONS

Reason:

EBCDRV06, EBCDRV07, EBCDRV08 was issued previously. This message indicates that SARAPPL=, RMOAPPL=, or INBAPPL= can be used to initialize the VTAM interface.

Action:

Correct the input parameters, and then restart the region.

EBCDRV10

PC PROGRAM pgm-name ACTIVE ADDR=xxxxxx x.x xx/xx/xx

Reason:

The displayed PC call routine has been loaded into the CSA at the address shown. The release, assembly date, and time are also shown. This message has a MSGLVL of INFO.

Action:

None.

EBCDRV11

PC#xxxx ASID=xxxx XMEMCNTL ADDR=xxxxxx ID=xxxxxxx

Reason:

The PC call function is now available to allow cross-memory communication to take place. The EC1XMSGN routine must start before cross-memory login can process. This message has a MSGLVL of NORM.

Action:

None.

EBCDRV12

NO USER INTERFACE WAS SPECIFIED, EITHER USE XMS=YES, OR USE A VTAM INTERFACE.

Reason:

Initialization has detected that an input parameter that requires a missing input parameter. For instance SARAPPL= must be specified when SARVTDB= is used. This is because SARAPPL= specifies that the VTAM interface is used, and SARVTDB= is only valid when VTAM is initialized.

Action:

Correct the input parameters; then restart the region.

EBCDRV30

pgm-name DETACHED

Reason:

The operator communication subtask has detached and is no longer available. If any login subtasks are still attached, they are forced off and the region finishes terminating. This message has a MSGLVL of CRIT.

Action:

None.

EBCDRV31

pgm-name DETACHED

Reason:

The cross-memory login subtask has detached and is no longer available. This message has a MSGLVL of CRIT.

Action:

None.

EBCDRV32

pgm-name DETACHED APPLID=applid

Reason:

The VTAM login subtask has detached and is no longer available. This message has a MSGLVL of CRIT.

Action:

None.

EBCDRV33

EC1DRVLG SYSLOG WRITER STOPPED

Reason:

The SYSPRINT writer subtask has stopped. This normally occurs when the region is shut down. It also occurs when the SYSPRINT log writer did not find a SYSPRINT DDCARD or the SYSPRINT log writer has abended for some reason.

Action:

If the SYSLOG writer abended. For assistance, contact Technical Support at <http://ca.com/support>; otherwise, no action must be taken.

EBCDRV40

SUBTASK FORCED TO DETACH PGM=pgm-name

Reason:

The operator subtask terminated and this subtask was still active. CA View has forced the subtask to shut down. This message has a MSGLVL of CRIT.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCDRV80

MSGn QUEUE ALLOCATED xxxxxxxx 1ST=xxxxxxx SIZE=xxxxxxx
FREE =xxxxxxx

Reason:

The SYSPRINT message queue was allocated in storage.

Action:

None.

EBCDRV90

RTUS POOL ALLOCATED xxxxx 1ST xxxxx END xxxxx SIZE xxxx NEXT
xxxxx

Reason:

This message is issued when the cross-memory region started. The size and location of the pool of user control blocks that are received at the system startup are displayed. This message has a MSGLVL of NORM.

Action:

The USERMAX initialization parameter sets the maximum number of user control blocks to allocate in the region. To increase the USERMAX initialization parameter, shut down and restart the region.

EBCDRV91

WAITING FOR TASK TO END

Reason:

The cross-memory region is terminating, but some subtasks are still active.

Action:

Wait for all subtasks to end.

EBCDRV99

OVERRIDE KEYWORD NOT ALLOWED IN SYSIN STATEMENTS NO VALUE ALLOWED FOR OVERRIDE KEYWORD

EBCDRV99 **text for invalid startup parameter**

Reason:

The OVERRIDE parameter is not valid in the SYSIN data set, or if coded in the execute statement PARM field, cannot contain sub parameter values.

The input parameter that is shown is unknown or invalid. The region abends. This message has a MSGLVL of CRIT.

Action:

Remove the OVERRIDE parameter from the SYSIN dataset or remove the sub parameter from the OVERRIDE parameter coded in the execute statement PARM field. Correct the invalid parameter and restart the task.

EBCERRW0

EBCERRWL INITIALIZED ECB=xxxxxxxx

Reason:

This message is issued when the EBCERRWL task is initialized.

Action:

It is an informational message, no action is required.

EBCERRW3

EBCERRWL TERMINATING

Reason:

This message is issued when the EBCERRWL task terminates.

Action:

It is an informational message, no action is required.

EBCERRW5

XMS logon request queue storage overlay, XMS terminated

Reason:

The logon request queue has been damaged. XMS stops accepting logons. This is accompanied with a U0005 abend.

Action:

Save the dump that is associated with this message. For assistance, contact Technical Support at <http://ca.com/support>.

EBCIFP02

CRITICAL ERROR. PROGRAM TERMINATED WITH DUMP.INVALID blk

Reason:

A CA View program has terminated, and a dump was generated. In this message, blk specifies the control block that CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It is suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart the program that terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

EBCOCLS4

pgm-name VTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The CLOSE operator command is attempting to close the VTAM interface ACB. The possible programs are SARVTAM, INBVTAM, and RMOVTAM. This message has a MSGLVL of OPER.

Action:

The text indicates whether there was an error. For assistance, contact Technical Support at <http://ca.com/support>.

EBCOCLS6

pgm-name VTAM IS NOT VALID FOR THIS REGION

Reason:

The CLOSE operator command has been issued, but the VTAM interface ACB is not open. The possible programs are INBVTAM and RMOVTAM. This message has a MSGLVL of OPER.

Action:

Verify that the specified ACB is open.

EBCOCM10

OPERAND (xxxxxxx - VALUE n) MUST BE YES/NO

Reason:

The operator command operand must be either YES or NO. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCM11

OPERAND (xxxxxxx - VALUE n) CAN ONLY HAVE A SINGLE VALUE

Reason:

The operator command operand must not specify more than one value. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCM12

OPERAND (xxxxxxx - VALUE n) CAN ONLY HAVE 10 VALUES

Reason:

The operator command operand is limited to 10 values. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCM13

OPERAND (xxxxxxx - VALUE n) INVALID NUMERIC OPERAND

Reason:

The operator command operand must be a number. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCM14

OPERAND (xxxxxxx) CANNOT HAVE A VALUE

Reason:

The operator command operand cannot be assigned a value. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCM15

USER=XXXXXXXXXXXXXXXXXXXXXXXXX WAS NOT FOUND

Reason:

The operator command could not locate this user on the system. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid connect ID of the user.

EBCOCMD1

--> **command-name**

Reason:

The displayed operator command was entered. This command processes now. This message has a MSGLVL of OPER.

Action:

None.

EBCOCMD2

COMMAND (command-name) NOT KNOWN

Reason:

The displayed operator command is not valid for cross-memory. This message has a MSGLVL of OPER.

Action:

Reenter a valid cross-memory operator command.

EBCOCMD3

OPERAND (operand-name) NOT KNOWN

Reason:

The operator command operand is not valid. This message has a MSGLVL of OPER.

Action:

Reenter the cross-memory operator command with a valid operand.

EBCOCMD4

OPERAND (operand-name) IS NOT VALID FOR command-name

Reason:

The operand is not valid for this operator command. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCMD5

OPERAND (operand-name) DID NOT HAVE A VALUE

Reason:

The operator command operand did not specify a value. This message has a MSGLVL of OPER.

Action:

Reissue the command with a value.

EBCOCMD6

OPERAND (xxxxxxx - VALUE n) UNBALANCED QUOTES

Reason:

The operator command operand must end with a quote mark if it begins with a quote mark. This message has a MSGLVL of OPER.

Action:

Reissue the command with balanced quote marks.

EBCOCMD7

OPERAND (xxxxxxx - VALUE N) STRING NOT VALID

Reason:

The operator command operand must not specify a character string. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOCMD8

OPERAND (xxxxxxx - VALUE n) EXCEEDS n CHARACTERS

Reason:

The operator command operand must not be more than n characters. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand length.

EBCOCMD9

INTERNAL ERROR TYPE UNKNOWN

Reason:

There was an internal error in the operator routine. This message has a MSGLVL of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOCL1

userid USER CANCELED BY OPERATOR REQUEST

Reason:

The CANCEL command has abended the requested user subtask. This message has a MSGLVL of OPER.

Action:

None.

EBCOCL2

MUST SPECIFY ALL/USER/UID#

Reason:

The CANCEL command did not indicate which user to cancel. This message has a MSGLVL of OPER.

Action:

Reissue the CANCEL command with a user connect ID.

EBCOCL4

NO USERS WERE CONNECTED

Reason:

The CANCEL command did not find any users in this region. This message has a MSGLVL of OPER.

Action:

None.

EBCOCL9

INTERNAL ERROR HAS OCCURRED

Reason:

The CANCEL command had an internal error. This message has a MSGLVL of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOLS10

***XMS* 00500 087 090 ACTIVE 8080 0080 EC1XSCTL**

Reason:

A LIST STATUS,ALL command was entered.

The meaning of the items displayed:

- USERNAME—The name is set to *XMS* for this message.
- MAX—The maximum number of XMS users allowed in all the of XMS regions (from EBCXMCTR).
- CUR—The current number of XMS users that are logged onto all of the XMS regions.
- HI—The high water mark of XMS users that are logged on to all of the XMS regions.
- STATUS—The status of the XMS environment.
- FLAG—A hex display of the flag bytes for the XMS environment.
- LONGWT—A hex display more flags for the XMS environment.
- VERSION—The name of the XMS control block that is used for XMS logons.

Action:

This message is informational.

EBCOLS11

```
**** SUPPORT SUBTASK USER LIST -----  
NO. -----CONNECT ID----- -SUBSYS- --APPL-- -STATUS-  
001 EC1XMSPFWTBOURG 0197 XMC1 SARAPLSX INACTIVE -  
-----  
          DATABASE----- SIZE  
SYS2.MVS.IVPR11, 001B0084 WTBOURG TPX10C0
```

Reason:

A LIST USERS,ALL command was entered.

The meaning of the items displayed:

- NO—The position in the list of users.
- CONNECT ID—The name of the XMS connection.
- SUBSYS—The name of the XMS subsystem.
- APPL—The application name.
- STATUS—The status of the user connection.
- DATABASE—The database that is associated with the user.
- SIZE—The terminal size in hex.

These fields are followed by two unnamed fields:

- The first is the name of the user (USERID).
- The second is the terminal name.

The high water mark displayed in EBCOLS10 is greater than the high water mark displayed in EBCOLST2. This is because inactive entries that are displayed in EBCOLS11 are not candidates for immediate reuse. This can cause a new logon to use a new entry rather than reusing an old entry.

Action:

This message is informational.

EBCOLS12

**** SUPPORT TASK LOGON QUEUE -----

Reason:

The operator list command is processing a LIST USER,ALL and found a pending login queue with active control blocks.

Action:

None.

EBCOLS14

XX

Reason:

The operator list command is processing a LIST S,TABLE. The message displays the contents of the EC1XMCTR table that is in use.

Action:

None.

EBCOLST1

```
NO. -----CONNECT ID----- -USERID- --APPL-- -STATUS-  
001 EC1XMSPFCCHARBI 0203 CCHARBI SARAPLSX WAIT  
-----DATABASE----- PANEL SYS2.SAR.SARE0 SARP7 CCHARBI TPX00BE
```

Reason:

A LIST USERS, ALL command was entered. The meaning of the items displayed:

- NO—The position in the list of users.
- CONNECT ID—The name of the XMS connection.
- USERID—The name of the user.
- APPL—The application name.
- STATUS—The status of the user connection.
- DATABASE—The database that is associated with the user.
- PANEL—The name of the current panel.

These fields are followed by two unnamed fields:

- The first is the name of the user (USERID).
- The second is the terminal name.

Action:

This message is informational.

EBCOLST2

```
USERNAME MAX CUR HI XMS VTM LGN STATUS FLAG ASID
SARTSX01 100 006 014 006 000 000 ACTIVE 8088 0049
          LONGWT VERSION
          000020 **XMCTCO
```

Reason:

A LIST STATUS,ALL command was entered.

The meaning of the items displayed:

- USERNAME—The name of the XMS region.
- MAX—The maximum number of users allowed in this XMS region.
- CUR—The current number of users that are logged on to this region.
- HI—The high water mark of users that is logged on to this XMS region.
- XMS—The number of XMS only users that are logged on to this XMS region.
- VTM—The number of VTAM users that are logged on to this XMS region.
- LGN—The number of users waiting to log on this XMS region.
- STATUS—The status of this XMS region.
- FLAG—A hex display of the flag bytes for the XMS region.
- ASID—The z/OS Address Space IDentifier assigned to this XMS region.
- LONGWT—The long wait value that is specified for this XMS region.
- VERSION—The version information that is kept in the XMCT for this XMS region.

Action:

This message is informational.

EBCOLST3

DOES NOT SPECIFY STATUS USERS OR USER/UID#

Reason:

The LIST command did not indicate what users to list. This message has a MSGLVL of OPER.

Action:

Reissue the command, specifying user connect-IDs.

EBCOLST4

LIST REQUEST SPECIFIES STATUS AND USER=, UID#-, USERS ACTIVE, or INACTIVE

Reason:

The operands that are specified with the STATUS LIST command are not valid STATUS operands. This message has a MSGLVL of OPER.

Action:

Reissue the command with valid operands.

EBCOLST5

NO USERS WERE CONNECTED

Reason:

The LIST command did not find any users in this region. This message has a MSGLVL of OPER.

Action:

None.

EBCOLST6

SUBSYS NOT ON SSCT CHAIN

Reason:

The LIST command had an internal error. This message has a MSGVLV of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOLST7

XMEMCNTL INVALID ID BLOCK

Reason:

The LIST command had an internal error. This message has a MSGVLV of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOLST8

RTUS INVALID ID BLOCK

Reason:

The LIST command had an internal error. This message has a MSGVLV of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOLST9

XXXXXXXXXX

Reason:

This is the LIST command display of database status.

Action:

None.

EBCOLST10

XXXXXXXXXX

Reason:

This is the LIST command display of XMSSUB task status.

Action:

None.

EBCOMDF1

USERMAX CHANGED

Reason:

The CHANGE command has altered the USERMAX parameter. This message has a MSGLVL of OPER.

Action:

None.

EBCOMDF2

LONGWAIT CHANGED

Reason:

The CHANGE command has altered the LONGWAIT parameter. This message has a MSGLVL of OPER.

Action:

None.

EBCOMDF3

CANCEL CHANGED

Reason:

The CHANGE command has altered the CANCEL parameter. This message has a MSGLVL of OPER.

Action:

None.

EBCOMDF4

VTAMPASS CHANGED

Reason:

The CHANGE command has altered the VTAMPASS parameter. This message has a MSGLVL of OPER.

Action:

None.

EBCOMDF5

USERMAX CHANGED

Reason:

The CHANGE command has altered the USERMAX parameter. This message has a MSGLVL of OPER.

Action:

None.

EBCOMDF6

BAD XMEMCNTL FOUND

Reason:

The CHANGE command had an internal error. This message has a MSGLVL of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOMDF9

INVALID VALUE

Reason:

The CHANGE command has found a value not in range. This message has a MSGLVL of OPER.

Action:

Reissue the command with a valid operand.

EBCOOPN2

SARVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The OPEN command attempted to open the SARVTAM ACB, the text indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOOPN3

SARVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The OPEN command has attempted to open the SARVTAM ACB, the message indicates if the request was successful or not. This message has a MSGLVL of OPER.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOPR01

OPER FUNCT xxxxxxxx ADDR=xxxxxxxx x.x xx/xx/xx

Reason:

The operator routine is loaded at the address indicated. This message has a MSGLVL of INFO.

Action:

None.

EBCOPR08

OPERATOR FUNCTION NOT SUPPORTED

Reason:

The operator routine was entered and there was no MODIFY or STOP command to process. This message has a MSGLVL of CRIT.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOPR09

ATTACH OF COMMAND

Reason:

The OPEN command has attempted to open the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of CRIT.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCOQSH1

XMS xxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The QUIESCE command has attempted to QUIESCE the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOQSH2

SARVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The QUIESCE command has attempted to QUIESCE the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOQSH3

RMOVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The QUIESCE command has attempted to QUIESCE the RMOVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCORSM1

XMS xxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The RESUME command has attempted to RESUME the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCORSM2

SARVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The RESUME command has attempted to RESUME the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCORSM3

RMOVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The RESUME command has attempted to RESUME the RMOVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOSPN1

XMS xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The SUSPEND command has attempted to SUSPEND the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOSPN2

SARVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The SUSPEND command has attempted to SUSPEND the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOSPN3

RMOVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The SUSPEND command has attempted to SUSPEND the RMOVTAM ACB, the message indicates if the request was successful or not. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOSTP1

XMS xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The SHUTDOWN command has attempted to SHUTDOWN the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOSTP2

SARVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The SHUTDOWN command has attempted to SHUTDOWN the SARVTAM ACB, the message indicates whether the request was successful. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCOSTP3

RMOVTAM xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

The SHUTDOWN command has attempted to SHUTDOWN the RMOVTAM ACB, the text indicates whether the request was successful or not. This message has a MSGLVL of OPER.

Action:

Your action depends on the actual message. Correct and reissue the command if the request was not successful.

EBCSFP01

CRITICAL ERROR. PROGRAM TERMINATED WITH DUMP INVALID blk

Reason:

A CA View program has terminated, and a dump was generated. In this message, blk specifies the control block that CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It could be suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart whatever program was terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

EBCXFP01

CRITICAL ERROR. PROGRAM TERMINATED WITH DUMP INVALID blk

Reason:

A CA View program has terminated, and a dump was generated. In this message, blk specifies the control block that CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It could be suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart whatever program was terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC01

NON-MVS/XA EXECUTION NOT ALLOWED

Reason:

You are not using MVS/XA or MVS/ESA. EC1XMCIC requires MVS/XA or MVS/ESA to work.

Action:

Use MVS/XA or MVS/ESA, and then try again.

EBCXMC02

NON-CICS/XA EXECUTION NOT ALLOWED

Reason:

The DFHPPT or RDO definition for the EC1XMCIC program is wrong. The comment indicates what specifically is found to be in error. You are possibly not using Version 4.1 or a later version of CICS. EC1XMCIC requires Version 4.1 or a later version of CICS to work.

Action:

Correct the EC1XMCIC definition.

EBCXMC03

EC1XSTSK NOT ACTIVE

Reason:

The EC1XSTSK program is not executing. EC1XMCIC requires the EC1XSTSK to work. EC1XMCIC ends. EC1CINIT, which starts the subtask, was not executing, or the subtask was stopped.

Action:

See your operations administrator for more information.

EBCXMC04

INVALID EBCXSCTL BLOCK FOUND

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC05

EC1XMCIC PROGRAM MUST BE RUN FROM A TERMINAL

Reason:

EC1XMCIC is designed to execute attached to a terminal. EC1XMCIC ends.

Action:

Execute EC1XMCIC from a terminal.

EBCXMC06

TRANSACTION COMAREA WRONG SIZE

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC07

COMAREA ID WRONG

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC08

EBCXSCTL ADDRESS CHANGED

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC09

EC1CICUX PROGRAM NOT FOUND

Reason:

EC1XMCIC cannot find the EC1CICUX program. EC1XMCIC requires the EC1CICUX to work. EC1XMCIC ends.

Action:

Define EC1CICUX for CICS RDO (Resource Definition Online), and then try again.

EBCXMC10

USER CONTROL BLOCK NOT ACTIVE

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC11

TIME OUT - CLEAR SCREEN AND RE-ENTER TRAN.

TIME OUT - CLEAR SCREEN AND ENTER XXXX.

Reason:

A CICS transaction has timed out and the session in EC1XMCIC is ended. The first message is the normal message issued. The second message is issued when XMC11= is specified on the EBCXMOPT MACRO where XXXX is the XMC11= value.

Action:

Restart the transaction.

EBCXMC12

EBCXSUSR ADDRESS INVALID

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC13

EBCXSTSK ABENDED, SESSION ABORTED

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC14

DATA PASSED EXCEEDS 102 BYTES

Reason:

Parameter data larger than 102 bytes is passed to EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC15

CICS SESSION TIMEOUT= EXCEEDED

Reason:

EC1XMCIC timed out waiting for the cross-memory region to respond.

Action:

If this condition occurs frequently, extend the parameter TIMEOUT in the EC1XMCTR table, if possible.

EBCXMC16

EBCXSTSK STOPPED, SESSION ABORTED

Reason:

EC1XMCIC found that EC1XSTSK is shut down. EC1XMCIC ends.
EC1CINIT, which starts the subtask, was not executing, or the subtask was stopped or failed.

Action:

For more information, see your operations administrator.

EBCXMC17

XMS SESSION EXCEEDED LONGWAIT

Reason:

Cross-memory region terminated the session because the XMS session exceeded the value of LONGWAIT in the cross-memory region.

Action:

If this condition occurs frequently, increase the value of LONGWAIT in the cross-memory region start-up file.

EBCXMC18

XMS REGION STOPPED

Reason:

EC1XMCIC found that the cross-memory region was terminated.
EC1XMCIC ends.

Action:

Start the cross-memory region, and then try again.

EBCXMC19

SUBTASK USERMAX LIMIT EXCEEDED

Reason:

The maximum number of users, which are specified by the USERMAX parameter of the EC1XMCTR macro EBCXMOPT has been reached, and no more sessions are allowed.

Action:

Make sure that CICS performance monitor software, such as TMON or Omegamon, is not configured to purge CA View CICS transactions. AKC3 abend messages in the CICS log are an indication that a transaction has been purged. This abend must never occur for a View transaction and issue the EBCXMC19 message. Otherwise, try to log on later or increase the USERMAX value and restart CICS region.

EBCXMC20

LOGON BLOCK FULL

Reason:

The maximum number of logons, which is specified in the EC1XMCTR macro EBCXMOPT, has been reached.

Action:

Try to log on later, or increase the value and restart the CICS region.

EBCXMC21

conid -LOGON REQ - EC1XMCIC ACTIVE ADDR=

Reason:

Informational message indicating that a transaction is starting.

Action:

None. This message is provided for reference only.

EBCXMC22

conid -INPUT REQ - EC1XMCIC ACTIVE ADDR=

Reason:

Informational message indicating transaction input.

Action:

None. This message is provided for reference only.

EBCXMC90

RELEASE DEPENDENT PROGRAM NOT FOUND

Reason:

The EC1XMCIC application program has abended.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMC91

conid -EC1XMCIC STOPPED-TRANSID

Reason:

Informational message indicating control has returned to CICS for a transaction and waits for further input.

Action:

None. This message is provided for reference only.

EBCXMC92

conid -EC1XMCIC STOPPED-TRANSID

Reason:

Informational message indicating control has returned to CICS after a transaction has ended.

Action:

None. This message is provided for reference only.

EBCXMM00

ACTION COMPLETED WITH NO ERRORS

Reason:

The previous operation is successfully completed.

Action:

None. This message is provided for reference only.

EBCXMM01

ACTION COMPLETED, ONE LINE MESSAGE IN BUFFER

Reason:

An internal error occurred in the cross-memory region.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM02

REQUESTED CONNECTION ID CANNOT BE FOUND

Reason:

Your session has been lost. This condition occurs when the time specified for LONGWAIT is exceeded in the cross-memory region, the cross-memory region is shut down or abnormally ends, or an operator cancels your session.

Action:

Restart your session.

EBCXMM03

CONNECTED PROGRAM ENDED NORMALLY

Reason:

You have ended your session, and the cross-memory session is completed without errors.

Action:

None. This message is provided for reference only.

EBCXMM04

CONNECTED PROGRAM ABENDED

Reason:

Your session was terminated. The cross-memory session failed.

Action:

Check the job log of the cross-memory region. Restart your session.

EBCXMM05

UNABLE TO SIGNON - ALREADY AT MAXUSERS

Reason:

All cross-memory regions are at the maximum user limit.

Action:

To enable more users start more cross-memory regions.

EBCXMM06

UNABLE TO SIGNON - SIGNONS ARE SUSPENDED

Reason:

Someone suspended the cross-memory region.

Action:

Review the cross-memory log to identify who suspended the region.
Have that person release the cross-memory region.

EBCXMM07

RECONNECTION REQUEST FAILED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM08

REQUESTED SERVICE IS UNKNOWN

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM09

UNABLE TO SIGNON - SYSTEM IS QUIESCING

Reason:

The cross-memory region is being terminated and logons are no longer accepted.

Action:

Review the cross-memory log to identify who terminated the cross-memory region. Start the cross-memory region.

EBCXMM10

REQUESTED ITEM IS NOT HANDLED BY SERVICE

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM11

UNABLE TO SIGNON - SYSTEM IN STARTUP

Reason:

The cross-memory region has not finished initializing.

Action:

Wait for cross-memory to finish initializing, and then retry your request.

EBCXMM12

CONNECTION ID IS ALREADY DISCONNECTED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM13

GETMAIN FAILURE FOR USER TABLE ENTRY

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM14

TIMEOUT WAITING FOR PROGRAM RESPONSE

Reason:

The last request exceeded the time-out value in the EC1XMCTR table entry for this transaction.

Action:

If too many of these failures occur, review and extend the TIMEOUT parameter.

EBCXMM15

CROSS-MEMORY ASCB CANNOT BE FOUND

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM16

DISCONNECTION REQUEST FAILED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM17

GETMAIN FAILURE FOR COMMUNICATION BLOCK

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM18

CROSS-MEMORY CONTROL BLOCK IS INVALID

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM19

CONNECTION ALREADY ESTABLISHED

Reason:

The connect identifier you that specified is already in use.

Action:

Ensure that ExxCICUX is generating a unique connect identifier for each user.

EBCXMM20

NO ACTIVE CROSS-MEMORY REGION AVAILABLE

Reason:

To log in, an XMS region must be active.

Action:

Start an XMS region, and then try to log on again.

EBCXMM21

PARAMETER LIST PASSED IS INVALID

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM22

GETMAIN FAILURE FOR SIGNON REQUEST BLOCK

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM23

USER TABLE ENTRY IS INVALID

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM24

SIGNON QUEUE ELEMENT HAS INVALID FORMAT

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM25

ATTACH OF REQUESTED PROGRAM FAILED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM26

USER TABLE CANNOT BE FOUND

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM27

GETMAIN FAILURE FOR SUBTASK PARAM LIST

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM28

XMSRETMG - REQUESTED CODE IS UNKNOWN

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM29

ONLY PARTIAL TEXT MOVED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMM30

XMS INTERFACE CONTROL BLOCK INVALID

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT01

xxxxxxx - LOGON REQ - xxxxxxxx

Reason:

A request to log in XMSSUB has been received.

Action:

None, the logon is being processed.

EBCXMT02

xxxxxxx - INPUT REQ - xxxxxxxx

Reason:

An input request has been received from the terminal.

Action:

None, the request is being processed.

EBCXMT03

EC1XSTSK NOT ACTIVE

Reason:

The EC1XSTSK program is not executing. XMSSUB=YES is required in the cross-memory address space, or the cross-memory region is not active.

Action:

Verify that XMSSUB=YES, and that the cross-memory region is active.

EBCXMT04

INVALID EBCXSCTL BLOCK FOUND

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT05

EC1XMCIC TERMINAL NOT SUPPORTED

Reason:

The terminal type is invalid.

Action:

Verify that the terminal type is 3270, or a PC emulator.

EBCXMT06

TRANSACTION COMAREA WRONG SIZE

Reason:

An internal error occurred.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT07

COMAREA ID WRONG

Reason:

An internal error occurred.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT08

EBCXSCTL ADDRESS CHANGED

Reason:

An internal error occurred.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT09

xxxxxxx PROGRAM NOT FOUND

Reason:

The specified user connection exit was not found.

Action:

Place the user exit in the LOADLIB.

EBCXMT10

USER CONTROL BLOCK NOT ACTIVE

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT11

USER CONNECTION LOST

Reason:

EC1XMCIC cannot find the user connection to continue the session.
EC1XMCIC ends.

Action:

Restart the transaction.

EBCXMT12

EBCXSUSR ADDRESS INVALID

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT13

EBCXSTSK ABENDED, SESSION ABORTED

Reason:

An internal error occurred in EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT14

DATA PASSED EXCEEDS 102 BYTES

Reason:

Parameter data larger than 102 bytes is passed to EC1XMCIC.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT15

TSO SESSION TIMEOUT EXCEEDED

Reason:

A time-out occurred waiting for the cross-memory region to respond.

Action:

If this condition occurs frequently, increase the parameter TIMEOUT in the EC1XMCTR table, if appropriate.

EBCXMT16

EBCXSTSK STOPPED, SESSION ABORTED

Reason:

EC1XMCIC found that EC1XSTSK is shut down. EC1XMCIC ends. EC1CINIT, which starts the subtask was not executing, or was stopped or failed.

Action:

For more information, see your operations administrator.

EBCXMT17

XMS SESSION EXCEEDED LONGWAIT

Reason:

Cross-memory terminated the session because the XMS session exceeded the value of LONGWAIT in the cross-memory region.

Action:

If this condition occurs frequently, increase the value of LONGWAIT in the cross-memory startup file.

EBCXMT18

XMS REGION STOPPED

Reason:

EC1XMCIC found that the cross-memory region was terminated. EC1XMCIC ends.

Action:

Start the cross-memory region, and then try again.

EBCXMT20

INVALID XMEMCNTL FOUND

Reason:

The region control block was invalid, or at the incorrect release level for this user connection.

Action:

Check the status of the cross-memory regions, they could have terminated.

EBCXMT21

NO ACTIVE XMS REGION AVAILABLE

Reason:

Active cross-memory region was not available.

Action:

Start up a cross-memory region. It must have the default SUBSYS= value, and must specify XMSSUB=YES. For details, see the *Installation Guide*.

EBCXMT24

EC1XSTSK USER MAX EXCEEDED

Reason:

The USERMAX value was exceeded.

Action:

If possible, increase the parameter value.

EBCXMT25

CANNOT FIND CROSS-MEMORY REGION

Reason:

No cross-memory region with the default SUBSYS= value has been started.

Action:

Start up a cross-memory region with the default SUBSYS= value.

EBCXMT26

XMSSUB=YES SUPPORT NOT ACTIVE

Reason:

No cross-memory region with XMSSUB=YES value is active.

Action:

Start up a cross-memory region with XMSSUB=YES.

EBCXMT27

SUPPORT SUBTASK NOT ACTIVE

Reason:

A cross-memory region with XMSSUB=YES has terminated, or the subtask has failed.

Action:

Start up a cross-memory region with XMSSUB=YES.

EBCXMT28

NON-MVS/XA EXECUTION NOT ALLOWED

Reason:

The application interface must be in 31-bit mode.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT29

NON-TSO/XA EXECUTION NOT ALLOWED

Reason:

The application interface must be in 31-bit mode.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT30

LOGON BLOCKS FULL

Reason:

All user logon blocks are in use. The system has problems logging on a user and all the logon blocks are full. Try again later.

Action:

None.

EBCXMT31

NO ACTIVE XMS REGION FOUND

Reason:

The cross-memory region failed.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT32

INVALID XMEMCNTL FOUND

Reason:

An internal error has occurred.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT33

BAD IMS TERMINAL TYPE

Reason:

The operand of the IMS/DC transaction does not specify a valid terminal type.

Action:

Reenter the transaction with a proper operand.

EBCXMT34

BAD TERMINAL OPTIONS

Reason:

The operand of the IMS/DC transaction does not specify a valid terminal option.

Action:

Reenter the transaction with a proper operand.

EBCXMT35

IMS/DC BAD PSB RETURN CODE

Reason:

An unexpected return code from IMS/DC was received.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT39

REQUIRED PROGRAMS MISSING FROM STEPLIB

Reason:

The EC1XMTSO program has checked and found that one or more required programs cannot be loaded from the STEPLIB. The EBCXMT44 message displays indicating the missing programs that must be available.

Action:

Copy the required programs to the STEPLIB, then restart the initialization process.

EBCXMT40

USER EXIT DENIED ACCESS

Reason:

A nonzero return code from the user connection exit was received.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT41

IMS/DC CALL (func) FAILED RC=rc, SESSION TERMINATED

Reason:

The indicated IMS/DC function call failed with IMSIO_STAT set to the given return code. Check the appropriate IMS guide for function and return code meanings.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXMT44

xxxxxxx yyyyyyyyyyyyyyyyyyyyyyyyyyyyyyyyyyy NOT FOUND ON STEPLIB

Reason:

The EC1XMTSO program has checked and found one or more required programs that cannot be loaded from the STEPLIB.

Action:

Copy the required programs to the STEPLIB, then restart the initialization process.

EBCXSC00

**QUEUE ALLOCATED # 1ST=1st SIZE=size FREE=free EBCXSCTL=xsctl
EBCXSUSR-1ST=xsuser XMPCSGPR-1=pcsgpr**

Reason:

This error message is displayed for debugging purposes.

In this message, #, 1st, size, free, xsctl, xsuser, and pcsgpr represent additional parameter values that are provided for further reference.

Action:

None. This message is informational.

EBCXSST1

NO USER TABLE --- RECOVERY- Sn ----SUBTASK WAIT----

Reason:

EC1XSTSK abnormally ended. In this message, n represents an additional parameter value that is provided for further reference.

Action:

None. EC1XSTSK attempts to restart itself automatically.

EBCXSST2

PSW=#A #B #C #D EC1XSTSK EPA=#E

Reason:

EC1XSTSK abnormally ended. In this message, #A, #B, #C, #D, and #E represent additional parameter values that are provided for further reference.

Action:

None. EC1XSTSK attempts to restart itself automatically.

EBCXSST3

GPR 0-3 #A #B #C #D
GPR 4-7 #A #B #C #D
GPR 8-11 #A #B #C #D
GPR 12-15 #A #B #C #D

Reason:

EC1XSTSK abnormally ended. In this message, #A, #B, #C, and #D represent additional parameter values that are provided for further reference.

Action:

None. EC1XSTSK attempts to restart itself automatically.

EBCXST01

SUBTASK EC1XSTSK ACTIVE ADDR=# 1.5 M/D/Y H.M
AWTO FUNCT EC1AWTO ACTIVE ADDR=# 1.5 M/D/Y H.M
QMSG FUNCT EC1QMSG ACTIVE ADDR=# 1.5 M/D/Y H.M
SUBT ETXR EC1XSETX ACTIVE ADDR=# 1.5 M/D/Y H.M
SUBT ESTAE EC1XSSTA ACTIVE ADDR=# 1.5 M/D/Y H.M
3270 DEV EC1D3270 ACTIVE ADDR=# 1.5 M/D/Y H.M
XMS MSGS EC1XMMSG ACTIVE ADDR=# 1.5 M/D/Y H.M
XMS CNTRL EC1XMCTR ACTIVE ADDR=# 1.5 M/D/Y H.M
SRVTRAN=XMC1 DEST=XMC1

Reason:

This error message is displayed for debugging purposes.

In this message, # represents an actual address. M, D, and Y represent the month, day, and year, respectively. H and M represent the hour and minutes.

Action:

None. This message is provided for reference only.

EBCXST02

xxxxxxx XMS LOGON xxxxxx HIGH LEVEL.QUAL xxxxxxxx

Reason:

The user is being logged on to the cross-memory address space.

Action:

None.

EBCXST03

xxxxxxx CICS TIMEOUT POSTED TO XMS

Reason:

The user has timed out; the session undergoes clean-up processing.

Action:

None.

EBCXST04

EC1XSOPR SUBTASK ATTACHED

Reason:

The EC1XSOPR (CICS operator subtask) has been attached to provide the CICS OPERATOR interface.

Action:

None.

EBCXST05

EC1XSOPR SUBTASK DETACHED

Reason:

The EC1XSOPR (CICS operator subtask) has been detached. This normally occurs only when the subtask is shutting down.

Action:

None.

EBCXST06

EC1XSOPR SUBTASK DETACH (failed)

Reason:

The EC1XSOPR (CICS operator subtask) has failed to stop. This operator subtask previously failed.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXST20

CROSS-MEMORY VIEW RETRIEVAL HAS ABENDED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXST21

NO CROSS-MEMORY SYSTEM REGION ACTIVE, SUBSYS=name

Reason:

You tried to log in to a subsystem on which a cross-memory region is not initialized and active. In this message, name represents the name that is assigned to the subsystem.

Action:

Initialize a cross-memory region on the subsystem, and then try to log on again.

EBCXST22

INSUFFICIENT MEMORY FOR CROSS-MEMORY OPERATION

Reason:

Not enough memory is allocated to cross-memory, or the USERMAX parameter is set too high.

Action:

Allocate more memory to cross-memory and reduce the number of users that are assigned to the USERMAX parameter.

EBCXST24

FREE OF LOCAL MEMORY FAILED - SESSION ENDED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXST25

USER CONNECTION ID IS INVALID

Reason:

The connection identifier that is modified by the EC1CICUX user exit is incorrect or invalid.

Action:

Verify that the connection identifier that is modified by the EC1CICUX user exit is valid.

EBCXST27

CROSS-MEMORY VIEW HAS TERMINATED NORMALLY - THIS SESSION IS ENDED

Reason:

Your session ended with no errors.

Action:

None. This message is provided for reference only.

EBCXST28

OUTPUT SCREEN EXCEEDS TERMINAL BUFFER SIZE – SESSION ENDED

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXST29

TRANSACTION TO DATABASE INDEX NAME TABLE IS EMPTY - SESSION ENDED

Reason:

Your EC1XMCTR table contains zero entries.

Action:

Rebuild the EC1XMCTR table with at least one transaction definition.

EBCXST30

INVALID CROSS-MEMORY CONTROL BLOCK FOUND (XMCT) - CONTACT CA CORP.

Reason:

An internal error occurred in cross-memory.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

EBCXST31

CROSS-MEMORY ADDRESS SPACE NO LONGER ACTIVE

Reason:

The cross-memory region is terminated.

Action:

None. This message is provided for reference only.

EBCXST32

DATABASE INDEX NAME NOT FOUND FOR TRANSACTION - SESSION ENDED

Reason:

The entry for this transaction does not have a valid database name.

Action:

Check the entry for the transaction to ensure that the database name is correct. Correct the database name if necessary, and then try again. For assistance, contact Technical Support at <http://ca.com/support>.

EBCXST33

MAXIMUM SESSIONS IN USE - SESSION ENDED

Reason:

The cross-memory session that you are trying to initiate exceeds the maximum number allowed in the EC1MCTR table. You cannot initiate new sessions.

Action:

Terminate cross-memory sessions, and then try again.

EBCXST34

DATABASE INDEX NAME NOT FOUND IN TABLE - SESSION ENDED

Reason:

The EC1XMCTR table does not contain the database index name that you specified, and so you are denied access to the table.

Action:

Add an entry to the EC1XMCTR table for the database you want to specify.

EBCXST35

PROGRAM NAME NOT FOUND IN TABLE ENTRY, VERIFY VERSION OF MACRO USED IN TABLE ASSEMBLE

Reason:

EC1XMCTR is assembled with the SARXMTRN macro from a previous release of a CA product.

Action:

Assemble the table again with the current macro library.

EBCXST40

ERROR DURING SIGNON -

Reason:

An error occurred in cross-memory.

Action:

Review the error message that is displayed after this error message for more information about the cause. Review the contents of the second error message and act accordingly.

EBCXST41

CROSS-MEMORY FIND ERROR -

Reason:

An error occurred in cross-memory.

Action:

Review the error message that is displayed after this error message for more information about the cause. Review the contents of the second error message and act accordingly.

EBCXST42

CROSS-MEMORY GET BUFFER ERROR -

Reason:

An error occurred in cross-memory.

Action:

Review the error message that is displayed after this error message for more information about the cause. Review the contents of the second error message and act accordingly.

EBCXST43

CROSS-MEMORY PUT BUFFER ERROR -

Reason:

An error occurred in cross-memory.

Action:

Review the error message that is displayed after this error message for more information about the cause. Review the contents of the second error message and act accordingly.

EBCXST44

CROSS-MEMORY GET COMAREA INFO ERROR -

Reason:

An error occurred in cross-memory.

Action:

Review the error message that is displayed after this error message for more information about the cause. Review the contents of the second error message and act accordingly.

EBCXST45

CROSS-MEMORY POST ERROR -

Reason:

An error occurred in cross-memory.

Action:

Review the error message that is displayed after this error message for more information about the cause. Review the contents of the second error message and act accordingly.

EBCXST50

XMS SUBTASK POSTED XSC_SUBF=#A XSC_ECB1=#B

Reason:

This error message is a trace message to the indicated logic flow. In this message, #A and #B represent parameter values that are provided for further reference.

Note: This message appears only if trace messages are requested.

Action:

None. This message is provided for reference only.

Chapter 3: Error Messages

This section contains the following topics:

[System Error Messages](#) (see page 99)

System Error Messages

This section describes error messages that are associated with CA View.

CAHAADL02

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAADL03

RECORD NOT FOUND

Reason:

The annotation or bookmark cannot be deleted because it is not found in the database. Most likely, another user deleted the annotation or bookmark.

Action:

Access the annotation list or the specific annotation again to refresh the display with current information.

CAHAADL04

**USER NOT AUTHORIZED TO DELETE NOTE "name" FOR REPORT "rid"
GEN=gen SEQ=seq**

Reason:

The SARSECUX security user exit or external security did not allow deletion of the annotation or bookmark for the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHAAGT01

END OF DATA

Reason:

An internal informational message indicating that all qualified table entries have been retrieved.

Action:

None. This message is informational.

CAHAAGT04

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAIN01

INVALID REPORT HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAIN02

INVALID RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAIN03

REPORT "rid" GEN=gen SEQ=seq NOT FOUND

Reason:

The annotation or bookmark cannot be added for the requested report because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAAIN04

VIEW nnn NOT FOUND FOR REPORT "rid"

Reason:

The annotation or bookmark cannot be added for the requested report because the logical view for the report is no longer in the database. The logical view was most likely deleted by another user.

Action:

Access the report data for the report again to refresh display information.

CAHAAIN05

**USER NOT AUTHORIZED TO ADD NOTE "name" FOR REPORT "rid"
GEN=gen SEQ=seq**

Reason:

The SARSECUX security user exit or external security did not allow addition of the annotation or bookmark for the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHAAIN06

INDEX NOT FOUND FOR REPORT "rid" GEN=gen SEQ=seq

Reason:

The annotation or bookmark cannot be added for the requested report because the report index for the report is no longer in the database. The report index for the report is not accessible or has been deleted by another user.

Action:

Access the report data for the report again to refresh display information.

CAHAAIN07

INVALID NOTE TYPE

Reason:

The annotation or bookmark cannot be added because a note type was not provided or it is invalid.

Action:

Contact CA Technical Support.

CAHAAIN08

INVALID NOTE NAME

Reason:

The annotation or bookmark cannot be added because a note name was not provided or it contains invalid characters. The annotation or bookmark name can consist of alphabetic, numeric, national, and selective special characters.

Action:

Provide a valid annotation or bookmark name before adding annotation or bookmark.

CAHAAIN09

INVALID NOTE PAGE/LINE

Reason:

The annotation or bookmark cannot be added because the page or line number on the report where the note is to be attached was not provided or it is invalid.

Action:

Contact CA Technical Support.

CAHAAIN10

INVALID NOTE ACCESS TYPE

Reason:

The annotation or bookmark cannot be added because an access type was not provided or it is invalid.

Action:

Contact CA Technical Support.

CAHAAIN11

ANNOTATION DATA NOT SUPPLIED

Reason:

The annotation cannot be added because annotation text was not provided.

Action:

Provide annotation text before adding the annotation.

CAHAAIN12

MAXIMUM NOTES DEFINED TO REPORT

Reason:

The annotation or bookmark cannot be added because the database contains too many annotations or bookmarks with the same name.

Action:

Provide a different annotation or bookmark name before adding the annotation or bookmark.

CAHAAIN13

ANNOTATION/BOOKMARK ASSIGNED TO DIFFERENT PAGE/LINE

Reason:

An annotation or bookmark with the same name has been assigned to a different page or line number.

Action:

The annotation or bookmark can be added at the other page and line number. If this is not wanted, provide a new annotation or bookmark name before adding the annotation or bookmark.

CAHAAIN14

NOTE PAGE/LINE REQUIRED FOR NEW NOTE

Reason:

The annotation or bookmark cannot be added because the page or line number on the report where the note is to be attached was not provided. This message can occur after allowing an annotation or bookmark to be added on a different page or line number.

Action:

Try adding the annotation. If the problem persists, contact Technical Support.

CAHAAOP01**INVALID ANNOTATION HANDLE****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAOP02**INVALID RETURN TOKEN****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAOP03**REPORT "rid" GEN=gen SEQ=seq NOT FOUND****Reason:**

The list of annotations or bookmarks cannot be accessed for the requested report because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAAOP04**VIEW nnn NOT FOUND FOR REPORT "rid"****Reason:**

The list of annotations or bookmarks cannot be accessed for the requested report because the logical view for the report is no longer in the database. The logical view was most likely deleted by another user.

Action:

Access the report data for the report again to refresh display information.

CAHAAOP05

USER NOT AUTHORIZED TO ACCESS REPORT "rid" GEN=gen SEQ=seq

Reason:

The SARSECUX security user exit or external security did not allow access to the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHAAOP06

INDEX NOT FOUND FOR REPORT "rid" GEN=gen SEQ=seq

Reason:

The list of annotations or bookmarks cannot be accessed for the requested report because the report index for the report is no longer in the database. The report index for the report is not accessible or has been deleted by another user.

Action:

Access the report data for the report again to refresh display information.

CAHAAUP01

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAUP02

INVALID RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAAUP03

NOTE NOT FOUND

Reason:

The annotation or bookmark cannot be updated because it is not found in the database. The annotation or bookmark was most likely deleted by another user.

Action:

Access the annotation list or the specific annotation again to refresh the display with current information.

CAHAAUP04

USER NOT AUTHORIZED TO UPDATE NOTE "name" FOR REPORT "rid" GEN=gen SEQ=seq

Reason:

The SARSECUX security user exit or external security did not allow the update of the annotation or bookmark for the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHAAUP05

INVALID NOTE ACCESS TYPE "type"

Reason:

The annotation or bookmark cannot be updated because an access type was not provided or it is invalid.

Action:

Contact CA Technical Support.

CAHAAUP06

INVALID NOTE PAGE/LINE

Reason:

The annotation or bookmark cannot be updated because the page or line number on the report where the note is to be attached was not provided or it is invalid.

Action:

Contact CA Technical Support.

CAHAAUP10

MAXIMUM NOTES DEFINED TO REPORT

Reason:

The annotation or bookmark cannot be updated because the database contains too many annotations or bookmarks with the same name.

Action:

Provide a different annotation or bookmark name before adding the annotation or bookmark.

CAHACGT01

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHACGT02

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHACGT03

END OF DATA

Reason:

Internal informational message indicating that all qualified table entries have been retrieved.

Action:

None. This message is informational.

CAHACOP01

INVALIDCAHAVXR TOKEN

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHACOP02

NO CROSS REPORT INDEXES FOUND

Reason:

No cross report indexes are found in the database for the requested filtering criteria.

Action:

Provide new filtering data before selecting cross report indexes.

CAHACOP03

NO SELECTABLE REPORTS FOR USERS DISTRIBUTION IDENTIFIER

Reason:

The distribution ID referenced in the CA View User Profile is not defined, nor has no reports defined. For EXP mode users, the DISTID and applicable reports are defined in CA Deliver. For SAR mode users, the DISTID and applicable reports are defined in CA View.

Action:

To produce lists of reports for the user, reports must be defined to the associated DISTID with CA Deliver (for EXP mode users) or CA View (for SAR mode users).

CAHACOP04

UNABLE TO QUALIFY SELECTION OF REPORTS DUE TO MISSING CA DELIVER INTERFACE ROUTINE (RMOGAM)

Reason:

The library containing the RMOGAM module is not defined to the CA DRAS task, or is not accessible.

Action:

Add the CA Deliver load library to the STEPLIB or JOBLIB concatenation to the CA DRAS job or started task, or add the CA Deliver load library to your system linklist.

CAHACOP05

INVALID ENTRY CODE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHADFS01

REPORT "rid" GEN=gen SEQ=seq NOT OPEN

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHADOP01

DATABASE HAS NOT BEEN INITIALIZED - RUN SARINIT UTILITY

Reason:

A user tried to access a CA View database that has not been initialized.

Action:

Initialize the database using the SARINIT utility.

CAHADOP02

LOGON USER EXIT "SARUSDUX" NOT FOUND

Reason:

The SARUSDUX user exit cannot be found.

Action:

Check your STEPLIB or linklist to ensure that the library containing SARUSDUX is available.

CAHADOP03

SECURITY USER EXIT "SARSECUX" NOT FOUND

Reason:

The library containing the SARSECUX module is not defined to the CA DRAS task or is not accessible.

Action:

Add the CA View load library to the STEPLIB or JOBLIB concatenation for the CA DRAS job or started task, or add the CA View load library to your system Linklist.

CAHADOP04

USERID NOT PROVIDED

Reason:

A logon is attempted without a user ID.

Action:

Retry with valid user ID.

CAHADOP05

PASSWORD NOT VALID FOR USERID

Reason:

A logon is attempted with an invalid password.

Action:

Retry with the correct password for the user ID.

CAHADOP06

USERID DOES NOT EXIST

Reason:

A logon is attempted with a user ID that is not defined to the system.

Action:

Retry with a valid user ID or call your Security Administrator.

CAHADOP07

USERID DENIED ACCESS TO DATABASE

Reason:

User does not have clearance for the database.

Action:

Contact your Security Administrator.

CAHADOP10

DATABASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The database and the software are at different releases.

Action:

Verify the STEPLIB or link listed version of the programs.

CAHADOP11

LOAD FAILED FOR SARDVECT

Reason:

The library containing the SARDVECT module is not defined to the CA DRAS task or is not accessible.

Action:

Add the CA View load library to the STEPLIB or JOBLIB concatenation for the CA DRAS job or started task, or add the CA View load library to your system Linklist.

Reason:

The SARDVECT program cannot be found.

Action:

Check your STEPLIB or linklist to make sure that the library containing SARDVECT is available.

CAHAFAG01

END OF DATA

Reason:

Internal informational message indicating that all qualified report records have been retrieved.

Action:

None. This message is informational.

CAHAFAG02

INVALID RECORD NUMBER

Reason:

An internal request is made to position to an invalid record in the report index file.

Action:

The database record for the report contains an invalid starting position for the extracted report index data. This condition is due to database corruption. The positioning information can be re-established by re-indexing the report.

CAHAFAL01

LOGICAL I/O ERROR PROCESSING INDEX FILE FOR REPORT "*rid*"
GEN=*gen* SEQ=*seq*

Reason:

An I/O error occurred while attempting to read index data for the referenced report.

Action:

The I/O error can be corrected by re-indexing the report. If problems persist, the database can be restored.

CAHAFA001

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT AVAILABLE FOR ACCESS

Reason:

The identified report is not accessible using the expanded access server, or online viewing of the report is not allowed due to the specification of the VIEWTAPE=NO ERO parameter.

Action:

If the report is accessible using the expanded access server, make sure that the SAREAS task is active. Otherwise, load the report into the database that is to be accessed.

CAHAFA002

LOGICAL I/O ERROR PROCESSING INDEX FILE FOR REPORT "*rid*"
GEN=*gen* SEQ=*seq*

Reason:

An I/O error occurred while attempting to read index data for the referenced report.

Action:

The I/O error can be corrected by re-indexing the report. If problems persist, the database can be restored.

CAHAFAP01

LOGICAL I/O ERROR PROCESSING INDEX FILE FOR REPORT "*rid*"
GEN=*gen* SEQ=*seq*

Reason:

An I/O error occurred while attempting to read index data for the referenced report.

Action:

The I/O error can be corrected by re-indexing the report. If problems persist, the database can be restored.

CAHAFAS01

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT OPEN

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAFRG01

END OF DATA

Reason:

Internal informational message indicating that all qualified report resource records have been retrieved.

Action:

None. This message is informational.

CAHAFRG02

RESOURCE FILE NOT OPEN

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAFRO01

NO RESOURCE FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The report that you have requested needs a resource to display correctly. This resource cannot be found on the database. (Acif and Xerox reports have resources.)

Action:

Reload report from tape.

CAHAFRO02

RESOURCE NOT FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The report that you have requested needs a resource to display correctly. This resource cannot be found on the database. (Acif and Xerox reports have resources.)

Action:

Reload report from tape.

CAHAFSG01

END OF DATA

Reason:

Internal informational message indicating that all qualified report records have been retrieved.

Action:

None. This message is informational.

CAHAFSG02

INVALID RECORD NUMBER

Reason:

An internal request is made to position to an invalid record in the report.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAFSG03

INVALID PAGE NUMBER

Reason:

An internal request is made to position to an invalid page in the report.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAFS001

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT AVAILABLE FOR ACCESS

Reason:

The identified report is not accessible using the expanded access server, or online viewing of the report is not allowed due to the specification of the VIEWTAPE=NO ERO parameter

Action:

If the report is accessible using the expanded access server, make sure that the SAREAS task is active. Otherwise, load the report into the database that is to be accessed.

CAHAGGT01

END OF DATA

Reason:

Internal informational message indicating that all qualified report information records have been retrieved.

Action:

None. This message is informational.

CAHAGGT02

RECORD NOT FOUND

Reason:

List information for the report is not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAGGT03

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAGGT04

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAGGT05

USER NOT AUTHORIZED TO ACCESS REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The SARSECUX security user exit or external security did not allow access to the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHAGOP01

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

List information for the report is not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAGOP02

UNABLE TO QUALIFY CROSS REPORT INDEX HANDLE

Reason:

An internal request is made to position to an invalid page in the report.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAGOP03

NO SELECTABLE REPORTS FOR USERS DISTRIBUTION IDENTIFIER

Reason:

The distribution ID referenced in the CA View user profile is not defined nor has no reports that are defined to it. For EXP mode users, the DISTID and applicable reports are defined in CA Deliver. For SAR mode users, the DISTID and applicable reports are defined in CA View.

Action:

To produce lists of reports for the user, reports must be defined to the associated DISTID with CA Deliver (for EXP mode users) or CA View (for SAR mode users).

CAHAGOP04

UNABLE TO QUALIFY SELECTION OF REPORTS DUE TO MISSING CA DELIVER INTERFACE ROUTINE (RMOGAM)

Reason:

The library containing the RMOGAM module is not defined to the CA DRAS task or is not accessible.

Action:

Add the CA Deliver load library to the STEPLIB or JOBLIB concatenation for the CA DRAS job or started task, or add the CA Deliver load library to your system linklist.

CAHAMSG01

INVALID TOKEN SPECIFIED

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHANGT01

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHANGT02

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHANGT03

END OF DATA

Reason:

Internal informational message indicating that all qualified index name records have been retrieved.

Action:

None. This message is informational.

CAHANOK01

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Index names for the report are not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHANOK02

NO INDEXES FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

An attempt is made to retrieve the indexes for a report, but the report is not indexed.

Action:

None. Only the native view of the report is accessible.

CAHANOK07

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT ACCESSIBLE, TAPE SERVER NOT ACTIVE

Reason:

The report cannot be accessed from tape because the Expanded Access Server (EAS) task is not active on the same system as CA DRAS.

Action:

Start and run the EAS task on the same system as CA DRAS. After the task has been started, the report can be accessed from CA DRAS.

CAHANOP01

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Index names for the report are not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHANOP02

NO INDEXES FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

An attempt is made to retrieve the indexes for a report, but the report is not indexed.

Action:

None. Only the native view of the report is accessible.

CAHARGT01

END OF DATA

Reason:

Internal informational message indicating that all qualified report resource records have been retrieved.

Action:

None. This message is informational.

CAHARGT02

INVALID ENTRY CODE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHARGT03

INVALID DRDB ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAROP01

INVALID REPORT HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAROP02

INVALID RETURN TOKEN

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAROP03

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Resource data for the report are not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAROP04

NO RESOURCE FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

No resource data is found for the requested report.

Action:

None. This message is informational.

CAHAROP05

USER NOT AUTHORIZED TO ACCESS REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The SARSECUX security user exit or external security did not allow access to the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHASGD01

END OF DATA

Reason:

Internal informational message indicating that all qualified report records have been retrieved.

Action:

None. This message is informational.

CAHASGD02

INVALID ENTRY CODE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASGT01

END OF DATA

Reason:

Internal informational message indicating that all qualified report records have been retrieved.

Action:

None. This message is an informational.

CAHASGT01

INVALID DRDB ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASGT02

INVALID ENTRY CODE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASGT03

INVALID DRDB ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASGV01

END OF DATA

Reason:

Internal informational message indicating that all qualified report records have been retrieved.

Action:

None. This message is informational.

CAHASGV02

INVALID ENTRY CODE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASGX04

PDF file allocate failed, RC=¢, Error/Info Code=¢

Reason:

An attempt to dynamically allocate the CA Spool Java Transformer output PDF file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Investigate the dynamic allocation return code, error, and info codes to determine the cause of the problem.

CAHASGX05

PDF file open failed

Reason:

An attempt to open the CA Spool Java Transformer output PDF file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. If the transformation failed, check the transformation report to determine the cause of the problem.

CAHASGX06

PDF file read failed

Reason:

An attempt to read the CA Spool Java Transformer output PDF file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. If the transformation failed, check the transformation report to determine the cause of the problem.

CAHASGX07

PDF file close failed

Reason:

An attempt to close the CA Spool Java Transformer output PDF file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. If the transformation failed, check the transformation report to determine the cause of the problem.

CAHASGX08

PDF file unallocate failed, RC=c, Error/Info Code=c

Reason:

An attempt to dynamically unallocate the CA Spool Java Transformer output PDF file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Investigate the dynamic allocation return code, error, and info codes to determine the cause of the problem.

CAHASGX09

File 999999 - ccccccc GEN# SEQ# - [A2PD | M2PD | TP2D]

[transform | - Copy -]

elapse: 9999.99 seconds

Reason:

This message is written to the JESMSGLG every time a transformation request completes if X2YY_TRACE=MIN/ALL specified. The message includes CA Spool file number or zero, CA View report name generation number, sequence number, type of transformation, transform, or copy info and request elapse time.

Action:

None.

CAHASOK01

INVALID REPORT HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASOK03

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Report data for the report are not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHASOK04

VIEW *nnn* NOT FOUND FOR REPORT "*rid*"

Reason:

The report data for the report cannot be accessed for the requested report because the logical view for the report is no longer in the database. The logical view was most likely deleted by another user.

Action:

Access the report data for the report again.

CAHASOK05

USER NOT AUTHORIZED TO ACCESS REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The SARSECUX security user exit or external security did not allow access to the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHASOK06

USE CROSS-REPORT INDEXING TO ACCESS REPORT

Reason:

The user does not have authorization to access all page of the report and must use cross-report indexing to access individual pages of the report.

Action:

Use cross-report indexing to access pages of the report.

CAHASOK07**REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT ACCESSIBLE, TAPE SERVER NOT ACTIVE****Reason:**

The report cannot be accessed from tape because the Expanded Access Server (EAS) task is not active on the same system as CA DRAS.

Action:

Start and run the EAS task on the same system as CA DRAS. After the task has been started, the report can be accessed from CA DRAS.

CAHASOK08**USER NOT AUTHORIZED TO ACCESS VIEW *nnn* FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*****Reason:**

The SARSECUX security user exit or external security did not allow access the logical view of the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHASOP01**INVALID REPORT HANDLE****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASOP02**INVALID RETURN TOKEN****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASOP03

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Report data for the report is not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHASOP04

VIEW *nnn* NOT FOUND FOR REPORT "*rid*"

Reason:

The report data cannot be accessed for the requested report because the logical view for the report is no longer in the database. The logical view was most likely deleted by another user.

Action:

Access the report data for the report again.

CAHASOP05

USER NOT AUTHORIZED TO ACCESS REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The SARSECUX security user exit or external security did not allow access to the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHASOP06**INDEX NOT FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*****Reason:**

The report data cannot be accessed for the requested report because the report index for the report is no longer in the database. The report index for the report is not accessible or has been deleted by another user.

Action:

Access the report data for the report again.

CAHASOP07**USER NOT AUTHORIZED TO ACCESS INDEX FOR REPORT "*rid*"
GEN=*gen* SEQ=*seq*****Reason:**

The SARSECUX security user exit or external security did not allow access to the report index of the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHASPNO1**RECORD POSITIONING NOT SUPPORTED ON VIEW****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASPNO2**POSITIONING NOT SUPPORTED ON ACIF, PPS OR LPD REPORT****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHASTP01

END OF DATA

Reason:

Internal informational message indicating that all qualified report records have been retrieved.

Action:

None. This message is informational.

CAHASTP02

INVALID ENTRY CODE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHATPR01

INVALID REPORT HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHATPR02

Report "rid" Gen=gen Seq=seq User user DB db_hlq recall request

Reason:

A recall request has been issued for the requested report to have the report loaded from tape to disk.

Action:

None. This message is informational.

CAHAUDL03

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUDL04

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUGT02

RECORD NOT FOUND

Reason:

The user definition cannot be found in the database. The user definition was most likely deleted by another user.

Action:

If you are changing your own mode or distribution identifier, log off and log on again to the CA OM Document Viewer.

CAHAUGT03

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUGT04

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUOP01

INVALID USER HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUOP02

INVALID RETURN TOKEN

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUUP02

INVALID PASSWORD

Reason:

The user definition cannot be updated because the password contains invalid characters.

Action:

Enter a new password and retry the request.

CAHAUUP03

USERID ALREADY EXISTS

Reason:

The user definition cannot be added to the database because the user definition exists. The user definition was most likely added by another user.

Action:

Attempt to add or update the user definition again. For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUUP04

USERID NOT FOUND

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAUUP07

INVALID MASTER AUTHORITY

Reason:

The user definition cannot be added or updated because the master authority field contains invalid characters.

Action:

Contact CA Technical Support.

CAHAUUP08

INVALID DISTRIBUTION MASK

Reason:

The user definition cannot be updated because the distribution mask field contains invalid characters.

Action:

Enter a valid distribution mask and retry the request.

CAHAUUP09

INVALID DISTID

Reason:

The user definition cannot be updated because the distribution identifier field contains invalid characters.

Action:

Enter a valid distribution identifier and retry the request.

CAHAUUP10

DISTID DOES NOT MATCH DISTRIBUTION MASK

Reason:

The user definition cannot be updated because the distribution identifier field does not conform to the distribution mask pattern.

Action:

Enter a valid distribution identifier and retry the request.

CAHAUUP11

INVALID ACCESS MODE

Reason:

The user definition cannot be added or updated because the access mode contains invalid characters.

Action:

Contact CA Technical Support.

CAHAUUP12

INVALID MODE

Reason:

The user definition cannot be added or updated because the mode field contains an invalid specification.

Action:

Contact CA Technical Support.

CAHAUUP13

MODE/ACCESS CONFLICT

Reason:

The user definition cannot be added or updated because the user is not allowed access to the specified mode.

Action:

Enter a valid accessible mode and retry the request.

CAHAUUP14

INVALID BANNER NAME

Reason:

The user definition cannot be added or updated because the banner page name contains invalid characters.

Action:

Enter a valid banner page name and retry the request.

CAHAUUP15

INVALID LANGUAGE CODE

Reason:

The user definition cannot be added or updated because the language code is not valid.

Action:

Enter a valid language code and retry the request.

CAHAUUP16

INVALID PRINTER NAME

Reason:

The user definition cannot be added or updated because the printer name contains invalid characters.

Action:

Enter a valid printer name and retry the request.

CAHAUUP17

USERID REQUIRED FOR ADD

Reason:

The user definition cannot be added because the userid was not specified.

Action:

Enter a userid and retry the request.

CAHAVGT01

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAVGT02

INVALID VIEW RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAVGT03

END OF FILE

Reason:

Internal informational message indicating that all qualified logical view records have been retrieved.

Action:

None. This message is informational.

CAHAVOP01**REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND****Reason:**

Logical views for the report are not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAVOP02**NO VIEWS FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*****Reason:**

An attempt is made to retrieve the logical views for a report, but no logical views are defined for the report.

Action:

None. Only the native view of the report is accessible.

CAHAXGC01**INVALID OPERATION TYPE****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXGC02**INVALID INDEX RECORD ADDRESS****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXGC03

END OF DATA

Reason:

Internal informational message indicating that all qualified index records have been retrieved.

Action:

None. This message is informational.

CAHAXGR01

INVALID OPERATION TYPE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXGR02

INVALID INDEX RECORD ADDRESS

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXGR03

END OF DATA

Reason:

Internal informational message indicating that all qualified index records have been retrieved.

Action:

None. This message is informational.

CAHAXOC01

INVALID INDEX HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXOC02

CROSS-REPORT INDEX NAME FROM INDEX HANDLE NOT FOUND

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXOC03

FILTER TEXT INCOMPATIBLE WITH INDEX DATA

Reason:

A filtering specification contains text that is longer than what is defined for the index.

Action:

Enter new filtering text and retry the selection request.

CAHAXOC04

NO QUALIFIED REPORTS FOR CROSS-REPORT INDEX

Reason:

No reports or indexing information found in the database for the selected cross report index name and filtering criteria.

Action:

Select another cross report index name or change the filtering criteria.

CAHAXOK01

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Indexing data for the report is not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAXOK02

INVALID INDEX HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXOK04

NO INDEX FILE FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The requested report does not contain any indexing data or has not been indexed.

Action:

If the report contains logical views with indexing criteria, the report can be indexed by the SARBCH utility.

CAHAXOK06**VIEW NOT FOUND FOR REPORT "rid" GEN=*gen* SEQ=*seq*****Reason:**

Indexing data cannot be accessed for the requested report because the logical view for the report is no longer in the database. The logical view was most likely deleted by another user.

Action:

Access the report data for the report again.

CAHAXOK07**REPORT "rid" GEN=*gen* SEQ=*seq* NOT ACCESSIBLE, TAPE SERVER NOT ACTIVE****Reason:**

The report cannot be accessed from tape because the Expanded Access Server (EAS) task is not active on the same system as CA DRAS.

Action:

Start and run the EAS task on the same system as CA DRAS. After the task has been started, the report can be accessed from CA DRAS.

CAHAXOK12**CROSS-REPORT INDEX NAME FROM INDEX HANDLE NOT FOUND****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXOP01**INVALID INDEX HANDLE****Reason:**

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXOR01

REPORT "*rid*" GEN=*gen* SEQ=*seq* NOT FOUND

Reason:

Indexing data for the report is not available because the report is no longer in the database. The report was most likely expired from the database by the backup cycle or deleted by another user.

Action:

If the report was accidentally expired or deleted, consult your system programming group to have the report added back into the database.

CAHAXOR02

INVALID INDEX HANDLE

Reason:

Logic error with inter-connection of internal product routines.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHAXOR03

FILTER TEXT INCOMPATIBLE WITH INDEX DATA

Reason:

A filtering specification contains text that is longer than what is defined for the index.

Action:

Enter new filtering text and retry the selection request.

CAHAXOR04

NO INDEX FILE FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The requested report does not contain any indexing data or has not been indexed.

Action:

If the report contains logical views with indexing criteria, the report can be indexed by the SARBCH utility.

CAHAXOR05

INDEX NOT FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

Indexing data for the requested report cannot be found.

Action:

If the report contains logical views with indexing criteria, the report can be indexed by the SARBCH utility.

CAHAXOR06

VIEW NOT FOUND FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

Indexing data cannot be accessed for the requested report because the logical view for the report is no longer in the database. The logical view was most likely deleted by another user.

Action:

Access the report data for the report again.

CAHAXOR07

NOT AUTHORIZED TO ACCESS INDEX FOR REPORT "*rid*" GEN=*gen* SEQ=*seq*

Reason:

The SARSECUX security user exit or external security did not allow access to the report index of the requested report.

Action:

Consult with your security administrator or system programming group to determine the reasons why the authorization was not provided.

CAHAX2Y01

STDENV open failed

Reason:

An attempt to open the STDENV DD allocation failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Check that the CA DRAS JCL specifies a valid STDENV environment variable configuration dataset. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y02

STDENV read failed

Reason:

An attempt to read from the STDENV DD allocation failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Check that the CA DRAS JCL specifies a valid STDENV environment variable configuration dataset. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y03

STDENV close failed

Reason:

An attempt to close the STDENV DD allocation failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Check that the CA DRAS JCL specifies a valid STDENV environment variable configuration dataset. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y04

STDENV missing X2YY definitions

Reason:

Incomplete CA Spool Java Transformer Environment Variables supplied in the STDENV DD allocation.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y05

STDENV invalid parameter value: X2YY_XXXXXXXX

Reason:

An undefined X2YY_XXXXXXXX environment variable read from the STDENV DD allocation.

Action:

Correct the syntax error and restart CA DRAS. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y06

ESFOPEN/ESFWRITE/ESFCLOS not found

Reason:

The CA Spool Java Transformer interface is unable to load the CA Spool API modules during startup.

Action:

Add the CA Spool Load Library to the CA DRAS JCL procedure and restart CA DRAS. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y07

[ESFOPEN | ESFWRITE | ESFCLOS] failed RC=xx [PID=zzz]

Reason:

The open, write, or close of the CA Spool file that failed with status code xx. See the CA Spool Operations, Commands, and Messages Guide section Call Interface Return Codes for the cause of the problem. If ESFOPEN failed with RC=PE, the PID=zzz of the parameter in error is included in the message.

Action:

Determine if additional messages were written to ESFLOG at the time of the error that could provide information regarding the cause of the failure.

CA DRAS continues.

CAHAX2Y08

CA Spool subsystem xxxx not active

Reason:

The X2YY_SUBID specified CA Spool subsystem xxxx was not active.

Action:

Start the CA Spool task and log on again to CA OM Web Viewer. CA DRAS continues without the CA Spool Java Transformer interface.

CAHAX2Y10

HFS output file allocate failed, RC=¢, Error/Info Code=¢

Reason:

An attempt to dynamically allocate the CA Spool Java Transformer output PDF file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Investigate the dynamic allocation return code, error, and info codes to determine the cause of the problem.

CAHAX2Y11**HFS input file allocate failed, RC=c, Error/Info Code=c****Reason:**

An attempt to dynamically allocate the CA Spool Java Transformer input file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Investigate the dynamic allocation return code, error, and info codes to determine the cause of the problem.

CAHAX2Y12**HFS input file open failed****Reason:**

An attempt to open the CA Spool Java Transformer input file for output failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. If the transformation failed, check the transformation report to determine the cause of the problem.

CAHAX2Y14**HFS input file close failed****Reason:**

An attempt to close the CA Spool Java Transformer input file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. If the transformation failed, check the transformation report to determine the cause of the problem.

CAHAX2Y15

HFS output file unallocate failed, RC=¢, Error/Info Code=¢

Reason:

An attempt to dynamically unallocate the CA Spool Java Transformer input file failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Investigate the dynamic allocation return code, error, and info codes to determine the cause of the problem.

CAHAX2Y21

CA Spool transformation failed

Reason:

The CA Spool Java Transformation request failed.

Action:

Determine if additional messages were written at the time of the error that could provide information regarding the cause of the failure. Check the transformation report to determine the cause of the problem.

CAHPDF01I

SAR FSA-PRTnn PROCESSING | COMPLETED *jobname(jobnum) stepname ddname*

Reason:

The message shows that a JES document has been selected for processing by the PDF FSS Collector. The message also displays when the processing of the PDF document has completed.

Action:

None.

CAHPDF02E

SAR FSA-PRTnn NOT A PDF DOCUMENT *jobname(jobnum) stepname ddname*

Reason:

A JES document has been sent to a PDF Collector, which is not a PDF document. The report is placed on hold.

Action:

Re-route the JES document to the correct JES printer definition to process correctly.

CAHPDF03E

Invalid initialization parameter "*invalid parameter*" for SAR FSA-PRTnn

Reason:

A parameter in the View printer definition is in error, the invalid parameter is displayed.

Action:

Correct the invalid parameter and restart the JES printer.

CAHPDF04E

Invalid initialization value "*invalid parameter & value*" for SAR FSA-PRTnn

Reason:

A parameter value in the View printer member is invalid. The invalid parameter and value are displayed.

Action:

Correct the invalid value in the View printer member and restart the JES printer to validate the changes made.

CAHPDF05E

Undefined CA View database high-level name for SAR FSA-PRTnn

Reason:

A value in the View printer member for the NAME parameter has not been specified or has been specified incorrectly.

Action:

Correct the invalid value in the View printer member NAME parameter and restart the JES printer to validate the changes made.

CAHPDF06I

Index control member "*member name*" not found for SAR FSA-PRTnn

Reason:

A JES form name is specified on the processed document but a member with this same name was not found in the PDFINDEX dataset specified in the PDF Collector FSS proc. This member is used for indexing the PDF document.

Action:

Add a member with the form name in the PDFINDEX dataset. If no indexing is required, then either remove the form name from the JES document or add the member with no parameters.

CAHPDF07E

Error opening PDFINDEX DD statement for SAR FSA-PRTnn

Reason:

There is no PDFINDEX DD specified in the PDF Collector FSS PROC being used by the JES printer definition.

Action:

Add the PDFINDEX DD in the PROC associated with the JES printer being used for the PDF collection. Restart JES printer to verify change.

CAHPDF08E

DATABASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The CA View database name specified in the printer member is not at the required release to support PDF Indexing. The database must be at release 11.5 or later.

Action:

Specify either the correct database name or version the database up to r11.5.

CAHPDF09E**SAR FSA-PRT nn ACCUMULATION ERROR-PDF DOCUMENT*****jobname(jobnum) stepname ddname*****Reason:**

There was an error in the processing of a PDF document and it cannot be indexed correctly into the database. A more detailed error message was issued prior explaining the reason for the error.

Action:

Review the error message issued before you determine the problem. Correct the problem and release the held PDF document from the JES queue to be processed through the PDF Collector.

CAHPDF10E**ERROR OPENING PDF DDN = *ddname* FOR SAR FSA-PRT nn** **Reason:**

The specified DD could not be opened. Either the DD specified in the PDFINDEX member associated with this report is not included in the PDF Collector FSS proc, or it was specified incorrectly.

Action:

Review your PDFINDEX member and your PDF Collector FSS proc, make the necessary corrections, restart the JES printer if necessary and release the held PDF document.

CAHPDF11E**– MAXIMUM LINES EXCEEDED FOR= *jobname (jobnum)*****Reason:**

The SYSOUT line count exceeds the database MAXLINES initialization parameter value.

Action:

None. This message is informational.

CAHPDF12E

– I/O ERROR WRITING PAGE INDEX FOR SYSOUT – Page index deleted

Reason:

An I/O error occurs while writing out the index data for the SYSOUT group. Any index data that is already written is deleted.

Action:

Correct the error with the database.

CAHPDF13E

INVALID MAXOBJECT VALUE "*parameter value*" SPECIFIED IN PDFINDEX MEMBER *membername*; MUST BE 1 to 2097151.

Reason:

The MAXOBJECT parameter in the specified PDFINDEX member does not contain a numeric value or is not specified with a value from 1 to 2097151.

Action:

Correct the MAXOBJECT parameter so that it contains a value from 1 to 2097151.

CAHPDF14E

INVALID MEMORY VALUE "*parameter value*" SPECIFIED IN PDFINDEX MEMBER *membername*; MUST BE 1 to 2097151

Reason:

The MEMORY parameter in the PDFINDEX DD member does not contain a numeric value or is not specified with a value from 1 to 2097151.

Action:

Correct the MEMORY parameter so that it contains a valid value from 1 to 2097151.

CAHPDF15E

Invalid keyword parameter "keyword" in PDFINDEX member *membername* (BYPASSED)

Reason:

An invalid keyword has been specified in the PDFINDEX member associated with the report being processed. The invalid keyword is displayed.

Action:

Correct the invalid keyword and release the held JES document.

CAHPDF16I

PDFINDEX *membername* COMMAND - *keyword=values*

Reason:

This message lists all of the keywords and values from the associated PDFINDEX member for the PDF document being processed. The indexing member name used is shown in the displayed message (*membername*).

Action:

None.

CAHPDF17E

**INVALID TRACE OPTION "*option*" SPECIFIED IN PDFINDEX MEMBER *membername*;
SHOULD BE EITHER ALL, DATA, FLOW, OBJECT, OBJECTTRANSLATE**

Reason:

The option specified on the trace command is invalid.

Action:

Correct the value specified for the TRACE option and release the held PDF document from the JES queue to process correctly.

CAHPDF18E

No more space in database – Reply R (retry) T (terminate)

Reason:

There is not enough space in the database to perform the archival.

Action:

Reply with either an R to reattempt archival or a T to terminate:

1. Run the SARDBASE program to add more space to the database, or manually delete SYSOUT groups to free up space while the archival task waits. After you make more space available, reply R to have the archival task retry its archival with the additional space.
2. Reply T to terminate the archival task.

CAHPDF19E

This message number represents one of the following messages:

Sequence number will WRAP for report 'report id' Reply R (retry) after a standard backup or T (terminate)

Invalid reply

Reason:

Each unique report Id can have up to 65,535 copies per database generation. A 'generation' being the time between Full Backup Cycles. Each unique report id in a generation is assigned a sequential number from 1 to 65,535. After 65,535, the sequence number will wrap back to zero and 'date selection' problems will occur. This message gives the user a chance to run a backup cycle so this number can be reset to one.

The second message of CAHPDF19E is displayed if a response other than 'R' or 'T' is made to the original message.

Action:

Reply with either an R after a backup cycle has been started or a T to terminate. The CAHPDF19E message can be reissued after replying T and re-starting the PDF FSS Collector.

CAHPDF20E

**SAR FSA-PRTnn CHANGE MEMORY IN PDFINDEX DDN *jobname(jobnum)*
*stepname ddname***

Reason:

The PDF document that is being processed requires more memory to process the complete document.

Action:

Adjust the MEMORY= parameter in the PDFINDEX member to a larger value. Memory = ### is the number of 1-KB blocks of memory for this document, that is, ###=96801 X 1024 = 99124224 = 94-MB. For more information, see the chapter titled 'PDF Indexing in CA View' in the *Reference Guide*.

CAHPDF21E

**SAR FSA-PRTnn CHANGE MAXOBJCT IN PDFINDEX DDN *jobnum(jobname)*
*stepname ddname***

Reason:

The PDF document being processed requires more MAXOBJCT to process the complete document.

Action:

Adjust the MAXOBJCT in the PDFINDEX member to a larger value. MAXOBJT=### is the maximum number of objects for the document, that is ###=1500 is the maximum number of objects. Change this number to a larger number and release the document from the JES queue to test new setting. For more information, see the chapter titled 'PDF Indexing in CA View' in the *Reference Guide*.

CAHPDF22E

SAR FSA-PRTnn PDF DOCUMENT IS TOO COMPLEX *jobnum(jobname)* *stepname ddname*

Reason:

The PDF document being processed is complex and has over 150 references to other objects from one or more objects.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

CAHPDF23E

MORE THAN 100 INDEX PAGES USED - IGNORING ALL FURTHER INDEX PAGE COMMANDS

Reason:

There are more than 100 INDEX commands specified in the PDFINDEX member associated with the report being processed.

Action:

Contact CA Technical Support.

CAHPDF24E

INDEX CARD HAS AN INVALID END OF CHARACTER DEFINITION FOR THE FIELD INDEX

Reason:

An INDEX statement in the PDFINDEX member associated with the report being processed contains an invalid end-of-character value.

Action:

Correct the end-of-character value and release the held PDF document from the JES queue. For more information, see the chapter titled 'PDF Indexing in CA View' in the *Reference Guide*.

CAHPDF25E

FORMAT ERROR WITH INDEX PAGE COMMAND

Reason:

An INDEX command has been incorrectly formatted in the PDFINDEX member.

Action:

The invalid INDEX command is displayed in the PDF Collector FSS SARLOG report dataset. Correct the format of INDEX command and release the PDF document from the JES queue.

CAHPDF26E**INDEX CARD HAS AN INVALID LENGTH DEFINED FOR THE INPUT FIELD. I.E. L(nn) n BYTES INPUT****Reason:**

All INDEX command has been incorrectly formatted in the PDFINDEX member and contains an invalid length field, which must be L(NN). NN=Numeric field.

Action:

The invalid INDEX command is displayed in the PDF Collector FSS SARLOG report dataset. Correct the format of INDEX command and release the PDF document from the JES queue.

CAHPDF27E**OPERATOR MUST BE EITHER EQ,NE,LE,LT,GT,GE - INVALID OPERATOR GIVEN ON INDEX REQUEST****Reason:**

An INDEX command has been incorrectly formatted in the PDFINDEX DD member and contains an invalid operator expression, which must be one of those listed in the message.

Action:

The invalid INDEX command is displayed in the PDF Collector FSS SARLOG report dataset. Correct the format of INDEX command and release the PDF document from the JES queue.

CAHPDF28E**INVALID keyword VALUE "*parameter value*" SPECIFIED FOR PDFINDEX MEMBER, *membername*****Reason:**

The ENDPAGE or XYPAGES parameter in the specified PDFINDEX member does not contain a numeric value or is not specified with a value from 0 to 2147483647.

Action:

Correct the ENDPAGE or XYPAGES parameter so that it contains a valid value from 0 to 2147483647.

CAHPDF29I

PDF DOCUMENT IS ENCRYPTED NO INDEXING ALLOWED

Reason:

A PDF document to be processed has been password protected and also encrypted. It is not possible to index these types of PDF documents.

Action:

None.

CAHPDF30I

SAR FSA-PRTnn REQUEUED *jobname(jobnum) stepname ddname*

Reason:

This message is displayed when a PDF document is requeued into the JES spool. An error message is written into the SARLOG report and also to SYSLOG if the ARCHMSG=YES has been specified.

Action:

Correct the error for the failing PDF document and release the JES document to process again.

CAHAPDF31E

INSUFFICIENT STORAGE TO PROCESS PDF DOCUMENT; REDUCE MEMORY AND/OR MAXOBJCT SPECIFICATION

Reason:

There is not enough virtual storage to allocate buffers based on the MEMORY and MAXOBJCT parameter specification. The amount of storage required is based on the following formula:

$$\text{Storage} = (\text{MEMORY value} * 1024) + (\text{MAXOBJCT value} * 684)$$

The default for MEMORY is 96801 (94 meg) and MAXOBJCT is 30000 (20 meg)

Action:

Increase the REGION size for the FSS printer or specify a lower value for the MEMORY and/or MAXOBJCT parameter. The sysout data set containing the PDF document is queued to a held status. After correcting the problem, the sysout data set can be released for subsequent archival.

CAHPDF99E

jobid jobname message

Reason:

An exceptional condition identified by message occurs for the specified job.

Action:

Take appropriate action.

SAMACL02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG function to determine why the database did not open.

SAMAGT02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG function to determine why the database did not open.

SAMAGT03

Sub-file not open

Reason:

The auxiliary sub-file is not opened or the SAMAOPN had failed.

Action:

Open the auxiliary sub-file or process the SAMAOPN non-zero return code with the SAMMSG function to determine why the auxiliary sub-file did not open.

SAMAGT04

End of file

Reason:

Reading the auxiliary sub-file has resulted in End of File.

Action:

This is an expected condition.

SAMAOP02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG Function to determine why the database did not open.

SAMAOP03

No sub-file to access

Reason:

The control element (such as Sysout) does not have an auxiliary sub-file (page separation index) or the auxiliary sub-file is no longer on the database.

Action:

Verify that the element can contain an auxiliary sub-file and that the auxiliary sub-file is on the database.

SAMAOP04

Sub-file is currently open

Reason:

The auxiliary sub-file is opened while the data is being archived or a system failure has left an auxiliary sub-file in open status.

Action:

If the data is being archived, wait for the completion of the archival function. If the auxiliary sub-file was left in open status, the Sysout must be deleted.

SAMAOP05

Not authorized to access sub-file

Reason:

The application user does not have authority to read the sub-file.

Action:

Add Browse authority to the application user for this Sysout.

SAMGET02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG Function to determine why the database did not open.

SAMGET03

Invalid operation code "xx"

Reason:

The SAMGET parameter list did not contain a correct GET Function Code.

Action:

Correct the GET Function Code and rerun the SARSAM application. The valid GET Function codes are:

- EQ—GET EQUAL
- LT—GET LESS THAN
- GT—GET GREATER THAN
- LE—GET LESS THAN OR EQUAL
- GE—GET GREATER THAN OR EQUAL

SAMGET04

Record not found
Beginning of file
End of file

Reason 1:

The SAMGET function requested a record which was not found.

Action 1:

This maybe an expected condition or the record no longer exists in the database, such as a Tape Control Record (TCR) for an expired tape.

Reason 2:

The application is reading the index backwards and all records have been read, this is the reverse of reaching 'End of File' while reading forward.

Action 2:

This is an expected condition when reading backwards.

Reason 3:

The application is reading the index forwards all records have been read.

Action 3:

This is an expected condition.

SAMINV02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG Function to determine why the database did not open.

SAMOPN03

Userid denied access to database

Reason:

The USER ID associated with the SARSAM application program is not defined in the database (DEF USER) and the default user mode is 'NNNNN'.

Action:

Add the USER ID to the database using the SARBCH/DEF USER Command.

SAMSCLO2

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG Function to determine why the database did not open.

SAMSGT02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG Function to determine why the database did not open.

SAMSGT03

Sub-file not open

Reason:

The sub-file is not opened or the SAMSOPN had failed.

Action:

Open the sub-file or process the SAMSOPN non-zero return code with the SAMMSG Function to determine why the sub-file did not open.

SAMSGT04

End of file

Reason:

Reading the sub-file has resulted in End of File.

Action:

This is an expected condition.

SAMSOP02

Database not open

Reason:

The database is not opened or the SAMOPEN had failed.

Action:

Open the database or process the SAMOPEN non-zero return code with the SAMMSG Function to determine why the database did not open.

SAMSOP03

No sub-file to access

Reason:

The control element (such as Sysout) does not have a sub-file or the sub-file is no longer on the database.

Action:

Verify that the element can contain a sub-file and that the sub-file is on the database.

SAMSOP04

Sub-file is currently open

Reason:

The sub-file is opened while the data is being archived or a system failure has left a sub-file in open status.

Action:

If the data is being archived, wait for the completion of the archival function. If the sub-file was left in open status, the Sysout must be deleted.

SAMSOP05**Not authorized to access sub-file****Reason:**

The application user does not have authority to read the sub-file.

Action:

Add Browse and All Pages authority to the application user for this Sysout.

SARACF25**INVALID KEYWORD PARAMETER xxxxxx IN SARINDEX MEMBER yyyyyyyy (BYPASSED)****Reason:**

The user has misused or misspelled parameter xxxxxx in the member yyyyyyyy. The parameter has been ignored.

Action:

Correct parameter xxxxxx in the member yyyyyyyy.

SARACI01**UNABLE TO SET SVC SCREENING FOR *product*****Reason:**

The SVC screening product must be initialized, it cannot be found.

Action:

Verify that the SVC screening product is available.

SARACI02**ACIF LOAD MODULE NOT FOUND FOR *product*****Reason:**

The APKACIF module cannot be found in your IBM target libraries.

Action:

Verify that the STEPLIB statement is concatenated to CAI.CVDELOAD, or verify that they are both in the LNKLST.

SARACI03

INVALID INITIALIZATION PARAMETER *keyword=parm* FOR *product*

Reason:

A keyword is misspelled in the `//PRTnnn` statement.

Action:

Correct the keyword, and then resubmit the job.

SARACI04

INVALID INITIALIZATION VALUE *keyword=parm* FOR *product*

Reason:

A keyword is assigned an invalid value.

Action:

Correct the keyword, and then resubmit the job.

SARACI05

UNDEFINED DATA BASE HIGH-LEVEL NAME FOR *product*

Reason:

The database name specified as the NAME statement was not found.

Action:

Correct the name, and then resubmit the job.

SARACI06

INDEX CONTROL MEMBER *member* NOT FOUND FOR *product*

Reason:

Either the index member name was misspelled or it does not exist.

Action:

Correct the name, and then resubmit the job.

SARACI07

ERROR OPENING SARINDEX DD STATEMENT FOR *product*

Reason:

There is a media problem.

Action:

Verify that the volume is online and functioning properly.

SARACI08

DATA BASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The database is not at the appropriate level.

Action:

Verify that your database level (set with the SARDBASE utility) is correct, then rerun SARDBASE if necessary.

SARACI09

ERROR FROM ACIF FOR *product*, RC=*return code*

Reason:

An error came back from ACIF, the return code is provided.

Action:

Check the IBM documentation on APKACIF messages.

SARACI10

product* AUTHORIZATION FAILED FOR USERLIB *userlib

Reason:

The RACROUTE request returned with an error code indicating that the security rules do not permit access to the userlib.

Action:

Ensure that the userlib is correctly specified and/or change the security rules for it.

SARACI22

product PROCESSING jobname(jobid) jobdsn

Reason:

This message is informational.

Action:

None. This message is informational.

SARACI24

No more space in database ...db_hlq... Reply R (retry) T (terminate)

Reason:

There is not enough space in the database to perform the archival.

Action:

Reply with either an R to reattempt archival or a T to terminate:

1. Run the SARDBASE program to add more space to the database, or manually delete SYSOUT groups to free up space while the archival task waits. After you make more space available, reply R to have the archival task retry its archival with the additional space.
2. Reply T to terminate the archival task.

SARACI25

This message number represents one of the following messages:

Sequence number will WRAP for report 'report id' Reply R (retry) after a standard backup or T (terminate)

Invalid reply

Reason:

Each unique report id can have up to 65,535 copies per database generation. A 'generation' being the time between Full Backup Cycles. Each unique report id in a 'generation' is assigned a sequential number from 1 to 65,535. After 65,535, the sequence number wraps back to zero and date selection problems will occur. This message gives the user a chance to run a backup cycle so this number can be reset to one.

The second format of SARACI25 is displayed if a response other than 'R' or 'T' is given to the original message.

Action:

Reply with either an R after a backup cycle has been started or a T to terminate. The SARACI25 message can be reissued after replying T and re-starting the ACIF FSS Collector.

SARACT01

I/O ERROR UPDATING ACCOUNTING DATASET

Reason:

An I/O error occurred at job initiation when an attempt is made to update the job accounting data set.

Action:

If this error persists, recreate the job accounting data set.

SARATH92

AUTHORIZATION FAILED userid UNDER interface RC=xx.xx.xx

CLASS=class ENTITY=resource entity

Reason:

Userid is not authorized to access the requested resource for the specified CLASS and ENTITY value. SARATH92 messages is only displayed when the SARINIT FEATURE=1 parameter is specified.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not granted.

SARATH93

**** task ** userid Logon Complete**

Reason:

User Logon has completed successfully.

task – DRAS

ROSCOE

VTAM

XMS/CICS

XMS/IMS

XMS/TSO

XMS/SPF

userid - the User's id

Action:

None. This message is informational.

SARATH94

**** task ** userid Logon Complete**

Reason:

User Logon was successfully completed.

task – DRAS

ROSCOE

VTAM

XMS/CICS

XMS/IMS

XMS/TSO

XMS/SPF

userid - the User's id

Action:

None. This message is informational.

SARBCB02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or system programming group to determine the reason why the authorization was not provided.

SARBCB05

Bundle successfully printed

Reason:

The bundle was successfully produced.

Action:

None. This message is informational.

SARBCB10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a backup cycle deleting the SYSOUT group before completion of the bundling process or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of all SYSOUT groups, change, or omit any nonexistent SYSOUT groups, then resubmit the bundle reprint request.

SARBCB11

Bundle id not specified

Reason:

The BID parameter was not specified and is required on the control statement.

Action:

Add the BID parameter to the /BPRINT control statement, and then resubmit the bundle reprint request.

SARBCB12

Bundle contents not specified

Reason:

The BCONT parameter was not specified and is required on the control statement.

Action:

Add the BCONT parameter to the /BPRINT control statement, and then resubmit the bundle reprint request.

SARBCB13

Invalid specification for BCONT parameter near position xxxx

Reason:

The syntax of the BCONT parameter is invalid. Null parameter data, invalid character data, or excessive parentheses or commas usually cause these.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB14

Distribution identifier "distid" too long in BCONT parameter

Reason:

The specified distribution identifier contains too many characters. The distribution identifier on the BCONT parameter must be from 1 to 32 characters in length.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB16

Report identifier "reportid" too long in BCONT parameter

Reason:

The specified report identifier contains too many characters. The report identifier on the BCONT parameter must be from 1 to 32 characters in length.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB17

Report identifier "reportid" not defined to bundle "bundleid" in BCONT parameter

Reason:

The specified report identifier is not defined to the specified bundle in the CA Deliver Output Management database because the report identifier was incorrectly named, was deleted from the bundle before completion of the bundle reprint request, or is never defined to the bundle.

Action:

Review the bundle definition in CA Deliver, change or delete the report identifier specification, and then resubmit the bundle reprint request.

SARBCB18

Distribution identifier "distid" not defined to report "reportid" in BCONT parameter

Reason:

The specified distribution identifier is not defined to specified report in the CA Deliver database because the distribution identifier was incorrectly named, was deleted from the report before completion of the bundle reprint request, or is never defined to the report.

Action:

Review the bundle definition in CA Deliver, change or delete the distribution identifier specification, and then resubmit the bundle reprint request.

SARBCB19

Generation "xxxx" too long in BCONT parameter

Reason:

The specified generation contains too many characters. The generation field in the BCONT parameter must be 1 to 5 characters in length.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB20

Generation "xxxx" invalid in BCONT parameter

Reason:

The specified generation contains invalid characters. The generation field in the BCONT parameter specifies an absolute or relative numeric value.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB21

Sequence number "xxxx" too long in BCONT parameter

Reason:

The specified sequence number contains too many characters. The sequence number field in the BCONT parameter must be 1 to 5 characters in length.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB22

Sequence number "xxxx" invalid in BCONT parameter

Reason:

The specified sequence number contains invalid characters. The sequence number field in the BCONT parameter specifies an absolute or relative numeric number.

Action:

Review the syntax of the BCONT parameter on the /BPRINT control statement, correct the parameter specification, and then resubmit the bundle reprint request.

SARBCB23

I/O error message

Reason:

I/O operation against the CA Deliver database failed. The error message can range from a severe error condition such as physical or logical I/O error to non-severe error condition such as record not found or database not defined.

Action:

If a database not found message is produced, verify that the EXPRESS initialization parameter references the correct database. If a record not found message is produced, the respective identifier may have to be removed from the bundle reprint request. Consult the CA Deliver documentation to remedy severe error conditions.

SARBCB25

User is not authorized to print report to this destination

Reason:

The SARDSTUX user exit did not allow the bundle to be printed to its respective destination.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCC02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the specified SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reasons why the authorization was not provided.

SARBCC03

ID missing

Reason:

The ID parameter is incorrectly specified without a SYSOUT identifier and is required on the control statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be changed, and then resubmit the print request.

SARBCC04

Sysout successfully changed

Reason:

The SYSOUT group is successfully updated with the requested information.

Action:

None. This message is informational.

SARBCC10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. A misspelled SYSOUT identifier normally causes this, the SYSOUT group was manually deleted from the online or batch retrieval facilities, or the backup cycle deleted the SYSOUT group before the completion of the change process.

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation number (GEN), and/or sequence number (SEQ) was specified incorrectly, change the parameter specification, then resubmit the change request.

SARBCC11

Sysout does not reside on disk

Reason:

The BACKUP=OFF parameter is specified on the change request to reset the tape backup indicator. When the tape backup indicator is reset, the SYSOUT group is re-archived to tape during the next backup cycle. The backup cycle requires that the SYSOUT group reside on disk, but the SYSOUT group specified on the change request does not currently reside on disk.

Action:

If the change request is being requested against the correct SYSOUT group, the SYSOUT group can be reloaded to disk using the LOAD request of the SARBCH utility.

SARBCC12

Sysout is not marked for deletion

Reason:

The DELETE=OFF parameter is specified on the CHANGE request to reset the delete indicator for the SYSOUT group, but the SYSOUT group is not currently in a delete status.

Action:

Verify that the correct SYSOUT group is being referenced on the change request. If additional parameters are being changed, remove the DELETE=OFF parameter, then resubmit the change request.

SARBCC13

Critical error, can not determine the correct Generation Number

Reason:

A SARBCH /CHANGE ARCHDATE function is trying to determine the new generation and sequence number for the report which is being back-dated and an error has occurred in the database which has prevented this process to successfully complete.

Action:

Save all the documentation associated with the job, run a SARDBASE IDXOUT and TERSE the output file, and notify CA Technical Support.

SARBCC14

Critical error, can not determine the correct Sequence Number

Reason:

A SARBCH /CHANGE ARCHDATE function is trying to determine the new generation and sequence number for report which is being back-dated and an error has occurred in the database which has prevented this process to successfully complete.

Action:

Save all the documentation associated with the job, run a SARDBASE IDXOUT and TERSE the output file, and notify CA Support.

SARBCC15

Invalid date format, must be "mm/dd/yyyy"

Reason:

A SARBCH /CHANGE Statement was provided and the ARCHDATE parameter has either an invalid format or an invalid month, day, or year.

Action:

Correct the format error and re-run the job.

SARBCC16

Can not back-date a report to a date in the future

Reason:

A SARBCH /CHANGE Statement was provided and the ARCHDATE parameter has date which is higher than the current date. Reports can be 'back-dated' but cannot be 'forward-dated.'

Action:

Correct the date to a previous date and re-run the job.

SARBCC17

Other parameters coded, these are ignored

Reason:

A SARBCH /CHANGE Statement is provided with an ARCHDATE parameter and some other CHANGE parameter. The archival date is the only change that can be made to the Sysout and the other parameters are ignored.

Action:

The other changes can be specified on a second /CHANGE Statement if desired.

SARBCC18

Report control record date changed,

From: ID=..... GEN=..... SEQ=..... ARCHDATE=..... ARCHTIME=.....

Reason:

A SARBCH /CHANGE Statement is provided with an ARCHDATE parameter and the function completed successfully, the old generation number, sequence number, archival date and time, and the new generation number, sequence number, archival date and time are displayed in the message.

Action:

None, informational message.

SARBCD02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or system programming group to determine the reason why the authorization was not provided.

SARBCD03**Sysout group successfully deleted****Reason:**

The disk space, if any, occupied by the requested SYSOUT group and the respective master index references have been successfully deleted from the database.

Action:

None. This message is informational.

SARBCD04**Disk media for sysout group successfully deleted****Reason:**

The disk space occupied by the requested SYSOUT group has been successfully deleted from the database. The SYSOUT group resides in non-disk status.

Action:

None. This message is informational.

SARBCD05**nn view(s) successfully deleted****Reason:**

The requested view(s) were successfully deleted from the master index.

Action:

None. This message is informational.

SARBCD06**User successfully deleted****Reason:**

The requested user ID and all associated online variables were successfully deleted from the master index.

Action:

None. This message is informational.

SARBCD07

Index file for sysout group successfully deleted

Reason:

The disk space occupied by the report index for the requested SYSOUT group has been successfully deleted from the database.

Action:

None. This message is informational.

SARBCD08

Device/Filter successfully deleted

Reason:

The requested device or filter was successfully deleted from the master index.

Action:

None. This message is informational.

SARBCD10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the delete process, or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Note: A generic SYSOUT identifier cannot be specified in the delete request.

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly, change the respective parameters, and then resubmit the delete request.

SARBCD11

ID missing

Reason:

The ID parameter is incorrectly specified without a SYSOUT identifier.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be deleted, then resubmit the delete request.

SARBCD12

Disk media not deleted because sysout group is currently open

Reason:

The disk space for the requested SYSOUT group was not deleted because the SYSOUT group is in open status. The SYSOUT group can be in open status due to a currently pending temporary load operation, a pending migration operation, or initial creation.

Action:

Wait until the status of the SYSOUT group has changed from open status, and then resubmit the delete request. If the open condition is invalid (for example, a system crash or abend occurred while the SYSOUT group was in open status and being processed) use the CLEAN operator command to remove the open status. Two backup cycles and the duration of four hours must have elapsed before the open status is removed.

SARBCD13

Disk media not deleted because sysout group has no backup

Reason:

The disk space for the requested SYSOUT group was not deleted because the SYSOUT group has no tape or optical archival copy. If the delete request was honored, the SYSOUT group would not have any archival copy and would therefore render it useless.

Action:

Wait until the completion of the backup cycle, or the next run of the optical migration subtask, and then resubmit the delete request.

SARBCD14

Disk media not deleted because sysout group does not reside on disk

Reason:

The SYSOUT group does not reside on disk. This is normally caused by a backup cycle deleting the disk space for the SYSOUT group before completion of the delete request, or another user or job deleted the disk space by using the online retrieval facility or batch retrieval facility (SARBCH). See the initialization parameter NGEND for more information.

Action:

None; since the SYSOUT group no longer resides on disk, the original intent of the delete disk request has been satisfied.

SARBCD15

Disk media not deleted because secondary storage driver was not available

Reason:

The SYSOUT group cannot be deleted because it resided on secondary disk storage, and no secondary disk storage driver was available.

Action:

Run SARINIT to redefine the secondary disk storage driver.

SARBCD16

VIEW missing

Reason:

The VIEW parameter is incorrectly specified without a view number.

Action:

Change the VIEW parameter to include the view number that is to be deleted or * to delete all views, and then resubmit the delete request.

SARBCD17**VIEW keyword conflicts with DISK/GEN/SEQ/INDEX KEYWORD(S)****Reason:**

The VIEW parameter cannot be specified with the DISK, GEN, SEQ, and/or INDEX parameters.

Action:

Either remove the VIEW parameter or remove the DISK, GEN, SEQ, and/or INDEX parameters from the control statement, then resubmit the delete request.

SARBCD18**Requested view(s) not found in master index****Reason:**

The requested view does not exist in the master index. This is normally caused by an incorrect specification of the ID parameter and/or the VIEW parameter, or another user or job already deleted the view by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the view. If the view (VIEW parameter) or SYSOUT identifier (ID parameter) was specified incorrectly, change the parameter specification, and then resubmit the delete request.

SARBCD19**USER missing****Reason:**

The USER parameter is incorrectly specified without a user ID.

Action:

Change the USER parameter to include the user ID that is to be deleted, and then resubmit the delete request.

SARBCD20

USER keyword conflicts with DISK/GEN/ID/SEQ/INDEX keyword(s)

Reason:

The USER parameter cannot be specified with the DISK, GEN, ID, SEQ, and/or INDEX parameters.

Action:

Either remove the USER parameter or remove the DISK, GEN, ID, SEQ, and/or INDEX parameters from the control statement, and then resubmit the delete request.

SARBCD21

Requested user not found in master index

Reason:

The requested user ID does not exist in the master index. This is normally caused by an incorrect specification of the USER parameter, or the user ID was already deleted by another job or user by using the online retrieval facility or batch retrieval facility (SARBCH).

Note: A generic user ID cannot be specified in the delete request.

Action:

Verify the existence of the user ID. If the user ID (USER) parameter was specified incorrectly, change the parameter, and then resubmit the job.

SARBCD22

User not authorized to delete userid

Reason:

The user ID extracted by the SARUSBUX does not have sufficient authority (master authority) to delete user IDs from the database. The user ID that requires authority is indicated in a previous (SARBCH05) message.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCD28

Disk media not deleted because sysout group was re-indexed and not backed up

Reason:

The user re-indexed a Sysout Group (with the 'I' command or the Batch '/INDEX' command) and the Sysout Group has not been re-written to the backup tape.

Action:

Wait for the backup cycle to complete or force a new backup cycle and retry the command.

SARBCD29

Disk media not deleted because sysout group is a Resource Group, only DELETE DISK allowed

Reason:

The SYSOUT group is a resource group and resource groups cannot be deleted.

Action:

Add the 'DISK' parameter to the /DELETE statement and rerun the step.

SARBCD30

This message number represents one of the following:

DELETE FORCE specified for rpt_id ensure job job_name(job_number) is not running

Reply Y to delete or C to cancel

Invalid reply

Reason:

The SYSOUT identified in the DELETE command is in OPEN status. The job can still be running and the command requires the confirmation to delete the SYSOUT.

Action:

Reply with either a Y if the job is not running and the delete must continue normally or C to cancel the delete function.

SARBCD31

DELETE FORCE function cancelled

Reason:

The user responded C to message SARBCD30.

Action:

None.

SARBCD32

Cannot delete OPEN Sysout, use DELETE FORCE

Reason:

The SYSOUT is in OPEN status and cannot be deleted.

Action:

Use the FORCE parameter on the DELETE command and confirm that the job is not running.

SARBCD33

Mandatory retention (REGDAYS) has not expired, cannot DELETE at this time

Action:

The DELETE function fails because it violates REGDAYS retention for this report

Reason:

The copy of the report you are trying to delete is controlled by REGDAYS retention – it cannot be deleted.

SARBCD34

DEV keyword conflicts with DISK/GEN/ID/SEQ/INDEX /VIEW/USER keyword(s)

Reason:

The DEV parameter cannot be specified with the DISK, GEN, ID, SEQ, INDEX, VIEW and/or USER parameters.

Action:

Either remove the DEV parameter or remove the DISK, GEN, ID, SEQ, INDEX, VIEW and/or USER parameters from the control statement, and then resubmit the delete request.

SARBCD35

Requested device/filter not found in master index

Reason:

The requested device or filter does not exist in the master index. This is usually caused by an incorrect specification of the DEV or FILT parameter, or the device or filter was already deleted by another job or user by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the device or filter. If the DEV or FILT parameter was specified incorrectly, change the parameter and resubmit the job.

SARBCD36

User not authorized to delete device/filter

Reason:

The user ID extracted by the SARUSBUX does not have sufficient authority (master authority) to delete the device or filter from the database. The user ID that requires authority is indicated in a previous (SARBCH05) message.

Action:

Consult your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCD37

Cannot delete INDEX files for a Dynamic Reports

Reason:

Dynamic Reports contain an index generate during initial processing of the report. This index cannot be reproduced without the original report; therefore, the /DELETE INDEX function is not supported for Dynamic Reports.

Action:

Verify that the correct report has been specified. Remove the INDEX parameter if the report is a Dynamic Report.

SARBCE02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or system programming group to determine the reason why the authorization was not provided.

SARBCE03

ID Missing

Reason:

The ID parameter is specified without a SYSOUT identifier that is required on the control statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be printed, then resubmit the print request.

SARBCE05

Report successfully printed

Reason:

The CA Deliver report was successfully queued to print.

Action:

None. This message is informational.

SARBCE07

Sysout queued for transmittal to PC

Reason:

The CA Deliver report was successfully queued for download to a PC. The download process can be completed at the user's discretion from the online retrieval interface.

Action:

None. This message is informational.

SARBCE10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the print process or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly, change the parameter specification, and then resubmit the print request.

SARBCE11

Sysout group was not archived by CA Deliver

Reason:

The print request referenced a SYSOUT group that is not archived by CA Deliver.

Action:

Either change the SYSOUT identifier (ID parameter) to specify a CA Deliver report, or print the report with the /PRINT control statement.

SARBCE12

Report identifier "reportid" not found in database

Reason:

The requested report does not exist in the master index. This is normally caused by a backup cycle deleting the report before completion of the print process, or the manual deletion of the report by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the report. If the report identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly, change the respective parameter, and then resubmit the print request.

SARBCE13

I/O error message

Reason:

I/O operation against the CA Deliver database failed. The error message can range from a severe error condition such as physical or logical I/O error, to non-severe error condition such as record not found or database not defined.

Action:

If a database not found message is produced, verify that the EXPRESS initialization parameter references the correct database. Also, verify that there is a STEPLIB statement for the CA Deliver load modules in:

- The CA View skeleton JCL
- The JCL for any of the online interfaces (these are both part of installing CA View)

If a record not found message is produced, the respective identifier may have to be removed from the print request. See your CA Deliver documentation to remedy severe error conditions.

SARBCE15

Invalid use of parenthesis in DIST parameter

Reason:

The syntax of the DIST parameter is invalid. This is normally caused by unbalanced parentheses or excessive parentheses.

Action:

Review the syntax of the DIST parameter on the /EPRINT control statement, correct the parameter specification, and then resubmit the reprint request.

SARBCE16

Invalid distribution identifier in DIST parameter

Reason:

The distribution identifier in the DIST parameter contains invalid characters or too many characters. The distribution identifier can be from 1 to 32 characters in length and consists of alphanumeric, and national (\$, @, or #) characters.

Action:

Review the syntax of the DIST parameter on the /EPRINT control statement, correct the parameter specification, and then resubmit the print request.

SARBCE17

Invalid destination in DIST parameter

Reason:

The destination field in the DIST parameter contains invalid characters or too many characters. The destination field can be from 1 to 17 characters in length and consists of two qualifiers that are alphanumeric, and national (\$, @, or #) characters.

Action:

Review the syntax of the DIST parameter on the /EPRINT control statement, correct the parameter specification, and then resubmit the print request.

SARBCE18

Invalid text string in INST parameter

Reason:

The syntax of the INST parameter is invalid. This can be caused by unbalanced quotes, excessive quotes (quotes within non-quoted string), invalid separator (blank, comma, or parenthesis not following quoted string), or too many characters in text string (maximum of 74 characters).

Action:

Review the syntax of the INST parameter on the /EPRINT control statement, correct the parameter specification, and then resubmit the print request.

SARBCE19

No distribution identifiers for report - Use /PRINT to print report

Reason:

You have tried to print a CA Deliver report without specifying any DIST IDs that are getting the report.

Action:

Specify either at least one receiving DIST ID or switch to SAR MODE and retry the print request. You can switch to SAR MODE by either typing SAR in the command area and pressing Enter, or by typing MODE SAR in the command line of the primary menu and pressing Enter.

SARBCE20

Report successfully printed, Dist=distid at xxxxxxxx

Reason:

The report is printed for the DIST ID indicated on the printer specified.

Action:

None. This message is informational.

SARBCE21

Errors on other destinations prevented printing, Dist=distid at xxxxxxxx

Reason:

The report cannot be printed for the DIST ID indicated on the printer specified because of another error in the print request.

Action:

Correct the error as indicated in the associated error message and try the print request again.

SARBCE22

Message text, Dist =distid at xxxxxxxx

Reason:

A subprogram returned a message that is being repeated here. The print request was to print the DISTID indicated on the printer specified.

Action:

The action varies depending on the message text displayed.

SARBCE31

SELECT specification conflicts with PAGE and/or RECORD specification

Reason:

The SELECT keyword and the PAGE and/or RECORD keywords are mutually exclusive.

Action:

Either remove the SELECT parameter or remove the PAGE and/or RECORD parameters from the control statement, then resubmit the print request.

SARBCE32

Sysout is not on primary disk and its index is unavailable for page selection

Reason:

The SELECT keyword was specified but the SYSOUT group resides on tape.

Action:

Either remove the SELECT keyword to print the entire SYSOUT group, or temporarily reload the SYSOUT group to the database so that its index is available for printing.

SARBCE33

SELECT specified without a valid logical view

Reason:

The SELECT keyword was specified and either the CA View keyword was omitted or specified for an invalid logical view.

Action:

Correct the parameter specification, and then resubmit the print request.

SARBCE34

Error occurred attempting to read in the index for the sysout

Reason:

An error occurred attempting to obtain the index for the SYSOUT group.

Action:

Either remove the SELECT keyword to print the entire SYSOUT group or re-archive the SYSOUT group to create an index.

SARBCE35

Sysout has not been indexed for the logical view or by ACIF

Reason:

The page separation definition in the logical view either did not exist when the SYSOUT group was archived or was changed subsequently.

Action:

Either remove the SELECT keyword to print the entire SYSOUT group, re-index the SYSOUT group, or re-archive the SYSOUT group to create an index.

SARBCE36

No pages found that match selection text

Reason:

The selection text does not exist in the index for the logical view of the SYSOUT group. An incorrect spelling on the SELECT keyword normally causes this, or the page separation criteria is never defined for the SYSOUT group.

Action:

Either change the SELECT parameter to reference a different index specification or remove the SELECT keyword to print the entire SYSOUT group.

SARBCE37

User is not authorized to print report from this destination

Reason:

The SARDSTUX user exit did not allow the report to be printed to its respective destination.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCE40

View not found

Reason:

The specified view does not exist in the master index.

Action:

Verify the existence of the view. If the view number was specified incorrectly, change the parameter specification, and then resubmit the print request.

SARBCE41

Requested index not found

Reason:

The page index value specified on the SELECT keyword of the print request is not found for the requested SYSOUT group.

Action:

Verify that the correct page index value, SYSOUT group, and view are being specified. Otherwise, remove the SELECT parameter and print the entire SYSOUT group.

SARBCE42

No TCR record found for requested sysout

Reason:

An attempt is being made to print a SYSOUT group from tape, but certain vital backup tape control information cannot be found.

Action:

Normally, tape control information is retained as long as there are reports that reference it. The tape control record (TCR) can be reinstated by re-adding the tape back into the database with the TADD facility of the SARTDR utility.

Important! This condition could identify a serious problem with the database or problems with the supporting code. Report the problem to CA Technical Support.

SARBCE43

Error during secondary disk or EAS access

Reason:

An error occurred opening a report on optical disk, or on tape accessed through an EAS tape server.

Action:

Browse the report online to see any error messages from the DSK2 driver or EAS tape server interface routine.

SARBCE46

User not authorized to access view

Reason:

The SARSECUX security user exit or external security has denied access to the logical view of the report.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCE47

User not authorized to access index

Reason:

The SARSECUX security user exit or external security has denied access to the specified index of the report.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCF01

ID parameter not supplied

Reason:

The ID keyword is not specified on the DEFFILT or LISTFILT control statement.

Action:

Add the appropriate keyword specification to the define or list request, and then resubmit the request.

SARBCF02

ID=

USER=

FILTERS=

Reason:

This message identifies the profile attributes of the Filter definition after processing the DEFFILT request.

Action:

None. This message is informational.

SARBCF03

Filter successfully added

Reason:

The Filter attributes are successfully added to the CA View database. This message is accompanied by the SARBCF02 message that details the View definition information.

Action:

None. This message is informational.

SARBCF04

Filter successfully modified

Reason:

The Filter attributes for an existing definition were successfully changed. This message is accompanied by the SARBCF02 message, which details the Filter definition information.

Action:

None. This message is informational.

SARBCF05

I/O error

Reason:

An error occurred while reading or writing data from the CA View database. This message is to be accompanied by a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARBCF06

Report successfully completed

Reason:

The listing of Filter is successfully written to the REPORT DD statement.

Action:

None. This message is informational.

SARBCF07

REPORT DD statement missing

Reason:

The REPORT JCL DD statement was not provided and is required for the control statement.

Action:

Specify the REPORT JCL DD statement, and then resubmit the job.

SARBCF08

User not authorized to list Filter(s).

Reason:

Listing a Filter definition requires MASTER authority.

Action:

Request that the job be run by a user with master authority.

SARBCF09**Requested Filter(s) not found in master index****Reason:**

The requested filter does not exist in the master index. This is typically caused by an incorrect specification of the ID parameter and/or the USER parameter, or another user or job already deleted the filter by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the filter. If the filter (ID parameter) or user identifier (USER parameter) was specified incorrectly, change the parameter specification and resubmit the request.

SARBCF10**Filter definition too large****Reason:**

Filter definition record exceeds maximum length.

Action:

Reduce FILTER definitions on the DEFFILT control statement, and then resubmit the define request.

SARBCF11**Filter definition too many entries****Reason:**

Filter definition contains more than 255 entries.

Action:

Reduce the number of FILTER entries on the DEFFILT control statement, and then resubmit the define request.

SARBCF12

xxxxxxx subparameter n is invalid

Reason:

The DEFFILT statement keyword xxxxxx subparameter number n is not valid.

Action:

Correct the keyword and then resubmit the define request.

SARBCF13

User not authorized to modify Filter(s).

Reason:

Modifying a Filter definition requires MASTER authority.

Action:

Request that the job be run by a user with master authority.

SARBCF15

User not authorized to do LISTFILT

Reason:

The user ID extracted by the SARUSBUX does not have sufficient authority (master authority) to list filters defined in the database. The user ID that requires authority is indicated in a previous (SARBCH05) message.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCG02

Report successfully completed

Reason:

The listing of Devices is successfully written to the REPORT DD statement.

Action:

None. This message is informational.

SARBCG03

Device successfully added

Reason:

The Device is successfully added to the CA View database. This message is accompanied by the SARBCG15 message that details the Device definition information.

Action:

None. This message is informational.

SARBCG04

Device successfully modified

Reason:

The Device attributes for an existing definition were successfully changed. This message is accompanied by the SARBCG15 message, which details the Device definition information.

Action:

None. This message is informational.

SARBCG05

I/O error

Reason:

An error occurred while reading or writing data from the CA View database. This message is to be accompanied by a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARBCG06

ID or TYPE parameter not supplied

Reason:

The ID keyword or TYPE keyword is not specified on the DEFDEV control statement.

Action:

Add the appropriate keyword specification to the DEFDEV request, and then resubmit the request.

SARBCG07

Missing parameter [CNODE | PUSERID | EXTPRT | VNODE]

Reason:

The CNODE, PUSERID, EXTPRT, or VNODE parameter is required for specified DEFDEV TYPE.

Action:

Add the missing keyword parameter to the DEFDEV request, and then resubmit the request.

SARBCG08

Specified user exit not found or does not begin with "SAR\$"

Reason:

The specified DEFDEV CEXIT or VEXIT device-specific user exit did not start with "SAR\$" or is not found in STEPLIB.

Action:

Correct or remove the DEFDEV CEXIT or VEXIT parameter, and then resubmit the request.

SARBCG09**REPORT DD statement missing****Reason:**

The REPORT JCL DD statement was not provided and is required for the control statement.

Action:

Specify the REPORT JCL DD statement, and then resubmit the job.

SARBCG10**Requested device not found in master index****Reason:**

The requested LISTDEV device does not exist in the master index. This is typically caused by an incorrect specification of the ID, USER, or TYPE parameters.

Action:

Verify the existence of the device. If the LISTDEV ID, USER or TYPE parameter was specified incorrectly, change the parameter specification and resubmit the request.

SARBCG11**User not authorized to perform [LISTDEV | DEFDEV]****Reason:**

The user ID extracted by the SARUSBUX does not have sufficient authority (master authority) to list devices, or add or modify a device to the database. The user ID that requires authority is indicated in a previous (SARBCH05) message.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCG12

Unsupported keyword parameter xxxxxxxx

Reason:

The keyword parameter xxxxxxxx is not supported for the specified DEFDEV TYPE.

Action:

Remove the unsupported keyword parameter from the DEFDEV request, and then resubmit the request.

SARBCG13

Invalid value for parameter xxxxxxxx

Reason:

The keyword parameter xxxxxxxx value is not valid.

Action:

Correct the keyword parameter value on the DEFDEV request, and then resubmit the request.

SARBCG14

Conflicting values

Reason:

The following DEFDEV keyword parameters are mutually exclusive:

- CSARCLS=N/Y and CCLASS=c
- CSARCOPY=N/Y and CCOPIES=nnn
- CSARFCB=N/Y and CFCB=cccc
- CSARFORM=N/Y and CFORM=cccc
- CSARHOLD=N/Y and CHOLD=N/Y
- JCONNECT=Y and JBANNER=Y
- JCONNECT=Y and RESONLY=Y and JDATONLY=Y

Action:

Remove one of the mutually exclusive parameters on the DEFDEV request, and then resubmit the request.

SARBCG15

`/DEFDEV ID=xxxxxxx TYPE=yyyyyyy . . .`

Reason:

This message identifies the profile attributes of the device definition after processing the DEFDEVT request.

Action:

None. This message is informational.

SARBCG16

Specified VDRIVER not found or does not begin with "SARVPS"

Reason:

The specified DEFDEV VDRIVER driver did not start with "SARVPS" or is not found in STEPLIB.

Action:

Correct or remove the DEFDEV VDRIVER parameter, and then resubmit the request.

SARBCG21

Invalid device type in device xxxxxxxx

Reason:

The device type found in device xxxxxxxx was invalid.

Action:

Correct the device type using Online DEF DEV or SARBCH DEFDEV.

SARBCH02

Job/User not authorized to access database

Reason:

The SARATHUX security user exit did not allow the job or user access to the database.

Action:

Consult with your security administrator or system programming group to determine the reason why the authorization was not provided.

SARBCH03

Invalid or misplaced control card, control statement must begin with a "/"

Reason:

A slash (/), denoting a new control statement, is expected in column 1 of the control statement but is not found.

Action:

Review syntax of control statement, insert a slash (/) before the function name in column 1 of the control statement, and then resubmit the job.

SARBCH04

Invalid function name

Reason:

The specified function name (name that follows the slash) contains invalid characters, contains too many characters, or is not a valid batch retrieval function.

Note: The function name must immediately follow a slash (/) that is coded in column 1 of the control statement. Also, control statements that continue onto multiple control statements are not prefixed with the slash.

Action:

Review the spelling of function name and the syntax of the control statement, correct the control statement specification, and then resubmit the job.

SARBCH05

Logon successful for userid to database

Reason:

The user ID determination exit (SARUSBUX) provided successful logon for the specified user ID to the specified database.

Action:

None. User ID logon is performed during initial access to the database.

SARBCH06

Logon unsuccessful for userid to database

Reason:

The user ID determination exit (SARUSBUX) did not allow logon for the specified user ID to the specified database.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCH10

Invalid keyword name "xxxxx"

Reason:

The specified keyword name contains invalid characters, contains too many characters, or is not a valid name.

Action:

Review syntax of control statement and spelling of the keyword name, correct the parameter specification, and then resubmit the job.

SARBCH11

Invalid parameter data for keyword

Reason:

The parameter data for the specified keyword contains invalid characters or is not an acceptable value.

Action:

Review syntax of control statement, correct the parameter specification, and then resubmit the job.

SARBCH12

Unbalanced quoted string encountered in parameter data for keyword

Reason:

The parameter data for the specified keyword contains a quoted string that is not terminated by an ending quote.

Action:

Review syntax of control statement, correct the parameter specification, and then resubmit the job.

SARBCH13

Unbalanced parentheses encountered in parameter data for keyword

Reason:

The parameter data for the specified keyword contains an incorrect number of parentheses. For every right parenthesis, there must be a matching left parenthesis.

Action:

Review syntax of control statement, correct the parameter specification, and then resubmit the job.

SARBCH14

Parameter data too long for keyword

Reason:

The parameter data for the specified keyword contains too many characters.

Action:

Review syntax of control statement, correct the parameter specification, and then resubmit the job.

SARBCH15

Too many parameters specified for keyword

Reason:

The parameter data for the specified keyword contains too many values.

Action:

Review syntax of control statement, correct the parameter specification, and then resubmit the job.

SARBCH21

Database at incorrect level for this release

Reason:

The program load modules and the database are not at the same version level. This is normally caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to old load modules, or the database has not been converted to the correct version level (new versions of product can require conversion of the database).

Action:

You can either STEPLIB to the correct load modules or convert the database to the correct release level.

SARBCI01

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or system-programming group to determine the reason why the authorization was not provided.

SARBCI02

ID missing

Reason:

The ID parameter is incorrectly specified without a SYSOUT identifier.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be re-indexed, and then resubmit the index request.

SARBCI03

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the index process, or the manual deletion of the SYSOUT group using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly, change the parameter specification, and then resubmit the index request.

SARBCI04

REGDAYS has not expired and report is located on CENTERA

Reason:

Indexing a report requires the report and INDEX to be replaced on CENTERA storage. Since this copy of the report is under REGDAYS retention, it cannot be deleted or changed.

Action:

Report cannot be Indexed or re-indexed.

SARBCK02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCK03

ID missing

Reason:

The ID parameter is incorrectly specified without a SYSOUT identifier and is required on the control statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be set to or removed from permanent status, then resubmit the PERM request.

SARBCK04

DISK/TAPE/DELETE keywords conflict, only one of these keywords may be specified

Reason:

The DISK, TAPE, and/or DELETE keywords are mutually exclusive and cannot be specified on the same control statement.

Action:

Change control statement to specify DISK, TAPE, or DELETE, and then resubmit PERM request.

SARBCK05

Sysout group successfully set to permanent disk status

Reason:

The SYSOUT group is successfully set to a permanent on disk status (location of PERM). The long-term status of the SYSOUT group depends on the setting of the Expanded Retention Option initialization parameters and table parameters.

Action:

None. This message is informational.

SARBCK06

Sysout group successfully set to permanent tape status

Reason:

The SYSOUT group is successfully set to permanent on tape status (location of PDSK, PTMP, or PTAP). The long-term status of the SYSOUT group depends on the setting of the Expanded Retention Option initialization parameters and table parameters.

Action:

None. This message is informational.

SARBCK07

Sysout group successfully removed from permanent status

Reason:

The SYSOUT group was successfully removed from permanent status. The disk and tape retention of the SYSOUT group depends on the setting of the NGEND and NGENT initialization parameters.

Action:

None. This message is informational.

SARBCK08**Sysout group is on secondary disk storage - permanent status not deleted****Reason:**

The SYSOUT group resides on secondary disk storage and must remain in permanent status.

Action:

None. Permanent status cannot be deleted.

SARBCK10**Requested sysout not found in master index****Reason:**

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the PERM process, or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly, change the parameter specifications, and then resubmit the PERM request.

SARBCK11**Permanent status not set because sysout group is currently open****Reason:**

The SYSOUT group is not set to or removed from permanent status because the SYSOUT group is in open status. The SYSOUT group can be in open status due to a currently pending temporary load operation, a pending migration operation, or initial creation.

Action:

Wait until the status of the SYSOUT group has changed from open status, then resubmit PERM request. If the open condition is invalid (for example, a system crash or an abend occurred while the SYSOUT group was in open status and being processed), use the CLEAN operator command to remove the open status. Two backup cycles and the duration of 4 hours must have elapsed before the open status is removed.

SARBCK12

Permanent disk status not set because sysout group is not on disk

Reason:

The SYSOUT group cannot be set to a permanent on disk status because the SYSOUT group does not reside on disk media.

Action:

Temporarily load SYSOUT group to the database, then resubmit PERM request.

SARBCL02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCL03

ID missing

Reason:

The ID parameter is incorrectly specified without a SYSOUT identifier and is required on the control statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be loaded, then resubmit the load request.

SARBCL04

DDNAME "ddname" NOT FOUND

Reason:

The JCL DD statement name specified in the DDNAME parameter was not provided.

Action:

Remove the DDNAME parameter or specify the respective JCL DD statement, and then resubmit the load request.

SARBCL05

Sysout successfully loaded

Reason:

The SYSOUT group is successfully loaded from tape to the database and resides in a temporary on disk status.

Action:

None. This message is informational.

SARBCL06

Sysout successfully written to DDNAME=ddname

Reason:

The SYSOUT group is successfully copied to the specified JCL DD statement.

Action:

None. This message is informational.

SARBCL07

Index file successfully loaded

Reason:

The page index file for the requested SYSOUT group is successfully loaded from tape or secondary disk to the CA View database.

Action:

None. This message is informational.

SARBCL10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the load process, or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly, change the parameter specification, and then resubmit the load request.

SARBCL12

Data set not loaded - already on disk

Reason:

The SYSOUT group is not loaded to the database because it already resides on disk.

Action:

Since the original intent of the load request has been satisfied, no further action is necessary. If the SYSOUT group was incorrectly loaded or is empty, the disk portion of the SYSOUT group can be deleted by using the online retrieval facility or batch retrieval facility, and the load request can be resubmitted.

SARBCL13

Requested sysout does not exist on any tape backup data set

Reason:

The SYSOUT group cannot be found on any tape backup.

Action:

None. The SYSOUT group is not available on tape.

SARBCL14

The tape file was not the selected sysout group - use SARTCP to map the tape

Reason:

The SYSOUT group located on the backup tape is not the same as referenced in the master index.

Action:

Use the SARTCP utility to map and correct the backup tape.

SARBCL15

Backup tape does not exist

Reason:

The backup tape cannot be found in the master index. This is normally caused by the backup cycle deleting the tape before completion of the load request.

Action:

None. The SYSOUT group is no longer available.

SARBCL16

Dynamic allocation failed for tape file, Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for allocating the backup tape file. The hexadecimal error and information codes are provided.

Action:

Consult the online retrieval HELP facility for a description of the dynamic allocation error code. Take appropriate action to correct the allocation error, and then resubmit the load request.

SARBCL17

I/O error positioning tape

Reason:

A permanent I/O error occurred attempting to position the archival tape to retrieve the SYSOUT group.

Action:

Resubmit the request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape.

SARBCL18

Sysout group is open for output

Reason:

The requested function cannot be performed because the specified SYSOUT group is open for output. The SYSOUT group can be in open status due to a currently pending temporary load operation, a pending migration operation, or initial creation.

Action:

Wait until the status of the SYSOUT group has changed from open status, then resubmit load request. If the open condition is invalid, that is, a system crash or an abend occurred while the SYSOUT group was in open status and being processed; use the CLEAN operator command to remove the open status. Two backup cycles and the duration of four hours must have elapsed before the open status is removed.

SARBCL19

Permanent I/O error on input tape

Reason:

A permanent I/O error occurred attempting to read SYSOUT data from a backup tape.

Action:

Resubmit the load request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape. Also, for recovery procedures, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARBCL20

View not found

Reason:

The specified view does not exist in the master index.

Action:

Verify the existence of the view. If the view number was specified incorrectly, change the parameter specification, and then resubmit the load request.

SARBCL21

Index file already resides on disk

Reason:

A load request was issued specifically to load the page index file for the requested SYSOUT group from tape or secondary disk to the CA View database, but the page index file already resides on the disk.

Action:

Since the page index file already resides on disk, the load request is not necessary. If something is wrong with the page index file on the CA View database, the page index file can be deleted and then reloaded.

SARBCL22

Index file was not found on tape or secondary disk

Reason:

A load request was issued specifically to load the page index file for the requested SYSOUT group from tape or secondary disk to the CA View database, but no page index file was generated for the SYSOUT group.

Action:

Re-index or re-archive the report to generate a page index file for the SYSOUT group.

SARBCP02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the specified SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCP03

ID missing

Reason:

The ID parameter is incorrectly specified without a SYSOUT identifier and is required on the control statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be printed, then resubmit the print request.

SARCMT01

Error nnn – Error Class (message text)

Reason:

A non-zero return code is encountered from a Centera API function call. The error code and message is provided. These errors normally indicate network, server, client, or Z/OS errors.

Action:

Centera error messages include an error class to identify where the error occurred.

The error class determines the action:

- FP_NETWORK_ERRORCLASS (network error)—Contact your network support group
- FP_SERVER_ERRORCLASS (Centera cluster error)—Contact EMC Centera Support
- FP_CLIENT_ERRORCLASS (client application error)—Contact Technical Support at <http://ca.com/support>.

SARCMT02

Improper Request Sequence nnn

Reason:

Internal error indicating that the incorrect request is issued during the migration of data to Centera.

Action:

Contact CA Support.

SARCMT03

Processing Terminated

Reason:

The backup cycle or migration task terminated migration of a report. This message is issued when the CA View started task or migration task is brought down while migrating a report to Centera. The report that was being migrated is again migrated the next time the CA View started task or migration task is started.

Action:

None.

SARBCP04

DDname "ddname" not found

Reason:

The JCL DD statement name specified in the DDNAME parameter was not provided.

Action:

Either remove the DDNAME parameter or specify the respective DDNAME.

SARBCP05

Sysout successfully printed

Reason:

The SYSOUT group was successfully queued to print.

Action:

None. This message is informational.

SARBCP06

Sysout successfully written to DDname=ddname

Reason:

The SYSOUT group is successfully copied to the specified JCL DD statement.

Action:

None. This message is informational.

SARBCP07

Sysout queued for transmittal to PC

Reason:

The CA Deliver report is successfully queued for download to a PC. The download process is complete at the user's discretion from the online retrieval interface.

Action:

None. This message is informational.

SARBCP10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before the completion of the print process, or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or sequence number (SEQ) was specified incorrectly. Change the parameter specification, and then resubmit the print request.

SARBCP12

Data set not loaded - already on disk

Reason:

The SYSOUT group is not loaded to the database because it already resides on disk.

Action:

Since the original intent of the load request has been satisfied, no further action is necessary. If the SYSOUT group was incorrectly loaded or is empty, the disk portion the SYSOUT group can be deleted by using the online retrieval facility or batch retrieval facility, and the load request can be resubmitted.

SARBCP13

Requested sysout does not exist on any tape backup data set

Reason:

The SYSOUT group cannot be found on any backup tape.

Action:

None. The SYSOUT group is not available on tape.

SARBCP14

The tape file was not the selected sysout group - use SARTCP to map the tape

Reason:

The SYSOUT group located on the backup tape is not the SYSOUT as referenced in the master index.

Action:

Use the SARTCP utility to map and correct the backup tape.

SARBCP15

Backup tape does not exist

Reason:

The backup tape cannot be found in the master index. This is normally caused by the backup cycle deleting the tape before completion of the load request.

Action:

None. The SYSOUT group is no longer available.

SARBCP16

Dynamic allocation failed for tape file, Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for allocating the backup tape file. The hexadecimal error and information codes are provided.

Action:

Consult the online retrieval HELP facility for a description of the dynamic allocation error code. Take appropriate action to correct the allocation error, and then resubmit the print request.

SARBCP17

I/O error positioning tape

Reason:

A permanent I/O error occurred attempting to position the archival tape to retrieve the SYSOUT group.

Action:

Resubmit the request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape.

SARBCP18

Sysout group is open for output

Reason:

The requested function cannot be performed because the specified SYSOUT group is open for output. The SYSOUT group can be in open status due to a currently pending temporary load operation, a pending migration operation, or initial creation.

Action:

Wait until the status of the SYSOUT group has changed from open status, then resubmit print request. If the open condition is invalid, that is, a system crash or abend occurred while the SYSOUT group was in open status and being processed; use the CLEAN operator command to remove the open status. Two backup cycles and the duration of four hours must have elapsed before the open status is removed.

SARBCP19

Permanent I/O error on input tape

Reason:

A permanent I/O error occurred attempting to read SYSOUT data from a backup tape.

Action:

Resubmit the request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape.

Note: For more information about recovery procedures, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARBCP20

View not found

Reason:

The specified view does not exist in the master index.

Action:

Verify the existence of the view. If the view number was specified incorrectly, change the parameter specification, and then resubmit the print request.

SARBCP21

Dynamic allocation failed for sysout file, Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for allocating the print SYSOUT data set. The hexadecimal error and information codes are provided.

Action:

Consult the online retrieval HELP facility for a description of the dynamic allocation error code. Take appropriate action to correct the allocation error, then resubmit load request.

SARBCP22

OUTADD failed for sysout file, Return code - xxxx, Reason code - xxxx

Reason:

The attempt to dynamically create an OUTPUT statement failed. The return and reason codes are provided. For an explanation of the return and reason codes, refer to the operating system IEFDORC macro.

Action:

The SYSOUT is printed without OUTPUT statement attributes. If you want, make appropriate changes and resubmit the print request.

SARBCP23

PC transmittal queue full - Sysout not queued to PC

Reason:

The PC transmittal queue is full for the user.

Action:

Have the user transmit their queue and clear the entries.

SARBCP24

PC destination invalid - Sysout not queued to pc

Reason:

The destination specified must be of the format PC user ID.

Action:

Correct the destination.

SARBCP25

User not defined - Sysout not queued to PC

Reason:

The user ID specified in the destination is not defined to CA View.

Action:

Correct the destination or define the user ID to CA View.

SARBCP26

Banner page "xxxxxxx" not found; default Banner page "xxxxxxx" being used

Reason:

The requested banner page name is not found in the database, and a default banner page member is used.

Action:

None. If you want, change the banner page name to one that is defined to the database or add the banner page member to the database with the BLOAD function of the SARDBASE utility and resubmit the request.

SARBCP27

Banner page "xxxxxxx" not found; banner pages will not be produced

Reason:

The requested banner page name is not found in the database, and the SYSOUT is printed without banner pages.

Action:

None. If you want, change the banner page name to one that is defined to the database or add the banner page member to the database with the BLOAD function of the SARDBASE utility and resubmit the request.

SARBCP28

Sysout queued for external print

Reason:

The external print request was successfully queued for processing.

Action:

None. This message is informational.

SARBCP30

PRINTER SPECIFICATION CONFLICTS WITH DEST AND/OR DDNAME SPECIFICATION

Reason:

The SARBCH print request has failed because the PRINTER keyword is mutually exclusive with the DEST and/or DDNAME specifications.

Action:

Eliminate either the DEST or DDNAME keyword specifications, then resubmit the print request.

SARBCP31

SELECT specification conflicts with PAGE and/or RECORD specification

Reason:

The SARBCH print request has failed because the SELECT keyword is mutually exclusive with the PAGE and RECORD specifications.

Action:

Eliminate either the SELECT, PAGE, or RECORD keyword specification, then resubmit the print request.

SARBCP32

Sysout is not on primary disk and its index is unavailable for page selection

Reason:

The SARBCH print request specifying the SELECT keyword has failed because the SYSOUT does not reside on disk. The most likely reason for this is that the location is TAPE.

Action:

Reload the SYSOUT to disk. Verify that the index is present, and then resubmit the print request.

SARBCP33

SELECT specified without a valid logical view

Reason:

The SARBCH print request specifying the SELECT keyword has failed because no views exist for the SYSOUT.

Action:

Do one of the following:

- Remove the SELECT keyword, and then resubmit the print request.
- Specify a view number that contained page indexing criteria when the SYSOUT was archived, then resubmit the request.

Note: Page indexing occurs only during archival.

SARBCP34

Error occurred attempting to read in the index for the sysout

Reason:

The SARBCH print request specifying the SELECT keyword has failed because an I/O error occurred while opening or reading the page index data from the database. The data is unreadable.

Action:

Do one of the following:

- Remove the SELECT keyword, and then resubmit the print request.
- Rebuild the page index data as follows:
 1. Reprint the SYSOUT to a held class.
 2. Delete the SYSOUT from CA View
 3. Release the SYSOUT to CA View for re-archival, retaining the same SYSOUT-ID.
 4. Resubmit the print request.

Note: The index can be rebuilt only by re-archiving the SYSOUT.

SARBCP35

Sysout has not been indexed for the logical view or by ACIF

Reason:

The SARBCH print request specifying the SELECT keyword has failed because indexing has not been established for the view.

Action:

Establish indexing criteria for the view if it does not exist. Re-index or re-archive the SYSOUT. Page indexing occurs only during archival.

SARBCP36

No pages found that match selection text

Reason:

The SARBCH print request specifying the SELECT keyword has failed because the SELECT text ID did not match any index selection.

Action:

Check that the SELECT text and index selection criteria are as intended. The SYSOUT must be archived again if the page indexing criteria is changed. Page indexing occurs only during archival.

SARBCP37

User is not authorized to print report from this destination

Reason:

The SARBCH print request has failed because the user exit SARDSTUX has denied the request.

Action:

See your system administrator or specify an authorized destination for the reprint.

SARBCP38

Printing has exceeded the specified maximum number of lines permitted

Reason:

Your print request exceeded the maximum number of lines permitted during a batch or on-line print request. The reprint line limit could have been defined in the VTAM Printer Device Definition, the CA Spool Device Definition, or the OUTLIM Initialization Parameter.

Action:

Do one of the following actions:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Increase the maximum permitted for all devices by using SARINIT parameter OUTLIM.
- Make multiple separate print requests.

SARBCP39

PRINTING VIA CMASPOOL EXCEEDED THE MAXIMUM PERMITTED PRINT LINES

Reason:

Your print request exceeded the maximum number of lines permitted during the CA Spool Print Management print processing. This message can also occur on non-VTAM printers as an indication that an error occurred while printing on both devices simultaneously.

Action:

Do one of the following actions:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Increase the maximum permitted for CA Spool devices by using SARINIT parameter CMAMAX.
- Make multiple separate print requests.

SARBCP40

Error in define device record

Reason:

The DEFine DEVice record is invalid. A record that was not completely defined could cause this error.

Action:

Correct the DEFine DEVice record and retry.

SARBCP41

Requested index not found

Reason:

The page index value specified on the SELECT keyword of the print request is not found for the requested SYSOUT group.

Action:

Verify that the correct page index value, SYSOUT group, and view are being specified; otherwise, remove the SELECT parameter, then print the entire SYSOUT group.

SARBCP42

No TCR record found for requested sysout

Reason:

An attempt is being made to print a SYSOUT group from tape, but certain vital backup tape control information cannot be found.

Action:

Normally, tape control information is retained as long as there are reports that reference it. The tape control record (TCR) can be reinstated by re-adding the tape back into the database with the TADD facility of the SARTDR utility.

Important! This condition could identify a serious problem with the database or problems with the supporting code. Report the problem to CA Technical Support.

SARBCP43

Error during secondary disk or EAS access

Reason:

An error occurred opening a report on optical disk or on tape accessed through an EAS tape server.

Action:

Browse the report online to see any error messages from the DSK2 driver or EAS tape server interface routine.

SARBCP45

Must use CA Output Management Web Viewer to print distributed files

Reason:

Distributed files archived into a CA View database can only be viewed and printed from CA Output Management Web Viewer.

Action:

Access and print the distributed file from the CA Output Management Web Viewer product.

SARBCP46

User not authorized to access view

Reason:

The SARSECUX security user exit or external security has denied access to the logical view of the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCP48

Report print suppressed by SARPRTUX

Reason:

This message is issued by SARBCP when a non-zero return code is returned by SARPRTUX.

Action:

This message is informational, no action is required.

SARBCP49

DSLIS keyword conflicts with SELECT keyword

Reason:

The DSLIS parameter cannot be specified with the SELECT parameter.

Action:

Remove the DSLIS or SELECT parameter specification, then resubmit the print request.

SARBCP50

SYSOUT does not contain data set List information

Reason:

The requested SYSOUT does not have an associated data set list and data set list entries cannot be printed. Data set list information is not captured for SYSOUT archived with a pre-r11.0 release.

Action:

The DSLIS parameter cannot be used to print pages related to data set list information. Specific pages or records can be printed by specifying the PAGE or RECORD parameters.

SARBCP51

DDNAME/STEP/PROCSTEP not found

Reason:

The specified ddname, step name, and/or procedure step name could not be found in the data set list for the SYSOUT.

Action:

Verify the data set list information from online retrieval by entering the "?" line command on the Sysout/Report Selection List panel for the SYSOUT. Correct the DSLIST specification, then resubmit the print request.

SARBCP47

User not authorized to access index

Reason:

The SARSECUX security user exit or external security has denied access to the specified index of the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCT02

Report successfully completed

Reason:

The listing of SYSOUT groups or USERIDs is successfully written to the REPORT DD statement.

Action:

None. This message is informational.

SARBCT03

ID missing

Reason:

No SYSOUT ID was specified in the control card.

Action:

Add a valid id in the ID=.

SARBCT04

Requested sysout is not a Dynamic Report

Reason:

The specified ID is not the SYSOUT of a Dynamic Report.

Action:

Change ID= to a Dynamic Report SYSOUT id.

SARBCT05

User not authorized to access sysout

Reason:

The SYSOUT indicated in the ID control card is not accessible to this user id.

Action:

Consult your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCT06

No undefined distids found for report

Reason:

UNDEF statement was added to the LISTDYND control card but there are no undefined distids for the indicated Dynamic Report.

Action:

None. This message is informational.

SARBCT07**No dynamic distids found for report****Reason:**

The specified dynamic report does not have any associated dynamic distribution identifiers.

Action:

None. This message is informational.

SARBCT08**error message****Reason:**

An error occurred while accessing the CA Deliver database.

Action:

The error message text gives an explanation of the error. If the error message indicated that the CA Deliver interface has not been installed or cannot be found, add the Deliver load library to STEPLIB or JOBLIB and run again.

SARBCT09**Report information incomplete due to access error****Reason:**

The distribute to/description information on the Dynamic Distid Listing report was not available due to access error(s) as indicated by the SARBCT08 message. The report is produced. The distribution to/description field contains text of '***Error***' for those entries that had an access error.

Action:

Refer to the SARBCT08 message for an explanation of the error.

SARBCT10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the list process, or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT groups. If the SYSOUT identifier (ID), and/or generation (GEN) was specified incorrectly, change the parameter specification, and then resubmit the list request.

SARBCT11

Requested User(s) not found in master index

Reason:

The requested user ID does not exist in the master index. This is normally caused by an incorrect specification of the USER parameter or the user ID was already deleted by another job or user by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the user ID. If the user ID (USER parameter) was specified incorrectly, change the parameter specification, and then resubmit the list request.

SARBCT12

USER keyword conflicts with EXCP/GEN/ID/FORMAT Keyword(s)

Reason:

The USER parameter cannot be specified with the EXCP, GEN, ID, and/or SEQ parameter.

Action:

Either remove the USER parameter or remove the EXCP, GEN, ID, and/or FORMAT parameters from the control statement, and then resubmit the list request.

SARBCT13

User not authorized to list Userid(s)

Reason:

The USERID extracted by the SARUSBUX utility does not have sufficient authority (master authority) to list USERIDs from the database. The USERID that requires authority is indicated in the SARBCH05 message.

Action:

Consult your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBCT14

REPORT DD statement missing

Reason:

The REPORT JCL DD statement was not provided and is required for the control statement.

Action:

Specify the REPORT JCL DD statement, and then resubmit the job.

SARBCT15

VIEW keyword conflicts with EXCP/GEN/ID/FORM Keyword(s).

Reason:

When listing a logical view definition, these keywords are not permitted.

Action:

Remove the mutually exclusive keywords.

SARBCT16

User not authorized to list Logical View(s).

Reason:

Listing a logical view definition requires MASTER authority.

Action:

Request that the job be run by a user with master authority.

SARBCT17

Requested logical view(s) not found in master index

Reason:

The requested logical view definitions do not exist in the master index. This is usually caused by an incorrect specification of the VIEW parameter.

Action:

Verify the existence of the logical view definitions. If the logical view definition (VIEW parameter) was specified incorrectly, change the parameter specification and then resubmit the list request.

SARBCT21

More than 99 Column Headings defined

Reason:

The SARBCH LISTVIEW function processed a logical view definition with more than 99 column headings.

Action:

Change the logical view to use 99 or less column headings.

SARBCU02

USER=
PASSWORD=
MASTER=
DISTMASK=
DISTID=
ACC=
MODE=
BANNER=
LANGUAGE=
PRINTER=
PBANNER=
PCLASS=
PDEST=
PWRITER=
ABANNER=
ACCLASS=
ADEST=
PWRITER=
JCL1=
JCL2=
JCL3=
JCL4=

Reason:

This message identifies the profile attributes of the online user after processing the DEFUSER request.

Action:

None. This message is informational.

SARBCU03

User successfully added

Reason:

The online user and profile attributes are successfully added to the CA View database. This message is accompanied by the SARBCU02 message that details the user profile information.

Action:

None. This message is informational.

SARBCU04

User successfully modified

Reason:

The online user and profile attributes for an existing user were successfully changed. This message is accompanied by the SARBCU02 message, which details the user profile information.

Action:

None. This message is informational.

SARBCU05

Sysout/Distid successfully defined

Reason:

The SYSOUT and DISTID references used to qualify selection of SYSOUT for online users in SAR mode have been successfully added to the CA View database.

Action:

None. This message is informational.

SARBCU12

User not authorized to perform DEFINE function

Reason:

Master authority is required to perform the DEFDIST, DEFSYS, or DEFUSER request.

Action:

Consult with your security administrator or systems programming group to determine the reasons why the authorization was not provided.

SARBCU13

User not authorized to perform add or update

Reason:

The SARSECUX security exit or external security has denied authorization to create or update a user, SYSOUT, or distribution definition.

Action:

Consult with your security administrator or systems programming group to determine the reasons why the authorization was not provided.

SARBCU15

Mode must be "ALL", "EXPO", "EXP", "SARO" or "SAR"

Reason:

The parameter specification for the MODE keyword on the DEFUSER control statement is invalid. The acceptable values are ALL, EXPO, EXP, SARO, or SAR.

Action:

Correct the MODE keyword specification on the DEFUSER control statement, then resubmit the define request.

SARBCU16

Userid not supplied

Reason:

The USER keyword was not specified, or a user ID is not supplied with the USER keyword. The USER parameter is required on the DEFUSER control statement.

Action:

Correct or add the USER keyword specification on the DEFUSER control statement, then resubmit the define request.

SARBCU17

Distid does not conform to distid mask specification

Reason:

The distribution identifier specified on the DISTID keyword of the DEFUSER request does not match the masking pattern of the DISTID mask.

Action:

Either change the distribution identifier on the DISTID keyword to conform to the DISTID mask or change the DISTID mask to encompass the specification of the specified distribution identifier.

SARBCU18

Access to specified mode denied by access indicators

Reason:

The access mode specified on the MODE parameter of the DEFUSER control statement is not accessible based on the access mode indicators defined to the user.

Action:

Either change the access mode specified on the MODE parameter to an accessible mode or change the access mode indicators to allow access to the specified access mode.

SARBCU19

Access mode indicators invalid

Reason:

The access mode indicator specification on the ACC parameter of the DEFUSER control statement is not valid. The access mode indicator specification can be Y or N for each of the five access modes, ALL, EXPO, EXP, SARO, and SAR, respectively.

Action:

Correct the specification of the access mode indicators on the ACC parameter, and then resubmit the define request.

SARBCU20

USER or SYSOUT parameter not supplied

Reason:

The USER keyword is not specified on the DEFUSER control statement, or the SYSOUT keyword is not specified on the DEFDIST or DEFSYS control statement.

Action:

Add the appropriate keyword specification to the define request, and then resubmit the request.

SARBCU21

Distid is missing for defining Sysout/Distid

Reason:

The DISTID keyword is not specified on the DEFDIST or DEFSYS control statement and is required.

Action:

Add the DISTID keyword specification to the define request, and then resubmit the request.

SARBCU22

I/O error

Reason:

An error occurred while reading or writing data from the CA View database. This message must be accompanied by a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARBCU23

Invalid language or its panels not found in database

Reason:

The online panels for the specified language are not found in the CA View database. When the LANGUAGE keyword is specified on the DEFUSER control statement, the CA View database is queried for the online member name SAxRP1, where x is the language specification. This error message is generated when that online member is not found.

Action:

Load the appropriate language panels into the CA View database or specify a language that is defined to your CA View database.

SARBCV02

VIEW=
NUM=
USER=
FILTER=
SECURED=
DESC=
DEFAULT=
LOCKLEFT=
DISPCC=
EXCPAGES=
EXCRECS=
DISPRECS=
ACL1=
AHL1=
ACL2=
AHL2=
ALINES=
HSCROLL=

Reason:

This message identifies the profile attributes of the online View definition after processing the DEFVIEW request.

Action:

None. This message is informational.

SARBCV03

View successfully added**Reason:**

The online View attributes are successfully added to the CA View database. This message is accompanied by the SARBCV02 message that details the View definition information.

Action:

None. This message is informational.

SARBCV04

User successfully modified**Reason:**

The online View attributes for an existing definition were successfully changed. This message is accompanied by the SARBCV02 message, which details the View definition information.

Action:

None. This message is informational.

SARBCV05

I/O error**Reason:**

An error occurred while reading or writing data from the CA View database. This message is to be accompanied by a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARBCV06

VIEW parameter not supplied or invalid

Reason:

The VIEW keyword on the DEFVIEW control statement was not specified or is invalid.

Action:

Correct the VIEW keyword specification on the DEFVIEW control statement, and then resubmit the request.

SARBCV07

ALINE parameter may not exceed 9

Reason:

The ALINE keyword value specified on the DEFVIEW control statement was greater than 9. Valid ALINE keyword values are 1 through 9.

Action:

Correct the ALINE keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV08

EXCRECS parameter may not exceed 60

Reason:

The EXCRECS keyword value specified on the DEFVIEW control statement was greater than 60. Valid EXCRECS keyword values are 1 through 60.

Action:

Correct the EXCRECS keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV09

DISPRECS parameter may not exceed 254

Reason:

The DISPRECS keyword value specified on the DEFVIEW control statement was greater than 254. Valid DISPRECS keyword values are 1 through 254.

Action:

Correct the DISPRECS keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV10

EXCRECS + DISPRECS parameters may not exceed 254'

Reason:

The total EXCRECS and DISPRECS keyword values specified on the DEFVIEW control statement was greater than 254. The total value specified on the EXCRECS and DISPRECS keywords cannot exceed 254.

Action:

Correct the EXCRECS and or DISPRECS keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV11

Invalid RC=12, I/O ERROR from SARGVCR

Reason:

An I/O error occurred while attempting to index data for the referenced report.

Action:

Correct the I/O error by re-indexing the report. If problems continue, restore the database.

SARBCV12

Invalid RC=16, PARAMETER ERROR from SARGVCR

Reason:

An internal parameter error occurred while attempting to index data for the referenced report.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARBCV13

A value must be specified for NUM; valid values are 1-255.

Reason:

The NUM keyword value specified on the DEFVIEW control statement is 0. Valid NUM keyword values are 1 through 255.

Action:

Correct the NUM keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV14

NUM parameter may not exceed 255

Reason:

The NUM keyword value specified on the DEFVIEW control statement is greater than 255. Valid NUM keyword values are 1 through 255.

Action:

Correct the NUM keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV15

ALINES value of 0 is invalid

Reason:

The ALINES keyword value specified on the DEFVIEW control statement is 0. Valid ALINES keyword values are 1 through 9.

Action:

Correct the ALINES keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV16

ACL1 or ACL2 value invalid, valid values are B, R, P, G, T, Y, or W

Reason:

The ACL1 or ACL2 keyword value specified on the DEFVIEW control statement is invalid. Valid ACL1 and ACL2 keyword values are B, R, P, G, T, Y, or W.

Action:

Correct the ACL1 or ACL2 keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV17

AHL1 or AHL2 value invalid, valid values are B, R, or U

Reason:

The AHL1 or AHL2 keyword value specified on the DEFVIEW control statement is invalid. Valid AHL1 and AHL2 keyword values are B, R, or U.

Action:

Correct the AHL1 or AHL2 keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV18

FILTER value invalid

Reason:

The FILTER keyword value specified on the DEFVIEW control statement contains invalid characters. Valid FILTER characters are limited to alphanumeric, national, and limited special characters.

Action:

Correct the FILTER keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV19

xxxxxxx subparameter n is invalid

Reason:

The DEFVIEW statement keyword xxxxxxx subparameter number n is not valid.

Action:

Correct the keyword and then resubmit the define request.

SARBCV20

HDGn parameter missing

Reason:

The DEFVIEW SEARCH keyword refers to an undefined DEFVIEW HDGn (HDG1-HDG99) keyword.

Action:

Correct the SEARCH keyword specification or add the missing HDGn keyword on the DEFVIEW control statement, and then resubmit the define request.

SARBCV21

CLRn value invalid, valid values are B, R, P, G, T, Y, or W

Reason:

The CLRn (CLR1-CLR6) keyword value specified on the DEFVIEW control statement is invalid. Valid CLRn keyword values are B, R, P, G, T, Y, or W.

Action:

Correct the CLRn keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV22

HLTn value invalid, valid values are B, R, or U

Reason:

The HLTn (HLT1-HLT6) keyword value specified on the DEFVIEW control statement is invalid. Valid HLTn keyword values are B, R, or U.

Action:

Correct the HLTn keyword specification on the DEFVIEW control statement, and then resubmit the define request.

SARBCV23

View definition too large

Reason:

View definition record exceeds maximum length.

Action:

Reduce HEADING, COLUMN, HDGn, or SEARCH definitions on the DEFVIEW control statement, and then resubmit the define request.

SARBCV24

View definition too many entries

Reason:

HEADING, COLUMN, HDGn, or SEARCH definition contains more than 255 entries.

Action:

Reduce the number of HEADING, COLUMN, HDGn, or SEARCH entries on the DEFVIEW control statement, and then resubmit the define request.

SARBCV25

COLUMN definition missing

Reason:

HDGn definitions specified without corresponding COLUMN definitions.

Action:

Either delete the HDGn definitions or add the corresponding COLUMN definitions on the DEFVIEW control statement, and then resubmit the define request.

SARBCV26

User not authorized to perform DEFVIEW function

Reason:

The SARSECUX security exit or external security has denied authorization to perform DEFVIEW function.

Action:

Consult your security administrator or systems programming group to determine the reasons why the authorization was not provided.

SARBCV27

User not authorized to perform add or update view

Reason:

The SARSECUX security exit or external security has denied authorization to create or update the logical view definition.

Action:

Consult your security administrator or systems programming group to determine the reasons why the authorization was not provided.

SARBCX02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security did not allow access to the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reasons why the authorization was not provided.

SARBCX03

ID missing

Reason:

The ID parameter is specified without a SYSOUT identifier, which is required on the control statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be extracted, then resubmit the extract request.

SARBCX04

CA Balance extraction program is not installed or is not available

Reason:

The CA Balancing Report Control (CA Balancing) extraction program, INBEXTP, was not found.

Action:

Ensure that the INBEXTP load module is accessible from the STEPLIB, JOBLIB, or the linklist; resubmit the request.

SARBCX05

CA Balance extraction completed successfully

Reason:

The CA Balancing extraction for the request SYSOUT group completed successfully.

Action:

None. This message is informational.

SARBCX06

CA Balance extraction completed (warning messages were issued)

Reason:

The CA Balancing extraction completed, but there were warning messages that were issued.

Action:

Review the warning message to determine if action is necessary.

SARBCX07

CA Balance extraction unsuccessful

Reason:

The CA Balancing extraction was unsuccessful due to a previous error.

Action:

Refer to the previous error to determine the appropriate action.

SARBCX10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before completion of the extract process, or the manual deletion of the SYSOUT group by using the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or the sequence number (SEQ) were specified incorrectly, change the parameter specification. Then resubmit the load request.

SARBCX12

Data set not loaded - already on disk

Reason:

The SYSOUT group is not loaded to the CA View database because it already resides on disk. Initial processing of the extract request determined that the SYSOUT group that resides on tape or secondary disk must be loaded to the CA View database to perform the extraction. Later, it was determined that the SYSOUT group is reloaded by another batch or online request.

Action:

Resubmit the extract request.

SARBCX13

Requested sysout does not exist on any tape backup data set

Reason:

The SYSOUT group cannot be found on any tape backup.

Action:

None. The SYSOUT group is not available on tape.

SARBCX14

The tape file was not the selected sysout group - use SARTCP to map the tape

Reason:

The SYSOUT group located on the backup tape is not the same as the one that is referenced in the master index.

Action:

Use the SARTCP utility to map and correct the backup tape.

SARBCX15

Backup tape does not exist

Reason:

The backup tape cannot be found in the master index. This is normally caused by the backup cycle deleting the tape before completion of the load request.

Action:

None. The SYSOUT group is no longer available.

SARBCX16

Dynamic allocation failed for tape file, Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for allocating the backup tape file. The hexadecimal error and information codes are provided.

Action:

Consult the online retrieval help facility for a description of the dynamic allocation error code. Take appropriate action to correct the allocation error, and then resubmit the extract request.

SARBCX17

I/O error positioning tape

Reason:

A permanent I/O error occurred attempting to position the archival tape to retrieve the SYSOUT group.

Action:

Resubmit the request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape.

SARBCX18

Sysout group is open for output

Reason:

The requested function cannot be performed because the specified SYSOUT group is open for output. The SYSOUT group can be in open status due to a currently pending temporary load operation, a pending migration operation, or initial creation.

Action:

Wait until the status of the SYSOUT group has changed from open status, and then resubmit the extract request. If the open condition is invalid (for example, a system crash or an abend occurred while the SYSOUT group was in open status and being processed) use the CLEAN operator command to remove the open status. Two backup cycles and the duration of four hours must have elapsed before the open status is removed.

SARBCX19

Permanent I/O error on input tape

Reason:

A permanent I/O error occurred attempting to read SYSOUT data from a backup tape.

Action:

Resubmit the extract request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape. In addition, for recovery procedures, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARBKT00

{STANDARD|INTERIM} BACKUP CYCLE STARTED FOR GEN *nnn* ON *ddddddd* AT *ttttttt*

Reason:

A CA View backup cycle has been initiated.

Action:

None. This message is informational.

SARBKT50

SYSOUT GROUP *xxxxxxxxxxxx* SKIPPED DUE TO PREVIOUS I/O ERROR

Reason:

An I/O error occurred attempting to backup the specified SYSOUT group. The remainder of the SYSOUT group is skipped.

Action:

Probably none; however, verify that there is no major problem with the database.

SARBKT51

Sysout group *xxxxxxx* not deleted due to previous I/O error

Reason:

An I/O error occurred attempting to delete the specified SYSOUT group. The group is not deleted.

Action:

Probably none; however, verify that there is no major problem with the database.

SARBKT52

*****WARNING*** RUN SARPAC TO COPY TAPES FOLLOWING MERGE OF DATABASES**

Reason:

The database contains references to tape volumes owned by another database. This condition is the result of a database merge.

Action:

Run SARPAC to copy the SYSOUT groups on tape to new tape volumes owned by this database.

SARBKT53**SYSOUT ALLOCATION ERROR CODE - *xxxx*, INFO CODE - *xxxx*****Reason:**

A dynamic allocation request for allocating the print data set to SYSOUT failed. The hexadecimal error and information codes are provided.

Action:

Determine the reason for the failure and fix the problem. Then resubmit the job.

SARBKT55**RECOVERY DATASET FILE ERROR - OPER=*xxxx*, RC=*nn*****Reason:**

Error attempting to access the recovery data set. The CA View backup cycle is terminated.

Action:

None. If a hardware error is not indicated, contact CA Technical Support.

SARBKT56**NO SARRECV DD STATEMENT - RECOVERY DATASET NOT UPDATED****Reason:**

There is no DD statement for the backup recovery file in the started task.

Action:

None, if you wish to run without the backup recovery file. Otherwise, change the started task JCL and restart.

SARBKT57**ERROR DETERMINING IF OPEN SYSOUT STILL BEING PROCESSED. RC= *xx*****Reason:**

The CA View started task issues the IEFSSREQ macro to verify that a SYSOUT is not yet being written to the CA View database when the backup cycle attempts to migrate it off disk. The IEFSSREQ macro had a return code of *xx*.

Action:

See the IBM documentation for return codes for the IEFSSREQ macro.

SARBKT58

UNEXPECTED IEFSSREQ RETURN CODE. RC=xx

Reason:

The CA View started task issues the IEFSSREQ macro to verify that a SYSOUT is not yet being written to the CA View database when the backup cycle attempts to migrate it off disk. The IEFSSREQ macro had a return code of xx. Field SSOBRETN contained an unanticipated value. This could be caused by changes to JES control blocks SSOB and SSCS.

Action:

See the IBM documentation for return codes for the IEFSSREQ macro.

SARBKT59

SYSOUT GROUP xxxxxxxx NOT DELETED DUE TO PREVIOUS ERROR

Reason:

This message is issued after message SARBKT57 or SARBKT58. It indicates that the identified SYSOUT sub-file data was to have been deleted from disk because it has expired through the NGEND initialization parameter value. Because the attempt to verify that the SYSOUT group was not still being processed failed, it is not deleted from disk.

Action:

See the IBM documentation for the IEFSSREQ return code indicated in the previously issued SARBKT57 or SARBKT58 message. Possibly, use the DD online command to manually change the location to TAPE to free the allocated disk space.

SARBKT60

SYSOUT GROUP xxxxxxxx NOT DELETED SINCE IT IS STILL BEING PROCESSED

Reason:

The CA View started task discovered a SYSOUT was still in OPEN status. This message is issued when the IEFSSREQ macro verifies whether the sysout is still being written to disk.

This message can also be produced during the backup cycle if a temporary ACIF resource subfile exists on the database. The SYSOUT group name references a report that does not appear to exist. This circumstance can occur when the ACIF Printer subtask (FSA) is terminated and then restarted without also terminating the FSS Collector at the same time an AFP report is being archived. A temporary ACIF resource subfile created during the archival process remains on the database until the FSS Collector is recycled, even though the report and associated resources were archived normally once the FSA restarted.

Action:

None. If the message persists, and you want to free the disk space, use the C online command to change the location from OPEN to DISK. With the next backup cycle, the partial SYSOUT is backed up to tape unless you delete it first.

If the message is caused by a temporary ACIF resource subfile, then the SYSOUT GROUP name shows the four character System Id followed by the eight character job number of the FSS Collector task. This temporary resource subfile can be residual from a database full condition. The backup cycle produces the message until the FSS Collector is stopped and restarted

SARBKT61

{STANDARD|INTERIM} BACKUP CYCLE STARTING PHASE *n*

Reason:

This message identifies which internal backup phase is beginning. Phase 1 backs up the current generation to tape and performs ERO processing. Phase 2 backs up the master index to tape, deletes expired reports, and uncatalogs expired tapes.

Action:

None. This message is informational.

SARBKT62

{STANDARD|INTERIM} BACKUP CYCLE ENDING PHASE *n* OF *nnn* REPORTS ON DATABASE, *nnn* WERE PROCESSED

Reason:

This message identifies which internal backup phase is ending. The number of reports on the database includes those that are not currently on DASD (they are on tape). The number processed only includes those in the current generation. Because archiving can continue during the backup, these numbers can change from backup phase to backup phase.

Action:

None. This message is informational..

SARBKT63

{STANDARD|INTERIM} PHASE *n* PROCESSING *rrrrrr*, ARCHIVED ON *dddd* AT *tttt*

Reason:

This message is a progress report issued during a backup. It appears at intervals specified by the SARINIT parameter DBMSGFRQ.

Action:

None. This message is informational.

SARBKT65

UNABLE TO DELETE SYSOUT GROUP *xxxxxxxx* FROM SECONDARY DISK

Reason:

An error occurred attempting to delete the report form optical disk.

Action:

Verify that the optical device is functioning properly.

SARBKT66

***stor-group-name* STORAGE GROUP IS BEING COPIED TO TAPE**

Reason:

The named storage group is being copied from disk to tape. STORGRP0 is named DEFAULT by CA View.

Action:

None. This message is informational.

SARBKT70

CLEAN PROCESSING STARTED

Reason:

Clean processing has been initiated.

Action:

None. This message is informational.

SARBKT71

CLEAN PROCESSING ENDED

Reason:

Clean processing has completed.

Action:

None. This message is informational.

SARBKT72

CLEAN=NO CLEAN PROCESSING BYPASSED

Reason:

The Initialization parameter CLEAN has been set to NO and the clean processing is not performed and is bypassed.

Action:

None. This message is informational.

SARBKT73

Secondary Disk Migration initialized

Reason:

Secondary disk migration is scheduled for this backup cycle and driver initialization has completed successfully.

Action:

None. Informational message.

SARBKT74

Secondary Disk Migration ended, xxx reports migrated and yyy reports deleted to/from secondary disk

Reason:

Secondary disk migration ended and xxx reports have been migrated to secondary disk and yyy reports have expired from secondary disk.

Action:

None. Informational message.

SARBKT99

BACKUP CYCLE ENDED FOR GEN *nnn* ON dddddd AT tttttt

Reason:

Backup cycle ended.

Action:

None. This message is informational.

SARBKT9A

CURRENT GENERATION IS {NOW|STILL} *nnn*

Reason:

Issued with SARBKT99 to advise you of current archival generation and whether the generation number has changed because of the just completed backup.

Action:

None. This message is informational.

SARBKU02**DIRECT TO TAPE ARCHIVAL SUSPENDED FOR COMPLETION OF BACKUP CYCLE****Reason:**

Direct-to-tape archival must be suspended until the backup cycle has completed.

Action:

None. Direct-to-tape archival resumes following completion of the backup cycle.

SARBKU03**ARCHIVAL SUSPENDED FOR COMPLETION OF BACKUP CYCLE****Reason:**

Another backup cycle has been started, possibly by the operator or due to insufficient storage, and so on. SYSOUT archival must be suspended until the backup cycle has completed.

Action:

None. This message is informational.

SARBKU04**TERMINATION SUSPENDED FOR COMPLETION OF BACKUP CYCLE****Reason:**

The operator has attempted to stop SAR with a P command. The SYSOUT archival termination must be suspended until the backup cycle has completed.

Action:

None. This message is informational.

SARBKU05**{STANDARD|INTERIM} BACKUP BYPASSED PER STACKBU=NO****Reason:**

The request for the type of backup indicated (standard or interim) has been ignored since to honor it would cause multiple backups to queue and you have specified STACKBU=NO as an initialization parameter.

Action:

None. This message is informational.

SARBKU06

***database-name* BACKUP BYPASSED DUE TO RECOVERY PROCESS**

Reason:

The backup cycle is bypassed because a SARDBASE RESTORE operation is in progress. The backup cycle scratches the old recovery files and creates new ones, but SARDBASE RESTORE is reading the old recovery files.

Action:

None. This message is informational.

SARBKU07

Backup cycle is running - Reply W (wait) to wait for it to complete or T (terminate)

Invalid reply

Reason:

You attempted to stop the archival task with a STOP (P) operator command while a backup cycle was running. This message gives you the option of having CA View terminate its backup.

Warning! If you cause CA View to terminate its backup, it will continue from where it left off the next time it is brought up. This is a consideration if you are using a tape management system, and canceling a tape backup job could result in the tape being scratched.

Action:

Reply W to let the backup cycle complete running or T to terminate it.

Note: If the backup cycle terminates before an operator response is received, the Archival Task (SARSTC) terminates normally and the outstanding operation action message is canceled.

SARBKU08

```

SARBKU08 *****
SARBKU08 * WARNING: The current generation number *
SARBKU08 * is going to exceed the allowable limit. *
SARBKU08 *****

```

Reason:

The database's generation number is greater than 32759 and is approaching the maximum limit of 32767.

Action:

See the action plan for message SARBKU09.

SARBKU09

Backup cycle bypassed, maximum generation number reached**Reason:**

The database's generation number has reached its maximum limit of 32767. No standard backup cycles run until this condition is resolved.

Action:

The database must be unloaded and merged to a new empty database. SARDBASE/MERGE re-sequence the Sysout generation numbers based on the oldest Sysout in the database, correcting the high generation number.

SARBKU30

```

*****
*                                     *
*   BACKUP ABENDED WITH CODE xxxx   *
*                                     *
*****

```

Reason:

The CA View backup cycle has abended. The system or user abend code is provided.

Action:

Consult the *IBM MVS System Messages* manual to determine the reason for the abend. If you still cannot determine the problem, for assistance contact CA Technical Support.

SARBPC01

MODEL BANNER PAGE "xxxxxxxx" NOT FOUND

Reason:

The model banner page cannot be found in the database.

Action:

Correct the model banner page name if it is in error, or add the model banner page member to the database with the BLOAD function of the SARDBASE utility.

SARBPC02

CARD *nnn* INVALID CONTROL CARD /xxxxxx

Reason:

Record number *nnn* of the model banner page definition contains an invalid control statement.

Action:

Correct the statement and reload the model banner page member into the database with the BLOAD function of the SARDBASE utility.

SARBPC03

CARD *nnn* NO TERMINATOR FOR SYMBOLIC VARIABLE xxxxxxxxxxxx

Reason:

The symbolic variable in record number *nnn* of the model banner page definition is missing its terminator.

Action:

Correct the symbolic variable and reload the model banner page member into the database with the BLOAD function of the SARDBASE utility.

SARBPC04

CARD *nnn* EXTRANEIOUS DATA IN SYMBOLIC FIELD xxxxxxxx

Reason:

The symbolic field following the variable name in record number *nnn* of the model banner page definition is not blank.

Action:

Correct the symbolic field and reload the model banner page member into the database with the BLOAD function of the SARDBASE utility.

SARBPC05

CARD *nnn* INVALID SYMBOLIC VARIABLE xxxxxxxxxxx+

Reason:

The symbolic variable in record number *nnn* of the model banner page definition is not in the correct syntax.

Action:

Correct the symbolic variable and reload the model banner page member into the database with the BLOAD function of the SARDBASE utility.

SARBPC06

CARD *nnn* MISSING SYMBOLIC VARIABLE NAME

Reason:

Record number *nnn* contains a symbolic field without any variable name.

Action:

Correct the symbolic field and reload the model banner page member into the database with the BLOAD function of the SARDBASE utility.

SARBPT01

Allocation failed for sysout data set, Code=xxxx Info=xxxx

Reason:

CA View was not able to allocate space for the SYSOUT data set indicated in the error message.

Action:

Correct and retry.

SARBPT02

No distribution identifiers for bundle

Reason:

No distribution identifiers for the report exist.

Action:

Correct and retry.

SARBPT03

No reports defined for distribution identifier

Reason:

No reports exist for the distribution identifier.

Action:

Correct and retry.

SARBPT05

The tape contained a null file for the sysout group

Reason:

A file on the mounted tape is null.

Action:

Correct and retry.

SARBPT06

The tape file was not the selected sysout group - Use SARTCP to map the tape

Reason:

The file specified is not the selected group.

Action:

Correct and retry.

SARBPT07

Backup tape does not exist

Reason:

The backup tape specified does not exist.

Action:

Correct and retry.

SARBPT08

Tape alloc error, Code=xxxx Info=xxxx

Reason:

Tape allocation was not possible because of reasons referenced by code.

Action:

Correct and retry.

SARBPT09

I/O error positioning tape

Reason:

I/O was not possible because of error positioning the tape.

Action:

Correct and retry.

SARBPT10

Sysout group is open for output

Reason:

The SYSOUT group specified is open for output.

Action:

Correct and retry.

SARBPT11

OUTADD failed for sysout file, Code=xxxx Reason=xxxx

Reason:

The attempt to dynamically create an OUTPUT statement failed. The return and reason codes are provided. For an explanation of the return and reason codes, refer to the operating system IEFDORC macro.

Action:

The bundle or portions of the bundle are printed without OUTPUT statement attributes. If you want, make appropriate changes and resubmit the bundle print request.

SARBPT12

Permanent I/O error on input tape

Reason:

A permanent I/O error occurred when reading the tape.

Action:

Use SARTCP to correct the problem with the tape.

SARBPX02

User not authorized to access sysout

Reason:

The SARSECUX security user exit or external security does not allow access to the specified SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBPX03

ID missing**Reason:**

The ID parameter is incorrectly specified without a SYSOUT identifier and is required on the PRINTIDX statement.

Action:

Change the ID parameter to include the SYSOUT identifier that is to be printed, and then resubmit the print request.

SARBPX04

DDname "ddname" not found**Reason:**

The JCL statement name specified in the DDNAME parameter of the PRINTIDX statement of the SARBCH utility was not provided.

Action:

Either remove the DDNAME parameter or specify the respective DDNAME.

SARBPX05

Index successfully printed**Reason:**

The index for the SYSOUT group was successfully queued to print.

Action:

None. This message is informational.

SARBPX06

Index successfully written to DDname=ddname**Reason:**

The index for the SYSOUT group is successfully copied to the specified JCL DD statement.

Action:

None. This message is informational.

SARBPX10

Requested sysout not found in master index

Reason:

The requested SYSOUT group does not exist in the master index. This is normally caused by a misspelled SYSOUT identifier, a backup cycle deleting the SYSOUT group before the completion of the print process, or the manual deletion of the SYSOUT group by using the online retrieval facility or the batch retrieval facility (SARBCH).

Action:

Verify the existence of the SYSOUT group. If the SYSOUT identifier (ID), generation (GEN), and/or the sequence number (SEQ) was specified incorrectly, change the parameter specification, and then resubmit the print request.

SARBPX11

View not found

Reason:

The requested logical view for the SYSOUT group does not exist in the master index. This is normally caused by a mistyped logical view number or by the deletion of the logical view from the online retrieval facility or batch retrieval facility (SARBCH).

Action:

Verify the existence of the logical view for the SYSOUT group. If the logical view (VIEW) was specified incorrectly, change the parameter specification, and then resubmit the print request.

SARBPX12

Requested index not found

Reason:

The requested index for the SYSOUT group was not found.

Action:

Verify the existence of the index for the SYSOUT group. If the index was specified incorrectly, change the parameter specification, and then resubmit the print request. If the index data does not exist for the SYSOUT group, the SYSOUT group can be re-indexed from the online retrieval facility or batch retrieval facility (SARBCH).

SARBPX13

Index is not on primary disk and its index is unavailable for page selection

Reason:

The index data for the SYSOUT group does not reside in the database, and access is not available from the Expanded Access Server (EAS).

Action:

Start the appropriate Expanded Access Server (EAS) task, or load the index data for the SYSOUT group to disk using the online retrieval facility or batch retrieval facility (SARBCH) and resubmit the print request.

SARBPX14

VIEW or INDEX keyword not specified

Reason:

The VIEW or INDEX parameter was not specified and is required on the PRINTIDX control statement.

Action:

Add the VIEW or INDEX parameter to the PRINTIDX statement and resubmit the print request.

SARBPX15

Excessive number of SELECT values for requested index

Reason:

A unique selection value can be specified for each index field for a logical view index, ACIF index, or XPPS index to limit the amount of index data that is printed. The SELECT parameter specified values that do not correspond to an index field for the requested index.

Action:

Correct or remove the SELECT parameter and resubmit the request.

SARBPX16

No index data found that matches SELECT values

Reason:

Index data that corresponds to the SELECT parameter is not found for the requested index.

Action:

Verify that the SELECT parameter references the correct values. If the SELECT parameter was specified incorrectly, correct the parameter and resubmit the print request.

SARBPX17

Invalid destination

Reason:

Index data cannot be queued for download to a PC user or printed using the external print interface.

Action:

Change the print destination (DEST) to a valid destination and resubmit the print request.

SARBPX18

User is not authorized to print report from this destination

Reason:

The SARBCH print request failed because the SARDSTUX user exit denied printing to the requested destination.

Action:

See your system administrator or specify an authorized destination for the reprint.

SARBPX21

Dynamic allocation failed for sysout file, Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for allocating the print SYSOUT data set. The hexadecimal error and information codes are provided.

Action:

Consult the online retrieval HELP facility for a description of the dynamic allocation error code. Take appropriate action to correct the allocation error, and then resubmit the print request.

SARBPX22

OUTADD failed for sysout file, Return code - xxxx, Reason code - xxxx

Reason:

The attempt to dynamically create an OUTPUT statement failed. The return and reason codes are provided. For an explanation of the return and reason codes, refer to the operating system IEFDORC macro.

Action:

The index for the SYSOUT group is printed without OUTPUT statement attributes. If you want, make appropriate changes and resubmit the print request.

SARBPX23

Error in device record

Reason:

The DEFINE DEVICE record is invalid. A record that was not completely defined could cause this error.

Action:

Correct the DEFINE DEVICE record and resubmit.

SARBPX24

Error occurred attempting to read index data

Reason:

An I/O error occurred while opening or reading the index data for a SYSOUT group. The data is unreadable.

Action:

Do one of the following actions:

- Reload the index data for the SYSOUT group to the database using the online retrieval facility or batch retrieval facility and resubmit the print request.
- Rebuild the page index data using the batch retrieval facility and resubmit the print request.

SARBPX25

Sysout has not been indexed for the logical view or by ACIF

Reason:

The requested index for the SYSOUT group was not found.

Action:

Verify the existence of the index for the SYSOUT group. If the index is specified incorrectly, change the parameter specification and resubmit the print request. If the index data does not exist for the SYSOUT group, the SYSOUT group can be re-indexed from the online batch retrieval facility or batch retrieval facility (SARBCH).

SARBPX28

Online printing to a VTAM printer exceeded the maximum permitted print lines

Reason:

Your print request exceeded the maximum number of lines permitted during online VTAM print processing. This message can also occur on non-VTAM printers as an indication that an error occurred while printing on both devices simultaneously.

Action:

Do one of the following actions:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEVice facility.
- Increase the maximum permitted for all devices by using the SARINIT parameter VPRTMAXO.

SARBPX29

Printing via CA Spool exceeded the maximum permitted print lines

Reason:

Your print request exceeded the maximum number of lines permitted during CA Spool print processing. This message can also occur on non-VTAM printers as an indication that an error occurred while printing on both devices simultaneously.

Action:

Do one of the following actions:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Increase the maximum permitted for CA Spool devices by using SARINIT parameter CMAMAX.
- Make multiple separate print requests.

SARBPX46

User not authorized to access view

Reason:

The SARSECUX security user exit or external security has denied access to the logical view of the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARBPX47

User not authorized to access index

Reason:

The SARSECUX security user exit or external security has denied access to the specified index of the SYSOUT group.

Action:

Consult with your security administrator or systems programming group to determine the reason why the authorization was not provided.

SARCAS00S

```
*****
*
*
*   CENTERA ACCESS SERVER
*
* SARCAS (XXXX) HAS ABENDED WITH CODE XXXXX *
*
* ***** RESTART SARCAS ASAP *****
*
*
*****
```

Reason:

The CENTERA access server has abended. The system or user abend code is provided.

Action:

See the IBM MVS System Messages Guide to determine the reason for the abend. If you still cannot determine the problem, contact CA Technical Support at <http://ca.com/support>.

SARCAS01S

```
SARCAS (xxxx) TASK HAS ABENDED WITH CODE XXXXX TASK=xxxxxxxx,
REQUEST=xxxxxxxx, TYPE=N, REQUESTER=xxxxxxxx
```

Reason:

A Centera processing thread has abended. The system or user abend code, TCB address, process request entry address, process request type, and requester's job ID are provided.

Action:

Consult the IBM MVS System Messages Guide to determine the reason for the abend. For assistance, contact Technical Support at <http://ca.com/support>.

Note: The task is restarted automatically and processing continues.

SARCAS02I**TASK WILL BE RESTARTED FOR SARCAS (jobname/sysid)****Reason:**

A Centera processing thread of the expanded access server for tape and robotics has abended and is being restarted automatically.

Action:

None. This message is informational.

SARCAS04I**NUMBER OF PROCESS REQUEST ENTRIES FOR SARCAS (jobname/sysid) ALLOCATED=N, HIGH WATER=N****Reason:**

This message is displayed whenever the server is stopped. You can use the information provided to adjust the NREQ initialization parameter.

Action:

None. This message is informational.

SARCAS09S**PRIMARY SERVER IS ALREADY ACTIVE FOR SARCAS (jobname/sysid)****Reason:**

The primary server is already active and cannot be started again.

Action:

None. This message is informational.

SARCAS10S**SARCAS (xxxx) IS ALREADY ACTIVE****Reason:**

The server is already active on this system and cannot be started again.

Action:

None. This message is informational.

SARCAS11W

INVALID COMMAND FOR SARCAS (jobname/sysid) Command=xxxxxxxxxxxxxxxxxxxx

Reason:

The specified operator command is invalid.

Action:

Reissue the operator command in its correct form.

SARCAS12W

**INVALID INITIALIZATION PARAMETER FOR SARCAS (jobname/sysid)
KEYWORD=xxxxxxx, VALUE=xxxxxxx**

Reason:

The specified parameter is invalid. The server uses the default value for the parameter and continues processing.

Action:

Correct the initialization parameter in the start procedure JCL.

SARCAS13W

**INVALID SERVER TYPE FOR SARCAS (JOBNAME/SYSID)
KEYWORD=xxxxxxx,VALUE=xxxxxxx**

Reason:

The specified server type is invalid. The server uses the default value ONLY for the server type and continues processing.

Action:

Correct the initialization parameter in the start procedure JCL.

SARCAS15I

**THE FOLLOWING PARAMETERS ARE BEING USED FOR SARCAS SARCA 16I
(JOBNAME/SYSID): KEYWORD = VALUE**

Reason:

A listing of the parameters used by the server is provided at startup time.

Action:

None. This message is informational.

SARCAS17W

**XCF xxxx REQUEST FAILED FOR SARCAS (JOBNAME/SYSID), RETURN=xxxx,
REASON=xxxx**

Reason:

The specified XCF request failed. The hexadecimal return and reason codes are provided.

Action:

For the return and reason codes to determine the cause of the failure, see the IBM Authorized Assembler Reference Guide. If you still cannot determine the problem, contact CA Technical Support at <http://ca.com/support>.

SARCAS19W

**INVALID COMMUNICATION MECHANISM FOR SARCAS (JOBNAME/SYSID)
KEYWORD=xxxxxxxx,VALUE=xxxxxxxx**

Reason:

The specified communication mechanism is invalid. The server uses the default value XCF for the communication mechanism and continues processing.

Action:

Correct the initialization parameter in the start procedure JCL.

SARCAS20I

COMMUNICATIONS RESET FOR SARCAS (jobname/sysid)

Reason:

The COMMRESET operator command was successfully executed.

Action:

None. This message is informational.

SARCAS22W

Unable to modify NTHREADS to nnn for SARCAS Maximum value is xxx Current value is yyy

This message number represents one of the following messages:

Unable to modify NTHREADS to nnn for SARCAS (taskname/smfid) Maximum value is xxx. Current value is yyy.

Reason:

SARCAS has processed a modify NTHREADS command request and rejected the new value (nnn) for NTHREADS. xxx is the value that was specified when the task was started, and yyy is the current value for NTHREADS.

Action:

Correct the NTHREADS value. This value cannot exceed what was defined when the task was started.

SARCAS23I

NTHREADS modified to nnn for SARCAS (taskname/smfid)

Reason:

SARCAS has processed a modify NTHREADS command request and accepted the new value (nnn) for NTHREADS.

Action:

None. This message is informational.

SARCAS27S

Unable to access EMC Centera API modules

Reason:

The EMC Centera API modules (FPAPIDLL, FPMZDZDLL, FPPOSDDL, FPPAIDLL, and/or XERCES26) were not found. This message occurs if a release 3.0 or prior EMC Centera load library is referenced.

Action:

Add the EMC Centera load library to JOBLIB, STEPLIB, or the link list. The EMC Centera load library can also be copied to CVDELOAD.

SARCAS28S

Unsupported version of EMC Centera API modules

Reason:

An unsupported version of the EMC Centera API modules is found in JOBLIB, STEPLIB, or the link list.

Action:

Add the EMC Centera load library distribute with CA View to JOBLIB, STEPLIB, or the link list. The EMC Centera load library can also be copied to CVDELOAD.

SARCEN01

Centera access server is not active

Reason:

The SARCAS server whose name appears in the CENTNAME parameter is not active.

Action:

See your system administrator to determine why SARCAS is not active. Generally, CA View attempts to directly mount the volume containing the report.

SARCEN02

Centera access primary server is not active

Reason:

The primary server (responsible for access to the Centera Cluster) is not active.

Action:

See your system administrator to determine why SARCAS is not active.

SARCEN03

Centera access server abended

Reason:

A severe problem has occurred in the Centera EAS Task.

Action:

Collect the appropriate information for problem analysis, and then see your system administrator to restart the server.

SARCEN05

Centera timeout exceeded - Retry later

Reason:

An attempt is made to view a report directly from Centera, using the Centera Access Server. After one minute, the Centera Access Server (SARCAS) did not return any data.

Action:

Retry later.

SARCEN06

Unable to locate page record vector

Reason:

You are viewing a tape report, and the Centera Access Server was unable to locate a page record vector.

Action:

See your system administrator. Each report's page record vector is located using a field in the GCR in the DASD database. The report could have been damaged. The system administrator can restore the report from the tape backup and can migrate another copy, after which you must be able to access it.

SARCEN08

End of data

Reason:

A report on Centera storage tape was being viewed using the Centera access server. The END OF DATA was unexpectedly reached.

Action:

The report's mapping information could have been overwritten. The system administrator can restore the report from the tape backup and can migrate another copy.

SARCEN09

Sysout group is not on Centera storage

Reason:

An attempt is made to view a report on Centera storage, but the report is not found on the Centera device.

Action:

See your system administrator. The system administrator can restore the report from the tape backup and can migrate another copy.

SARCEN11

Logical I/O error on Centera - ID=REPORTID GEN=NNNNN SEQ=NNNNN

Reason:

An attempt is made to view a report on tape using the Centera access server, and an I/O error was encountered.

Action:

See your system administrator. The system administrator can restore the report from the tape backup and can migrate another copy.

SARCEN12

Centera migration subtask terminated

Reason:

An internal error has occurred.

Action:

The migration sub-task has unexpectedly terminated. Add an FPCONFIG DD Statement to failing task. The FPCONFIG statement must point to a symbolic data set which contains the name of the Centera API Trace file (see System Reference Guide). Rerun the task and provide CA Technical Support with the data collected in the Centera API Trace file. For assistance, contact Technical Support at <http://ca.com/support>.

SARCEN13

**Insufficient storage available to access report - ID=REPORTID GEN=NNNNN
SEQ=NNNNN**

Reason:

An internal error has occurred.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARCEN14

Corrupted GCR record - ID=REPORTID GEN=NNNNN SEQ=NNNNN

Reason:

An internal error occurred. SARCEN14 does not recognize the format of this GCR.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARCEN27

Unable to access EMC Centera API modules

Reason:

The EMC Centera API modules (FPAPIDLL, FPMDZDLL, FPPOSDLL, FPPAIDLL, and/or XERCES26) were not found. This message occurs if a release 3.0 or prior EMC Centera load library is referenced.

Action:

Add the EMC Centera load library to JOBLIB, STEPLIB, or the link list. The EMC Centera load library can also be copied to CVDELOAD.

SARCEN28

Unsupported version of EMC Centera API modules

Reason:

An unsupported version of the EMC Centera API modules is found in JOBLIB, STEPLIB, or the link list.

Action:

Add the EMC Centera load library distribute with CA View to JOBLIB, STEPLIB, or the link list. The EMC Centera load library can also be copied to CVDELOAD.

SARCIC01

CA VIEW 12.1 TERMINATED

Reason:

SYSOUT archival was terminated.

Action:

None. This message is informational.

SARCIC02

CA VIEW 12.1 ABENDED

Reason:

The CA View CICS conversational interface has abended.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARCMA01

CA Spool XXXXX failed on XXXXXXXX, RC=XX

Reason:

This message is issued when CA Spool rejected a request made by CA View in an unexpected fashion (no other more specific error message applies). *fffff* is the function, which can be OPEN, WRITE, or CLOSE. *ddddddd* is the target CA Spool device. *rr* is the CA Spool return condition found in the CA Spool parameter list field @OPENSTA. *ppp* is only present when the error is an invalid CA Spool parameter list, and identifies the unacceptable parameter as found in the CA Spool parameter list field @OPENPID.

Action:

Check the CA Spool documentation for the return condition that was found.

SARCMA02

CA Spool not available for XXXXXXXX

Reason:

CA Spool rejected a CA View open request because the CA Spool subsystem is not available. *ddddddd* is the target CA Spool device.

Action:

Bring up the CA Spool subsystem. If the problem still occurs, verify that the SARINIT parameter CMASPOOL= has the same value as the CA Spool ESFPARM parameter SUBID=. If you are using the CA View DEFine DEvIce facility, and have overridden the SARINIT CMASPOOL parameter by specifying SUB-SYSTEM ID, then it must be the same as the CA Spool ESFPARM SUBID= parameter.

SARCMA03

CA Spool full for XXXXXXXX

Reason:

The CA Spool database is full. *ddddddd* is the target CA Spool device.

Action:

Make room in the CA Spool database by either waiting for SYSOUT to finish printing, deleting items, or making the database larger.

SARCMA04**CA Spool device XXXXXXXX does not exist****Reason:**

You are trying to print to a device that is not defined to CA Spool. *ddddddd* is the target CA Spool device.

Action:

Specify a device that is already defined to CA Spool, or define the new device to CA Spool.

SARCMA05**CA Spool interface program ESF xxxx****Reason:**

The installation of the CA View-to-CA Spool interface was not finished. It requires a link-edit of the AESFPRIV routine provided on the user's CA Spool distribution tape into the SARCMAIX program provided on the CA View distribution tape. *ddddddd* is the target CA Spool device.

Action:

Finish the installation.

SARCMA06**CMASPOOL INVALID INTERNAL REQUEST FOR *ddddddd*****Reason:**

CA View posted an unacceptable request code to CA Spool. *ddddddd* is the target CA Spool device.

Action:

Contact CA Technical Support.

SARCMT01

Error *nnn* message

Reason:

A non zero return code is encountered from a Centera API function call. The error code and message are provided. These errors normally indicate network errors, server errors, client errors, or Z/OS errors.

Action:

Centera error messages include a message class to identify where the error occurred.

The class of message:

- FP_NETWORK_ERRORCLASS (network error) - Contact your network support group
- FP_SERVER_ERRORCLASS (Centera cluster error) - Contact EMC Centera Support
- FP_CLIENT_ERRORCLASS (client application error) – Contact Technical Support at <http://ca.com/support>.

SARCMT02

Improper Request Sequence *nnn*

Reason:

Internal error indicating that the incorrect request is issued during the migration of data to Centera.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARCMT03

Processing Terminated

Reason:

The backup cycle or migration task terminated migration of a report. This message is issued when the CA View started task or migration task is brought down while migrating a report to Centera. The report that was being migrated will be re-migrated the next time the CA View started task or migration task is started.

Action:

None.

SARCOP03

NO SELECTABLE REPORTS FOR USERS DISTRIBUTION ID

Reason:

The distribution ID referenced in the CA View user profile is not defined, or it has no reports defined to it. For EXP mode users, the DISTID and applicable reports are defined in CA Deliver. For SAR mode users, the DISTID and applicable reports are defined in CA View.

Action:

To produce lists of reports for the user, reports must be defined to the associated DISTID with CA Deliver (for EXP mode users) or CA View (for SAR mode users).

SARCOP04

UNABLE TO QUALIFY SELECTION OF REPORT DUE TO MISSING CA DELIVER INTERFACE ROUTINE (RMOGAM).

Reason:

The library containing the RMOGAM module is not defined to the DRAS task or is not accessible.

Action:

Add the CA Deliver load library to the STEPLIB or JOBLIB concatenation for the DRAS job or started task, or add the CA Deliver load library to the linklist.

SARCPI01

Sysout is not on primary disk

Reason:

A SYSOUT must be on the primary disk to be indexed.

Action:

Reload the SYSOUT to disk (Online L Command or SARBCH LOAD), then resubmit the index request.

SARCP102

No index specified for this sysout

Reason:

No page separation criteria is specified with any logical view for this SYSOUT.

Action:

Specify the desired page separation criteria online, with at least one logical view definition.

SARCP103

Can't find sysout in database

Reason:

An I/O error occurred opening the SYSOUT.

Action:

Report the problem to your CA View administrator.

SARCP104

Report end-of-data not found

Reason:

An I/O error occurred reading the SYSOUT.

Action:

Report the problem to your CA View administrator.

SARCP105

Can't allocate subfile for the new page index

Reason:

The database is possibly out of space.

Action:

Run SARDBASE STATUS, to check the percentage of utilization of the database. If the utilization is high, report the problem to your CA View administrator for appropriate action.

SARCP106

Error writing last block of new page index

Reason:

An I/O error occurred writing the page index, possibly because the database is out of space.

Action:

Report the problem to your CA View administrator.

SARCP107

Error updating group control record

Reason:

An I/O error occurred updating the SYSOUT Group Control Record.

Action:

Report the problem to your CA View administrator.

SARCP108

Error deleting old page index

Reason:

An I/O error occurred when deleting the old page index.

Action:

Report the problem to your CA View administrator.

SARCP109

New page index has been created

Reason:

A new page index has been created.

Action:

None. This message is informational.

SARCPI10

Error rewriting group control record

Reason:

An I/O error occurred rewriting the SYSOUT Group Control Record.

Action:

Report the problem to your CA View administrator.

SARCPI11

Error writing page index to new subfile

Reason:

The database is possibly out of space.

Action:

Run SARDBASE STATUS, to check the percentage of utilization of the database.

SARCPI12

Error on get of database index

Reason:

A database I/O error occurred.

Action:

Report the problem to your CA View administrator.

SARCPI13

Can't create page index for ACIF sysout

Reason:

SARBCH INDEX cannot index An AFP report, archived using the AFP Conversion and Indexing Facility (ACIF).

Action:

AFP reports are indexed with ACIF index control statements. For more information, see Indexing AFP Reports in the chapter "Archival" in the *Reference Guide*.

SARCPI14

Sysout is being loaded

Reason:

The requested SYSOUT is being loaded to disk to perform index extraction for the report.

Action:

None. This message is informational.

SARCPI15

Can't create page index for distributed files

Reason:

Indexing data cannot be extracted for distributed files.

Action:

None.

SARCPR01

Invalid entry code nnn

Reason:

An internal error has occurred within CA View.

Action:

Contact Technical Support.

SARCPR02

Invalid key designation xx - Entry=nnn

Reason:

An internal error has occurred within CA View.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARCST01

CICS SUBTASK STARTED

Reason:

The CICS interface subtask has been started.

Action:

None. This message is informational.

SARCST02

CICS SUBTASK ENDED

Reason:

The CICS interface subtask has ended.

Action:

None. This message is informational.

SARCTE01

SUBTASK IS NOT ACTIVE

Reason:

A request has been made to deactivate the CA View CICS subtask, but the subtask is already inactive.

Action:

None.

SARCTE02

ACTIVE SESSIONS USING SUBTASK - ENTER Y/N TO FORCE TERMINATION

Reason:

A request has been made to deactivate the CA View CICS subtask, but active users were found.

Action:

Enter Y to force termination, or N to cancel subtask inactivation.

SARCTE03

SUBTASK NOT TERMINATED

Reason:

Unable to terminate the CICS interface subtask.

Action:

Correct the problem and retry.

SARCTE04

SUBTASK SUCCESSFULLY TERMINATED

Reason:

The CICS interface subtask has been successfully terminated.

Action:

None. This message is informational.

SARD0001

Invalid index name

Reason:

The index prefix in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0002

Invalid unit name

Reason:

The unit name in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0005

Invalid blksize

Reason:

The block size in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0006

Catalog error RC=XXXX.XXXX.XXXX, DSN=DSNAME

Reason:

A catalog management error was received when attempting to catalog the data set. The decimal value of registers 15, 0, and 1 are provided.

Action:

Determine the reason for the catalog error, and then correct the problem.

SARD0007

No access under VM/CMS, reload sysout group to database

Reason:

The optical disk device cannot be accessed directly from VM/CMS.

Action:

Use the L selection code to submit a batch job to temporarily load the SYSOUT group to primary disk so that it can be accessed.

SARD0008

End of data

Reason:

An unexpected end of data condition was encountered when accessing the SYSOUT group on secondary disk storage. This condition must never happen.

Action:

Delete and re-archive the SYSOUT group.

SARD0009**Sysout group is not on secondary disk storage****Reason:**

The SYSOUT group is identified in the master index as residing on secondary disk storage, but it cannot be found there.

Action:

Delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0010**System abend XXX creating DSN=****Reason:**

The driver is abnormally terminated by the system when attempting to create a data set. The abend code is provided.

Action:

Determine the reason for the abnormal termination and correct the problem.

SARD0011**Dynamic alloc err, LOC=nn, ERR=xxxx-xxxx, DSN=dsname****Reason:**

A dynamic allocation request for allocating a data set failed. The hexadecimal error and information codes are provided.

Action:

Determine the reason for the allocation failure and correct the problem.

SARD0013**Logical error processing DSN=****Reason:**

The internal format of the archived SYSOUT group is in error and cannot be used.

Action:

Delete and re-archive the SYSOUT group.

SARD0101

Invalid unit name

Reason:

The unit name in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0102

Invalid low volser

Reason:

The low or high volume serial number in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0103

Invalid high volser

Reason:

The low or high volume serial number in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0104

Low/high volser specified without the other

Reason:

Only one volume serial number for the range of volume serial numbers in the DSK2PARAM initialization parameter was specified.

Action:

Specify both volume serial numbers for the range.

SARD0105**Low/high volser does not end with a numeric****Reason:**

Either the low or high volume serial is specified without a numeric character as its last character.

Action:

Review and correct the specified volume serial.

SARD0106**Low and high volsers are different formats****Reason:**

When specifying a range of volume serial numbers in the DSK2PARAM initialization parameter, the volume serial numbers must be the same format.

Action:

Correct the volume serial numbers.

SARD0107**No access under VM/CMS, reload sysout group to database****Reason:**

The optical disk device cannot be accessed directly from VM/CMS.

Action:

Use the L selection code to submit a batch job to temporarily load the SYSOUT group to primary disk so it can be accessed.

SARD0108**End of data****Reason:**

An unexpected end of data condition was encountered when accessing the SYSOUT group on secondary disk storage.

Action:

Delete and re-archive the SYSOUT group.

SARD0109

Sysout group is not on secondary disk storage

Reason:

The SYSOUT group is identified in the master index as residing on secondary disk storage, but it cannot be found there.

Action:

Delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0111

Error processing output file on secondary disk

Reason:

An error occurred when writing to the optical disk device.

Action:

Correct the problem with the optical disk device.

SARD0120

Sysout group not found

Reason:

The SYSOUT group has been deleted by another user between the time the selection list was created and the time you made your request to access the SYSOUT group.

Action:

None. The SYSOUT group is no longer archived.

SARD0121

Dynamic allocation Err=xxxx, Info=xxxx

Reason:

A dynamic allocation request for allocating the secondary disk storage copy failed. The hexadecimal error and information codes are provided.

Action:

Determine the reason for the allocation failure and correct the problem.

SARD0122

Positioning error

Reason:

An error occurred attempting to position the secondary disk storage emulation tape to retrieve the SYSOUT group.

Action:

Resubmit the request. If the problem occurs again, then the SYSOUT group can no longer be accessed from secondary disk. You can then delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0123

I/O error on secondary disk

Reason:

An I/O error occurred attempting to access the secondary disk storage emulation tape.

Action:

Resubmit the request. If the problem occurs again, then the SYSOUT group can no longer be accessed from secondary disk. You can then delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0201

Invalid index name

Reason:

The index prefix in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0202

Invalid account number

Reason:

The account identification code in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0203

Invalid account password

Reason:

The account password in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0204

Invalid storage machine id

Reason:

The storage machine identifier in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0205

Unable to load LSMCALL

Reason:

When loading the FileTek Callable Interface, module LSMCALL cannot be found.

Action:

Verify that the FileTek Callable Interface library is available to the step.

SARD0207

No access under VM/CMS, reload sysout group to database

Reason:

The optical disk device cannot be accessed directly from VM/CMS.

Action:

Use the L selection code to submit a batch job to temporarily load the SYSOUT group to primary disk so it can be accessed.

SARD0208

End of data

Reason:

An unexpected end of data condition was encountered when accessing the SYSOUT group on secondary disk storage. This condition must never happen.

Action:

Delete and re-archive the SYSOUT group.

SARD0209

Sysout group is not on secondary disk storage

Reason:

The SYSOUT group is identified in the master index as residing on secondary disk storage, but it cannot be found there.

Action:

Delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0301

Invalid index name

Reason:

The index prefix in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0302

Invalid account number

Reason:

The account identification code in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0303

Invalid account password

Reason:

The account password in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0304

Invalid storage machine id

Reason:

The storage machine identifier in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0305

Unable to load LSMCALL

Reason:

When loading the FileTek Callable Interface, module LSMCALL cannot be found.

Action:

Verify that the FileTek Callable Interface library is available to the step.

SARD0308

End of data

Reason:

An unexpected end of data condition was encountered when accessing the SYSOUT group on secondary disk storage. This condition must never happen.

Action:

Delete and re-archive the SYSOUT group.

SARD0309**Sysout group is not on secondary disk storage****Reason:**

The SYSOUT group is identified in the master index as residing on secondary disk storage, but it cannot be found there.

Action:

Delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0310**This message number represents one of the following messages:****No more platters in juke box - Reply R (retry), T (terminate)****Invalid reply****Reason:**

CA View is waiting for more platters to be inserted into the FILETEK jukebox.

Action:

Reply R after the platters are inserted or T to terminate optical migration. Any other response is an invalid reply.

SARD0311**Error return code xxxx from FILETEK LSMCALL****Reason:**

CA View was accessing the FILETEK jukebox when the preceding error occurred.

Action:

For the LSMCALL macro return codes, refer to the documentation provided by FILETEK.

SARD0313**Logical error processing DSN=****Reason:**

The internal format of the archived SYSOUT group is in error and cannot be used.

Action:

Delete and re-archive the SYSOUT group.

SARD0401

Invalid unit name

Reason:

The unit name in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0402

Invalid low volser

Reason:

The low or high volume serial number in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0403

Invalid high volser

Reason:

The low or high volume serial number in the DSK2PARM initialization parameter is invalid.

Action:

Correct the value.

SARD0404

Low/high volser specified without the other

Reason:

Only one volume serial number for the range of volume serial numbers in the DSK2PARM initialization parameter was specified.

Action:

Specify both volume serial numbers for the range.

SARD0405**Low/high volser does not end with a numeric****Reason:**

Either the low or high volume serial is specified without a numeric character as its last character.

Action:

Review and correct the specified volume serial.

SARD0406**Low and high volsers are different formats****Reason:**

When specifying a range of volume serial numbers in the DSK2PARM initialization parameter, the volume serial numbers must be of the same format.

Action:

Correct the volume serial numbers.

SARD0408**End of data****Reason:**

An unexpected end of data condition was encountered when accessing the SYSOUT group on secondary disk storage.

Action:

Delete and re-archive the SYSOUT group.

SARD0409**Sysout group is not on secondary disk storage****Reason:**

The SYSOUT group is identified in the master index as residing on secondary disk storage, but it cannot be found there.

Action:

Delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0411

Error processing output file on secondary disk

Reason:

An error occurred when writing to the optical disk device.

Action:

Correct the problem with the optical disk device.

SARD0413

Unable to load MDRSCALL

Reason:

When loading MDRS, the MDRSCALL module cannot be found.

Action:

Verify that the MDRS library is available to the step.

SARD0414

Invalid MDRS subsystem id

Reason:

The specified subsystem ID is not defined to MDRS for a connected optical disk device.

Action:

Check that the specified subsystem ID is correct for the desired optical disk device.

SARD0420

Secondary disk volume not found

Reason:

The requested emulated tape volume cannot be found on the optical disk device. This condition could occur if the tape volume was deleted before your request for access.

Action:

Check the requested volume serials for validity.

SARD0421

MDRS interface error RC=xxxx

Reason:

The Data/Ware MDRS interface has encountered an error.

Action:

Consult your Data/Ware MDRS documentation for the meaning of the return code.

SARD0501

Invalid index name

Reason:

The index prefix in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0502

Invalid storage class

Reason:

The storage class in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0503

Invalid management class

Reason:

The management class in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0504

Invalid DB2 system id

INVALID DB2 SYSTEM ID

Reason:

The DB2 system ID in the DSK2PARAM initialization parameter is invalid.

Action:

Correct the value.

SARD0506

system request failed, RC=xxxx, Reason=xxxx ID=reportid GEN=nnnnn SEQ=nnnnn

Reason:

The OAM or DB2 request failed with the specified return and reason codes.

Action:

For a list of reason and return codes, see the Object Access Method Application Programmer's Reference.

SARD0508

End of data

Reason:

An unexpected end of data condition was encountered when accessing the SYSOUT group on secondary disk storage.

Action:

Delete and re-archive the SYSOUT group.

SARD0509

Sysout group is not on secondary disk storage

Reason:

The SYSOUT group is identified in the master index as residing on secondary disk storage, but it cannot be found there.

Action:

Delete the disk copy of the SYSOUT group to enable the tape copy to be accessed.

SARD0513

Logical error processing DSN=**Reason:**

The internal format of the archived SYSOUT group is in error and cannot be used.

Action:

Delete and re-archive the SYSOUT group.

SARD2M01

No database high-level index specified**Reason:**

No database high-level index is specified in the SARDSK2B batch job for optical disk migration.

Action:

Rerun the job with the appropriate parameters.

SARD2M02

No PCR record found in database**Reason:**

ERO (Expanded Retention Option) settings are not specified for this database.

Action:

Verify that you have implemented the Expanded Retention Option for the reports in the database.

Note: For more information, see the chapter "Expanded Retention Option" in the *Reference Guide*.

SARD2M03

DSK2DRVR must be specified with SARINIT**Reason:**

No DSK2DRVR parameter is specified in the SARINIT job.

Action:

Specify the appropriate DSK2DRVR parameter for the optical device you are using.

SARD2M04

Error loading DSK2DRVR

Reason:

An error occurred loading the secondary disk driver.

Action:

Verify that the DSK2DRVR ERO initialization parameter is appropriately specified (00, 01, 02, and so on).

SARD2M05

Error initializing DSK2DRVR

Reason:

An error occurred initializing the secondary (optical) disk driver.

Action:

Verify that all components of your optical system, including hardware, OAM (if it is used) and so forth, are properly working. If the problem persists, contact CA Technical Support.

SARD2M06

Error initializing SARPAR

Reason:

An error occurred while initializing ERO (Expanded Retention Option).

Action:

Verify that the SARPATAB DD statement is specified in your CA View started task JCL (SARSTC), and that the correct name of the table is specified.

SARD2M07

Error finalizing SARPAR

Reason:

An error occurred while finalizing ERO (Expanded Retention Option).

Action:

Verify that your ERO table is valid. If the problem persists, contact CA Technical Support.

SARD2M51**Sysout group xxxxxxxx not deleted due to previous I/O error****Reason:**

The SYSOUT group was not deleted from secondary disk due to an I/O error.

Action:

See the discussion and action for the previously issued I/O error message.

SARD2M63**Secondary disk migration reading GCR for: rptid, Gen nn Seq nn****Reason:**

This informational message is issued every 10 minutes, when the optical migration subtask is reading the GCRs (Group Control Records) from the disk database.

Action:

None. This message is informational.

SARD2M97**Secondary disk migration ended due to backup****Reason:**

The backup cycle began running, so the optical migration subtask stopped.

Action:

None. This message is informational.

SARD2M98**Secondary disk migration ended due to DSK2MIGD****Reason:**

Since the ERO initialization parameter DSK2MIGD parameter had an N specified (no migration), optical migration has ended.

Action:

None. This message is informational.

SARD2M99

Secondary disk migration ended scheduled time range

Reason:

This message is informational.

Action:

None. This message is informational.

SARDBA01

DATASET SUCCESSFULLY ADDED TO DATABASE

DSNAME:	<i>dsname</i>
UNIT REQUESTED:	<i>unit</i>
VOLUME SERIAL NO.:	<i>volser</i>
CYLINDERS:	<i>nnnnn</i>
BLOCKS:	<i>nnnnn</i>
BLOCK SIZE:	<i>nnnnn</i>
MANAGEMENT CLASS:	<i>mgmtclass</i>
STORAGE CLASS:	<i>storclass</i>
DATA CLASS:	<i>dataclass</i>

Reason:

The requested space has been added to the database. Physical attributes of the newly added data set are provided. Non-SMS data sets are shown as having a management, storage, and data class of NON-SMS.

Action:

None. This message is informational.

SARDBA02

DATABASE SUCCESSFULLY RENAMED

Reason:

The database was successfully renamed.

Action:

None. This is an informational message.

SARDBA03

**DATABASE SUCCESSFULLY DELETED
INDEX FILE(S) SUCCESSFULLY DELETED
DATA FILE(S) SUCCESSFULLY DELETED**

This message ID represents one of these messages.

Reason:

The database, index file data sets, or data file data sets were successfully deleted.

Action:

None. This is an informational message.

SARDBA04

INVALID CONTROL STATEMENT OPERATION

Reason:

The control statement has an invalid operator.

Action:

Correct the control statement, and then resubmit the job.

SARDBA05

INVALID OR MISSING HIGH-LEVEL INDEX NAME

Reason:

The high-level index name is missing or invalid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA06

INVALID VOLUME SERIAL NUMBER

Reason:

The volume serial number is invalid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA07

INVALID OR MISSING CYLINDER SPECIFICATION

Reason:

The number of cylinders specification is invalid or missing.

Action:

Correct the control statement, and then resubmit the job.

SARDBA08

INVALID UNIT NAME

Reason:

The unit name is missing or invalid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA09

This message number represents one of the following messages:

STATUS OF DATABASE *xxxxxxxxxxxxxxxxxxxx at release xx.x*

INDEX FILE STATISTICS:

BLOCK SIZE:	<i>nnnnnnnn</i>
TOTAL CYLINDERS:	<i>nnnnnnnn</i>
TOTAL BLOCKS:	<i>nnnnnnnn</i>
TOTAL USED BLOCKS:	<i>nnnnnnnn</i>
PERCENT UTILIZATION:	<i>nnnnnnnn</i>
TOTAL LEVELS:	<i>nnnnnnnn</i>
TOTAL RECORDS:	<i>nnnnnnnn</i>
TOTAL ALLOCATIONS:	<i>nnnnnnnn</i>
TOTAL POINTER BLOCKS:	<i>nnnnnnnn</i>
TOTAL DATA BLOCKS:	<i>nnnnnnnn</i>
TOTAL EMPTY BLOCKS	<i>nnnnnnnn</i>

DATA FILE STATISTICS:

BLOCK SIZE:	<i>nnnnnnnn</i>
TOTAL CYLINDERS:	<i>nnnnnnnn</i>
TOTAL BLOCKS:	<i>nnnnnnnn</i>
TOTAL USED BLOCKS:	<i>nnnnnnnn</i>
PERCENT UTILIZATION:	<i>nnnnnnnn</i>

DATA SET *xx*

CYLINDERS:	<i>nnnnnnnn</i>
BLOCKS:	<i>nnnnnnnn</i>
USED BLOCKS:	<i>nnnnnnnn</i>
ERROR BLOCKS:	<i>nnnnnnnn</i>

SARDBA09 **NO LOCK CURRENTLY HELD ON DATABASE**
LOCK HELD BY *userid* **ON** *date* **AT** *time*

Note: One of these messages may be issued if a lock file has been created for the database:

Reason:

A request for the status of the database was made with the SARDBASE STATUS command. Statistics on the database are presented. Depending on the options specified, statistics on the index are also presented.

Note: For more information about the STATUS control statement and the SARDBA09 index statistics, see STATUS in the chapter "Database Utilities" in the *Reference Guide*.

Action:

None. This message is informational.

SARDBA10

DATABASE SUCCESSFULLY COPIED

Reason:

The database was successfully copied.

Action:

None. This is an informational message.

SARDBA11

INDEX FILE SUCCESSFULLY OUTPUT

Reason:

The master index is successfully written to the sequential output file.

Action:

None. This message is informational.

SARDBA12

ONLINE LIBRARY MEMBERS SUCCESSFULLY LOADED

Reason:

The online library members are successfully loaded to the database.

Action:

None. This message is informational.

SARDBA13

INVALID OPERAND operand

Reason:

The specified operand is invalid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA14

INVALID RELATIVE GENERATION NUMBER

Reason:

The relative generation number that is specified is invalid or a backup of the relative generation does not exist.

Action:

Correct the control statement, and then resubmit the job.

SARDBA15

AUTHORIZATION FAILED

Reason:

The user is not authorized to perform the requested function.

Action:

Contact the appropriate personnel to obtain authorization to perform the function.

SARDBA16

DATABASE INDEX SUCCESSFULLY REORGANIZED

Reason:

The database INDEX was successfully reorganized.

Action:

None. This is an informational message.

SARDBA17

DATABASE SUCCESSFULLY RESTORED

Reason:

The database was successfully restored.

Action:

None. This is an informational message.

SARDBA18

DATABASE SUCCESSFULLY LOADED

Reason:

The database was successfully loaded.

Action:

None. This is an informational message.

SARDBA19

DATABASE SUCCESSFULLY UNLOADED

Reason:

The database was successfully unloaded.

Action:

None. This is an informational message.

SARDBA20

DATABASE SUCCESSFULLY VERIFIED

Reason:

The database was successfully verified.

Action:

None. This is an informational message.

SARDBA21

VERIFICATION TERMINATED - UNCORRECTABLE ERROR

Reason:

A critical error as indicated by previous SARDBV and/or SARDVP messages disallowed successful completion of the verify process.

Action:

The recovery process must be accomplished by using the RESTORE control statement of the SARDBASE utility.

Note: For more information, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARDBA22**LOCK DATASET SUCCESSFULLY CREATED****Reason:**

The lock data set was successfully allocated and formatted.

Action:

None. This is an informational message.

SARDBA23**LOCK DATASET SUCCESSFULLY DELETED****Reason:**

The lock data set was successfully deleted.

Action:

None. This is an informational message.

SARDBA24**NO LOCK CURRENTLY HELD ON DATABASE****Reason:**

The unlock function of the SARDBASE utility attempted to release a lock held on the lock data set but no lock existed.

Action:

None. This is an informational message.

SARDBA25**LOCK HELD BY *name* ON *mm/dd/yy* AT *hh:mm:ss* SUCCESSFULLY RELEASED****Reason:**

The lock held to the lock data set was unsuccessfully released.

Action:

None. This is an informational message.

SARDBA26

DATABASES SUCCESSFULLY MERGED

Reason:

The databases were successfully merged.

Action:

None. If the newly merged database contains backup tapes from the merge process, run the SARPAC utility to copy the SYSOUT groups on tape to new tape volumes owned by this database.

SARDBA27

INVALID HIGH-LEVEL INDEX TAPE INDEX

Reason:

The high-level tape index name indicated on the MERGE control statement is invalid. The tape index name is from 1 to 17 bytes and must conform to data set naming conventions.

Action:

Correct the tape index name, and then resubmit the job.

SARDBA28

INVALID SECONDARY DISK DRIVER

Reason:

A syntax error is present in the secondary disk driver specification of the MERGE control statement.

Action:

Verify that the secondary disk driver specification is the same as the DSK2DRVR initialization parameter. Check to see that it is the name of an accessible authorized load module.

SARDBA29

INVALID SECONDARY DISK PARAMETERS

Reason:

A syntax error is present in the secondary disk driver parameters specification of the MERGE control statement.

Action:

For the parameters required, see the chapter "Using the Optical Disk Interface" in the *Reference Guide*.

SARDBA30

NO LOCK DATASET EXISTS

Reason:

This message indicates that a SARDBASE UNLOCK request was entered; however, the database does not have an associated VM lock file.

Action:

None. This is an informational message.

SARDBA31

INVALID BLOCKSIZE

Reason:

The block size is invalid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA32

INVALID DATABASE RELEASE LEVEL

Reason:

The CA View programs being used are not at the same release level as what is specified in the SARDBASE control statement.

Action:

Verify the STEPLIB or linklisted version of the programs.

SARDBA33

RELEASE SUCCESSFULLY CONVERTED TO *xxx*

Reason:

The database version has been successfully changed with the SARDBASE VERSION control statement.

Action:

None. This is an informational message.

SARDBA34

STATISTICS SUCCESSFULLY CALCULATED

Reason:

Database statistics were successfully calculated using the SARDBASE STATUS control statement.

Action:

None. This is an informational message.

SARDBA35

UNKNOWN KEYWORD *xxxxxxxx*

Reason:

The keyword specified in the ADDDS control statement specifications was not a valid ADDDS keyword.

Action:

Correct the control statement, and then resubmit the job.

SARDBA36

INVALID PARAMETER SPECIFICATION

Reason:

The appropriate syntax of keyword=value is not used in the ADDDS control statement specifications.

Action:

Correct the control statements to follow the keyword=value syntax, and then resubmit the job.

SARDBA37**INVALID DATA CLASS NAME****Reason:**

The SMS data class specified in the ADDDS control statement specifications was not valid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA38**INVALID MANAGEMENT CLASS NAME****Reason:**

The SMS management class specified in the ADDDS control statement specifications was not valid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA39**INVALID STORAGE CLASS NAME****Reason:**

The SMS storage class specified in the ADDDS control statement specifications was not valid.

Action:

Correct the control statement, and then resubmit the job.

SARDBA40**INCORRECT GENLEVEL FOR CAIRIM****Reason:**

CA View requires a higher genlevel for CA Common Services to perform licensing authentication.

Action:

Install a more current version of CA Common Services. For more information about CA Common Services, see the *CA View Installation Guide*.

SARDBA41

DATA OR INDEX PARAMETER NOT SPECIFIED ON ADDDS STATEMENT

Reason:

The DATA or INDEX parameter is requested on the ADDDS statement of the SARDBASE utility to indicate whether to add an index file or a data file space to the database.

Action:

Add the DATA or the INDEX parameter to the ADDDS statement and resubmit the request.

SARDBA46

Large format data sets only supported for a release 11.6 or higher database

Reason:

The SARDBASE ADDDS statement specified to add a large format data set (more than 4369 cylinders) to a r11.5 or earlier release level database. Large format data sets are only supported for r11.6 or higher release level databases.

Action:

Version the database level of the database to r11.6 or higher with the SARDBASE VERSION statement. You can then add the large format data set or reduce the number of cylinders on the SARDBASE ADDDS statement.

SARDBA90

PROCESSING TERMINATED DUE TO STOP COMMAND

Reason:

A stop command is issued for the SARDBASE utility. Control statement processing was prematurely ended.

Action:

None.

SARDBA91

INVALID COMMAND *command*

Reason:

The operator command that is issued to the SARDBASE utility is invalid or not supported.

Action:

For the syntax of the operator commands for the SARDBASE utility, see the chapter "Database Utilities" in the *Reference Guide*, and reissue the operator command.

SARDBC01

ERROR ON "FROM" DATABASE

Reason:

An I/O error occurred reading the SYSOUT to be copied. The SYSOUT is skipped and execution continues with the next SYSOUT group.

Action:

See the associated message for the I/O error.

SARDBC02

ERROR ON "TO" DATABASE

Reason:

An I/O error occurred writing the SYSOUT on the output database. Execution is terminated.

Action:

See the associated message for the I/O error.

SARDBC03

SYSOUT GROUP IS BEING COPIED - ID=*id*, GEN=*nnnnn*, SEQ=*nnnnn*

Reason:

The specified SYSOUT group is being copied.

Action:

None.

SARDBC04

INPUT DATABASE AT INCORRECT LEVEL

Reason:

The CA View database that is used as input for SARDBASE COPY is at the incorrect release level.

Action:

Verify the versions of the TO and FROM databases for the SARDBASE COPY. If necessary, change the versions with SARDBASE VERSION.

SARDBC05

SYSOUT INDEX IS BEING COPIED - ID=xxxxxxxxxxxxx GEN=xxxxx, SEQ=xxxxx

Reason:

This message indicates that the page index for the given SYSOUT group is being copied.

Action:

None. This is an informational message.

SARDBC06

SORT FAILED CC=xxxx, UNABLE TO SUCCESSFUL CREATE ALTERNATE INDEX RECORDS

Reason:

An external sort is used to sequence alternate index records for date selection before writing the records to the database. The sort phase ended with the specified nonzero return code resulting in the loss of all or some of the alternate index records.

Action:

The nonzero return code from the sort phase can be caused by a critical error as indicated by a previous message or a sort error as indicated in the sort message data set (SYSOUT). Review the messages to determine the appropriate action. Recreate the new database and resubmit the COPY request.

SARDBC10

Release 11.5 or earlier database cannot be copied to database with large format data sets

Reason:

The SARDBASE COPY statement specified to copy a r11.5 or earlier release level database to a new database that contains a large format data set (with more 4369 cylinders). Large format data sets are only supported for r11.6 or higher release level databases.

Action:

Version the database level of the "FROM" database to r11.6 or higher with the SARDBASE VERSION statement. Or, recreate the "TO" database with data sets that have 4369 cylinders or less before copying the database.

SARBD01

MEMBER =xxxxxxx IS BEING LOADED TO DATABASE

Reason:

The specified model banner page library member is being loaded to the database.

Action:

None. This is an informational message.

SARBD02

INPUT DATA SET IS EMPTY OR NO MEMBERS WERE LOADED

Reason:

The specified input data set is empty, or the requested members are not found in the input data set referenced by the SARBLIB DD statement.

Action:

Check the JCL to ensure that you specified the correct input data set name on the SARBLIB DD statement or that you specified the correct members to be loaded into the database.

SARDBD03

DDNAME "SARBLIB" NOT FOUND

Reason:

The SARBLIB DD statement is required for the SARDBASE utility BLOAD control statement to load model banner pages into the database.

Action:

Add the SARBLIB DD statement to the JCL, and then rerun the job.

SARDBD04

OPEN FAILED FOR DDNAME "SARBLIB"

Reason:

The SARDBASE utility BLOAD function was unable to open the SARBLIB DD statement. The job log must contain messages identifying the error.

Action:

Correct the error, and then rerun the job.

SARDBD40

DATABASE AT INCORRECT LEVEL

Reason:

The program load modules and the database are not at the same release level. This issue is usually caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to the old load modules, or the database has not been converted to the correct release level (new releases of the product can require conversion of the database).

Action:

You can either STEPLIB to the correct load modules or convert the database to the correct release level.

SARDBG01**ERROR ON DATABASE****Reason:**

An error occurred in the processing of the database. The message preceding this message indicates the error condition.

Action:

Respond to the preceding error message.

SARDBG02**DATABASE IS BEING CONVERTED****Reason:**

A REORG during database conversion is in process.

Action:

None.

SARDBG04**ARCHIVAL DATE FORMAT INVALID FOR ID=xxxxxxxxxxxxx, RECORD DROPPED****Reason:**

An alternate control record entry cannot be added to the alternate index because the archival date for the specified SYSOUT was invalid.

Action:

None. The problem can be the result of a database corruption or a SARSTCUX user exit that was coded erroneously.

SARDBG05

REORGANIZING xxxxxxxxxxxx, GEN=nnnn, ARCHIVED ON mm/dd/yy AT hh:mm

Reason:

This informational message is a progress report issued during a SARDBASE REORG. It appears at intervals specified by the SARINIT parameter DBMSGFRQ, which only counts SYSOUT IDs. Therefore, with a default DBMSGFRQ=5000, this message appears for every 5000th SYSOUT.

Action:

None.

SARDBG06

ALTERNATE INDEX REORGANIZATION STARTED

Reason:

This informational message indicates the start of the alternate index record reorganization phase of an asynchronous SARDBASE REORG. The alternate index records identify the starting date and SYSOUT IDs of a generation. These records are updated to reflect current SYSOUTs and reports in the database.

Action:

None. This message is informational.

SARDBG07

INDEX RECORD REORGANIZATION STARTED

Reason:

This message indicates the start of the index record reorganization phase of an asynchronous SARDBASE REORG. During this phase of the REORG, the database index structure is compressed to provide optimal access time.

Action:

None. This is an informational message.

SARDBG08**REORG PROCESSING ALTERNATE INDEX GEN *gen* WITH *count* GEN(S) REMAINING****Reason:**

This message indicates that the SARDBASE utility is in the second phase of the asynchronous REORG. This message is issued in response to the status operator command.

Action:

None. This message is informational.

SARDBG09**REORG SUCCESSFULLY TERMINATED DUE TO STOP COMMAND****Reason:**

A stop command is issued during processing of the SARDBASE asynchronous REORG. Reorganization processing has been properly terminated, leaving all reorganization activity intact.

Action:

None. This message is informational.

SARDBG10**REORG CANCELLED DUE TO STOP COMMAND****Reason:**

A stop command is issued during processing of the SARDBASE standard REORG. Reorganization processing was terminated and the database was reset to the pre-organization state.

Action:

None. This message is informational.

SARDBI00

DATABASE database DOES NOT EXIST <<PDC

Reason:

An access error occurred trying to access the CA View database.

Action:

Correct the problem. This can require copying the database with the SARDBASE utility or, in the extreme case, recovering the database. For more information, see the chapters "Database Utilities" and "Backing Up and Recovering the Database" in the *Reference Guide*.

SARDBI01

DDname "SARIOUT" not found

Reason:

The SARIOUT DD statement is required for the SARDBASE utility IDXOUT control statement to write the master index.

Action:

Add the SARIOUT DD statement to the JCL, and then rerun the job.

SARDBI02

Open failed for DDname "SARIOUT"

Reason:

The SARDBASE utility IDXOUT function was unable to open the SARIOUT DD statement. The job log must contain messages identifying the error.

Action:

Correct the error, and then rerun the job.

SARDBI03 through SARDBI10

SARDBI00 DATABASE *database* DOES NOT EXIST
SARDBI03 BLOCK OUT OF RANGE ON *database* - DCCB=*dccb*
SARDBI04 DATA SET RENAME FAILED REQ=*function* RC=*nnn* REASON=*xxxx*
SARDBI05 UNSUPPORTED DEVICE TYPE - BLKS/CYL=*nnn*
SARDBI06 MAXIMUM OF 255 DATA SETS DEFINED TO *database*
SARDBI07 NO MORE SPACE IN DATABASE *database*
SARDBI08 MISSING HIGH-LEVEL INDEX NAME OF DATABASE
SARDBI09 LOGICAL I/O ERROR *eeee* ON *database* - DCCB=*dccb*
SARDBI10 UNEXPECTED END OF DATA, *ccc*KEY=*kkkkkkkkkkkkkkkkkk*'

Reason:

An allocation error, access error, or I/O error occurred with the CA View database as described by the text of the message where:

<i>database</i>	Identifies the high-level prefix of the database
<i>dccb</i>	Represents a hexadecimal string identifying the data set, relative cylinder, and relative block in the database
<i>filetype</i>	Indicates the type of database file, either DATA or INDEX
<i>function</i>	Identifies the type of catalog function that failed for a RENAME
<i>ccc</i>	Indicates the internal control block being accessed (SFB, IFB, or XFB)
<i>eeee</i>	Identifies the internal error code of the logical I/O error
<i>kkkkkkkkkkkkkkkkkk</i>	Specifies the key of the record in hex (if the key is longer than 16 bytes, only the first 16 bytes are shown)
<i>nnn</i>	Represents a number to identify a data set number, number of blocks, return code, or error code
<i>xxxx</i> or <i>xxxxxxxx</i>	Represents a hexadecimal number for an error code, information code, or reason code

Action:

Correct the problem with the database. This can require copying the database with the SARDBASE utility or, in the extreme case, recovering the database. For more information, see the chapters "Database Utilities" and "Backing Up and Recovering the Database" in the *Reference Guide*.

SARDBI11

This number represents one of the following:

Record not found, cccKEY=x'kkkkkkkkkkkkkkkk'

Record not found, Panel= panel_name

Record not found, Banner= banner_name

Record not found, RCR=resource_id

Record not found, GCR=report_id GEN=gen SEQ=seq

Reason:

A database read function was executed and the required record is not found in the database. The format can include the report, resource, banner, panel, or the binary key for other formats.

ccc	Indicates the internal control block being accessed (SFB, IFB, or XFB)
kkkkkkkkkkkkkkkk	Specifies the key of the record in hex (if the key is longer than 16 bytes, only the first 16 bytes are shown)
panel_name	Specifies the name of the panel record
banner_name	Specifies the name of the banner record
Resource_id	Specifies the Id of the ACIF/Xerox resource record
Report_id	Specifies the Id of the report
Gen	Specifies the database generation number assigned to the report
Seq	Specifies the database sequence number assigned to the report

Action:

Correct the problem with the database. This can require copying the database with the SARDBASE utility or, in the extreme case, recovering the database. For more information, see the chapters "Database Utilities" and "Backing Up and Recovering the Database" in the *Reference Guide*.

SARDBI12

LOCK FILE FOR database ALREADY EXISTS

Reason:

An allocation error, access error, or I/O error occurred with the LOCKFILE for the CA View database as described by the text of the message.

Action:

Verify that the LOCKFILE exists. If necessary, reallocate the LOCKFILE.

SARDBI13

LOCK FILE FOR database DOES NOT EXIST

Reason:

An allocation error, access error, or I/O error occurred with the LOCKFILE for the CA View database as described by the text of the message.

Action:

If the LOCKFILE is needed, then allocate a new LOCKFILE.

SARDBI14

DATACLAS/MGMTCLAS/STORCLAS ALLOWED ONLY FOR SMS DATA SETS

Reason:

In the ADDDS statement of a SARDBASE job, one of the SMS parameters (DATACLAS/MGMTCLAS/STORCLAS) was specified, but the data set CA View attempted to allocate for the database was a non-SMS data set.

Action:

If the data set must not be SMS-managed, follow these steps:

1. Remove the SMS parameters from the ADDDS statement.
2. Ensure that the storage class is not defaulted by a site-written ACS routine.
3. Resubmit the SARDBASE job.

If the data set must be SMS-managed, specify an appropriate STORCLAS, or ensure that storage class is selected by a site-written ACS routine, then resubmit the SARDBASE job.

SARDBI15

UNIT/VOLSER ALLOWED ONLY FOR NON-SMS DATA SETS

Reason:

In the ADDDS statement of a SARDBASE job, the UNIT or VOLSER parameter was specified, but the data set CA View attempted to allocate for the database was an SMS data set.

Action:

If the data set must not be SMS-managed, follow these steps:

1. Remove any SMS parameters from the ADDDS statement.
2. Ensure that the storage class is not selected by a site-written ACS routine.
3. Resubmit the SARDBASE job.

If the data set must be SMS-managed, remove the UNIT and VOLSER parameters from the ADDDS statement, then resubmit the SARDBASE job.

SARDBI16

DATABASE IS INCOMPATABLE WITH CA VIEW 2.0
DATABASE IS INCOMPATABLE WITH CA VIEW 2.0 SARPAM FUNCTION 'nn'
DATABASE 'HLQ' AT INCORRECT RELEASE LEVEL
DATABASE 'HLQ' AT INCORRECT RELEASE LEVEL SARPAM FUNCTION 'nn'

Reason:

Incorrect release of the CA View program is attempting to access a CA View database.

Accessing a CA View r11 or higher database with the CA View 2.0 programs results in the Format #1 SARDBI16 message.

Accessing a CA View r11 or higher database with CA Deliver 1.7 "Direct-to-View" Archival using the CA View 2.0 program library results in the Format #2 SARDBI16 message. The application program abnormally terminates U0041.

Accessing a CA View 2.0 database with the CA View r11 or higher programs can result in either of two messages.

- If an index extent has not been allocated, message "SARDBI00 Index file for 'hlq' does not exist" is displayed.
- If an index extent has been allocated for the CA View database but the database has not been "versioned" to CA View r11 or higher, the Format #3 SARDBI16 message is displayed.

Accessing a CA View 2.0 Database with the CA Deliver "Direct-to-View" Archival using a CA View r11 or higher program library can result in either of the following two messages:

- If an index extent has not been allocated, message "SARDBI00 Index file for 'hlq' does not exist, SARPAM FUNCTION 'nn'" is displayed.
- If an index extent has been allocated for the CA View database but the database has not been "versioned" to CA View r11 or higher, the Format #4 SARDBI16 message is displayed.

Action:

Correct the STEPLIB to point to the correct release of CA View or refresh LLA with the correct release of CA View if STEPLIB is not used.

SARDBI17

DATABASE SPACE FOR THE FILE DELETED OR REUSED

Reason:

A user is browsing a report which is deleted by another user or system function, such as, the backup cycle expiring the report and the space is re-used by an archival function. The space is no longer owned by this report and can no longer be browsed.

Action:

If the report is needed, contact your site's CA View administrator who can recover the report if it is available on tape. If the report is not needed, no additional action is required.

SARDBI18

NO MVS SUPPORT FOR COMPRESSION SERVICES

Reason:

A report was compressed and archived to disk using MVS compression service, but your current operating system does not support MVS compression service.

Action:

If the report is archived to tape, delete the disk copy and reload the report from tape. If the report is not archived to tape, access the report from the same machine that archived it.

SARDBI19

Encryption is not supported in r11.5

Reason:

A database function attempted to access a Sysout which is created with encryption enabled (initialization parameter ENCRYPT set to ICSF) under r11.6 or higher and cannot be processed by CA View r11.5.

Action:

The database must be versioned back to r11.6 or higher, the database must be copied (SARDBASE/COPY) with the initialization parameter ENCRYPT set to NO. Then version the database back to r11.5.

SARDBI20

Database "database" not initialized

Reason:

A database read function is executed for a database Master Control Record (MCR) and the record is not found in the database.

database

Identifies the high-level prefix of the database.

Action:

Run the initialization utility (SARINIT) to format and add a Master Control Record (MCR) to the database.

SARDBI21

Subfile allocation I/O error on data set xxxx - next data set used

Reason:

An I/O error occurred while allocating space on the specified data set. The allocation is attempted on the next data set in the database.

Action:

Probably none; however, verify that the database has no major problem.

SARDBI22

I/O error for block xxxx - block removed from database file

Reason:

An I/O error occurred writing a block to the database. The block is marked in error and the data in the block is rewritten to a different location in the database.

Action:

Probably none; however, verify that the database has no major problem.

SARDBI23

database INDEX file(s) at nn% utilization

database DATA file(s) at nn% utilization

Reason:

The database has exceeded maximum threshold of utilization; the actual percentage that is used is given.

Action:

None; however, the database must be monitored to see that it does not run out of space. It may be necessary to add more space to the database. Changing the DBTHRESH initialization parameter can alter the maximum threshold setting.

SARDBI24

Unallocation failed for data set dataset - ERROR=xxxx INFO=xxxx

Reason:

A Dynamic De-allocation request is made by CA View to detach its connection to the database. But, the database is still in use by some other function that is associated with the task. This can occur during termination of CA View utilities if the site defines that job to be captured by CA Deliver Pre-spool, Direct-to-View.

Action:

Save all of the documentation that is associated with the job and notify CA Technical Support.

SARDBI30

**Job jobname(jobid) waiting for exclusive lock on database
Lock held by name on mm/dd/yy at hh:mm:ss**

Note: This message ID represents one of these messages.

Reason:

The specified job cannot obtain an exclusive lock on the lock data set to update data in the specified database. The message is issued in one-minute intervals until the lock is resolved.

Action:

If the lock is held by a user or job that is no longer executing due to an abend or cancellation, use the UNLOCK control statement of the SARDBASE utility to release the lock. Otherwise, the lock is obtained when available.

SARDBL01**MEMBER xxxxxxxx IS BEING LOADED TO DATABASE****Reason:**

The specified online library member is being loaded to the database.

Action:

None. This is an informational message.

SARDBL02**INPUT DATASET IS EMPTY, NOTHING TO LOAD****Reason:**

No panels are found in the input OLIB data set.

Action:

Verify that your CA View OLIB data set is correctly named in the STEPLIB, and that it contains panels.

SARDBL03**SAROLIB DD STATEMENT MISSING****Reason:**

An OLOAD control statement is issued to load online members into the CA View database, but the SAROLIB DD statement was not specified. The SAROLIB DD statement references the library containing the online members and is required for the load request.

Action:

Add the SAROLIB DD statement referencing the library containing the online members, and then resubmit the load request.

SARDBM01**SECONDARY DISK ERROR FOR ID=xxxxxxx, GEN=xxxxx, SEQ=xxxxx****Reason:**

CA View cannot write to the secondary disk.

Action:

Verify your DSK2PARAM initialization parameter.

SARDBM02

ERROR ON "TO" DATABASE

Reason:

The database being copied to has an error.

Action:

Verify that the database has enough allocation (you can increase the allocation with SARDBASE ADDDS) and that the DASD is available to the system.

SARDBM03

UNEXPECTED END OF DATA ON INPUT FILE

Reason:

CA View found the end of the SARLOAD file before the database was fully loaded.

Action:

Verify that the SARLOAD data set is complete.

SARDBM04

INCORRECT UNLOAD FILE FORMAT

Reason:

The unload file that is referenced by the SARLOAD DD statement contains records that are not consistent with this release of the product.

Action:

Recreate the unload file, recreate the new database, and resubmit the LOAD or MERGE request.

SARDBM06

SORT FAILED CC=xxxx, UNABLE TO SUCCESSFUL CREATE ALTERNATE INDEX RECORDS

Reason:

An external sort is used to sequence alternate index records for date selection before writing the records to the database. The sort phase ended with the specified nonzero return code resulting in the loss of all or some of the alternate index records.

Action:

The nonzero return code from the sort phase can be caused by a critical error as indicated by a previous message or a sort error as indicated in the sort message data set (SYSOUT). Review the messages to determine the appropriate action. Recreate the new database and resubmit the LOAD or MERGE request.

SARDBM07

DDname "ddname" not found

Reason:

The SARLOAD or SARMERGN DD statement is required for the SARDBASE utility LOAD or MERGE control statement to load or merge the database.

Action:

Add the SARLOAD or SARMERGN DD statement to the JCL, then rerun the job.

SARDBM08

Open failed for DDname "ddname"

Reason:

The SARDBASE utility LOAD or MERGE function was unable to open the SARLOAD or SARMERGN DD statement. The job log must contain messages identifying the error.

Action:

Correct the error and rerun the job.

SARDBM10

Release 11.5 or earlier database cannot be loaded/merged to database with large format data sets

Reason:

The SARDBASE LOAD or MERGE statement specified to load or merge an r11.5 or earlier release level database to a new database that contains a large format data set (data set with more than 4369 cylinders). Large format data sets are only supported for r11.6 or higher release level databases.

Action:

Recreate the new database with data sets that have 4369 cylinders or less before loading or merging the database.

Alternatively, version the old r11.5 or earlier release level database(s) to r11.6 or higher with the SARDBASE VERSION statement. Perform a new unload the database(s) now, and then load or merge the database(s).

SARDBN01

SARMERG1 AND SARMERG2 DD STATEMENTS MISSING

Reason:

A SARDBASE MERGE job was submitted without DD statements.

Action:

Include the DD statements in the SARDBASE JCL.

SARDBN02

UNEXPECTED END OF DATA ON INPUT TAPE

Reason:

One of the SARDBASE MERGE input tapes is incomplete.

Action:

Verify that all SARDBASE MERGE input tapes are correct, and rerun SARDBASE MERGE.

SARDBN03

NOTHING ARCHIVED - MERGE TERMINATED

Reason:

The MERGE input tapes do not contain any data.

Action:

Verify that all SARDBASE MERGE input tapes are correct, and rerun SARDBASE MERGE.

SARDBN04

LOAD FAILED - MERGE TERMINATED

Reason:

One of the input tapes for SARDBASE MERGE failed to load to the database.

Action:

Verify that all SARDBASE MERGE input tapes are created by the SARDBASE UNLOAD facility.

SARDBN05

PHASE 1 SCAN FOR SARMERGx

Reason:

Input tape SARMERGx began scan processing.

Action:

None. This is an informational message.

SARDBN06

LOAD INVOKED FOR SARMERGx

Reason:

Input tape SARMERGx began load processing.

Action:

None. This is an informational message.

SARDBN07

MAXIMUM SYSOUT SEQUENCE NUMBER EXCEEDED FOR NEW GENERATION *nnnnnnnn*

Reason:

In the SARDBASE MERGE operation, a new generation *nnnnnnnn* exceeded 65,535 SYSOUTs.

Action:

Reduce the number of input databases and rerun SARDBASE MERGE.

SARDBN08

CONFLICT EXISTS WITH NEW TAPE HIGH-LEVEL INDEX

Reason:

The tape index for the output database is the same as one of the SARDBASE MERGE input tapes.

Action:

Name the output tape index differently than any of the MERGE input tapes, and rerun SARDBASE MERGE.

SARDBN09

SECONDARY DISK FILES WERE NOT UNLOADED

Reason:

One or more of the SARMERGX tapes containing data on optical disk was not properly UNLOADED with the SECOND/NOSECOND parameter of the SARDBASE MERGE facility.

Action:

Unload all databases with the SECOND/NOSECOND parameter of SARDBASE UNLOAD specified. Then rerun SARDBASE MERGE.

SARDBN10**UNLOADED SECONDARY SYSOUT GROUPS BEING LOADED TO PRIMARY DATABASE****Reason:**

SARDBASE MERGE is loading SYSOUTS to disk. The SYSOUTs were on the optical disk, and are unloaded to tape by SARDBASE UNLOAD, with the SECOND parameter specified.

Action:

None. This message is informational.

SARDBN12**LOAD FAILED FOR SECONDARY DISK DRIVER****Reason:**

The secondary disk storage driver specified in the MERGE control statement of SARDBASE cannot be successfully loaded for execution.

Action:

Correct the control statement, and rerun SARDBASE MERGE.

SARDBN13**NO MCR RECORD FOUND****Reason:**

One of the SARDBASE MERGE input tapes is missing the Master Control Record.

Action:

Check the output of all SARDBASE UNLOAD jobs that are used to create input tapes for SARDBASE MERGE. Verify that complete tapes were created. Rerun SARDBASE MERGE.

SARDBN14

MERGE exceeds database maximum of 65535 tapes

Reason:

User is attempting to MERGE databases, but the combined database exceeds 64K backup tapes.

Action:

MERGE is TERMINATED in phase1 with a return code of 16. If you are attempting to merge more than two databases into a single database, consider merging half of these databases into one database and the other half into a second database.

SARDBN15

MERGE exceeds database maximum of 65535 DR tapes

Reason:

User is attempting to MERGE databases, but the combined database exceeds 64K DR tapes.

Action:

MERGE is TERMINATED in phase1 with a return code of 16. If you are attempting to merge more than two databases into a single database, consider merging half of these databases into one database and the other half into a second database.

SARDBN16

TCR nnnnn does not exist -- SARMERGN DROPPING REPORT

XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX

Reason:

The database from SARMERGN contains a report that is on Backup tape nnnnn, but CA View has no TCR record for this tape.

Action:

The report is dropped and processing continues. The MERGE eventually ends with a return code of 4. This error is caused by when a user runs SARTDR to TADD reports to a database, but for some reason the SARTDR abended before it added the TCR record to the database.

SARDBP01

Critical error, program terminated with dump. Invalid blk

Reason:

A CA View program has terminated, and a dump was generated. In this message, *blk* specifies the control block that CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It can be suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart whatever program was terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

SARDBR01

ERROR ON "FROM" DATABASE

Reason:

An I/O error occurred reading the SYSOUT to be restored. The SYSOUT is skipped and execution continues with the next SYSOUT group.

Action:

See the associated message for the I/O error.

SARDBR02

ERROR ON "TO" DATABASE

Reason:

An I/O error occurred writing the SYSOUT on the output database. Execution is terminated.

Action:

See the associated message for the I/O error.

SARDBR03

**ATTEMPT TO COPY SYSOUT GROUP FROM OLD DATABASE - ID=*id*, GEN=*nnnnn*,
SEQ=*nnnnn***

Reason:

The specified SYSOUT group is being copied.

Action:

None. This is an informational message.

SARDBR04

REQUESTED TAPE FILE DOES NOT CONTAIN INDEX BACKUP

Reason:

The file recorded in the backup recovery file or specified in the JCL does not contain a backup of the master index.

Action:

Use SARTCP to map the backup tape to locate the backup of the master index.

SARDBR05

ATTEMPT TO COPY ONLINE MEMBER FROM OLD DATABASE - NAME=*xxxxxxxx*

Reason:

The specified member of the online library is being copied.

Action:

None. This is an informational message.

SARDBR06

SORT FAILED CC=xxxx, UNABLE TO SUCCESSFUL CREATE ALTERNATE INDEX RECORDS

Reason:

An external sort is used to sequence alternate index records for the date selection before writing the records to the database. The sort phase ended with the specified nonzero return code resulting in the loss of all or some of the alternate index records.

Action:

The nonzero return code from the sort phase can be caused by a critical error as indicated by a previous message or a sort error as indicated in the sort message data set (SYSOUT). Review the messages to determine the appropriate action. Recreate the new database and resubmit the RESTORE request.

SARDBR07

DATABASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The program load modules and the database are not at the same release level. This is normally caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to old load modules, or the database has not been converted to the correct release level (new releases of the product can require conversion of the database).

Action:

You can either STEPLIB to the correct load modules or convert the database to the correct release level.

SARDBR08

ATTEMPT TO COPY BANNER PAGE FROM OLD DATABASE – NAME=xxxxxxxx

Reason:

The specified member of the model banner page library is being copied.

Action:

None. This is an informational message.

SARDBR10

Release 11.5 or earlier database cannot be restored to database with large format data sets

Reason:

The SARDBASE RESTORE statement specified to restore an r11.5 or earlier release level database to a new database that contains a large format data set (data set with more than 4369 cylinders). Large format data sets are only supported for r11.6 or higher release level databases.

Action:

Recreate the new database with data sets that have 4369 cylinders or less before loading or merging the database.

SARDBR12

PERMANENT I/O ERROR READING TAPE

Reason:

A permanent I/O error occurs while reading the tape backup of the master index.

Action:

Resubmit the job. If the error recurs, use a different backup for restoring the master index.

SARDBR13

REQUESTED BACKUP DOES NOT EXIST

Reason:

The requested backup for the master index cannot be located.

Action:

Restore the master index from a newer backup.

SARDBR14**TAPE ALLOCATION ERROR CODE - *xxxx*, INFO CODE - *xxxx*****Reason:**

Dynamic allocation failed for the backup tape file. The hexadecimal error and information codes are provided.

Action:

Correct the problem, and then resubmit the job.

SARDBR16**RESTORE OF DATABASE BEGUN****Reason:**

The restore function has begun.

Action:

None. This is an informational message.

SARDBR17**PARTIAL RESTORE COMPLETED - ARCHIVAL AND ONLINE ACTIVITY MAY BE RESUMED FOR *high-level-prefix*****Reason:**

This message is informational indicating that the restore process has restored the index data necessary to resume archival and online activity. The restore process continues with the restoration of SYSOUT groups and SYSOUT data.

Action:

If errors occurred during the loading of panel data or if the FROM database is omitted from the RESTORE control statement, reload online panels to the database before resuming online activity.

SARDBR18

LOADING OF SUBFILE DATA BEGUN

Reason:

This message is informational indicating that the restore process proceeds with the restoration of SYSOUT groups and SYSOUT data.

Action:

None. This message is informational.

SARDBR20

SYSOUT GROUP ADDED TO INDEX - ID=XXXXXXXXXXXX, GEN=XXXXX, SEQ=XXXXX

Reason:

This message indicates that the SYSOUT groups are added to the database during the restore process. This message is also written to the operator console at intervals based on the DBMSGFRQ initialization parameter to inform the operator of the progress of the restore process.

Action:

None. This message is informational.

SARDBR21

NEITHER SARRECV NOR SARTAPE DD STATEMENTS SUPPLIED FOR RESTORE

Reason:

A SARTAPE DD statement or a SARRECV DD statement has not been included in the JCL for the job. CA View cannot determine the backup tape to use for the restore.

Action:

Correct the JCL, and then resubmit the job.

SARDBR22**MASTER INDEX IS NOT COMPLETE ON BACKUP TAPE SUPPLIED****Reason:**

The master index must be contained on a single tape volume when the SARRECV DD statement is not specified.

Action:

Correct tape sequence and retry.

SARDBR23**RECOVERY DATASET ERROR OPER=xxxx****Reason:**

Error attempting to access the recovery data set.

Action:

None. If a hardware error is not indicated. Contact CA Technical Support.

SARDBR24**MULTI-VOLUME MASTER INDEX IS INVALID****Reason:**

The first record on this tape must be an index continuation record. This tape could have been used out of sequence.

Action:

Correct tape sequence and retry.

SARDBR26**PANEL, BANNER, AND SYSOUT DATA NOT RESTORED, USE SARDBASE OLOAD/BLOAD, SARRSP, AND/OR SARTDR UTILITIES TO RESTORE****Reason:**

The panel, banner, and SYSOUT data is not restored because an old database name is not specified in the RESTORE control statement.

Action:

The SARDBASE, SARRSP, and/or SARTDR utilities must be used to restore or load panel, banner, or SYSOUT data to the database.

SARDBT01

ERROR ON DATABASE

Reason:

An I/O error occurred when opening the database.

Action:

Probably none; however, verify that there is no major problem with the database.

SARDBT02

DATABASE ALREADY AT THE DESIRED LEVEL

Reason:

The database is already at the desired level.

Action:

None. This is an informational message.

SARDBT03

UNSUPPORTED DATABASE LEVEL

Reason:

The release level to be converted to is not supported.

Action:

Check the release number, and then resubmit the job.

SARDBT04

DATABASE RELEASE LEVEL SUCCESSFULLY CONVERTED TO *xxx*

Reason:

The specified release is being converted.

Action:

None. This is an informational message.

SARDBT06

SORT FAILED CC=xxxx, UNABLE TO SUCCESSFUL CREATE ALTERNATE INDEX RECORDS

Reason:

An external sort is used to sequence alternate index records for the date selection before writing the records to the database. The sort phase ended with the specified nonzero return code resulting in the loss of all or some of the alternate index records.

Action:

The nonzero return code from the sort phase can be caused by a critical error as indicated by a previous message or a sort error as indicated in the sort message data set (SYSOUT). Review the messages to determine the appropriate action. Recreate the new database and resubmit the VERSION or CONVERT request.

SARDBT07

LOGICAL VIEW xxxxxxxxxxxxxx nnn TOO LARGE – RECORD DROPPED

Reason:

The specified logical view was too large to be converted to Release 11.0 format. The logical view definition is not converted.

Action:

If the logical view definition is needed, manually add the logical view definition to the Release 11.0 database.

SARDBT08

DDNAME "SARCONV" NOT FOUND

Reason:

The SARCONV DD statement is required for the SARDBASE utility CONVERT control statement to output previous release database records.

Action:

Add the SARCONV DD statement to the JCL, and then rerun the job.

SARDBT09

OPEN FAILED FOR DDNAME "SARCONV"

Reason:

The SARDBASE utility CONVERT function was unable to open the SARCONV DD statement. The job log must contain messages identifying the error.

Action:

Correct the error, and then rerun the job.

SARDBT10

CONVERT CANCELLED DUE TO STOP COMMAND

Reason:

A stop command was issued while processing the VERSION or CONVERT control statement of the SARDBASE utility. Control statement processing ended prematurely.

Action:

None. The database conversion has to be resubmitted and run to completion before the database can be used.

SARDBT11

DDNAME "SARCTAB" NOT FOUND

Reason:

The SARCTAB DD statement is required for the SARDBASE utility CONVERT TABLE control statement to output identifiers that require short identifier names.

Action:

Add the SARCTAB DD statement to the JCL, and then rerun the job.

SARDBT12

OPEN FAILED FOR DDNAME "SARCTAB"

Reason:

The SARDBASE utility CONVERT function was unable to open the SARCTAB DD statement. The job log must contain messages identifying the error.

Action:

Correct the error, and then rerun the job.

SARDBT13

CONVERT TABLE IDENTIFIER MISSING OR INVALID – RECORD *nnn*

Reason:

The SARCTAB DD statement contains an invalid control record, a missing identifier name, or an invalid identifier name.

Action:

Correct the control statement, and then rerun the job.

SARDBT14

CONVERT TABLE DUPLICATE IDENTIFIER OR NEW IDENTIFIER ALREADY EXISTS - RECORD *nnn*

Reason:

An identifier name with the same name is previously encountered in the SARCTAB DD statement or exists in the database.

Action:

Correct the SARCTAB DD statement record, and then rerun the job.

SARDBT15

NO TRANSLATION SUPPLIED FOR REPORT IDENTIFIER "xxxxxxxxxxxxx" – CONVERT TERMINATED

Reason:

The specified report identifier name is too long, and a short name is not supplied in the convert table referenced by the SARCTAB DD statement. The conversion process terminates.

Action:

Add a control statement to the)REPORT section of the SARCTAB DD statement identifying the specified report identifier and its associated short name and rerun the job. If the convert table has not been created, the SARDBASE utility can be run with a CONVERT TABLE statement to build a table of long identifier names that require short identifier names.

SARDBT16

NO TRANSLATION SUPPLIED FOR SYSOUT IDENTIFIER "XXXXXXXXXXXX" – CONVERT TERMINATED

Reason:

The specified SYSOUT identifier name is too long, and a short name is not supplied in the convert table referenced by the SARCTAB DD statement. The conversion process terminates.

Action:

Add a control statement to the)SYSOUT section of the SARCTAB DD statement identifying the specified SYSOUT identifier and its associated short name and rerun the job. If the convert table has not been created, the SARDBASE utility can be run with a CONVERT TABLE statement to build a table of long identifier names that require short identifier names.

SARDBT17

NO TRANSLATION SUPPLIED FOR DISTID "XXXXXXXXXXXX" – CONVERT TERMINATED

Reason:

The specified distribution identifier name is too long, and a short name is not supplied in the convert table referenced by the SARCTAB DD statement. The conversion process terminates.

Action:

Add a control statement to the)DIST section of the SARCTAB DD statement identifying the specified distribution identifier and its associated short name and rerun the job. If the convert table has not been created, the SARDBASE utility can be run with a CONVERT TABLE statement to build a table of long identifier names that require short identifier names.

SARDBT18

NO TRANSLATION SUPPLIED FOR DISTID MASK "xxxxxxxxxxxxx" – CONVERT TERMINATED

Reason:

The specified distribution mask name is too long, and a short name is not supplied in the convert table referenced by the SARCTAB DD statement. The conversion process terminates.

Action:

Add a control statement to the)DISTMASK section of the SARCTAB DD statement identifying the specified distribution mask and its associated short name and rerun the job. If the convert table has not been created, the SARDBASE utility can be run with a CONVERT TABLE statement to build a table of long identifier names that require short identifier names.

SARDBT19

NO TRANSLATION SUPPLIED FOR VIEW IDENTIFIER "xxxxxxxxxxxxx" – CONVERT TERMINATED

Reason:

The specified logical view identifier name is too long, and a short name is not supplied in the convert table referenced by the SARCTAB DD statement. The conversion process terminates.

Action:

Add a control statement to the)VIEW section of the SARCTAB DD statement identifying the specified logical view identifier and its associated short name and rerun the job. If the convert table has not been created, the SARDBASE utility can be run with a CONVERT TABLE statement to build a table of long identifier names that require short identifier names.

SARDBT20

NO TRANSLATION SUPPLIED FOR NOTE NAME "xxxxxxxxxxxxx" – CONVERT TERMINATED

Reason:

The specified note name is too long, and a short name is not supplied in the convert table referenced by the SARCTAB DD statement. The conversion process terminates.

Action:

Add a control statement to the)NOTE section of the SARCTAB DD statement identifying the specified note name and its associated short name and rerun the job. If the convert table has not been created, the SARDBASE utility can be run with a CONVERT TABLE statement to build a table of long identifier names that require short identifier names.

SARDBT21

SEARCH CRITERIA FOR LOGICAL VIEW xxxxxxxxxxxx nnn DROPPED – REVIEW LOGICAL VIEW DEFINITION

Reason:

The specified logical view definition contained search criteria and possible relative references to the search criteria that is dropped during conversion.

Action:

Review the logical view definition to determine that index values are extracted from the correct location of a page.

SARDBT22

CORRUPTED SDR RECORD FOR SYSID: ssssssssss – Record skipped

Reason:

A corrupted sysout Description Record exists in a CA View database which is being versioned to a later release.

Action:

The sysout Id is identified in the message, the corrupted record is skipped, and a return code of 4 is set by the SARBASE/VERSION Function. The record can be redefined in the database after the versioning function is complete.

Note: For more information about online specifications, see the chapter "System Administration: Defining Online Specifications" in the *User Guide*.

SARDBT23

Database with large format data sets cannot be versioned to release 11.5 or earlier

Reason:

The SARDBASE VERSION statement is being used to version a database to release level r11.5 or earlier but the database contains a large format data set (data set with more than 4369 cylinders). Large format data sets are only supported for r11.6 or higher release level databases and cannot be versioned to release 11.5 or earlier.

Action:

To be compatible with the r11.5 or earlier database structure, re-create the r11.6 or higher release level database. Create a database with data sets that have 4369 cylinders or less. Copy or load the r11.6 or higher release level database into the new database. After the copy or load, the database can be versioned to the r11.5 or earlier database release level.

SARDBU01

ERROR ON "FROM" DATABASE

Reason:

An I/O error occurred reading the SYSOUT to be written to tape. The SYSOUT is skipped and execution continues with the next SYSOUT group.

Action:

See the associated message for the I/O error.

SARDBU02

This message number represents one of the following messages:

SECONDARY DISK ERROR FOR ID=xxxxxxxx, GEN=xxxxx, SEQ=xxxxx
SECONDARY DISK ERROR FOR RESOURCE=xxxxxxxxxxxxx

Reason:

CA View cannot write to the secondary disk.

Action:

Verify your DSK2PARAM initialization parameter.

SARDBU03

UNABLE TO LOAD SECONDARY DISK STORAGE DRIVER

Reason:

CA View cannot find the program that is required to access secondary storage.

Action:

Determine if the program is available in STEPLIB or linklist.

SARDBU04

ERROR ON GET EQUAL FOR ID=XXXXXXXXXXXXX GEN=XXXXX, SEQ=XXXXX

Reason:

The given SYSOUT group was being unloaded from the secondary disk to the unload file, but the SYSOUT group is no longer in the CA View database.

Action:

None. The SYSOUT group is not unloaded, and unload processing continues with the next SYSOUT group.

VWZr7--SARDBU05

DDname "SARUNLD" not found

Reason:

The SARUNLD DD statement is required for the SARDBASE utility UNLOAD control statement to unload the database.

Action:

Add the SARUNLD DD statement to the JCL, and then rerun the job.

SARDBU06

Open failed for DDname "SARUNLD"

Reason:

The SARDBASE utility UNLOAD function was unable to open the SARUNLD DD statement. The job log must contain messages identifying the error.

Action:

Correct the error, and then rerun the job.

SARDBU07

Selective unload card error detected. Unloaded file may not contain expected results. Check prior SARUNL99 messages.

Reason:

The selective unload process detected an input card parameter error. The job log contains SARUNL99 messages identifying the error.

Action:

Delete the unloaded file. Correct the invalid parameter card. Rerun the job.

SARDBU08

No reports found which match selective unload criteria. Unloaded file may be incomplete.

Reason:

Sysouts specified for the selective unload were not found on the View database.

Action:

Delete the unloaded file. Correct the sysout ids specified for selective unload. Rerun the job.

SARDBV01

Index block verification started

Reason:

Informational message indicating the start of the index file block mapping phase of the database verification process. The verification process involves three phases which are the index file block mapping phase, the index record verification and subfile (SYSOUT data and panel data) mapping phase, and the alternate index and extended index record verification phase.

Action:

None. This is an informational message.

SARDBV10

Index record/sub-file data verification started

Reason:

This is an informational message indicating the start of the index record verification and subfile (SYSOUT data and panel data) mapping phase of the database verification process. The verification process involves three phases which are the index file block mapping phase, the index record verification and subfile mapping phase, and the alternate index and extended index record verification phase.

Action:

None. This is an informational message.

SARDBV11

Index verification for ID=REPORTID, GEN=XXXX, SEQ=XXXX

Reason:

This is an informational message indicating the index record currently being processed in index record verification and subfile mapping phase. This message is written to the operator console on an interim basis depending on the frequency defined in the DBMSGFRQ initialization option.

Action:

None. This is an informational message.

SARDBV12

Alternate index from incomplete reorg deleted

Reason:

The data space occupied by the incomplete REORG function is freed from the database.

Action:

None. This is an informational message.

SARDBV13

Sub-file verification for online member

Reason:

The data space that is occupied by the specified online member (panel, message, or skeleton JCL) is being verified and mapped. If the internal structure of the subfile is incorrect, the online member can be truncated or lost.

Action:

None. This message is informational.

SARDBV14

This number represents one of the following messages:

Sub-file verification for sysout member
Sub-file verification for resource member

Reason:

The data space that is occupied by the subfile for the specified SYSOUT or page layout RESOURCE is being verified and mapped. If the internal structure of the subfile is incorrect, the archival SYSOUT data can be truncated or lost.

Action:

None. This message is informational.

SARDBV15

This number represents one of the following messages:

Auxiliary file verification for sysout member
Auxiliary file verification for resource member

Reason:

The data space that is occupied by the auxiliary file (SYSOUT indexing mapping data) for the specified SYSOUT or page layout RESOURCE is being verified and mapped. If the internal structure of the subfile is incorrect, the auxiliary data can be truncated or lost.

Action:

None. This message is informational.

SARDBV16

Dummy MCR record is being created

Reason:

A master control record (index record which contains initialization parameters and other vital information) cannot be found in the database and is being created.

Action:

After the database verification process is complete, run the SARINIT utility to reinstate all initialization options.

SARDBV17

Generation and tape numbers reset in MCR

Reason:

SYSOUT groups are found in the database to contain a higher generation number, sequence number, and/or tape sequence number than indicated in the master control record (index record which contains initialization parameters and other vital information). The higher generation number, sequence number, and/or tape sequence number are being placed in the master control record.

Action:

None. This is an informational message.

SARDBV18

Generation/sequence numbers complemented for master control record

Reason:

The current generation number and sequence number in the master control record are being changed from a complemented form to a non-complemented form.

Action:

None. This is an informational message.

SARDBV19

Sub-file verification for banner page member

Reason:

The data space that is occupied by the specified model banner page member is being verified and mapped. If the internal structure of the subfile is incorrect, the model banner page member can be truncated or lost.

Action:

None. This message is informational.

SARDBV20

Alternate index/extended record verification started

Reason:

This is an informational message indicating the start of the alternate index and extended index record verification phase of the database verification process. The verification process involves three phases, as follows:

- The index file block mapping phase
- The index record verification and subfile (SYSOUT data and panel data) mapping phase
- The alternate index and extended index record verification phase

Action:

None. This is an informational message.

SARDBV21

Alternate index verification for ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

This message is informational indicating the index record that is being processed in the alternate index and extended index record verification phase. This message is written to the operator console on an interim basis depending on the frequency defined in the DBMSGFRQ initialization option.

Action:

None. This message is informational.

SARDBV22

Invalid extended index record X'record-key' deleted

Reason:

The extended index record for the specified key contains invalid data and has been deleted from the database.

Action:

None. This is an informational message.

SARDBV23

Invalid group control record ID=reportid, Gen=xxxx, Seq=xxxx deleted

Reason:

The index record for the specified SYSOUT group contains invalid data and has been deleted from the database.

Action:

None. This is an informational message.

SARDBV30

Database verification completed

Reason:

Informational message indicates the end of the verification process.

Action:

None. This is an informational message.

SARDRPO0

Forward recovery capture activated for dataset

Reason:

The SARSTC archival task has been started with Forward Recovery activated. The CA View initialization parameters RCVPRIM=xxxx and RCVUNIT=nnnn activate Forward Recovery.

Action:

None. This is an informational message.

SARDRP01

Allocation failed for xxxxx - Error=XXXX, Info=XXXX

Reason:

An error occurred during the allocation of a forward recovery data set. The hexadecimal error and information codes are provided.

Action:

The allocation error message may not be critical if issued during the recovery process or during the deletion process of the backup cycle. If the message, however, is issued by the archival task during archival of SYSOUT data, forward recovery can be disabled as indicated by the SARDRP99 message. In this case, resolve the error before forward recovery can be restarted. Forward recovery can be restarted by recycling the archival task or by initiating a backup cycle.

SARDRP02

Physical I/O error on xxxxx - ECB=XXXXXXXX

Reason:

An error occurred while performing I/O to a forward recovery data set.

Action:

If the I/O error occurred while recording archival data, an attempt is made to recover from the I/O error by allocating a new forward recovery data set and writing the appropriate information to the new data set. If recovery fails, the SARDRP99 message indicates that forward recovery is disabled. In this case, resolve the error before forward recovery can be restarted. Restart forward recovery by recycling the archival task or by initiating a backup cycle.

SARDRP03

Unrecoverable error on

Reason:

Forward recovery was unable to recover from a previous error.

Action:

See the explanation and action in the previous error message for resolution. When the previous error is resolved, restart forward recovery by recycling the archival task or by initiating a backup cycle.

SARDRP04

This message number represents one of the following messages:

End of file
Master control record not found
End of file reading tape control records
End of file reading group control records
End of file reading data records
End of file reading auxiliary records
Master control record not written
Tape control record not written
GCR control record not written
Data set not allocated due to initialization parameters

Reason:

The end-of-file messages are purely informational and rarely issued. The not found/not written messages can indicate possible logic errors. These logic errors arise when there are no forward recovery data sets to read from or write to. The data set not allocated message indicates that the RCVUNIT and/or RCVPRIM initialization parameters were not initialized to activate forward recovery.

Action:

The only messages that can require attention are the not found and not written messages. Normally, these messages are accompanied by previous error messages. See the explanation and action of the previous error messages for resolution.

SARDRP05

Open failed for

Reason:

An error occurred opening a forward recovery data set.

Action:

Normally, forward recovery continues processing by allocating a new forward recovery data set. In extreme cases, forward recovery can be disabled as indicated by the SARDRP99 message. In this case, resolve the error before forward recovery can be restarted. Forward recovery can be restarted by recycling the archival task or by initiating a backup cycle.

SARDRP06

Unknown or inconsistent data format for

Reason:

The forward recovery data set does not conform to the data structure of its data records. This condition can occur when foreign data is copied into a forward recovery data set or a foreign data set is renamed to conflict with a current forward recovery data set. This message can also be produced with new releases of the product when the length of database index records has changed.

Action:

None. Forward recovery continues processing with a new forward recovery data set.

SARDRP07

Device residence error for

Reason:

The residence or location of the forward recovery data set on a DASD device has changed. This condition can occur when a forward recovery data set is moved to a different volume or to a different location in the same volume.

Action:

None. Forward recovery continues processing with a new forward recovery data set.

SARDRP08

Insufficient space allocation for

Reason:

The space allocation for the forward recovery data set was not large enough to contain its internally maintained control records and archival control data.

Action:

Increase the primary and/or secondary space allocation amount for the forward recovery data set that is identified by the RCVPRIM and RCVSEC initialization parameters.

SARDRP10

Invalid or overlaid control block

Reason:

The internal control block structure that is used to control the forward recovery data sets has been overlaid or destroyed.

Action:

This error can occur from incorrectly modified user exits or from internal logic errors. Forward recovery is disabled as indicated by the SARDRP99 message. Forward recovery can be restarted by recycling the archival task or by initiating a backup cycle. For assistance, contact Technical Support at <http://ca.com/support>.

SARDRP11

This message number represents one of the following messages:

Read functions not permitted during output processing

Write functions not permitted during input processing

Reason:

I/O activity issued against a forward recovery data set is inconsistent with its designed processing features.

Action:

This error identifies a flaw in the internal processing logic. Contact CA Technical Support for resolution.

SARDRP12

Write of group control record required before writing of record or auxiliary data

Reason:

I/O requests to write archived data or auxiliary data to the forward recovery data set are not preceded by an I/O request to write the archival group control that identifies the archival data.

Action:

This error identifies a flaw in the internal processing logic. For assistance, contact Technical Support at <http://ca.com/support>.

SARDRP13

Possible data lost on**Reason:**

Forward recovery was unable to successfully write control data and/or archival data to the forward recovery data set.

Action:

This error is accompanied by the SARDRP12 I/O error message. Processing usually continues with a new forward recovery data set. In extreme cases, forward recovery is disabled as indicated by the SARDRP99 message. Restart forward recovery by recycling the archival task or by initiating a backup cycle.

SARDRP20

Data set "dataset" created on volume xxxxxx**Reason:**

This message indicates that a forward recovery data set has been allocated on the specified volume.

Action:

None. This is an informational message.

SARDRP21

Data set "dataset" deleted**Reason:**

This message indicates that a forward recovery data set has been deleted. Old forward recovery data sets are deleted as part of the normal processing flow at the end of the backup cycle.

Action:

None. This is an informational message.

SARDRP99

Forward recovery capture deactivated for dataset

Reason:

The SARSTC archival task has stopped the process of capturing SYSOUT and writing a duplex copy of it to the forward recovery data set. This message is normal during shutdown of SARSTC.

Action:

No action is required for normal shutdown. Check for previous error messages indicating I/O errors on the forward recovery data set if this message occurs at a time other than normal shutdown.

SARDVP01

Index file - space allocation verification

Reason:

The index file space allocation is being verified.

Action:

None. This is an informational message.

SARDVP02

*** Space allocation corrected

Reason:

The space allocated for the file overlaps the space allocation of another. The allocation has been corrected.

Important! Some of the data can be lost.

Action:

None. This message is informational.

SARDVP03

***** Invalid block pointer corrected**

Reason:

The file contains an invalid block pointer. The pointer has been corrected. Some of the data can be lost.

Action:

None. This message is informational.

SARDVP04

Re-write of data base allocation blocks

Reason:

The database allocation blocks are being rewritten.

Action:

None. This is an informational message.

SARDVP05

Index file - logical index verification

Reason:

The contents of the index file are being logically verified.

Action:

None. This is an informational message.

SARDVP06

***** Index entry deleted for KEY=**

Reason:

A logical error is found in the index file. The index entry is deleted.

Action:

None. This is an informational message.

SARDVP07

***** Index entry set to high KEY=**

Reason:

A logical error is found in the index file. The index entry is corrected to the high key for the lower block.

Action:

None. This is an informational message.

SARDVP08

***** Invalid data record removed from index**

Reason:

A logical error is found in the index file. Unrecognizable data is found in an index entry. The entry is corrected.

Action:

None. This is an informational message.

SARDVP09

***** Index data record deleted for KEY=**

Reason:

A logical error is found in the index file. The index data record is deleted.

Action:

None. This is an informational message.

SARDVP10

***** Invalid index key removed from index**

Reason:

A logical error is found in the index file. The number of index entries in an index block is in error and has been corrected.

Action:

None. This is an informational message.

SARDVP11

*** Index block used data count corrected

Reason:

A logical error is found in the index file. The used data count is in error and has been corrected.

Action:

None. This is an informational message.

SAREA00S

```

*****
*                                     *
*           EXPANDED ACCESS SERVER           *
*   SAREAS (XXXX) HAS ABENDED WITH CODE XXXXX *
*           ***** RESTART SAREAS ASAP ***** *
*                                     *
*****

```

Reason:

The expanded access server for tape and robotics has abended. The system or user abend code is provided.

Action:

Consult the *IBM MVS System Messages* manual to determine the reason for the abend. If you still cannot determine the problem, contact CA Technical Support.

SAREA01S

**SAREAS (xxxx) TASK HAS ABENDED WITH CODE XXXXX TASK=xxxxxxxxx,
REQUEST=xxxxxxxxx, TYPE=N, REQUESTER=xxxxxxxxx**

Reason:

A tape-processing task of the expanded access server for tape and robotics has abended. The system or user abend code, TCB address, process request entry address, process request type, and the job ID of the requestor are provided.

Action:

Consult the *IBM MVS System Messages* manual to determine the reason for the abend. If you still cannot determine the problem, contact Technical Support at <http://ca.com/support>.

Note: The task is restarted automatically and processing continues.

SAREA02I

TASK WILL BE RESTARTED FOR SAREAS (*jobname/sysid*)

Reason:

A tape-processing task of the expanded access server for tape and robotics has abended and is being restarted automatically.

Action:

None. This is an informational message.

SAREA03S

DYNAMIC ALLOCATION ERROR FOR SAREAS (*jobname/sysid*) ERROR=*xxxx*, INFO=*xxxx*, DSN=*dsname*

Reason:

Dynamic allocation failed for the tape specified by dsname. The hexadecimal error and information codes are provided.

Action:

None. The tape cannot be used. Processing continues.

SAREA04I

NUMBER OF PROCESS REQUEST ENTRIES FOR SAREAS (*jobname/sysid*) ALLOCATED=*N*, HIGH WATER=*N*

Reason:

This message is displayed whenever the server is stopped. You can use the information that is provided to adjust the NREQ initialization parameter.

Action:

None. This message is informational.

SAREA05S

DEVICE TYPE *x'xxxxxxxx'* INVALID FOR SAREAS (*jobname/sysid*), DSN=*dsname*

Reason:

The device type is invalid for the tape specified by dsname. The server can only process 3480/3490 type cartridge tapes.

Action:

None. The tape cannot be used. Processing continues.

SAREA06S

ATTEMPT TO ACCESS SARTCP COPIED TAPE FOR SAREAS (*jobname/sysid*) DSN=*dsname*

Reason:

An attempt is made to read data from a copy of an archival tape that had been created by the SARTCP utility. SARTCP created tapes cannot be used directly. However, the data on the SARTCP created tape can be made available again by compacting the tape to another tape with the SARPAC utility.

Action:

None. The tape cannot be used. Processing continues.

SAREA09S

PRIMARY SERVER IS ALREADY ACTIVE FOR SAREAS (*jobname/sysid*)

Reason:

The primary server is already active and cannot be started again.

Action:

None. This is an informational message.

SAREA10S

SAREAS (*xxxx*) IS ALREADY ACTIVE

Reason:

The server is already active on this system and cannot be started again.

Action:

None. This is an informational message.

SAREA11W

INVALID COMMAND FOR SAREAS (*jobname/sysid*) Command=xxxxxxxxxxxxxxxxxxxx

Reason:

The specified operator command is invalid.

Action:

Reissue the operator command in its correct form.

SAREA12W

**INVALID INITIALIZATION PARAMETER FOR SAREAS (*jobname/sysid*)
KEYWORD=xxxxxxx,VALUE=xxxxxxx**

Reason:

The specified parameter is invalid. The server uses the default value for the parameter and continues processing.

Action:

Correct the initialization parameter in the start procedure JCL.

SAREA13W

**INVALID SERVER TYPE FOR SAREAS (*JOBNAME/SYSID*)
KEYWORD=xxxxxxx,VALUE=xxxxxxx**

Reason:

The specified server type is invalid. The server uses the default value ONLY for the server type and continues processing.

Action:

Correct the initialization parameter in the start procedure JCL.

SAREA15I

THE FOLLOWING PARAMETERS ARE BEING USED FOR SAREAS

SAREA16I

(JOBNAME/SYSID): KEYWORD = VALUE

Reason:

A listing of the parameters that are actually used by the server is provided at startup time.

Action:

None. This message is informational.

SAREA17W

**XCF xxxx REQUEST FAILED FOR SAREAS (JOBNAME/SYSID), RETURN=xxxx,
REASON=xxxx**

Reason:

The specified XCF request failed. The hexadecimal return and reason codes are provided.

Action:

For the return and reason codes to determine the cause of the failure, see the *IBM Authorized Assembler Reference Guide*. If you still cannot determine the problem, Contact CA Technical Support.

SAREA18W

**L-SERV xxxx REQUEST FAILED FOR SAREAS (JOBNAME/SYSID), RETURN=xxxx,
REASON=xxxx**

Reason:

The specified L-Serv request failed. The hexadecimal return and reason codes are provided.

Action:

Consult the *CA L-Serv System Guide* for the return and reason codes to determine the cause of the failure. If you still cannot determine the problem, contact CA Technical Support.

SAREA19W

INVALID COMMUNICATION MECHANISM FOR SAREAS (*JOBNAME/SYSID*)
KEYWORD=xxxxxxx,VALUE=xxxxxxx

Reason:

The specified communication mechanism is invalid. The server uses the default value LSERV for the communication mechanism and continues processing.

Action:

Correct the initialization parameter in the start procedure JCL.

SAREA20I

COMMUNICATIONS RESET FOR SAREAS (*jobname/sysid*)

Reason:

The COMMRESET operator command was successfully executed.

Action:

None. This is an informational message.

SAREA21I

UNLOAD COMMAND POSTED FOR SAREAS (*jobname/sysid*)

Reason:

The UNLOAD operator command is posted to the tape processing threads.

Action:

None. This message is informational.

SAREA22W

Unable to modify NTHREADS to *nnn* for SAREAS (*taskname/smfid*)

SAREA22W

Maximum value is xxx. Current value is yyy.

This message number represents a two line message:

Reason:

SAREAS has processed a modify NTHREADS command request and rejected the new value (*nnn*) for NTHREADS. *xxx* is the value that was specified when the task was started, and *yyy* is the current value for NTHREADS.

Action:

Correct the NTHREADS value.

SAREA23I

NTHREADS modified to *nnn* for SAREAS (*taskname/smfid*)

Reason:

SAREAS has processed a modify NTHREADS command request and accepted the new value (*nnn*) for NTHREADS.

Action:

None. This is an informational message.

SAREDM01

XXXXXXXX - Invalid or missing printer id

Reason:

The SARINIT initialization parameter *xxxxxxxx* contains an invalid or missing printer ID.

Action:

Correct the initialization parameter.

SAREDM02

XXXXXXXX - Invalid sysout class

Reason:

The SARINIT initialization parameter *xxxxxxxx* contains an invalid SYSOUT class.

Action:

Correct the initialization parameter.

SAREDM03

XXXXXXXX - Invalid destination

Reason:

The SARINIT initialization parameter `xxxxxxxx` contains an invalid destination.

Action:

Correct the initialization parameter.

SAREDM04

XXXXXXXX - Invalid forms name

Reason:

The SARINIT initialization parameter `xxxxxxxx` contains an invalid forms name.

Action:

Correct the initialization parameter.

SAREDM05

XXXXXXXX - Invalid external writer name

Reason:

The SARINIT initialization parameter `xxxxxxxx` contains an invalid external writer name.

Action:

Correct the initialization parameter.

SAREDM06

Invalid external print interface

Reason:

An invalid external print interface is found in the master control record. Only types JESDS and PGM are valid.

Action:

Run SARINIT to correct the external print initialization parameters.

SAREDM07**Dynamic allocation Err=xxxx Info=xxxx****Reason:**

Dynamic allocation failed for the JESDS data set. The hexadecimal error and information codes are provided.

Action:

Run SARINIT to correct the external print initialization parameters.

SAREDM08**Too many distids/instructions for external print request****Reason:**

Too many distribution identifiers, special instructions, or both are contained in the CA Deliver external print request.

Action:

Reissue the external print request with fewer distribution identifiers, special instructions, or both.

SAREDM09**XXXXXXXX - Invalid or missing interface type****Reason:**

The SARINIT initialization parameter xxxxxxxx contains an invalid or missing interface type.

Action:

Correct the initialization parameter.

SAREDM10**XXXXXXXX - Invalid or missing program name****Reason:**

The SARINIT initialization parameter xxxxxxxx contains an invalid or missing program name.

Action:

Correct the initialization parameter.

SAREDM11

XXXXXXXX - Invalid program parameter

Reason:

The SARINIT initialization parameter `xxxxxxxx` contains an invalid program parameter.

Action:

Correct the initialization parameter.

SAREDM12

Load failed for external print interface program XXXXXXXX

Reason:

The external print interface was unable to load program `xxxxxxxx`.

Action:

Correct the program name in the corresponding external *print* initialization parameter. If it is already correct, supply the STEPLIB DD statement for the library that contains the program.

SAREPI01

Invalid function code

Reason:

The requested function code is invalid. This problem is in the coding of the external print interface product.

Action:

Contact the vendor who supplied the external print interface product for a resolution.

SAREPI02

Invalid initialization token passed

Reason:

The requested initialization token is invalid, probably the result of an improper initialization request. This problem is in the coding of the external print interface product.

Action:

Contact the vendor who supplied the external print interface product for a resolution.

SAREPI03

Invalid access token passed

Reason:

The requested access token is invalid, probably the result of an improper access request. This problem is in the coding of the external print interface product.

Action:

Contact the vendor who supplied the external print interface product for a resolution.

SAREPI04

Invalid external print record

Reason:

The external print record is invalid. This problem is in the coding of the external print interface product.

Action:

Contact the vendor that supplied the external print interface product and have them correct the error.

SAREPI05

Database at incorrect level for this release

Reason:

The program load modules and the database are not at the same release level. CA View does not execute.

Action:

Correct the problem and retry.

SAREPI06

GCR not found for ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The group control record for the archived SYSOUT cannot be found in the database. A user deleting the SYSOUT GROUP between the time it was queued for external printing and the time that the external print actually occurs usually causes this issue.

Action:

None. The SYSOUT group is no longer available.

SAREPI07

Page selection text conflicts with page and/or record specification

Reason:

A page range, record range, or both are specified for an external print of a page selection request for a SYSOUT group.

Action:

Resubmit the external print request omitting the page range, record range, or both.

SAREPI08

Page selection text specified without a valid logical view

Reason:

The page selection text specification requires a valid logical view.

Action:

Resubmit the external print request with a valid logical view.

SAREPI09

Sysout is not on disk and its index is unavailable for page selection

Reason:

The SYSOUT group does not currently reside on DISK and its page selection is not available.

Action:

Reload the SYSOUT group to disk and then resubmit the external print request.

SAREPI13

Requested sysout does not exist on any tape backup data set

Reason:

The SYSOUT group that is requested for the external print cannot be found on any backup tape.

Action:

None. The SYSOUT group is not available on tape.

SAREPI14

The tape file was not the selected sysout group - use SARTCP to map the tape

Reason:

The SYSOUT group that is located on the backup tape for external printing is not the SYSOUT as referenced in the master index.

Action:

Use the SARTCP utility to map and correct the backup tape.

SAREPI15

Backup tape does not exist

Reason:

The backup tape cannot be found in the master index. This is usually caused by the backup cycle deleting the tape before completion of the load request.

Action:

None. The SYSOUT group is no longer available.

SAREPI16

Dynamic allocation failed for tape file, Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for allocating the backup tape file. The hexadecimal error and information codes are provided.

Action:

Consult the online retrieval HELP facility for a description of the dynamic allocation error code. Take appropriate action to correct the allocation error, and then resubmit the print request.

SAREPI17

I/O error positioning tape

Reason:

A permanent I/O error occurred attempting to position the archival tape to retrieve the SYSOUT group for external printing.

Action:

Resubmit the request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape.

SAREPI19

Permanent I/O error on input tape

Reason:

A permanent I/O error occurred attempting to read SYSOUT data from a backup tape.

Action:

Resubmit the request. If the I/O error occurs again, use the SARTCP utility to map and correct the tape.

Note: For more information about recovery methods, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SAREPI20

View not found

Reason:

The specified view does not exist in the master index.

Action:

Verify the existence of the view. If the view number was specified incorrectly, change the parameter specification, and then resubmit the external print request.

SAREPI33

Select specified without a valid logical view

Reason:

The external print request specifying the SELECT keyword has failed because no views exist for the SYSOUT.

Action:

Do one of the following actions:

- Remove the SELECT keyword, and then resubmit the external print request.
- Specify a view number that contained page indexing criteria when the SYSOUT was archived, then resubmit the request.

Page indexing occurs only during archival.

SAREPI34

Error occurred attempting to read in the index for the sysout

Reason:

The external print request specifying the SELECT keyword has failed because an I/O error occurred while opening or reading the page index data from the database. The data is unreadable.

Action:

Do one of the following actions:

- Remove the SELECT keyword, and then resubmit the external print request.
- Rebuild the page index data as follows:

Note: The index can be rebuilt only by re-archiving the SYSOUT.

1. Reprint the SYSOUT to a held class.
2. Delete the SYSOUT from CA View.
3. Release the SYSOUT to CA View for re-archival, retaining the same SYSOUT-ID.
4. Resubmit the print request.

SAREPI35

Sysout has not been indexed for the logical view

Reason:

The external print request specifying the SELECT keyword has failed because indexing has not been established for the view.

Action:

Establish indexing criteria for the view if it does not exist. Re-archive the SYSOUT. Page indexing occurs only during archival.

SAREPI36

No pages found that match selection text

Reason:

The external print request specifying the SELECT keyword has failed because the SELECT text ID did not match any index selection.

Action:

Check that the SELECT text and index selection criteria are as intended. Re-archive the SYSOUT if the page indexing criteria is changed. Page indexing occurs only during archival.

SAREPI48

Report print suppressed by SARPRTUX

Reason:

SARSTC issues this message when a non-zero return code is returned by SARPRTUX.

Action:

This message is informational, no action is required.

SARFAG02

INVALID RECORD NUMBER

Reason:

An internal request is made to position to an invalid record in the report index file.

Action:

The database record for the report contains an invalid starting position for the extracted report index data. This condition is due to database corruption. The positioning information can be reestablished by re-indexing the report.

SARFAL01

**LOGICAL I/O ERROR PROCESSING INDEX FILE FOR REPORT "XXXXXXXXXXXX" GEN=XXXXX
SEQ=XXXX'**

Reason:

An I/O error occurred while attempting to read index data for the referenced report.

Action:

The I/O error can be corrected by re-indexing the report. If problems persist, restore the database.

SARFA001

REPORT "*reportid*" GEN=XXXXX SEQ=XXXXX NOT AVAILABLE FOR ACCESS

Reason:

The identified report is not accessible through the expanded access server, or online viewing of the report is not allowed due to the specification of the VIEWTAPE=NO ERO parameter.

Action:

If the report is accessible through the expanded access server, make the SAREAS task is active. Otherwise, load the report into the database.

SARFA002

**LOGICAL I/O ERROR PROCESSING INDEX FILE FOR REPORT "*reportid*" GEN=XXXXX
SEQ=XXXX'**

Reason:

An I/O error occurred while attempting to read index data for the referenced report.

Action:

The I/O error can be corrected by re-indexing the report. If problems persist, restore the database.

SARFAP01

**LOGICAL I/O ERROR PROCESSING INDEX FILE FOR REPORT "*reportid*" GEN=*xxxxx*
SEQ=*xxxxx*'**

Reason:

An I/O error occurred while attempting to read index data for the referenced report.

Action:

The I/O error can be corrected by re-indexing the report. If problems persist, restore the database.

SARFRO01

NO RESOURCE FOR REPORT "*reportid*" GEN=*xxxxx* SEQ=*xxxxx*

Reason:

The report that you have requested needs a resource to display correctly. This resource cannot be found on the database. (ACIF and Xerox reports have resources.)

Action:

Reload report from tape.

SARFRO02

RESOURCE NOT FOUND FOR REPORT "*reportid*" GEN=*xxxxx* SEQ=*xxxxx*

Reason:

The report that you have requested needs a resource to display correctly. This resource cannot be found on the database. (ACIF and Xerox reports have resources.)

Action:

Reload report from tape.

SARFSG02

INVALID RECORD NUMBER

Reason:

An internal request is made to position to an invalid record in the report.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARFSG03

INVALID PAGE NUMBER

Reason:

An internal request is made to position to an invalid page in the report.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARFSA03

FSA CONNECT FAILED FOR *fssname*, SSOBRETN=*nnnn* FSIRESN=*nnnn*

Reason:

The connect request from the FSA to JES failed; the return and reason codes are provided.

Action:

The FSA is terminated.

SARFSA04

FSA DISCONNECT FAILED FOR *fssname*, SSOBRETN=*nnnn*,FSIRESN=*nnnn*

Reason:

The disconnect request from the FSA to JES failed; the return and reason codes are provided.

Action:

The FSA is terminated.

SARFSA05

FSA SEND FAILED FOR *fssname*, RC=*nnnn*

Reason:

A send request from the FSA to JES failed; the return and reason codes are provided.

Action:

The FSA is terminated.

SARFSA06**FSA GETDS FAILED FOR *fssname*, RC=*nnnn*****Reason:**

A get data set request from the FSA to JES failed; the return and reason codes are provided.

Action:

The FSA is abnormally terminated.

SARFSA07**FSA RELDS FAILED FOR *fssname*, RC=*nnnn*****Reason:**

A release data set request from the FSA to JES failed; the return and reason codes are provided.

Action:

The FSA is abnormally terminated.

SARFSA08**FSA GETREC FAILED FOR *fssname*, RC=*nnnn*, GLRFLGS1=*nnnn*****Reason:**

A get record request from the FSA to JES failed; the return and reason codes are provided.

Action:

The FSA is abnormally terminated.

SARFSA09**FSA GETREC PERMANENT I/O ERROR FOR *fssname*****Reason:**

A permanent I/O error occurred attempting to get a record from JES.

Action:

Processing for the data set is ended, and execution continues.

SARFSA10

FSA GETREC LOGIC ERROR FOR *fssname*

Reason:

A logical I/O error occurred attempting to get a record from JES.

Action:

Processing for the data set is ended, and execution continues.

SARFSA11

fssname* OPEN FAILED FOR DEVICE DD STATEMENT *ddname

Reason:

An attempt to open the input parameter file for the device failed.

Action:

The FSA is terminated.

SARFSA13

***fssname* FIRST CNTL STATEMENT IS NOT "TYPE="**

Reason:

The first control statement in the input parameter file for the device must be a TYPE= statement.

Action:

The FSA is terminated. Add the TYPE= control statement.

SARFSA14

UNDEFINED DATA COLLECTOR "TYPE" FOR *fssname*

Reason:

An invalid data collector name is specified on the TYPE= statement in the input parameter file for the device.

Action:

The FSA is terminated. Correct the TYPE= control statement.

SARFSA15

LOAD MODULE *module* NOT FOUND FOR *fssname*

Reason:

The load module is not found for the FSA.

Action:

The FSA is terminated. Verify that the correct step/job libraries are specified in the FSS startup procedure.

SARFSA16

SJF RETRIEVE ERROR FOR *fssname*, RC=*nnnn*

Reason:

An error occurred attempting to retrieve the OUTPUT statements for a data set.

Action:

The data set is placed on hold and not processed.

SARFSA17

fssname* CONTROL STATEMENT - *xxxxxxxxxxxxxxxxxxxx

Reason:

A copy of the input parameter statement is logged.

Action:

None. This is an informational message.

SARFS001

REPORT "*reportid*" GEN=*xxxxx* SEQ=*xxxxx* NOT AVAILABLE FOR ACCESS

Reason:

The identified report is not accessible through the expanded access server, or online viewing of the report is not allowed due to the specification of the VIEWTAPE=NO ERO parameter.

Action:

If the report is accessible through the expanded access server, make the SAREAS task is active. Otherwise, load the report into the database.

SARFSS01

***fssname* NOT STARTED BY JES**

Reason:

An attempt has been made to start the FSS directly with a START operator command, bypassing JES.

Action:

Use the appropriate JES command to start the FSS.

SARFSS02

INVALID START COMMAND FOR *fssname*

Reason:

An invalid start command is issued for the FSS.

Action:

Use the appropriate JES command to start the FSS.

SARFSS03

FSS CONNECT FAILED FOR *fssname*, SSOBRETN=*nnnn* FSIRESN=*nnnn*

Reason:

The connect request from the FSS to JES failed.

Action:

Take the appropriate action, based on the return and reason codes provided.

SARFSS04

FSS DISCONNECT FAILED FOR *fssname*, SSOBRETN=*nnnn*,FSIRESN=*nnnn*

Reason:

The disconnect request from the FSS to JES failed; the return and reason codes are provided.

Action:

Take the appropriate action, based on the return and reason codes provided.

SARFVC03**INVALID INITIALIZATION PARAMETER *keyword=parm* FOR *product*****Reason:**

A keyword is misspelled in the `//PRTnnn` statement.

Action:

Correct the keyword, and then resubmit the job.

SARFVC04**INVALID INITIALIZATION VALUE *keyword=parm* FOR *product*****Reason:**

A keyword is assigned an invalid value.

Action:

Correct the keyword, and then resubmit the job.

SARFVC05**UNDEFINED DATA BASE HIGH-LEVEL NAME FOR *product*****Reason:**

The database name that is specified as the NAME statement was not found.

Action:

Correct the name, and then resubmit the job.

SARFVC06**INDEX CONTROL MEMBER *member* NOT FOUND FOR *product*****Reason:**

Either the index member name is misspelled, or it does not exist.

Action:

Correct the name, and then resubmit the job.

SARFVC07

ERROR OPENING SARINDEX DD STATEMENT FOR *product*

Reason:

A media problem exists.

Action:

Verify that the volume is online and functioning properly.

SARFVC08

DATA BASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The database is not at the appropriate level.

Action:

Verify that your database level (set with the SARDBASE utility) is correct, and then rerun SARDBASE if necessary.

SARFVC09

INVALID KEYWORD PARAMETER "*keyword*" IN SARINDEX MEMBER *member-name* (BYPASSED)

Reason:

A keyword is misspelled in a SARINDEX *member-name* group parameter control statement.

Action:

Correct the keyword, and then resubmit the job.

SARFVC10

OPEN FAILED FOR ACCOUNTING FILE (SARACT) – ARCHIVAL JOB ACCOUNTING DISABLED ON *product*

Reason:

A SARACT DD statement was present in the job stream, but the data set failed to open successfully.

Action:

Verify that the data set is correct, or remove the DD statement to disable accounting.

SARFVC11

INVALID RECORD LENGTH OF BLOCK SIZE FOR ACCOUNTING FILE (SARACT) ARCHIVAL JOB ACCOUNTING DISABLED ON *product*

Reason:

The data set specified by the SARACT DD statement has an invalid logical record length, an invalid block size, or is not a CA View accounting file.

Action:

Verify that the data set is correct, or remove the DD statement to disable accounting.

SARFVC22

product PROCESSING jobname(jobid) jobdsn

Reason:

This is an informational message.

Action:

None.

SARFVC23

MAXIMUM LINES EXCEEDED FOR *jobname(jobid)*

Reason:

The SYSOUT line count exceeds the MAXLINES initialization parameter value of the database.

Action:

None. This message is informational.

SARFVC24

No more space in database ...db_hlq... Reply R (retry) T (terminate)

Reason:

There is not enough space in the database to perform the archival.

Action:

Reply with either an R to reattempt archival or a T to terminate:

1. Run the SARDBASE program to add more space to the database, or manually delete SYSOUT groups to free up space while the archival task waits. After you make more space available, reply R to have the archival task retry its archival with the additional space.
2. Reply T to terminate the archival task.

SARFVC25

This message number represents one of the following:

Sequence number will WRAP for report 'report id' Reply R (retry) after a standard backup or T (terminate)

Invalid reply

Reason:

Each unique report id can have up to 65,535 copies per database generation. A 'generation' being the time between Full Backup Cycles. Each unique report id in a generation is assigned sequential numbers from 1 to 65,535. After 65,535, the sequence number will wrap back to zero and date selection problems will occur. This message gives a chance to the user to run a backup cycle so this number can be reset to one.

The second format of SARFVC25 is displayed if a response other than 'R' or 'T' is given to the original message.

Action:

Reply with either an R after a backup cycle has been started or a T to terminate. The SARFVC25 message can be reissued after replying T and re-starting the View FSS Collector.

SARFVC99

jobid jobname text

Reason:

The View Collector user exit (SARFVCUX) requested the display of a message with the specified *text*.

Action:

This depends on the site's requirements for the message.

SARGAM01

Database "xxxxxxx" at incorrect level for this release

Reason:

The program load modules and the database are not at the same version level. This is normally caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to old load modules, or the database has not been converted to the correct version level (new versions of the product can require conversion of the database).

Action:

You can either STEPLIB to the correct load modules or convert the database to the correct release level.

SARGAM02

Error opening or reading auxiliary file for report "rid", Gen=gen, Seq=seq

Reason:

During CA Deliver bundle or rerun processing SARGAM failed to open or read the auxiliary file for a dynamic report.

Action:

Review your CA Deliver Dynamic Report definitions.

SARGET01

**** Maximum lines exceeded specified limits ****

Reason:

Your print request exceeded the maximum number of lines that are permitted during a batch or on-line print request. The reprint line limit could have been defined in the VTAM Printer Device Definition, the CA Spool Device Definition, or the OUTLIM Initialization Parameter. This message appears at the end of the report which was being printed and the remainder of the report is truncated.

Action:

Do one of the following actions:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Increase the maximum permitted for all devices by using SARINIT parameter OUTLIM.
- Make multiple separate print requests.

SARGET02

***** MAXIMUM LINES EXCEEDED ON CMASPOOL PRINTER *****

Reason:

Your print request exceeded the maximum number of lines that are permitted during CA Spool print processing. This message can also occur on non-VTAM printers simultaneously.

Action:

Do one of the following actions:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Make multiple separate print requests.

SARGGT03**INVALID OPERATION TYPE****Reason:**

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARGGT04**INVALID INDEX RECORD ADDRESS****Reason:**

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARGGT05**USER NOT AUTHORIZED TO ACCESS REPORT "*reportid*" GEN=*xxxxx* SEQ=*xxxxx*****Reason:**

User does not have access to the requested report.

Action:

Check with your Security Administrator.

SARGOP03**NO SELECTABLE REPORTS FOR USERS DISTRIBUTION ID****Reason:**

The distribution ID referenced in the CA View user profile is not defined or has no reports that are defined to it. For EXP mode users, the DISTID and applicable reports are defined in CA Deliver. For SAR mode users, the DISTID and applicable reports are defined in CA View.

Action:

To produce lists of reports for the user, define the reports to the associated DISTID with CA Deliver (for EXP mode users) or CA View (for SAR mode users).

SARGOP04

UNABLE TO QUALIFY SELECTION OF REPORT DUE TO MISSING CA DELIVER INTERFACE ROUTINE (RMOGAM).

Reason:

The library containing the RMOGAM module is not defined to the DRAS task or is not accessible.

Action:

Add the CA Deliver load library to the STEPLIB or JOBLIB concatenation for the DRAS job or started task. Or, add the CA Deliver load library to the linklist.

SARH001E

CA View database "xxxxxxxx" has detected a setting of MASTER=ALL

Reason:

A warning that MASTER is set to ALL. The CA View MASTER=ALL setting is designed to allow for initial creation of a database. MASTER=ALL indicates no restrictions, so that all users have access to administrative functions.

When a database is used in a production environment, change the SARINIT MASTER parameter to MASTER=userid. This does not limit MASTER authority to a single user. A user with master authority can assign master authority to any other user through the online DEF USER command.

Action:

Contact the administrator responsible for this CA View database. The following response is the best to this condition:

1. Determine the user ID of the master user for this database.
2. Run SARINIT with the MASTER=userid parameter.
3. Notify this user to use the DEF USER command to assign master authority to any other users that require administrative access.

Changing the parameter does not require the CA View started task to be cycled. As users log on to the system, the new value is used.

SARH001I

CA VIEW database "xxxxxxx" has identified the master user as uuuuuuuu. This restricts access to administrative database functions and adheres to the best practices standards.

Reason:

Informational message.

Action:

None.

SARH003E

CA View database "xxxxxxxxx" has detected the default setting for CLSL/FORM/DEST. This will cause every non-held sysout in the spool to be archived to CA View and deleted from JES.

Reason:

A warning that all three parameters CLSL/FORM/DEST are not set and CA View archives all classes, all forms, and all destinations. CA View archives sysouts based on CLSL, FORM, and DEST parameters. For a sysout to be archived, it must meet the selection criteria that are specified by all three of these parameters. If a parameter is not set, it defaults to all classes or forms or destinations.

Action:

Stop or Cancel the CA View started task. Notify the systems programmer. The following response is the best to this condition:

1. Run SARINIT and set either CLSL, FORM, or DEST to a non-blank value. This restricts the sysouts that CA View can archive.
2. Review any sysouts that are archived in error--these can be viewed and reprinted within CA View.
3. Restart the CA View started task.

SARH003I

CA VIEW has verified that database "....." will selectively archive sysouts based on the following parameters: CLSL=xxx, FORM=yyy, DEST=zzz

Reason:

Informational message.

Action:

None.

SARH004E

CA View database "xxxxxxxx" has detected a setting of TBACKUP=NO.

Reason:

A warning that TBACKUP=NO is set. CA View database backup occurs automatically or can be manually triggered through operator commands. When NO is set, the backup cycle runs and deletes expired reports, but neither the master index nor the new report data are written to a backup tape. If a hardware or software error occurs, the database cannot be restored using CA View utilities. CA View continues processing.

Action:

Notify the systems programmer. The following response is the best to this condition:

1. Run SARINIT and set TBACKUP=YES.
2. Optionally, you can also set TBACKUP=INDEX if you are migrating reports to a Centera device.
3. Recycle the CA View started task.

SARH004I

CA VIEW has verified the setting of the TBACKUP parameter. Setting TBACKUP=YES insures that the CA View database can be restored via CA View utilities.

Reason:

Informational message.

Action:

None.

SARH005E

CA View database "xxxxxxxx" has detected a setting of ENCRYPT=ICSF, but encryption hardware (CPACF) is not installed on this machine.

Reason:

This message is informational. CA View can encrypt and decrypt reports without encryption hardware, but emulating encryption hardware is very CPU intensive.

Action:

See the CA View Health Checks section earlier in this guide for more information.

SARH005I

CA View has detected that CA View database "xxxxxxxxx" has a setting of ENCRYPT=ICFS. This machine has the recommended hardware encryption (CPACF) support to minimize the CPU encryption overhead.

Reason:

Informational message.

Action:

None.

SARIAP01

INVALID GROUP CONTROL RECORD, ID=xxxxxxxxxxxx, GEN=nnnn and SEQ=nnnn IGNORED.

Reason:

An attempt is made to add a SYSOUT group index record with an invalid generation and sequence number. The record is ignored and processing continues.

Action:

None. This message is informational.

SARICF01

ICSF key(s) generated - be sure to backup ICSF CKDS data

Reason:

New keys have been placed in the ICSF CKDS data set. Back up this data set as soon as possible.

Action:

CA View has updated encryption keys in the ICSF CKDS dataset. These keys are required when encrypting and decrypting report data. To insure that these keys are available, back up this data set and send it to your disaster recovery site.

SARICF02

ICSF error - Service=xxxxxxx RC=nnn Reason=nnn Entry=nnn

Reason:

ICSF has returned an error code. The return and reason codes are described in Appendix A of the IBM publication ICSF Application Programmers Guide (SA22-7522).

xxxxxxx is the name of the ICSF service that failed.

Action:

For assistance, contact Technical Support at <http://ca.com/support> (see page 3).

SARICF03

ICSF not active - Service=xxxxxxx RC=nnn Reason=nnn Entry=nnn

Reason:

The ICSF services task is not active or available. The return and reason codes are described in Appendix A of the IBM publication ICSF Application Programmers Guide (SA22-7522).xxxxxxx is the name of the ICSF service that failed.

Action:

Ensure that ICSF is running on the system where the error occurred.

SARICF04

ICSF not installed - Service=xxxxxxx Entry=nnn

Reason:

The ICSF service routine xxxxxxxx is not resident in the link list. During ICSF installation, the ICSF service routines are placed in the link list and made available to all applications. The non-availability of the service routine indicates that ICSF has not been installed.

Action:

Ensure that ICSF is installed correctly. For assistance, contact Technical Support at <http://ca.com/support>.

SARICF05

ICSF key xxxxxxxx not found - Entry=nnn

Reason:

CA View has requested the above key from the ICSF key store (CKDS) and it was not found. This type of error occurs when the CKDS has been restored to an old version or multiple CKDS data sets are used for the same CA View database.

xxxxxxx is the name of the missing key

Action:

Contact Technical Support at <http://ca.com/support> to determine if the key can be recovered and the extent of the data loss.

SARIFP01

Invalid group control record, ID=reportid, Gen=xxxx, and Seq=xxxx encountered, program terminated

Reason:

An attempt is made to add or update a SYSOUT group index record with an invalid generation and sequence number. Processing is terminated with a USER 100 abend.

Action:

If this occurs during a SARDBASE REORG, the program automatically corrects the error and you can ignore this message. If bad records reside in the database from prior releases of the product, correct the database with the VERIFY control statement from the SARDBASE utility. Otherwise, the processing can be resumed.

For assistance, contact Technical Support at <http://ca.com/support>.

SARIFP02

Critical error, program terminated with dump. Invalid blk

Reason:

A CA View program has terminated, and a dump was generated. In this message, *blk* specifies the control block CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It can be suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart whatever program was terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

SARIFP03

bt-Index block corruption (et) at block dccb on database

bt - Indicates block type:

DL - Data level index block

HL - High level index block

et - Indicates error type:

HK - High key encountered in block

ID - Incorrect block identifier

IS - Index record too small

IL - Invalid index record length

KL - Incorrect key length

LK - Low key encountered in block

LN - Invalid index block length

NI - No index keys in block

SC - Invalid split count

SQ - Index records out of sequence

UN - Unknown type of index block

dccb - Block DASD location

database - Database high level prefix

Reason:

A master index block in the database contains abnormal data. This is usually due to a system failure, power outage, cancellation, or timeout.

1. An error type (*et*) of HK, LK, or SQ indicates the results of an incomplete block split. The block can be corrected as indicated by a subsequent SARIFR07 message. The applicable index records are bypassed.
2. The other error types indicate more severe corruption of the master index.

Action:

For #1, the error condition can be automatically corrected as indicated by a SARIFR07 message. If not, resolve this error condition by performing a standard REORG or an unload/load. For #2, resolve these problems by a database verify or restore.

SARIFP04

bt-Index block corruption at block dccb on database - corrected

bt - Indicates block type:

DL - Data level index block

HL - High level index block

dccb - Block DASD location

database - Database high level prefix

Reason:

A master index block in the database, which contains abnormal data, was corrected. When a system failure, power outage, cancellation, or timeout occurs, I/O to the master index can be interrupted while inserting index records. This condition creates inconsistencies in the master index that can be corrected. This message is preceded by the SARIFR06 message identifying the specific error.

Action:

None. This message is informational.

SARIFR02

REORG HAS PROCESSED TO KEY=XXXXXXXXXXXX

Reason:

This informational message is periodically issued to indicate the progress of an asynchronous SARDBASE REORG.

Action:

None. This message is informational.

SARIFR03

RECOVERED INDEX BLOCKS = nnnn

Reason:

This informational message specifies the number of empty blocks in the index file that have been recovered by an asynchronous SARDBASE REORG.

Action:

None. This message is informational.

SARIFR04

DATABASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The program load modules and the database are not at the same release level. This is normally caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to old load modules, or the database has not been converted to the correct release level (new releases of product may require conversion of the database).

Action:

You can either STEPLIB to the correct load modules or convert the database to the correct release level.

SARIFR05

REORG ENDED AT KEY=XXXXXXXXXXXX

Reason:

A stop command is issued during processing the SARDBASE asynchronous REORG. This message indicates where the asynchronous REORG ended.

Action:

None. This message is informational.

SARIFR06

bt*-INDEX BLOCK CORRUPTION (*et*) AT BLOCK *dccb* ON *database

***bt* - Indicates block type:**

DL - Data level index block

HL - High level index block

***et* - Indicates error type:**

HK - High key encountered in block

ID - Incorrect block identifier

IS - Index record too small

IL - Invalid index record length

KL - Incorrect key length

LK - Low key encountered in block

LN - Invalid index block length

NI - No index keys in block

SC - Invalid split count

SQ - Index records out of sequence

UN - Unknown type of index block

***dccb* - Block DASD location**

***database* - Database high level prefix**

Reason:

A master index block in the database contains abnormal data. This is usually due to a system failure, power outage, cancellation, or timeout.

1. An error type (*et*) of HK, LK, or SQ indicates the results of an incomplete block split. The block can be corrected as indicated by a subsequent SARIFR07 message. The applicable index records are bypassed.
2. The other error types indicate more severe corruption of the master index.

Action:

For #1, the error condition can be automatically corrected as indicated by a SARIFR07 message. If not, resolve this error condition by performing a standard REORG or an unload/load. For #2, resolve these problems by a database verify or restore.

SARIFR07

***bt*-INDEX BLOCK CORRUPTION AT BLOCK *dccb* ON *database*- CORRECTED**

***bt* - Indicates block type:**

DL - Data level index block

HL - High level index block

***dccb* - Block DASD location**

***database* - Database high level prefix**

Reason:

A master index block in the database, which contains abnormal data, was corrected. When a system failure, power outage, cancellation, or timeout occurs, I/O to the master index can be interrupted while inserting index records. This condition creates inconsistencies in the master index that can be corrected. This message is preceded by the SARIFR06 message identifying the specific error.

Action:

None. This message is informational.

SARINA11

Open failed for accounting file

Reason:

The SARA CT DD statement is not provided and is required.

Action:

Specify SARA CT DD statement in execution JCL, and then resubmit the job.

SARINA12

Multiple extents for accounting file

Reason:

The accounting file has multiple extents.

Action:

Recreate the accounting file, and then resubmit the job.

SARINA22

Utility processing successfully completed

Reason:

Processing has successfully completed.

Action:

None. This is an informational message.

SARINI01

Syntax error

Reason:

The specified option statement contains a syntax error.

Action:

Correct the option statement, and then resubmit the job.

SARINI02

Option not found

Reason:

The specified option is not valid.

Action:

Correct the option; then resubmit the job.

SARINI03

Invalid value

Reason:

The specified value is invalid for the option.

Action:

Correct the value; then resubmit the job.

SARINI04

Duplicate statement

Reason:

The option has been previously specified.

Action:

Correct the problem; then resubmit the job.

SARINI05

TVSER1/TVSER2 specified without the other in the storage group

Reason:

Only one volume serial number for a range of volumes has been specified.

Action:

Correct the problem; then resubmit the job.

SARINI06

Code page "XXXXXXXX" is not available

Reason:

The CODEPAGE initialization parameter references a codepage member name that does not exist.

Action:

Ensure that the codepage name indicated on the error message resides in your STEPLIB, JOBLIB, or linklist and rerun.

SARINI07

Tape volume serial numbers do not end with a numeric

Reason:

One of the volume serial numbers for a range of tape volumes does not end with numeric characters.

Action:

Correct the volume serial number, and then resubmit the job.

SARINI08

Tape volume serial numbers are different formats

Reason:

When specifying a range of tape volumes, the volume serial numbers must be of the same format.

Action:

Correct the volume serial numbers, and then resubmit the job.

SARINI09

Secondary disk storage driver not found or not authorized

Reason:

The DSK2DRVR parameter specifies the name of a load module that cannot be found or is not authorized.

Action:

Verify that DSK2DRVR specifies the name of an authorized load module accessible to SARINIT.

SARINI10

Language code "_" is not installed

Reason:

The CA View database contains no panels for the indicated language code.

Action:

Either install the desired panels or specify a language code for panels that are already in the database.

SARINI19

Job/User not authorized to access data base

Reason:

The authorization user exit does not allow the job or user to access the database.

Action:

Consult the system programming group or security group to determine the reason why the authorization user exit explicitly denies access to the database.

SARINI20

Processing terminated due to previous errors

Reason:

Previous errors have occurred.

Action:

A '*' is displayed on the line following the invalid parameter. Correct the invalid parameter or value and retry.

SARINI22

Utility processing successfully completed

Reason:

Processing has successfully completed.

Action:

None. This is an informational message.

SARINI23

Database at incorrect level for this release

Reason:

The program load modules and the database are not of the same release level. CA View does not execute.

Action:

Correct the problem and retry.

SARINI24

GEN=, TAPESEQ=, DRTSEQ= only valid during first init of database; ignored

Reason:

The GEN=, TAPESEQ=, and DRTSEQ= initialization parameters can only be used for newly created databases.

Action:

None. The unacceptable parameters are ignored.

SARINI25**FINDLIM must be less than or equal to FINDMAX****Reason:**

The second portion of the FINDLIM initialization parameter is a maximum for the parameter (that is, FINDLIM=*limit,max-limit*).

Action:

Correct the parameter and rerun.

SARINI26**Tape storage group names must be unique****Reason:**

The tape storage group names which are defined by the STORGRP*n* initialization parameters must be unique.

Action:

Correct the STORGRP*n* parameter and rerun.

SARINI27**Tape storage volser ranges must not partially overlap****Reason:**

The tape VOLSER ranges specified for the STORGRP*n* initialization parameters must be either the same, or disjoint. No partial overlaps are allowed.

Action:

Correct the tape VOLSER ranges for the STORGRP*n* parameter and rerun.

SARINI28**ERO option is not active****Reason:**

The EROOPT=NO initialization parameter was specified and all of the ERO parameters have been removed from the CA View database.

Action:

None. This is an informational message.

SARINI29

Parameter conflict with ERO parameter specification and EROOPT=NO specification

Reason:

The EROOPT=NO initialization parameter was specified, indicating that all ERO options are to be removed and new ERO initialization parameters are being specified.

Action:

Either remove the EROOPT=NO parameter, or remove the ERO initialization parameters and rerun.

SARINI30

Previous update by Job: jjjjjjj on mm/dd/yyyy hh:mm:ss

Reason:

The job specified in the message updated the database initialization parameters on the specified date and time.

Action:

None.

SARINI31

Parameter conflict, DSK2DRVR cannot be specified with CENTADR

Reason:

CA View supports only one type of secondary disk feature for a given database. Centera is implemented as a form of secondary disk storage and cannot be configured in a database which is also using an optical secondary disk feature. The parameters CENTADR and DSK2DRVR are mutually exclusive and only one form of secondary disk can be configured. SARINIT terminates with a return code 16.

Action:

Code either Centera configuration parameters or optical secondary disk parameters for this database.

SARJPS01

Subsystem request failed - return code xxxx

Reason:

A subsystem request failed. The hexadecimal return code is provided.

Note: Conditions that cause error message SARJPS01 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJPS02

Process sysout request failed - return code xxxx

Reason:

A process SYSOUT request failed for the subsystem. The hexadecimal return code is provided.

A return code of X'1C' indicates an invalid destination. Verify that the destination specified with the DEST initialization option is known to JES.

Note: Conditions that cause error message SARJPS02 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJPS03

Subsystem allocation failed - error code xxxx, info code xxxx
Job jobname(jobid), Data set dataset

Reason:

Dynamic allocation failed for the process SYSOUT data set. The hexadecimal error and information codes are provided.

Note: Conditions that cause error message SARJPS03 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJPS04

Subsystem open request failed - return code xxxx, error code xxxx
Job jobname(jobid), Data set dataset

Reason:

A subsystem open request failed. The hexadecimal error and return codes are provided.

Note: Conditions that cause error message SARJPS04 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJPS05

Subsystem get request failed - RPL feedback xxxx

Reason:

A subsystem GET request failed. The hexadecimal feedback code is provided. This is normally due to a system crash while the job that created the data set was executing.

Note: For RPL=08022C, the problem is usually attempting to send a line longer than 32767 bytes.

Action:

None. This is an informational message.

SARJSA01

Subsystem request failed - return code xxxx

Reason:

A subsystem request failed. The return code is provided.

Note: Conditions that cause error message SARJSA01 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJSA02

SAPI process request failed - return code xxxx, reason code xxxx

Reason:

A process SYSOUT request failed for the subsystem. The return and reason codes are provided. For an explanation of the reason and return codes, refer to the operating system IAZSSS2 macro.

A return code of 32 and a reason code of 36 indicate an invalid destination. Verify that the destination specified with the DEST initialization option is known to JES.

Note: Conditions that cause error message SARJSA02 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJSA03

Subsystem allocation failed - error code xxxx, info code xxxx
Job jobname(jobid), Data set dataset

Reason:

Dynamic allocation failed for the process SYSOUT data set. The hexadecimal error and information codes are provided.

Note: Conditions that cause error message SARJSA03 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJSA04

**Subsystem open request failed - return code xxxx, error code xxxx
Job jobname(jobid), Data set dataset**

Reason:

A subsystem open request failed. The return code and hexadecimal error code is provided.

Note: Conditions that cause error message SARJSA04 will, in turn, cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to terminate normally also. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide either to terminate the backup cycle immediately or to wait until the completion of the backup cycle.

Responding WAIT to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARJSA05

Subsystem get request failed - RPL feedback xxxx

Reason:

A subsystem GET request failed. The hexadecimal feedback code is provided. This is normally due to a system crash while the job that created the data set was executing.

Note: For RPL=08022C, the problem is usually attempting to send a line longer than 32767 bytes.

Action:

None. This is an informational message.

SARJSA06

SJF retrieve error rc=xxxx

Reason:

A Scheduler JCL Facility request failed trying to obtain output statement attributes for a SYSOUT data set. The hexadecimal return code is provided. No output statement attributes are obtained for the SYSOUT.

Action:

None. This is an informational message.

SARJS201

WARNING, SARJS205 PDDB LOCATE FAILED - CONTACT CA TECHNICAL SUPPORT

Reason:

During network input processing, the product was unable to positively identify the version of JES2 being used to locate the JES2 PDDB, which is required to obtain SYSOUT information. The product continues processing assuming OS/390 V2R10 or higher is being used. This is a WARNING error only. It can occur only during network input processing and would, most likely, occur after an MVS and/or JES2 upgrade.

Action:

Determine if network input processing is functioning correctly. The JES2 PDDB can change with the release of JES2. Check the CA Technical Support web site, supportconnect@ca.com, to ensure that you have applied the solutions that are needed for your release of the operating system.

SARMET01

SMFTYPE=' PARM MISSING OR INVALID

Reason:

The parameter value is invalid due to one of the following conditions:

- The parameter is missing from the first parameter statement.
- The specified value is not numeric.
- The specified value is not in the allowable range (128–255).
- The parameter specified different values on separate parameter statements.
- The parameter is duplicated on the same statement.

Action:

Correct the value and resubmit the Metrics job.

SARMET02

'DATE=' PARM VALUES INVALID

Reason:

The parameter value is invalid due to one of the following conditions:

- The specified value contains a non-numeric character.
- The specified value for century is not a numeric 0 or 1.
- The specified value for day is less than 1 or greater than 366.
- The FROM-TO values are not separated by a hyphen.
- The FROM-TO values are not equal to 6 digits in length.
- The parameter is duplicated on the same statement.

Action:

Correct the value and resubmit the Metrics job.

SARMET03

'TIME=' PARM VALUES INVALID

Reason:

The parameter value is invalid due to one of the following conditions:

- The specified value contains a non-numeric character.
- The specified value for hour is less than 00 or greater than 23.
- The specified value for minute is less than 00 or greater than 59.
- The FROM-TO values are not separated by a hyphen.
- The FROM-TO values are not equal to 4 digits in length.
- The parameter is duplicated on the same statement.

Action:

Correct the value and resubmit the Metrics job.

SARMET04

'RPT=' PARM MISSING OR INVALID

Reason:

The parameter value is invalid due to one of the following conditions:

- The specified value is not equal to the function defined report values (FILE, ACCS, DELE, USER).
- The parameter literal is not specified as RPT=.

Action:

Correct the value and resubmit the Metrics job.

SARMET05

'RPT=FILE' NOT LOCATED ON FIRST PARAMETER STATEMENT

Reason:

The parameter is not located on the first parameter statement.

Action:

If the user does not wish to copy to a work file, remove this parameter statement. If the user does wish to copy the input file, make certain that this parameter statement is specified as the first in the group.

SARMET06

'RPT=' PARM DUPLICATED IN PARAMETER STATEMENTS

Reason:

The parameter specified value is repeated in the previous parameter statement.

Action:

Remove the parameter statement containing the duplicate RPT value and resubmit the Metrics job.

SARMET08

PARAM STATEMENTS EXCEED A MAXIMUM OF 4

Reason:

The maximum number of control statements to execute at one time is four.

Action:

Remove the extraneous statements and resubmit the Metrics job.

SARMET09

ERROR LOADING METRICS REPORT PROGRAM

Reason:

An error occurred during loading of a report program.

Action:

Resubmit the Metrics job. If the condition persists, contact CA Technical Support.

SARMET10

ERROR PROCESSING SUBTYPES

Reason:

An error occurred during the processing of SMF record subtypes.

Action:

Rerun the Metrics job. If the condition persists, contact CA Technical Support.

SARMF03

DEFAULT ATTRIBUTES USED FOR OUT DATASET

Reason:

Either RECFM, LRECL, or BLKSIZE has been omitted for the output file. Default attributes have been used.

Action:

Verify that the default attributes are wanted.

SARMFP04

INVALID DCB ATTRIBUTES FOR OUT DATASET

Reason:

The output file has been assigned an invalid DCB attribute.

Action:

Correct the DCB specifications for the output file.

SARMFP05

INVALID GENERATION IN PARM FIELD

Reason:

An invalid generation number has been passed to the program in the parm field.

Action:

Correct the problem and start SARMFP again.

SARMFP06

No records written to output file

Reason:

The SARMFPUX user exit did not select any GCR records. SARMFP issues return code 4 for the step.

Action:

Do one of the following options:

- Remove the SARMFTAB DD statement (thereby selecting **all** records).
- Code either *J=jobname* or *S=sysoutid* in the SARMFTAB DD to allow the SARMFPUX user exit to select GCR records.

SARMFP08

INVALID SORT FIELD NAME xxxxxxxx

Reason:

One of the options, MSORT1, MSORT2, and so on, contains an invalid value. The field is ignored and processing continues.

Action:

Correct the option.

SARMFP10

DATABASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The program load modules and the database are not of the same release level. CA View does not execute.

Action:

Correct the problem and retry.

SARMHL01

INVALID ONLINE CODE IN MCA

Reason:

The online interface LMP key is invalid.

Action:

Verify that your LMP code and product code are correctly specified (in CAIRIM) for the online feature that you are attempting to use. For complete instructions on how to set up your LMP keys, see the chapter "Configuring Your Product" in the *Installation Guide*.

SARMHL02

INVALID CA VIEW PRODUCT CODE

Reason:

The product code is invalid.

Action:

Verify that your product code and LMP code are correctly specified (in CAIRIM) for the feature that you are attempting to use.

Note: For more information about the instructions on how to set up your LMP keys, see the chapter "Configuring Your Product" in the *Installation Guide*.

SARMHL07

CAIRIM SERVICES NOT INSTALLED ATTEMPTING TO RETRY

Reason:

CAIRIM is not started or initialized before the starting of SARSTC.

Action:

If CAIRIM is not started, start it. If CAIRIM is initialized within 15 minutes of the first message being issued, *no* action is required.

If CAIRIM is *not* initialized within 15 minutes of the first message being issued, you receive the SARMHL99 error message. See the action for the SARMHL99 message.

SARMHL99

CAIRIM SERVICES NOT INSTALLED OR AT INCORRECT GENLEVEL

Reason:

CAIRIM is not started or is at an incorrect genlevel.

Action:

Start CAIRIM. When you receive the INITIALIZED message in CAIRIM, restart SARSTC. If you are at an incorrect genlevel of CAIRIM, apply genlevel maintenance on CAIRIM before starting SARSTC.

SARNGT02

INVALID INDEX RECORD ADDRESS

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARNOK02

NO INDEXES FOUND FOR REPORT "*reportid*" GEN=*xxxxx* SEQ=*xxxxx*

Reason:

An attempt is made to retrieve the indexes for a report, but the report is not indexed.

Action:

None. Only the native view of the report is accessible.

SARNOPO2

NO INDEXES FOUND FOR REPORT "*reportid*" GEN=*xxxxx* SEQ=*xxxxx*

Reason:

An attempt is made to retrieve the indexes for a report, but the report is not indexed.

Action:

None. Only the native view of the report is accessible.

SAROLR03

Database at incorrect level for this release

Reason:

The program load modules and the database are not of the same release level. CA View does not execute.

Action:

Correct the problem and retry.

SAROLR05

Warning - Code page XXXXXXXX not found; using default EBCCP037

Reason:

The translation table (xxxxxxx) as specified by SARINIT parameter CODEPAGE cannot be loaded. The system uses the default CODEPAGE EBCCP037.

Action:

Ensure that SARINIT parameter CODEPAGE has been properly defined. If CODEPAGE has been defined, CA View libraries have probably lost authorization (that is, ISPF startup procedures).

SARPAC02

Expanded retention was never initialized

Reason:

The Expanded Retention Option (ERO) has never been initialized, sets return code 16.

Action:

Run SARINIT to initialize the Expanded Retention Option.

SARPAC03

Master index is already in use

Reason:

Another consolidation task with the same database is already executing, sets return code 16.

Action:

Correct the problem.

SARPAC04

Verify SARPAC not active on system xxxx, reply Y/N to continue

Reason:

The database indicates that a tape consolidation job (SARPAC) is already active on system 'xxxx'. This message can also be issued if a tape consolidation job (SARPAC) terminated with an ABEND or the system crashed the last time a tape consolidation job (SARPAC) was active.

Action:

Verify whether a tape consolidation job (SARPAC) is active on the specified system. If it is active, reply N to terminate this job; if it is not active, reply Y to continue.

Replying N causes message SARPAC03 to be displayed and return code 16 set.

Important! Never run a tape consolidation job (SARPAC) for the same database on more than one system at the same time because this can destroy the database's master index.

SARPAC05

Error on input tape ***

Reason:

An error occurs while reading the input tape, sets return code 8.

Action:

See the associated SARTPIxx message.

SARPAC06

Error on output tape ***

Reason:

An error occurs while writing to the output tape, sets return code 16.

Action:

See the associated SARTPOxx message.

SARPAC10

No sysout groups require consolidation

Reason:

No SYSOUT groups are on expired CA View backup tapes; therefore, consolidation is not necessary, sets return code 4.

The return code is set to 4 when this message is issued.

Action:

None. This is an informational message.

SARPAC11

XXXXXXX sysout groups copied

Reason:

Tape consolidation has completed and copied xxxxx SYSOUT groups, sets return code 0.

Action:

None. This is an informational message.

SARPAC15

Data base at incorrect level for this release

Reason:

The program load modules and the database are not of the same release level, sets return code 16.

Action:

Correct the problem and retry.

SARPAC20

SYSIN control cards governing this SARPAC

Reason:

Optional SYSIN control statements are being used for this run of SARPAC, set return code 0.

Action:

None. This is an informational message.

SARPAC21

No TAPESEQ= or STORGRP= found

Reason:

SYSIN control statements did not specify either a storage group or tape sequence number, sets return code 16.

Action:

Either remove the optional SYSIN DD statement, or use the TAPESEQ= or STORGRP= control statement.

SARPAC22

Invalid or extraneous control card found

Reason:

Only one STOPGRP= or one TAPESEQ= control statement is valid as SYSIN, sets return code 16.

Action:

Use only one control statement for each run of SARPAC. You can run SARPAC multiple times to accomplish the desired result.

SARPAC23

Storage group not defined in database

Reason:

SYSIN control statement STORGRP= specified a storage group whose definition does not currently exist in the database using the SARINIT parameter's STORGRP*n*, sets return code 16.

Action:

Check the storage group name for misspelling. If the storage group name is correct, be sure that the database name is correct. The storage group name must be correct, and a backup cycle must have run to set the storage group name in the reports in the database. SARPAC does not read the ERO table directly.

SARPAC24

Invalid tape sequence number specification or tape sequence number(s) not found in database

Reason:

The tape sequence number that is specified on the TAPSEQ control statement contains invalid characters. Or, no tape control records are found in the database that match the specified tape sequence number or range of tape sequence numbers, sets return code 16.

Action:

Change the tape sequence number specification on the TAPSEQ control statement to reference an existing tape sequence number, and resubmit the job.

SARPAC52

*****WARNING*** Run SARPAC to copy tapes following merge of data bases**

Reason:

The database contains references to tape volumes owned by another database, sets return code 16. This condition is the result of a database merge.

Note: This message continues to appear even after all tape volumes have been copied until the started task backup cycle is executed.

Action:

Run SARPAC, as necessary, to copy the SYSOUT groups on tape to new tape volumes owned by this database, and then execute a backup cycle.

SARPAC86

Syntax error in REPORT keyword parameter

Reason:

The SARPAC parameter must be VIEW-database-name,REPORT, or VIEW-database-name. The parameter specified was not the keyword REPORT, sets return code 16.

Action:

Correct the parameter and rerun.

SARPAC97

Invalid command "xxxxxx"

Reason:

A modify command is issued against the SARPAC job but the parameter "xxxx" is not a valid command, does not set a return code.

Action:

Correct the modify command.

SARPAC98

SARPAC will terminate after the current report is processed

Reason:

A "STOP" modify command is issued against the SARPAC job, SARPAC terminates once the current report is moved to the output tape, does not set a return code.

Action:

None. This message is informational.

SARPAC99

Operator issued STOP command - processing terminated

Reason:

The operator has issued a STOP command to terminate SARPAC.

Action:

SARPAC will terminate normally *after* the completion of the current report.

SARPAM21

DATABASE AT INCORRECT LEVEL FOR THIS RELEASE

Reason:

The program load modules and the database are not at the same release level. CA Deliver-direct-to-CA View archival does not operate.

Action:

Set the version of the database (with the VERSION control statement of the SARDBASE utility) to the current release level, and then resubmit the job.

SARPAM22**I/O ERROR WRITING PAGE INDEX FOR SYSOUT - PAGE INDEX DELETED****Reason:**

An I/O error occurs while writing out the index data for the SYSOUT group. Any index data that is already written is deleted.

Action:

Correct the error with the database.

SARPAM23**MAXIMUM LINES EXCEEDED FOR *jobname* (*job#*)****Reason:**

The maximum number of lines (as defined by the MAXLINES initialization parameter for reports defined to CA Deliver as Direct-to-CA View) has been exceeded. Records in excess of the specified limit are discarded. If the report is designated for printing, the entire report is printed.

Action:

None. This message is informational.

SARPAM24**DATABASE *database-name* FULL - REPLY R (RETRY) OR T (TERMINATE)****Reason:**

The database has no more space to hold direct-to-CA View archival reports from CA Deliver.

Action:

Create more space in the database by either deleting SYSOUTS or adding more space to the database by either ADDDS or SARDBASE. Reply R to retry or reply T to terminate (abend) the application job.

SARPAM25

This message number represents one of the following messages:

Sequence number will WRAP for report 'report id' Reply R (retry) after a standard backup or T (terminate)

Invalid reply

Reason:

Each unique report id can have up to 65,535 copies per database generation. A 'generation' being the time between Full Backup Cycles. Each unique report id in a generation is assigned sequential numbers from 1 to 65,535. After 65,535, the sequence number will wrap back to zero and date selection problems will occur. This message gives the user a chance to run a backup cycle so this number can be reset to one.

The second format of SARPAM25 is displayed if a response other than 'R' or 'T' is given to the original message.

Action:

Reply with either an R after a backup cycle has been started or a T to terminate. The SARPAM25 message can be reissued after replying T and re-starting the application job.

SARPAM27

PENDING I/O COMPLETED FOR *dataset* RC=xxxx CC=xxxx

Reason:

When report data is being written directly to a CA View database and the job abends, is canceled, or times out, outstanding I/O requests can be pending for the database. To avoid potential corruption of the database, all I/O requests to the database are completed.

Action:

None. This message is informational.

SARPAM30

External key manager error obtaining key for database database - Reply R (retry) or T (terminate)

Reason:

The direct to CA View archival feature is attempting to write report data to an encrypted database but the external key manager product (ICSF) is not active, not installed, or rejected the service request to obtain the encryption key. The write to operator message is preceded by a SARICF message that identifies the specific error.

Action:

The SARICF message specifically identifies the nature of the error. If the SARICF error message identifies a return and reason code, a description of the code can be found in Appendix A of the *IBM z/OS Cryptographic Service Application Programmer's Guide*.

After the problem is resolved and the external key manager product is active, reply "R" to the SARPAM30 to resume direct to CA View archival for the job. The direct to CA View archival interface attempts to reestablish communication with the external key manager product every minute. If connection is reestablished, the SARICF and SARPAM30 messages are deleted. If the external key manager product error cannot be resolved in the near term, the job can be terminated by replying "T" to the SARPAM30 message. If so, it is also desirable to turn off direct to CA View archival or turn off encryption to the affected database(s).

SARPAR01

(CARD xxxx) INVALID CONTROL CARD *control card*

Reason:

A permanent archival control statement is invalid. The backup cycle of the CA View started task terminates with a U0001 user abend.

Action:

Correct the control statement, and then restart the started task to complete the backup cycle.

SARPAR02

(CARD xxxx) INVALID ID xxxxxxxxxxxx+ - SKIPPING TO NEXT CONTROL CARD

Reason:

The SYSOUT identifier on a permanent archival control record is too long. The backup cycle of the CA View started task terminates with a U0001 user abend.

Action:

Correct the control statement, and then restart the started task to complete the backup cycle.

SARPAR03

(CARD xxxx) INVALID KEYWORD xxxxxxxx+ FOR ID=xxxxxxxxxxxxx - SKIPPING TO NEXT CONTROL CARD

Reason:

The keyword on a permanent archival control record is too long. The backup cycle of the CA View started task terminates with a U0001 user abend.

Action:

Correct the control statement, and then restart the started task to complete the backup cycle.

SARPAR04

(CARD xxxx) Duplicate keyword xxxxxxxx+ for ID=xxxxxxxxxxxxx - skipping to next control card

Reason:

A duplicate keyword is found for the specified ID. The backup cycle of the CA view started task terminates with a U0001 user abend.

Action:

Correct the control card, then restart the started task to complete the backup cycle.

SARPAR05

(CARD *xxxx*) INVALID VALUE FOR KEYWORD=*xxxxxxxx*, ID=*xxxxxxxxxxxx* - SKIPPING TO NEXT CONTROL CARD

Reason:

The value for the keyword on a permanent archival control record is invalid. The backup cycle of the CA View started task terminates with a U0001 user abend.

Action:

Correct the control statement, and then restart the started task to complete the backup cycle.

SARPAR06

(CARD *xxxx*) EXCESSIVE OPERANDS FOR KEYWORD=*xxxxxxxx*, ID=*xxxxxxxxxxxx* - SKIPPING TO NEXT CONTROL CARD

Reason:

The keyword on a permanent archival control record contains too many operands. The backup cycle of the CA View started task terminates with a U0001 user abend.

Action:

Correct the control statement, and then restart the started task to complete the backup cycle.

SARPAR07

KEYWORD *x* CONFLICTS WITH KEYWORD *y* FOR ID=*z*, *x* ASSUMED

Reason:

The specified keywords cannot be specified on the same control statement and are mutually exclusive. The message is issued with the specification of the Expanded Retention option ALL, LAST, and MARK parameters.

Action:

Execution continues with the assumed specification. Change the Expanded Retention Option control statement to specify either ALL, LAST, or MARK.

SARPAR08

(CARD *nnn*) SEQUENCE ERROR IN TABLE - ID=XXXXXXXXXXXXX PRECEDES ID=XXXXXXXXXXXXX

Reason:

The ERO table contains report ID statements that are out of order. Since this table is searched sequentially, the most specific entries must precede generic entries. This error occurs when the SARSTC task is started, and the task immediately abends if this error is found.

Action:

Correct the order of the ERO table entries so that the more specific entries precede the more generic entries.

SARPAR09

SARPATAB DD STATEMENT MISSING

Reason:

ERO processing was selected (EROOPT=YES initialization parameter) with the ERO table being the single source of retention information (PRETAIN=TABLE initialization parameter), but the ERO table that is referenced by the SARPATAB DD statement is not specified in the archival task (SARSTC) job stream. The backup cycle of the CA View started task terminates with a U1009 user abend.

Action:

Add the SARPATAB DD statement to the archival task job stream referencing a sequential file or a member of a PDS that containing the ERO table entries or change PRETAIN to INIT if there is no ERO Table.

Note: Processing continues without the ERO table data.

SARPAR10

SARPATAB DATA SET EMPTY

Reason:

ERO processing was selected (EROOPT=YES initialization parameter) with the ERO table being the single source of retention information (PRETAIN=TABLE initialization parameter), but the data set that is referenced by the SARPATAB DD statement in the archival task (SARSTC) job stream does not contain any ERO table entries. The backup cycle of the CA View started task terminates with a U1010 user abend.

Action:

Point the SARPATAB DD statement to a sequential file or member of a PDS that contains the table entries or change PRETAIN to INIT if there is no ERO Table.

SARPAR11

(Card n) Id: aaa.. - DRETPD extended to DSK2DAYS specification to allow for migration

Reason:

DRETPD is not coded or is coded with a value less than DSK2DAYS, DRETPR is set to the same value as DSK2DAYS to allow for migration.

Action:

Add DRETPD or extend its value to keep the Sysout on primary disk until it is migrated (DSK2DAYS). Or, remove the DSK2DAYS parameter if it must not be migrated to the secondary disk.

SARPAR12

SARPATAB data set LRECL greater than 256

Reason:

The logical record length (LRECL) of the data set pointed to by the SARPATAB DD Statement in the Archival Task (SARSTC) procedure exceeds 256 characters. The Archival Task abnormally terminates with a U1012 abend code.

Action:

Re-allocate the data set with a logical record length (LRECL) of 256 characters or less and restart the Archival Task.

SARPAR13

(CARD nnn) KW keyword not supported at release level of database

Reason:

The keyword KW is used in the ERO table but is not supported at the level of the current database.

Action:

Use a database where the keyword is supported or remove the conflicting keyword from the ERO table.

SARPAR14

(CARD nnn) REGDAYS keyword cannot be verified when using the TABLE parameter

Reason:

When only verifying an ERO table using the TABLE parameter in SARVERO, the REGDAYS keyword cannot be verified.

Action:

Run SARVERO simulation without TABLE parameter to simulate a backup using the REGDAYS keyword.

SARPPS24

No more space in database ...db_hlq... Reply R (retry) T (terminate)

Reason:

There is not enough space in the database to perform the archival.

Action:

Reply with either an R to reattempt archival or a T to terminate:

1. Run the SARDBASE program to add more space to the database, or manually delete SYSOUT groups to free up space while the archival task waits. After you make more space available, reply R to have the archival task retry its archival with the additional space.
2. Reply T to terminate the archival task.

SARPPS25

This message number represents one of the following:

Sequence number will WRAP for report 'report id' Reply R (retry) after a standard backup or T (terminate)

Invalid reply

Reason:

Each unique report id can have up to 65,535 copies per database generation. A 'generation' being the time between Full Backup Cycles. Each unique report Id in a generation is assigned a sequential number from 1 to 65,535. After 65,535, the sequence number will wrap back to zero and date selection problems will occur. This message gives the user a chance to run a backup cycle so this number can be reset to one.

The second format of SARPPS25 is displayed if a response other than 'R' or 'T' is given to the original message.

Action:

Reply with either an R after a backup cycle has been started or a T to terminate. The SARPPS25 message can be reissued after replying T and re-starting the Xerox XPPS FSS Collector.

SARPQP60

PC TRANSMITTAL QUEUE FULL - SYSOUT NOT QUEUED TO PC

Reason:

The PC transmittal queue is full for the user.

Action:

Have the user transmit their queue and clear the entries.

SARPQP64

PC DESTINATION INVALID - SYSOUT NOT QUEUED TO PC

Reason:

The specified destination must be of the format PC user ID.

Action:

Correct the destination.

SARPQP68

USER NOT DEFINED - SYSOUT NOT QUEUED TO PC

Reason:

The user ID specified in the destination is not defined to CA View.

Action:

Correct the destination or define the user ID to CA View.

SARPRT01

Unable to load VTAM device driver "xxxxxxx"

Reason:

Your print request specified the synonym for a VTAM Print Option device. The DEFINE DEVICE specification for that synonym specified that the indicated special device driver was to be used when doing the printing, but that device driver cannot be found.

Action:

Either correct the device driver specification on the VTAM DEVICE ATTRIBUTE PANEL of the DEFINE DEVICE facility, or make the device driver accessible by putting it in the CA View LOADLIB, or in a library concatenated to CA View LOADLIB.

SARPRT02

Unable to load device's user exit "xxxxxxx"

Reason:

Your print request specified the synonym for a real device. The DEFINE DEVICE specification for that synonym specified that the indicated special user exit was to be used when doing the printing, but that user exit cannot be found.

Action:

Either correct the device driver specification on the appropriate DEVICE ATTRIBUTE PANEL of the DEFINE DEVICE facility, or provide access to the device user exit by putting it in the CA View LOADLIB, or in a library concatenated to the CA View LOADLIB.

SARPRT99**Unexpected Return code - xxxx****Reason:**

An internal logic error occurred. Online retrieval or batch retrieval terminates with a U1015 abend.

Action:

Contact CA Technical Support.

SARPRX01**Unable to load VTAM device driver "xxxxxxx"****Reason:**

Your print request specified the synonym for a VTAM Print Option device. The DEFINE DEVICE specification for that synonym specified to use the indicated special device driver for printing, but that device driver cannot be found.

Action:

Either correct the device driver specification on the VTAM Device Attribute panel of the DEFINE DEVICE facility, or make the device driver accessible by putting it in the CA View LOADLIB or in a library concatenated to the CA View LOADLIB.

SARPRX02**Unable to load device's user exit "xxxxxxx"****Reason:**

Your print request specified the synonym for a real device. The DEFINE DEVICE specification for that synonym specified to use the indicated special user exit for printing, but that user exit cannot be found.

Action:

Either correct the device driver specification on the Device Attribute panel of the DEFINE DEVICE facility, or provide access to the device user exit by putting it in the CA View LOADLIB or in a library concatenated to the CA View LOADLIB.

SARPRX03

External print or PC queuing not available for index data list

Reason:

Index data cannot be printed using the external print interface or queued to a PC user.

Action:

Specify a different destination and resubmit the print request.

SARPRX99

Unexpected Return code - xxxx

Reason:

An internal logic error occurred. Online retrieval or batch retrieval terminates with a U1015 abend.

Action:

Contact CA Technical Support.

SARRCO01

FILESEQ= must start in column 1

Reason:

The first control statement must be a FILESEQ statement and the keyword must start in column 1.

Action:

Correct the control statement and rerun the utility.

SARRCO02

DSN must start in column 1 and max 44 bytes

Reason:

The second and subsequent control statements must be DATA SET NAME/VOLSER control statement. Start the data set name in column 1 and terminate with either a space or the comma of the optional [,VOLSER] volume serial number.

Action:

Correct the control statement and rerun the utility.

SARRC004

Failed to process SARBFIL

Reason:

A failure writing the recovery data to the recovery file has occurred.

Action:

Delete the file pointed to by the SARRECV DD Statement, allocate a new empty file, and rerun the SARRCOV Utility.

SARRGT02

INVALID ENTRY CODE

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARRGT03

INVALID DRDB ADDRESS

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARROP01

INVALID REPORT HANDLE

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARROP02

INVALID RETURN TOKEN

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARRSPO0

Sysout restore started

Reason:

This message indicates the start of the restore process.

Action:

None. This is an informational message.

SARRSP01

Error opening database

Reason:

The database that is specified by the PARM parameter of the execution JCL cannot be opened. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

Verify that the correct database prefix is specified in the PARM parameter of the execution JCL. Otherwise, see the explanation and action of the SARDBlxx message for resolution.

SARRSP02

Error opening index file

Reason:

An error occurs while opening the master index. The restore process cannot access this master index data, and is terminated. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

Ensure that the restore process by using the RESTORE control statement of the SARDBASE utility completes successfully. See the explanation and action of the SARDBlxx message for resolution.

SARRSP03

Error reading master control record

Reason:

An error occurs while reading the master control record. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

Ensure that the restore process by using the RESTORE control statement of the SARDBASE utility completes successfully. See the explanation and action of the SARDBlxx message for resolution.

SARRSP04

Error opening file for panel=xxxxxxx

Reason:

An error occurs while attempting to restore the specified panel to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP05

Error writing file for panel=xxxxxxx

Reason:

An error occurs while attempting to restore the specified panel to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP06

Error updating index record for panel=xxxxxxx

Reason:

An error occurs while attempting to restore the specified panel to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP07

Error opening file for sysout=sysoutid

Reason:

An error occurs while attempting to restore the specified SYSOUT to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP08

Error writing file for sysout=sysoutid

Reason:

An error occurs while attempting to restore the specified SYSOUT to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP09

Error updating index record for sysout=sysoutid

Reason:

An error occurs while attempting to restore the specified SYSOUT to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP11

Error reading index file

Reason:

An error occurs while reading an index record from the master index of the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP12

Abnormal end to sort, return code=xxxx

Reason:

The sort phase of the restore process ends with the specified nonzero return code.

Action:

The nonzero return code from the sort phase can be caused by a critical error as indicated by a previous SARRSPxx message, a missing SYSOUT DD statement (return code 20), or a sort error as indicated in the sort message data set. Take the appropriate action, and then resubmit the job.

SARRSP13

Database at incorrect level for this release

Reason:

The program load modules and the database are not at the same release level. This is normally caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to old load modules, or the database has not been converted to the correct release level (new releases of the product can require conversion of the database).

Action:

Either STEPLIB to the correct load modules or convert the database to the correct release level.

Note: For more information, see VERSION in the SARDBASE Control Statements section of the chapter "Database Utilities" in the *Reference Guide*.

SARRSP14

Unload tape at incorrect level for this release

Reason:

The unload tape that is referenced by the SARLOAD DD statement is not produced by a compatible release level of the SARDBASE utility.

Action:

Remove the SARLOAD DD statement from the restore execution JCL, or use an unload tape from a compatible release level of the SARDBASE utility.

SARRSP15

Unload tape is formatted incorrectly

Reason:

The unload tape that is referenced by the SARLOAD DD statement contains unrecognizable data.

Action:

Remove the SARLOAD DD statement from the restore execution JCL, or specify a different unload tape.

SARRSP16

No tape backup copy for sysout, ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The specified SYSOUT group cannot be restored because the SYSOUT does not reside on any backup tape.

Action:

None. The status of the SYSOUT group remains unchanged, and processing continues.

SARRSP17

Sysout not restored because of tape error, ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The specified SYSOUT group cannot be restored due to problems with the related backup tape. This message accompanies a SARTPOxx message indicating the nature of the error.

Action:

None. The SYSOUT group is removed from disk status and processing continues. For future use of the SYSOUT group, recover the backup tape.

Note: For more information, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARRSP18

Sysout could not be found on backup tape, ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The specified SYSOUT group cannot be restored because the SYSOUT cannot be found on the related backup tape. This message accompanies a SARTPOxx message indicating the nature of the error.

Action:

None. The SYSOUT group is removed from disk status and processing continues. For future use of the SYSOUT group, recover the backup tape.

Note: For more information, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARRSP19

Sysout removed from restore status due to tape error, ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The specified SYSOUT group cannot be restored due to problems with the related backup tape and therefore, is being removed from disk status.

Action:

None. The SYSOUT group is removed from disk status and processing continues. For future use of the SYSOUT group, recover the backup tape.

Note: For more information, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARRSP20

Error opening file for resource=xxxxxxxxxx

Reason:

An error occurs while attempting to restore the specified page layout RESOURCE to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP21

Error writing file for resource=xxxxxxxxxx

Reason:

An error occurs while attempting to restore the specified page layout RESOURCE to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP22

Error updating index record for resource=xxxxxxxxxx

Reason:

An error occurs while attempting to restore the specified page layout RESOURCE to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP23

No backup copy for resource, ID=xxxxxxxxxx

Reason:

The specified page layout RESOURCE cannot be restored because the RESOURCE does not reside on any backup tape.

Action:

None. The status of the RESOURCE remains unchanged, and processing continues.

SARRSP24

Resource not restored because of tape error, ID=xxxxxxxxxx

Reason:

The specified page layout RESOURCE cannot be restored due to problems with the related backup tape. This message accompanies a SARTPOxx message indicating the nature of the error.

Action:

None. The RESOURCE is removed from disk status and processing continues. For future use of the RESOURCE, recover the backup tape.

Note: For more information, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARRSP25

Resource could not be found on backup tape, ID=xxxxxxxxxx

Reason:

The specified page layout RESOURCE cannot be restored because the SYSOUT cannot be found on the related backup tape. This message accompanies a SARTPOxx message indicating the nature of the error.

Action:

None. The RESOURCE is removed from disk status and processing continues. For future use of the RESOURCE, recover the backup tape.

Note: For more information about backing up, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARRSP26

Resource removed from restore status due to tape error, ID=xxxxxxxxxx

Reason:

The specified page layout RESOURCE cannot be restored due to problems with the related backup tape and therefore, is being removed from disk status.

Action:

None. The RESOURCE is removed from disk status and processing continues. For future use of the RESOURCE, recover the backup tape.

Note: For more information about restore, see the chapter "Backing Up and Recovering the Database" in the *Reference Guide*.

SARRSP30

Panel restored from load tape, member=xxxxxxxxxx

Reason:

The specified panel has been successfully restored from the unload tape.

Action:

None. This is an informational message.

SARRSP31

Sysout restored from load tape, ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The specified SYSOUT group has been successfully restored from the unload tape and now resides on disk media.

Action:

None. This is an informational message.

SARRSP32

Sysout restored from backup tape, ID=reportid, Gen=xxxx, Seq=xxxx

Reason:

The specified SYSOUT group has been successfully restored from the backup tape and now resides on disk media.

Action:

None. This is an informational message.

SARRSP33

SYSOUT DATA WAS NOT RESTORED DURING THE RECOVERY PROCESS BECAUSE THERE WAS NO TAPE ARCHIVAL OR UNLOAD BACKUP CONTAINING THE SYSOUT

Reason:

This message becomes the data for the SYSOUT attempted to be restored.

Action:

None. If a tape that contains the SYSOUT can be located, the SYSOUT can be reloaded using CA View utilities.

SARRSP34

Resource restored from load tape, ID=xxxxxxxxxx

Reason:

The specified page layout RESOURCE has been successfully restored from the unload tape and now resides on disk media.

Action:

None. This is an informational message.

SARRSP35

Resource restored from backup tape, ID=xxxxxxxxxx

Reason:

The specified page layout RESOURCE has been successfully restored from the backup tape and now resides on disk media.

Action:

None. This is an informational message.

SARRSP36

Error opening file for banner=xxxxxxxxxx

Reason:

An error occurs while attempting to restore the specified model banner page member to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP37

Error writing file for banner=xxxxxxxxxx

Reason:

An error occurs while attempting to restore the specified model banner page member to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP38

Error updating index record for banner=xxxxxxxxxx

Reason:

An error occurs while attempting to restore the specified model banner page member to the database. This message accompanies a SARDBlxx message indicating the nature of the error.

Action:

See the explanation and action of the SARDBlxx message for resolution.

SARRSP39

Banner page restored from load tape, banner=xxxxxxxxxx

Reason:

The specified model banner page member has been successfully restored from the unload tape.

Action:

None. This is an informational message.

SARRSP99

Sysout restore completed

Reason:

This message indicates that the restore process is finished (whether successfully or not).

Action:

None. This is an informational message.

SARSAM01

Invalid function code

Reason:

The parameter list that is passed to SARSAM does not contain a valid function name.

Action:

Correct the parameter list or use the SARSAM Macros which generates the correct parameter list values. The valid functions are:

- SAMOPEN— SAR Access Method Open
- SAMCLOSE—SAR Access Method Close
- SAMGET—Read Index Record
- SAMINVL—Invalidate Buffers
- SAMMSG—Return Error Message
- SAMSOPN—Open Sub-file
- SAMSGET—Read Sub-file Record
- SAMSCLS—Close Sub-file
- SAMAOPN—Open Auxiliary Sub-file
- SAMAGET—Read Auxiliary Sub-file Record
- SAMACLS—Close Auxiliary Sub-file
- SAMDFMT—Date Formatting
- SAMTFMT—Time Formatting
- SAMOPEN—SAR Access Method Open Messages:
- SAMOPN02—Database not initialized

Reason:

The database exists but has never been initialized.

Action:

Use the SARINIT Initialization Utility to initialize the database and rerun the SARSAM application.

SARSEP30

```

*****
*                                     *
*  CA VIEW FSS/FSA  (jobname /jobid ) *
*  PRODUCT HAS ABENDED WITH CODE code *
*    ***  RESTART PRODUCT ASAP  ***  *
*                                     *
*****

```

Reason:

The CA View FSS (Functional Subsystem) or CA View FSA (Functional Subsystem Application) has abended. The system or user abend code is provided.

Action:

Consult the *MVS System Messages* manual to determine the reason for the abend. If you still cannot determine the problem, contact CA Technical Support.

SARSP01**Critical error, program terminated with dump. Invalid blk****Reason:**

A CA View program has terminated, and a dump was generated. In this message, *blk* specifies the control block CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It can be suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Customer Support. Restart whatever program was terminated. For assistance, contact Technical Support at <http://ca.com/support>.

SARSGA02**INVALID ENTRY CODE****Reason:**

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSGD02

INVALID ENTRY CODE

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSGR02

INVALID ENTRY CODE

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSGR03

INVALID DRDB ADDRESS

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSGT01

INVALID DRDB ADDRESS

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSGV02

INVALID ENTRY CODE

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSMF90

SARSMF90 SARSMFT module is not sufficiently authorized to write an SMF record

SARSMF90 SARSMFT module must be added to the TSO authorization table and reside in an authorized library

Reason:

This message indicates insufficient authority to write SMF records.

Action:

Add the SARSMFT module to the TSO authorization table, and ensure that it is located in an authorized library.

SARSOK07

REPORT "reportid" GEN=xxxxx SEQ=xxxxx NOT ACCESSIBLE, TAPE SERVER NOT ACTIVE

Reason:

The report cannot be accessed from tape because the Expanded Access Server (EAS) task is not active on the same system as DRAS.

Action:

The EAS task must be started and running on the same system as DRAS. After the task has been started, the report can be accessed from DRAS.

SARSOP01

INVALID REPORT HANDLE

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSOP02

INVALID RETURN TOKEN

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSPN01

RECORD POSITIONING NOT SUPPORTED ON VIEW

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSPN02

POSITIONING NOT SUPPORTED ON ACIF OR PPS REPORT

Reason:

This message indicates a logic error with interconnection of internal product routines.

Action:

Contact CA Technical Support.

SARSPT01

Sysout allocation failed, Error=xxxx, Info=xxxx

Reason:

Dynamic allocation failed for allocating the print data set to SYSOUT. The hexadecimal error and information codes are provided.

Action:

Correct the problem, and then resubmit the job.

SARSPT02

OUTADD failed for report xxxxxxxxxx - Code=xxxx, Reason=xxxx, Token=xxxx

Reason:

The attempt to dynamically create an OUTPUT statement failed. The return and reason codes are provided. For an explanation of the return and reason codes, refer to the operating system macro IEFDORC.

Action:

The SYSOUT is printed without OUTPUT statement attributes. If you want, make appropriate changes and resubmit the print request.

SARSPT03

No distribution identifiers for report - Use CA View print report

Reason:

Distribution identifier has not been specified for the desired report.

Action:

Specify a distribution identifier for the report or enter the keyword SAR and print through CA View directly.

SARSPT04

No sysout could be printed

Reason:

Problems are encountered with the CA Deliver database interface, or problems are encountered printing banner pages for reports in CA Deliver. Processing is terminated.

Action:

Respond to the additional message that precedes this message.

SARSPT05

The tape contained a null file for the sysout group

Reason:

The SYSOUT group cannot be found on the tape backup.

Action:

None. The SYSOUT group is not available on tape.

SARSPT06

The tape file was not the selected sysout group - Use SARTCP to map the tape

Reason:

The SYSOUT group that is located on tape is not the same as referenced in the master index.

Action:

Use the SARTCP utility to map and correct the tape.

SARSPT07

Backup tape does not exist

Reason:

The backup tape cannot be found in the index file. This is normally caused by a backup cycle deleting the tape between the time the job was submitted and the time it was executed.

Action:

None. The SYSOUT group is no longer available.

SARSPT08

Tape alloc Error code - xxxx, Info code - xxxx

Reason:

Dynamic allocation failed for the backup tape file. The hexadecimal error and information codes are provided.

Action:

Correct the problem, and then resubmit the job.

SARSPT09

I/O error positioning tape

Reason:

A permanent I/O error occurs while attempting to position the archival tape to retrieve the SYSOUT group.

Action:

Resubmit the job. If the I/O error occurs again, then the desired SYSOUT group can no longer be printed.

SARSPT10

Sysout group is open for output

Reason:

The requested function cannot be performed because the specified SYSOUT group is open for output.

Action:

If the open condition is valid (for example, the SYSOUT group is still being archived or is being loaded to disk), wait for the SYSOUT group to be closed and rerun the job.

If the open condition is invalid (for example, there was a system crash or abend while the SYSOUT group was open leaving the SYSOUT group in an open status), use the CLEAN operator command to remove the open status. Two backup cycles and the duration of four hours must have elapsed before the open status is removed.

SARSPT11

Permanent I/O error on input tape

Reason:

A permanent I/O error occurs while reading the SYSOUT from tape. The print function is terminated.

Action:

Use the SARTCP utility to map and correct the tape.

SARSPT12

View definition for report was not found

Reason:

The logical view definition for the report is not found.

Action:

Respecify the print request with a new logical view.

SARSPT13

message text varies

Reason:

A subprogram returned a message that is being repeated here.

Action:

The action varies depending on the message text displayed.

SARSPT14

The GCR record was not found for the resource group

Reason:

The resource group that is identified by a group control record is not found in the CA View database.

Action:

Use the SARTCP utility to map and locate the resource group. Use the SARTDR utility to reload the resource group back into the CA View database.

SARSPT16

No print pages for distribution id, Dist=distid at dest

Reason:

The distribution id is not within the requested page range for printing.

Action:

Adjust the Deliver definition for this report so the pages are distributed to the distribution id listed or change the index to include pages defined for this distribution id. If no pages were expected to be printed to this distribution id, this is a notification and no action is required.

Note: When using the external print interface, no destination is available. The message appears without the dest as follows:

No print pages for distribution id, Dist=distid

SARSPT56

Sysout queued for transmittal to PC

Reason:

The SYSOUT group is successfully queued for PC transmittal.

Action:

None. This is an informational message.

SARSPT60

PC transmittal queue full - Sysout not queued to PC

Reason:

The PC transmittal queue for the user is full. The SYSOUT group cannot be added to the queue.

Action:

Transmit and clear the queue.

SARSPT64

PC destination invalid - Sysout not queued to PC

Reason:

The destination is not of the form PC user ID.

Action:

Correct the destination.

SARSPT68

User not defined - Sysout not queued to PC

Reason:

The PC user is not defined to CA View.

Action:

Correct the user ID in the destination.

SARSPT78

Unable to load VTAM device driver "xxxxxxxxxx"

Reason:

The DEFINE DEVICE information requests that output be processed by an optional device driver called xxxxxxxx, but it cannot be found.

Action:

Either make the device driver available (perhaps through LINKLIST or STEPLIB), or remove it from the DEFINE DEVICE.

SARSPT80

Maximum specified lines was exceeded

Reason:

Your print request exceeded the maximum number of lines that are permitted during a batch or on-line print request. The reprint line limit could have been defined in the VTAM Printer Device Definition, the CA Spool Device Definition, or the OUTLIM Initialization Parameter.

Action:

Do one of the following options:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Increase the maximum permitted for all devices by using SARINIT parameter OUTLIM.
- Make multiple separate print requests.

SARSPT81

Not printed due to errors on other destinations

Reason:

This destination has no problems printing, but an error occurs while printing to another destination in your reprint request.

Action:

Do one of the following actions:

- Correct the other error and retry.
- Make multiple separate print requests.

SARSPT82

Invalid define device record

Reason:

The DEFine DEvice record is invalid. A record that is not completely defined can cause this.

Action:

Correct the DEFine DEvice record and retry.

SARSPT83

Duplicate VTAM printer id, LU=xxxxxxxxxx

Reason:

You are attempting to print more than one SYSOUT or report on the same VTAM printer at the same time. This cannot be done.

Action:

Either use more than one printer or make more than one print request to the printer in question.

SARSPT84

CA Spool maximum print lines was exceeded

Reason:

Your print request exceeds the maximum number of lines that are permitted during CA Spool print processing.

Action:

Do one of the following options:

- Print in smaller segments.
- Increase the maximum permitted for this device by using the DEFine DEvice facility.
- Increase the maximum permitted for CA Spool devices by using SARINIT parameter CMAMAX.

SARSPT85

Unable to load device's user exit "xxxxxxxxxx"

Reason:

The DEFine DEvice information requests that the output be processed by an optional device-specific user exit called xxxxxxxx, but it cannot be found.

Action:

Either make the device driver available (perhaps through LINKLIST or STEPLIB), or remove it from the DEFine DEvice.

SARSPT86**Sysout queued for external printing****Reason:**

The external print request was successfully queued for processing.

Action:

None. This is an informational message.

SARSPT99**Unexpected Return code - xxxx****Reason:**

An internal logic error has occurred. Online retrieval or batch retrieval terminates with a U1111 abend.

Action:

Contact CA Technical Support.

SARSS001**ALLOCATION FAILED FOR ARCHIVAL SYSOUT - ERROR xxxx, INFO xxxx****Reason:**

A dynamic allocation request for allocating the archival copy for the automatic report archival feature failed. The hexadecimal error and information codes are provided. Execution continues without creating the archival copy of the SYSOUT—no archival of the SYSOUT is done.

Action:

Correct the parameter information for the automatic report archival feature.

SARSS002**OPEN FAILED FOR ARCHIVAL SYSOUT - ERROR xx****Reason:**

The open request failed for the archival copy for the automatic report archival feature.

Action:

Correct the problem with open.

SARSTC00

CA View release (genlevel) is initialized

Reason:

Initialization has completed for the archival task.

Action:

None. This is an informational message.

SARSTC01

SUBSYSTEM REQUEST FAILED - RETURN CODE xxxxxxxx

Reason:

A subsystem request failed. The hexadecimal return code is provided.

Note: Conditions that cause error message SARSTC01 in turn cause the started task to perform normal termination.

The normal termination of SARSTC (the CA View started task) causes the Direct-To-Tape function and a backup cycle function to also terminate normally. The Direct-To-Tape function terminates after completion of the current SYSOUT processing if one is in progress.

A backup cycle is also terminated if one is in progress but based on the response of the operator to the SARBKU07 message. SARBKU07 requests the operator to decide to either terminate the backup cycle immediately or wait until the completion of the backup cycle.

Responding "Wait" to the SARBKU07 message can cause an unwanted delay in restarting the CA View started task.

Action:

Contact your systems programmer.

SARSTC07

Attempt to archive sysout from archival task - Sysout deleted

Reason:

The job name of the SYSOUT passed to CA View for archival is the same as the archival started task, and the producing ddname is *SYSnnn*. To prevent a potential archival-print loop, CA View deletes the SYSOUT without ever archiving it.

Action:

Correct or specify the NEWCLSL, NEWDEST, or NEWFORM options to prevent the archival of SYSOUT automatically printing the archival started task.

SARSTC09

sub-task Task terminated return code xxxx

Reason:

The named sub-task (Backup, Archive, or Comm) has terminated with a 'nnnn' return code.

Action:

Determine the required action from other accompanying messages which can indicate a component failure.

SARSTC10

Open failed for accounting file (saract) - archival job accounting disabled on database

Reason:

A SARACT DD statement was present in the job stream, but the data set failed to open successfully.

Action:

Verify that the data set is correct, or remove the DD statement to disable accounting.

SARSTC11

Invalid record length of block size for accounting file (SARACT) - Archival job accounting disabled on database

Note: This message number represents one of these messages.

Reason:

The data set specified by the SARACT DD statement has an invalid logical record length, an invalid block size, or is not a CA View accounting file.

Action:

Verify that the data set is correct, or remove the DD statement to disable accounting.

SARSTC14

ESTAE failed - return code xxxx

Reason:

An ESTAE failed. The hexadecimal return code is provided.

Action:

Contact your systems programmer.

SARSTC15

INVALID COMMAND

Reason:

The modify command for the archival started task is invalid and ignored.

Action:

Correct and reissue the modify command.

SARSTC18

OUTADD FAILED FOR SYSOUT - ERROR CODE *xxxx*, INFO CODE *xxxx*

Reason:

The attempt to dynamically create an OUTPUT statement failed. The return and reason codes are provided. For an explanation of the return and reason codes, refer to the operating system macro IEFDORC.

Action:

The SYSOUT is printed without OUTPUT attributes. If you want, make appropriate changes and resubmit the print request.

SARSTC19

Database is already exclusively being used

Reason:

Another archival task with the same database is already executing.

Action:

Correct the problem.

SARSTC20

Database at incorrect level for this release

Reason:

The program load modules and the database are not the same release level. This is normally caused by the STEPLIB, JOBLIB, linklist, or LPA pointing to old load modules, or the database has not been converted to the correct release level (new releases of the product can require conversion of the database).

Action:

You can either STEPLIB to the correct load modules or convert the database to the correct release level.

SARSTC21

Verify taskname not active on system xxxx, Reply Y/N to continue

Reason:

The master index indicates that the archival task is already active on system xxxx. This message can also be issued if the archival task abended or the system crashed the last time the archival task was active.

Action:

Verify whether the archival task is active on the specified system. If it is, reply N to terminate this task; if not, reply Y to continue.

Important! Never run the archival task for the same index file on more than one system at the same time; this can destroy the master index.

SARSTC22

Processing jobname/dsname

Reason:

CA View is processing the specified SYSOUT data set.

Action:

None. This is an informational message.

SARSTC23

Maximum lines exceeded for job(jobid)

Reason:

The maximum number of lines that can be archived for a SYSOUT data set (defined by the MAXLINES initialization parameter) has been exceeded. If BYPASS has been coded as a subparameter of MAXLINES, all remaining SYSOUTs for the data set are deleted without archival. If BYPASS is not coded, the records are passed to SARSTCUX for processing.

Action:

None. This is an informational message.

SARSTC24

No more space in database xxxxxxxxxxxxxxxxxx - Reply R (retry), B (backup), N (new), C (clean), OR T (terminate)

Invalid reply

Reason:

The database is out of space.

The second format of SARSTC24 is displayed if a response other than 'R', 'B', 'N', 'C', or 'T' is given to the original message.

Action:

Your recovery options are as follows:

- Run the SARDBASE program to add more space to the database, or manually delete SYSOUT groups to free up space while the archival task waits. After you allot more space, reply R to have the archival task retry its archival with the additional space.
- Reply B to force the archival task to execute its backup cycle. As part of its backup cycle, the archival task deletes the generation of SYSOUT on disk that is in excess of the NGEND= initialization parameter, freeing some space.
- Replying N has the same effect as B except that a new tape is used for the backup cycle.
- Reply C to force the archival task to scan its database for SYSOUT groups left in an open state due to a system crash and recover the space used by them.
- Reply T to terminate the archival task.

SARSTC25

Sequence number will WRAP report reportid - Reply B (backup) or T (terminate)

Invalid reply

Reason:

Each unique reportid can have up to 65,535 copies per database generation. A generation is the time between Full Backup Cycles. Each unique reportid in a generation is assigned sequential numbers from 1 to 65,535. After 65,535, the sequence number would wrap back to zero and date selection problems would occur. This message gives the user a chance to run a backup cycle so this number can be reset to one.

The second format of SARSTC25 is displayed if a response other than 'B' or 'T' is given to the original message.

Action:

Reply with either a B to run a backup cycle or a T to terminate. The SARSTC25 message can be reissued after replying T and re-starting the archival (SARSTC) task.

SARSTC26

No response from JES2/3 in nn minutes

Reason:

This message is informational. The message informs a user that CA View is operative, though JES has not had any outputs in the queue in the predefined five-minute time spans.

Action:

None. This message is informational.

SARSTC27

I/O error writing page index for sysout - page index deleted

Reason:

An I/O error occurs while writing out the index data for the SYSOUT group. Any index data that is already written is deleted.

Action:

Correct the error with the database.

SARSTC28

SARSTC requires APF-authorization

Reason:

CA View initialization failed because the program authorization using the Authorized Program Facility (APF) is required.

Action:

APF authorize the libraries containing the CA View load modules or move the load modules to an authorized library.

SARSTC29

Forward recovery terminated due to error

Reason:

The SARSTC archival task has encountered an error while writing a duplex copy of a SYSOUT to the forward recovery data set.

Action:

Archival continues without forward recovery capture. Check the RCVPRIM, RCVSEC, RCVSPACE, and RCVUNIT initialization parameters for values that could cause problems allocating, reading, or writing to the forward recovery data set.

SARSTC30

```

*****
SARSTC30 *
*
SARSTC30 *   SARSTC has abended with code xxxx   *
SARSTC30 *   Sysoutid=xxxxxxxx
Jobname=xxxxxxxx Jobid=xxxxxxxx
*
*****

```

Reason:

The CA View started task has abended. The system or user abend code is provided.

Action:

Consult the *MVS System Messages* manual to determine the reason for the abend. If you still cannot determine the problem, contact CA Technical Support.

SARSTC31

PC transmittal queue full - Sysout xxxxxxxx not queued to PC for userid

Reason:

The PC transmittal queue is full for the user. The SYSOUT group is not queued for transmittal to the PC.

Action:

Have the user transmit the queue and clear the entries.

SARSTC32

PC destination invalid - Sysout xxxxxxxx not queued to PC for userid

Reason:

The specified destination must be of the format PC.user ID.

Action:

Correct the destination.

SARSTC33

User not defined – Sysout xxxxxxxxxx not queued to PC for userid

Reason:

The user ID specified in the destination is not defined to CA View.

Action:

Correct the destination or define the user ID to CA View.

SARSTC37

Maximum lines exceeded for sysout xxxxxxxx on VTAM printer xxxxxx

Reason:

Your print request exceeded the maximum number of lines that are permitted during VTAM print processing. This message can also occur on non-VTAM printers as an indication that an error occurred while printing on both devices simultaneously.

Action:

Increase the maximum permitted for this device by using the DEFine DEVice facility or increase the maximum permitted for all devices by using SARINIT parameter VPRMAXO.

SARSTC38

Maximum lines exceeded for sysout xxxxxxxx on CA Spool xxxxxx

Reason:

Your print request exceeded the maximum number of lines that are permitted during online CA Spool print processing. This message can also occur on non-VTAM printers as an indication that an error occurred while printing on both devices simultaneously.

Action:

Increase the maximum permitted for this device by using the DEFine DEvice facility or increase the maximum permitted for CA Spool devices by using SARINIT parameter CMAMAX.

SARSTC39

Error in define device record for sysout xxxxxxxxxxx

Reason:

The device record is invalid. A record that was not completely defined could cause this.

Action:

Correct the device record by using the DEFine DEvice facility.

SARSTC40

Unexpected return code printing sysout id on dest. RC=xxxx

Reason:

An unknown return code is detected in response to a print request.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARSTC42

Encryption enabled for xxx...xxx

Reason:

xxx...xxx is the name of the CA View database.

This is a confirmation that reports are being encrypted.

Action:

None.

SARSTC50

CA Health Checker Initialization failed with RC=nn

Reason:

An unknown return code is detected in the CA Health Check startup.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARSTC51

CA Health Checker Termination failed with RC=nnnn and Reason Code=nnnn

Reason:

An unknown return code is detected in the CA Health Checker terminate.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARSTC52

CA Health Checker ADD-CHK failed for (name of health check) - RC=xxxx and Reason Code=xxxx

Reason:

An unknown return code is detected when CA Deliver tried to add a Health Check.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARSTC99

jobid jobname message

Reason:

An exceptional condition identified by message occurs for the specified job.

Action:

Take appropriate action.

SARSVR02

DYNAMIC INTERFACE MISSING FOR xxxxxxxxxxxx

Reason:

The dynamic interface verification for the interface xxxxxxxx failed.

Action:

Contact CA Technical Support.

SARSVR03

DYNAMIC INTERFACE RE-EFFECTUATED FOR xxxxxxxx

Reason:

The CA View systems extension interface was installed. The systems extension interface routines are loaded or reloaded and then activated when SARXTD is executed.

Action:

None. This is an informational message.

SARTCH01

INVALID PARM SPECIFICATION: CORRECT JCL AND RESUBMIT JOB

Reason:

The tape sequence number or range specified in the JCL PARM field for the SARTCHK program is invalid. The syntax for the JCL PARM field is as follows:

```
EXEC PGM=SARTCHK,PARM=' database, tapeseq1 - tapeseq2'
```

where:

database Specifies the high-level prefix name of the database

tapeseq1 Specifies the starting tape sequence number

tapeseq2 Specifies the ending tape sequence number (optional)

Action:

Correct the parameter specification, and then resubmit the job.

SARTCH02

NO UNCATALOGUED TAPE DATA SETS WERE FOUND

Reason:

All the tape data sets referenced in the database, referenced by the tape sequence number, or range on the JCL PARM field is catalogued.

Action:

None. This is an informational message.

SARTCH03

NO MATCHING TAPE SEQUENCE NUMBERS FOUND

Reason:

The database does not contain any tape control records, the tape sequence number, or range specified in the JCL PARM field is not in the database.

Action:

If the tape sequence number or range specified in the JCL PARM field is incorrect, correct the parameter specification, and resubmit the job.

SARTCP01

Control card error

Reason:

There is an error in the specified control statement.

Action:

Correct the control statement, and then resubmit the job.

SARTCP02

Invalid parm specification

Reason:

The JCL PARM field for the SARTCP program is invalid. The only valid JCL PARM field is COPYASIS.

Action:

Omit or correct the parameter specification, and then resubmit the job.

SARTCP03

ADDHDR parm not valid, tape has a CA View Header

Reason:

Copying a tape using the ADDHDR parameter but the input tape has a CA View Header (SARHDR).

Action:

Remove the ADDHDR parameter and re-run the tape copy.

SARTCP10

Input tape I/O error, ECB=XX, BLOCK=XXXXXXXX,SENSE=XXXX Enter S(kip blk), E(nd), OR C(ancel)

Reason:

A permanent I/O error occurs while reading the specified block from the input tape. The ECB and SENSE codes are provided.

Action:

Reply S to skip the bad block and continue, E to terminate the job, or C to abend the job.

SARTCP11

Output tape I/O error, ECB=XX, BLOCK=XXXXXXXX, SENSE=XXXX

Reason:

A permanent I/O error occurs while writing the specified block to the output tape.

Action:

Resubmit the job using a different output tape.

SARTCP12

Write tape mark I/O error, ECB=XX, SENSE=XXXXX

Reason:

A permanent I/O error occurs while writing a tape mark on the output tape.

Action:

Resubmit the job using a different output tape.

SARTCP16

Processing successfully completed

Reason:

Processing has been successfully performed.

Action:

None. This is an informational message.

SARTDO42

**Device allocation error - ERR=xxxx, INFO=xxxx
DSNAME=xxxxxxxxxxxxxxxxxxxxxx
Reply Y/N to continue processing with new tape**

Reason:

Dynamic allocation has failed for the DR tape. The hexadecimal error and information codes are provided.

Action:

Reply Y to the message to allocate a new tape and continue processing. Otherwise, reply N, correct the problem with the tape, and restart the function.

SARTDO43

I/O error forward spacing media - new volume forced

Reason:

A permanent I/O error occurs when attempting to forward space the DR tape. A new tape volume is used and execution continues.

Action:

None. This is an informational message.

SARTDO44**Catalog error on DR tape - DSN=(dataset), RC=nn.nn****Reason:**

An error occurs when attempting to catalog the DR tape. The data set name, the return code, and reason code from the catalog management are provided.

Action:

Correct the problem with the catalog structure.

SARTDO46**(dataset name) already exists - new volume forced****Reason:**

Allocation of a new DR tape is being attempted for the specified dsname, but the dsname is already cataloged to the system.

Action:

None. A new tape volume and dsname are used.

SARTDO47**Unable to obtain device characteristics for unit****Reason:**

The device characteristics for the specified unit are not available by using the DEVTYPE system service.

Action:

Normally, an invalid device name as specified by the DRUNITB or DRUNITP initialization parameter causes this condition. Otherwise, consult your systems programming group to determine why the DEVTYPE system service cannot be performed against the unit.

SARTD049

Permanent I/O error writing DR media, new restart OPT=NEW

Reason:

A permanent I/O error occurs while writing to the DR tape. The Backup Cycle abnormally terminates with a user U'0049'.

Action:

Restart the archival task (SARSTC) with a 'NEW' or 'INEW' parameter to allocate new tapes. The archival task can also be restarted with the 'STOPBU' parameter followed by the system modify command 'F SARSTC, NEW' or 'F SARSTC, 'INEW' to allocate new tapes.

SARTD054

Tape to be mounted needs write capability

Reason:

The DR tape to be mounted is written on and requires a write-enabled cartridge.

Action:

Verify that the tape to be mounted is not write-protected.

SARTD056

DR tapes must be created on 3480 or higher tape units

Reason:

DR tapes require a 3480 or higher device type.

Action:

Correct the tape unit name in the DRUNITB or DRUNITP definition.

SARTDO59

Bad block ID, using SEQUENTIAL reading to locate append point

Reason:

For best performance, CA View uses a block ID to locate the appendage point on a tape volume. Because CA View did not find the correct information at that point on the tape volume, it rewound the volume and used sequential read to locate the point to append.

Action:

Contact Technical Support at <http://ca.com/support> to report the problem. This message is informational only. If the locate by sequential reading succeeds, the only impact is on performance. If the located by forward space file fails, a new tape volume is requested.

SARTDO60

Error closing DR tape

Reason:

An unrecoverable hardware I/O error occurred while writing the tape's end-of-file label or one of the two required tape marks. The tape is usable as a backup media for reports and master index copies, but the tape can cause a locate block ID (SARTDO59) error if additional backup cycles are written to this tape.

Action:

The tape can be used to recreate the DR tape.

SARTDR00

**TADD of tape "tape dsn" to database "dbname" is NOT RECOMMENDED
Report dates and generations will be out of sequence and a MERGE will be required
Reply "C" to continue or "S" to stop**

Reason:

SARTDR allows any backup tape to be added to any DATABASE. If the tape was from another database, it often causes date selection errors where users are unable to locate some reports within a date range. After this occurs a MERGE must be run to correct these date selection errors. Tape "tapedsn" contains dates and/or generation numbers which are inconsistent with dates and generation numbers on database "dbname". A response is required.

Action:

Reply with either a C to continue with the TADD Utility or S to terminate the TADD Utility. If option C is selected to continue, execute a SARDBASE MERGE at the earliest convenience.

SARTDR01

INVALID REPLY

Reason:

The console reply to the SARTDR00 message is invalid.

Action:

When the SARTDR00 message is reissued, reply Y to authorize the execution of SARTDR, or N to cancel the execution of SARTDR.

SARTDR02

**Tape sequence number does not match that of sysout group xxxxxxxx
Recorded=nnnnn Actual=nnnnn**

Reason:

The actual tape sequence number obtained from the data set name for the tape does not match that recorded with the SYSOUT group or page layout RESOURCE that is being added. The SYSOUT group or RESOURCE is not added.

Action:

Verify the data set name for the tape.

SARTDR03

Invalid or misplaced control card, control statement must begin with a "/"

Reason:

The specified control statement contains an error in its syntax.

Action:

Correct the statement, and then resubmit the job.

SARTDR04

POSITIONOF SYSOUT GROUP xxxxxxxx INVALID RECORDED=nnnnn

ACTUAL=nnnnn

POSITION OF RESOURCE xxxxxxxx INVALID RECORDED=nnnnn

ACTUAL=nnnnn

Reason:

The actual position of the SYSOUT group or page layout RESOURCE on the tape does not match that recorded with it. The SYSOUT group or RESOURCE is not added.

Action:

USE SARTCP to correct the problem with the tape.

SARTDR05

I/O error positioning tape

Reason:

A permanent I/O error occurs while attempting to position the archival tape to retrieve the SYSOUT group.

Action:

Salvage the data on the tape using the SARTCP utility, and then resubmit the job.

SARTDR06

Tapes not added in order for SYSOUT GROUP xxxxxxxx GEN=nnnnn SEQ=nnnnn

Tapes not added in order for RESOURCE xxxxxxxx GEN=nnnnn SEQ=nnnnn

Reason:

A multi-tape SYSOUT group or page layout RESOURCE is being added but the tapes for it have not been added in ascending order.

Action:

Re-add the tapes for the SYSOUT group or RESOURCE in ascending order.

SARTDR07

Authorization denied by operator

Reason:

The operator replies N to message SARTDR00.

Action:

Obtain authority to run SARTDR from the operator, and then resubmit the job.

SARTDR08

TAPE DD statement not found

Reason:

The DD statement for the tape cannot be found.

Action:

Add the DD statement to the JCL, and then resubmit the job.

SARTDR09

Invalid tape data set name

Reason:

The data set name for the tape to be added does not conform to the naming conventions for archival tapes.

Action:

Correct the problem, and then resubmit the job.

SARTDR10

Current generation set to nnnn

Reason:

The addition of the tape requires the current generation number to be reset.

Action:

None. This is an informational message.

SARTDR11

Tape added - dsname Seq=nnnn Lgen=nnnnn Hgen=nnnnn TM=nnnnn

Reason:

The specified archival tape is successfully added to the master index file. The tape sequence number, low generation number, high generation number, and number of tape marks are given in the message.

Action:

None. This is an informational message.

SARTDR14

Tape error processing sysout group xxxxxxxxxx Gen=xxxxx Seq=xxxxx

Tape error processing resource group xxxxxxxxxx Gen=xxxxx Seq=xxxxx

Reason:

An error occurs when loading the SYSOUT group or page layout RESOURCE from tape.

Action:

Consult the associated tape error message that is written to the job log for the appropriate action.

SARTDR15

Invalid function name

Reason:

A control statement was encountered with an invalid function name in the SYSIN DD statement of the SARTDR utility. The only valid functions are /TADD and /TLOAD.

Action:

Correct the control statement specification, and then resubmit the job.

SARTDR16

Invalid keyword name "xxxxxxx"

Reason:

A control statement is encountered with an invalid keyword name in the SYSIN DD statement of the SARTDR utility.

Action:

Correct the control statement specification, and then resubmit the job.

SARTDR17

Invalid parameter data "xxxxxxx" for keyword xxxxxxxx

Reason:

A control statement is encountered with an invalid parameter specification for the specified keyword in the SYSIN DD statement of the SARTDR utility.

Action:

Correct the control statement specification, and then resubmit the job.

SARTDR18

Unbalanced parentheses encountered in parameter data for keyword xxxxxxxx

Reason:

Parameter data for the specified keyword did not contain an ending parenthesis on a control statement in the SYSIN DD statement of the SARTDR utility.

Action:

Correct the control statement specification, and then resubmit the job.

SARTDR19**Tape load successfully completed****Reason:**

The /TLOAD function of the SARTDR utility completed successfully.

Action:

None. This is an informational message.

SARTDR20**Tape load ended with errors****Reason:**

The /TLOAD function of the SARTDR utility completed unsuccessfully.

Action:

Review previous error messages to determine the appropriate action, and then resubmit the job.

SARTDR21**NO REPORTS ADDED TO DATABASE****Reason:**

No reports are added to the database as a result of the /TADD function of the SARTDR utility.

Action:

The /TADD control statement could have specified a GEN, ID, or RESOURCE specification that does not exist in the specified backup tape. If so, change the parameter specification, and then resubmit the job.

SARTDR23

SYSOUT GROUP xxxxxxxx ADDED/LOADED to disk GEN=nnnnn

SEQ=nnn

RESOURCE xxxxxxxx ADDED/LOADED to disk

Reason:

The specified Sysout group or page layout Resource has been successfully added or loaded to primary or secondary disk.

Action:

None. This is an informational message.

SARTDR24

Database is already in use

Reason:

Another archival task with the same database is already executing.

Action:

Correct the problem.

SARTDR26

Specified identifier, resource, generation, and/or tape not found in database

Reason:

The master index does not contain any SYSOUT groups that match the ID, RESOURCE, GEN, and/or TAPSEQ parameter specification on the TLOAD control statement.

Action:

SYSOUT groups must be previously added to the master index by using the TADD control statement. If an invalid identifier name, resource name, generation, or tape sequence number was specified, correct the specification, and then resubmit the job.

SARTDR27

Storage group "xxxxxxx" not defined

Reason:

The storage group name specified on the TADD control statement of the SARTDR utility was not found in the database.

Action:

Change the TADD control statement to reference a valid storage group name or remove the STORGRP parameter from the TADD control statement and resubmit the request.

SARTDR28

SECOND but no Secondary Disk Driver is defined to the database

Reason:

The SECOND option requires the full definition of the secondary disk processing initialization parameters in order to copy the Sysout groups to secondary disk.

Note: For more information, see the chapters 'Using the Optical Disk Interface' and 'EMC Centera Disk Option' in the *Reference Guide*.

Disk Interface or Chapter 15 EMC Centera Disk Option.

Action:

Correct the missing configuration parameters and rerun the job.

SARTDR29

Error loading DSK2DRVR Driver

Reason:

The secondary driver module defined in the DSK2DRVR initialization parameter could not be loaded and the TLOAD SECOND function could not complete.

Action:

Verify the JOBLIB, STEPLIB, and LLA concatenation to insure that the correct libraries have been defined and rerun the job.

SARTDR30

DSK2DRVR Driver initialization error

Reason:

The secondary driver initialization function did not perform the required initializations due to some definition error.

Action:

Verify the initialization parameters associated with the secondary disk driver are correct.

SARTDR49

Permanent I/O error reading tape

Reason:

An I/O error occurs while loading a SYSOUT group to disk.

Action:

Salvage the data on the tape using the SARTCP utility, and then resubmit the job.

SARTIA01

Expanded access tape server is not active

Reason:

TAPEOPT=EAST for the CA View database and the SAREAS server whose name appears in the EASTNAME parameter is not active.

Action:

See your system administrator to determine why SAREAS is not active. Generally, CA View attempts to directly mount the volume containing the report.

SARTIA02

Expanded access primary tape server is not active

Reason:

The primary server (responsible for mounting volumes and performing I/O) is not active.

Action:

See your system administrator to determine why SAREAS is not active. Generally, CA View attempts to directly mount the volume containing the report.

SARTIA03

Expanded access tape server abended

Reason:

The server has abended while the user's request was outstanding.

Action:

Collect the appropriate information for problem analysis, and then see your system administrator to restart the server.

SARTIA05

EASTMAXW timeout exceeded - retry later

Reason:

An attempt is made to view a report directly from tape, using the Expanded Access Server. The EASTMAXW parameter, which specifies a time-out time, was exceeded.

Action:

Retry later.

SARTIA06

Unable to locate page record vector

Reason:

You are viewing a tape report, and the Expanded Access Server was unable to locate a page record vector.

Action:

See your system administrator. Each report's page record vector is located using a field in the GCR in the DASD database. The tape could have been damaged. The system administrator can be successful in running SARPAC on just the volume containing the report, after which you can access it.

SARTIA08

End of data

Reason:

A report on tape was being viewed using the expanded access server. The END OF DATA was unexpectedly reached.

Action:

See your system administrator about running SARPAC on the volume containing the report. The report's mapping information could have been overwritten. SARPAC writes new mapping information for each report on the tape.

SARTIA09

Sysout group is not on expanded access tape

User: uuuuuuu
Gen: ggggg
Seq: sssss
ID: nnnnnnnnnnn
ArchDate: dd/mm/yy
Database HLQ: ddddddddddddddd
TapeSeq: ttttt
Src: rrrrrrr

Where:

uuuuuuu	- Userid
ggggg	- Generation
sssss	- Sequence
nnnnnnnnnnn	- Report ID
dd	- day
mm	- month
yy	- year
dddddddddddddd	- Database High-Level Qualifier
ttttt	- Tape Sequence
rrrrrrr	- Source of access

Reason:

An attempt is made to view a report on a tape that is not created with TAPEOPT=EAST or TAPEOPT=3480.

Action:

See your system administrator about running SARPAC on the volume containing the report.

SARTIA11

Logical I/O error on tape

Reason:

An attempt is made to view a report on tape using the expanded access server, and an I/O error was encountered.

Action:

See your system administrator about running SARPAC on the volume containing the report.

SARTIA12

EAS server request cancelled

Reason:

A client (DocView or DVWeb) issues a request for report data which is on tape and the CA View DRAS agent waits for EAS to return the data. But, a communications timeout has occurred and the request is cancelled.

Action:

See your system administrator to determine the reason that the timeout has occurred. A timeout value can be set too low for the requested action to complete.

SARTIA14

Encryption is not supported in r11.5

Reason:

A tape created with encryption enabled (initialization parameter ENCRYPT set to ICSF) under r11.6 or higher cannot be processed by View r11.5.

Action:

The database must be versioned back to r11.6 or higher, the tapes must be consolidated (SARPAC) with the initialization parameter ENCRYPT set to NO, then the database can be versioned back to r11.5.

SARTIA20

Tape volume not found or not cataloged

Reason:

The tape on which the selected report resides on is not cataloged, or a dynamic allocation error or an open error occurred in an attempt to access the tape.

Action:

See your system administrator to determine the reason that the tape cannot be found or accessed. The system log of the SAREAS server gives dynamic allocation return codes for problem analysis. Check the system catalog to ensure that the correct volume is cataloged.

SARTIA30

Report spans more than 32 volumes

Reason:

An attempt is made to view a report on tape using the Expanded Access Server, and the report spans more than 16 tapes.

Action:

SAREAS can accommodate reports spanning 16 or fewer volumes. The report is not viewable unless CA Technical Support can create an optional zap. The entire page record vector is read in before the report can be accessed, so response time could have been slow and memory requirements in a multi-user environment could have been prohibitive.

If software compression was not in effect when the report is written to tape, the system administrator could set the SOFT option of the TAPEOPT parm and SARPAC the volumes containing the report, and the user could try accessing the report again.

SARTIA40

No direct access of this unit allowed

Reason:

None of the EASTNAMx parameters currently specifies the unit containing the report. That is, the report is on a tape volume for which no server has been defined.

Action:

Retry the access. The device must be requested directly without the server. Alternatively, ask the CA View administrator to define a server for the unit.

SARTPI41**TAPE OPEN FAILED****Reason:**

The OPEN of the tape data set failed although the dynamic allocation succeeded. Since the device allocation and tape mounts completed successfully, the OPEN failure can be due to security problems or other obvious errors, consult the job logs and/or system logs for other non-CA View messages related to this tape data set.

Action:

An attempt is made to switch to the duplex. Map the original tape using SARTCP to determine if any CA View utility can access this tape dataset without problems. If no obvious problems exist, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, a SARTSLST list of the tape sequence number, and the error if no security problems or other obvious errors exist.

SARTPI42

Tape allocation ERR=xxxx DSN=xxxxxxxx

Reason:

ERR= is the error code returned by the operating system's Dynamic Allocation function and DSN= is the tape data set name.

Dynamic allocation has failed for the archival tape (DSN). The hexadecimal error is provided. The following are the most common dynamic allocation errors:

021C

Invalid unit specification, a SARTSLST of the failing tape sequence number can be run to determine the unit name originally assigned to the tape when it was created. The following job can be run outside of CA View to determine if this unit name is valid:

```
//      JOB
//STEP EXEC PGM=IEFBR14
//TAPE DD DSN=. .tape_dsn. . ,DISP=OLD,UNIT=unitname
```

0220

The tape volume is currently mounted and in use by another job, as an example, attempting to /LOAD or /PRINT a report from a tape which is currently in use by the Backup Cycle or a tape consolidation utility (SARPAC). Retry after the job holding the tape volume has completed.

1708

The SMS controlled tape is not cataloged. Catalog the tape.

Action:

Attempt to correct the above stated condition. If recovery is unsuccessful, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, and a SARTSLST list of the tape sequence number.

SARTPI43

I/O Error positioning tape

Reason:

A permanent I/O error occurs while attempting to position the archival ape. The error can occur for any of the following reasons:

- Attempting to position the tape to read the operating system's Header Record to determine if this tape was created by SARTCP Copy.
- Attempting to position the tape using the hardware Block Id assigned to the Sysout when it is originally written to tape. This must also be accompanied by message SARTPI59.
- Attempting to position the tape by forward spacing files due to a hardware Block Id failure.
- The operating system can also provide an IOS000I I/O error message which can contain additional information concerning the I/O error.

Recovery is attempted by switching to the duplex/primary tape.

Action:

If the I/O error is due to a hardware tape drive failure, rerun the failing job to obtain a different hardware tape drive. If the I/O error is due to a tape media failure, SARTCP can be used to create a new primary tape if a duplex tape exists, or the offending sub-files can be skipped/nulled during a copy to a new physical tape.

If recovery is unsuccessful, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, and a SARTSLST list of the tape sequence number.

SARTPI44

tttt Tape does not exist or does not contain file-TSQ=nnn

Reason:

tttt is the tape type, PRIMARY, DUPLEX, or DRTAPE, and nnn is the tape sequence number. The reason is one of the following:

- The tape sequence number recorded for the Sysout is zero, this may be due to a logical database error.
- The PRIMARY or DUPLEX tape entry is not found in the database for the Sysout, this can be due to a logical database error.
- The Sysout's file position number is higher than the number of Sysout groups originally written to the tape, this can be due to a logical database error.
- The CA View EOD record was found while positioning the tape to the tape sequence number recorded for the Sysout, this can be due to a logical database error.

Action:

Use SARTCP to map the tape and attempt to locate the desired Sysout. If the Sysout is found on the tape, SARTDR/TADD the tape to the database.

If recovery is unsuccessful, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, and a SARTSLST list of the tape sequence number.

SARTPI45

NULL file located

Reason:

The file for the requested SYSOUT group is empty. This is most likely caused by a tape recovery using SARTCP. An attempt is made to switch to the duplex/primary tape.

Run SARTSLST List against the tape sequence number to find the recorded file position number. Use SARTCP Map to determine if the file position contains the desired Sysout or a NULL file.

Action:

If the tape contains the desired Sysout, SARTDR/TADD the tape to the database and retry the failing job. If the tape contains a NULL file at the designated location, attempt to create a PRIMARY tape from a DUPLEX tape if one exists, if not, the data is lost.

If recovery is unsuccessful, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, and a SARTSLST list of the tape sequence number.

SARTPI46

Permanent I/O error on tape

Reason:

A permanent I/O error occurs when reading the data on the tape. The operating system can also provide an IOS000I I/O error message which can contain additional information concerning the I/O error. Recovery is attempted by switching to the duplex/primary tape.

Action:

Use SARTCP Copy to SKIP/NULL the bad sections of the tape, if the desired Sysout is in the area where the I/O error is occurring than use SARTCP Copy to create a PRIMARY tape from a DUPLEX tape if one exists, if not, the data is lost.

SARTPI47

Tape switch is being attempted

Reason:

In order to recover from an error with the archival tape, a switch to the duplex/primary tape is being made.

Action:

None, this is an informational message. If you do not want the switch to occur, you can reply NO to the tape mount message.

SARTPI48

Invalid header located for file

Reason:

When positioning the archival tape, a tape Sysout header record (the Sysout's Group Control Record (GCR)) did not contain the same Sysout designations as the copy in the database, that is, the Sysout Id, generation and/or sequence numbers did not agree with the database copy. If the Sysout spans multiple tapes, the header record on the succeeding tape(s) can be invalid. Recovery is attempted by switching to the duplex tape.

Action:

Run SARTSLST List against the tape sequence number and SARTCP Map against the tape to determine that the correct Sysouts are in the correct positions.

If the tape contains the desired Sysout, SARTDR/TADD the tape to the database and retry the failing job. If the tape does not contain the Sysout, the data can be lost.

If recovery is unsuccessful, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, and a SARTSLST list of the tape sequence number.

SARTPI50

Encryption is not supported in r11.5

Reason:

A tape created with encryption enabled (initialization parameter ENCRYPT set to ICSF) under r11.6 or higher cannot be processed by View r11.5.

Action:

The database must be versioned back to r11.6 or higher, the tape must be consolidated (SARPAC) with the initialization parameter ENCRYPT set to NO, then the database can be versioned back to r11.5.

SARTPI59**Locate block failure, requested xxxxxx received yyyyyy, switching to file positioning****Reason:**

xxxxxx is the requested hardware Block Id, and yyyyyy is the Block Id of the block after the hardware LOCATE BLOCK ID command is issued to the tape.

A hardware failure has occurred while CA View was trying to position to a report on tape. The operating system can also provide an IOS000I I/O error message which can contain additional information concerning the I/O error.

Action:

CA View attempts to read the tape sequentially rather than using high-speed record positioning LOCATE BLOCK ID command.

If recovery is unsuccessful, contact Technical Support at <http://ca.com/support> to report the problem. Include the job logs showing the problem messages, a SARTCP map of the physical tape volume, and a SARTSLST list of the tape sequence number.

SARTP042

**Device allocation error - ERR=xxxxx, INFO=xxxx
DSNAME=xxxxxxxxxxxxxxxx
Reply Y/N to continue processing with new tape**

Reason:

Dynamic allocation has failed for the backup tape. The hexadecimal error and information codes are:

ERR=

The error code returned by the operating system's Dynamic Allocation function.

INFO= -

The Dynamic Allocation function REASON Code.

DSN=

The tape data set name.

The following are the most common dynamic allocation errors:

021C

Invalid unit specification, the unit specification is defined in the STORGRP Initialization parameter:

STORGRPn=/db/maxgent/primary-unit,duplex-unit/

The following job can be run outside of CA View to determine if this unit name is valid:

```
//      JOB
//STEP EXEC PGM=IEFBR14
//TAPE DD  DSN=..tape_dsn..,DISP=NEW,UNIT=unitname
```

0220

The requested volume is not available which can be the result of a code defect.

0270

Request requires more non-sms-managed volumes than are eligible. Assistance from the group managing SMS can be required.

0484

Request denied by operator.

04E5

The system cannot allocate tape devices, because a tape allocation subsystem eliminated all eligible devices from consideration. Assistance from the group managing SMS can be required.

1708

The request tape is not in the catalog.

9700

A severe Storage Management Subsystem (SMS) error occurred which can be the result of SMS rules for the dataset name and unit specifications and can require assistance from the group managing SMS.

9704

A severe Storage Management Subsystem (SMS) error occurred which can be an internal SMS code defect.

Action:

Reply Y to the message to allocate a new tape and continue processing. Otherwise you can reply N and correct the problem with the tape, and restart the function.

SARTPO43

I/O error forward spacing media - new volume forced

Reason:

A permanent I/O error occurs when attempting to forward space the archival tape. A new tape volume is used and execution continues. This message is normally accompanied by messages SARTPO59 and IOS000I which must provide additional information.

Action:

None. This message is informational.

SARTP044

Catalog error on backup tape - DSN=DSNAME, RC=xxxx.xxxx

Reason:

An error occurs when attempting to catalog the archival tape. The data set name, the return code, and reason code from catalog management are provided.

DSN=

The tape dataset name.

RC=

The LOCATE Macro return (rr) and reason (SS) codes.

The Z/OS LOCATE Macro return codes are:

- 4 Either the required catalog does not exist or it is not open.
- 8 One of the following happened:
 - The existing catalog structure is inconsistent with the operation requested.
 - The user is not authorized to perform the operation.
- 20 There is insufficient space in the catalog data set.
- 28 One of the following happened:
 - A permanent I/O or unrecoverable error was encountered.
 - An error is found in a parameter list.
 - There was a nonzero return code from ESTAE or GETMAIN.

The Z/OS LOCATE Macro reason codes are:

Unable to allocate a required catalog.

Either the data set was not found or the catalog could not be opened.

There was an I/O or unrecoverable error on locate.

There was an I/O or unrecoverable error on nonlocate.

Insufficient space was supplied.

The function was not valid.

Security or password verification failure.

ESTAE or GETMAIN return code was nonzero.

Action:

Correct the problem with the catalog structure.

SARTPO45**Duplex tape not compatible with primary tape - new tape volume forced****Reason:**

A primary tape with archival data normally appends with more archival data, however; tape duplexing has been requested. Since the primary and duplex tape volumes must be exact copies of each other, a new primary tape is forced. This can be due to a system failure while writing the Duplex Tape Control Record and the count of Sysouts on each tape are not identical.

Action:

None. This message is informational.

SARTPO46**dsn already exists - new volume forced****Reason:**

Allocation of a new backup tape is being attempted for the specified dsn, but the dsname is already cataloged to the system.

Action:

None. A new tape volume and dsname are used.

SARTPO47**Unable to obtain device characteristics for unit****Reason:**

The device characteristics for the specified unit are not available by using the DEVTYPE system service. Recovery is attempted by switching to the duplex tape.

Action:

Normally, this condition is caused by an invalid device name as specified by the UNITT sub-parameter of the STORGRP_x initialization parameter. Otherwise, consult your systems programming group to determine why the DEVTYPE system service cannot be performed against the unit.

SARTP049

Permanent I/O error writing backup media, restart OPT=NEW

Reason:

A permanent I/O error occurs while writing to the primary, duplex, or DR tape. The backup cycle abnormally terminates with a user U '0049'.

Action:

Restart the archival task (SARSTC) with a 'NEW' or 'INEW' parameter to allocate new tapes. The archival task can also be restarted with the 'STOPBU' parameter followed by the system modify command 'F SARSTC,NEW' or 'F SARSTC,INEW' to allocate new tapes.

SARTP054

Tape to be mounted needs write capability

Reason:

The archival tape to be mounted is written on and requires a write enabled cartridge.

Action:

Verify that the tape to be mounted is not write-protected. If tapes are not write-protected, this message can be eliminated by setting the TPO54 initialization parameter to NO.

SARTP055

Secondary disk does not emulate 3480 device

Reason:

The DSK2PARAM specifies a unit that is not a tape device.

Action:

Correct the DSK2DRVR name to use the correct driver if it is in error, correct the DSK2PARAM to use a tape device, or correct the tape unit's system definition.

SARTP056**Immediate tape access requires 3480 devices****Reason:**

The TAPEOPT parameter specifies EAST, but the tape unit does not support block ID processing.

Action:

Correct the tape unit name in the STORGRP_x definition, correct the tape unit's system definition, or change TAPEOPT to use 3420 processing.

SARTP057**Volser range nnnnn-nnnnn exceeded (volser range must be extended or changed), processing terminated****Reason:**

CA View must create a tape volume, but the specified range has been exhausted.

Action:

Define new volumes and modify the range in the STORGRP_x or STORGRX_x parameter.

SARTP058**MAXBLKS for storage group set too low****Reason:**

CA View writes several blocks to a tape volume simultaneously. The maxblks specification in the STORGRX_x parameter is below this number (currently 10).

Action:

Correct the maxblks specification in the STORGRX_x parameter.

SARTPO59

Bad block ID, using file count to append

Reason:

For best performance, CA View uses a block ID to locate the appendage point on a tape volume. CA View did not find the correct information at that point on the tape volume, so it rewound the volume and used forward-space-file to locate the point to append.

Action:

Contact Technical Support at <http://ca.com/support> to report the problem. The message is informational only, and, if the locate by forward-space-file succeeds; the only impact is on performance. If the locate by forward-space-file fails, a new tape volume is requested.

SARTPO60

Error closing primary tape

Error closing duplex tape

Reason:

An unrecoverable hardware I/O error occurred while writing the tape's End-of-File Label, or one of the two required tape marks. The tape is usable as a backup media for reports and Master Index copies, but can cause a Locate Block ID (SARTPO59) error if additional backup cycles are written to this tape. This message is normally accompanied by an IOS000i message.

Action:

The tape can be consolidated using the SARPAC utility (if you are an EAS site) or SARTCP utility to create new primary and/or duplex tapes.

SARTP099

Error flushing buffered reports to tape

Reason:

CA View queues up to 100 'tape write block' commands while the tape sub-system is writing the data to the physical tape, and waits until 100 blocks are queued while the tape catches up and issues 'block id sync' command to test the tape drive's progress. If the tape drive's block id status does not change after 100 sync commands, message SARTP099 is issued, all I/O is canceled and the task, either the Backup Cycle or the SARPAC Consolidation Utility is terminated with a Return Code 4.

Action:

This is a hardware error and the function must be re-tried. For assistance, contact Technical Support at <http://ca.com/support>.

SARTSL01

INVALID PARM SPECIFICATION; CORRECT JCL AND RESUBMIT JOB

Reason:

The tape sequence number or range specified in the JCL PARM field for the SARTSLST program is invalid. The syntax for the JCL PARM field is as follows:

```
EXEC PGM=SARTLSLT,PARM='database,tapeseq1-tapeseq2'
```

where:

database Specifies the high-level prefix name of the database
tapeseq1 Specifies the starting tape sequence number
tapeseq2 Specifies the ending tape sequence number (optional)

Action:

Correct the parameter specification, and then resubmit the job.

SARTSL02

CTLCARDS DD STATEMENT MISSING; CORRECT JCL AND RESUBMIT JOB

Reason:

The CTLCARDS DD statement is required for the SARTSLST program when a tape sequence number or range is specified on the JCL PARM field.

Action:

Add the CTLCARDS DD statement to the JCL and resubmit the job.

SARTSL03

NO MATCHING TAPE SEQUENCE NUMBERS FOUND

Reason:

The database does not contain any tape control records or the tape sequence number or range specified in the JCL PARM field is not in the database.

Action:

If the tape sequence number or range specified in the JCL PARM field is incorrect, correct the parameter specification and resubmit the job.

SARUNL88

ATIME= contains invalid hours (>23)

Reason:

The optional argument, 'ATIME=', added to the SARUNLTB DD statement, contains an invalid value for the hour.

Action:

Correct the value for the hour and resubmit the job.

SARUNL89

ATIME= contains invalid minutes (>59)',

Reason:

The optional argument, 'ATIME=', added to the SARUNLTB DD statement, contains an invalid value for minutes.

Action:

Correct the value for minutes and resubmit the job.

SARUNL91

ATIME= is invalid, HH:SS is not numeric'

Reason:

The optional argument, 'ATIME=', added to the SARUNLTB DD statement, contains non-numeric values for either the hours or minutes. This can also indicate that the separating colon is missing or incorrect.

Action:

Correct the values for the hour and minute, ensure that there is a colon separating the values, and resubmit the job.

Example

ATIME=hh:mm

SARUNL92

ATIME= specified twice',ROUTCDE=11

Reason:

The optional argument, 'ATIME=', has been specified on the SARUNLTB DD statement more than once.

Action:

Remove extra occurrences of 'ATIME=' from the DD statement and resubmit the job.

SARUNL93

ADATE= specified twice',ROUTCDE=11

Reason:

The optional argument, 'ADATE=', has been specified on the SARUNLTB DD statement more than once.

Action:

Remove extra occurrences of 'ADATE=' from the DD statement and resubmit the job.

SARUNL94

JID= specified twice',ROUTCDE=11

Reason:

The optional argument, 'JID=', has been specified on the SARUNLTB DD statement more than once.

Action:

Remove extra occurrences of 'JID=' from the DD statement and resubmit the job.

SARUNL95

Invalid day in date',ROUTCDE=11

Reason:

The optional argument, 'ADATE=', added to the SARUNLTB DD statement, contains an invalid value for the day.

Action:

Correct the day value for a valid day in the particular month specified and resubmit the job.

SARUNL96

Invalid month in ADATE= (not 01-12)',

Reason:

The optional argument, 'ADATE=', added to the SARUNLTB DD statement, contains an invalid value for the month.

Action:

Correct the value for the month and resubmit the job.

SARUNL97

Invalid date, mm/dd/yyyy is not numeric'

Reason:

The optional argument, 'ADATE=', added to the SARUNLTB DD statement, contains non-numeric values for either the month, day, or year. This can also indicate that the separating forward slashes between the month, day, and time are missing or incorrect.

Action:

Correct the values for the month, day, and year, ensure there are forward slashes separating the values, and resubmit the job.

Example

```
ADATE=mm/dd/yyyy
```

SARUNL98

Expected JID=/ADATE=/ATIME= not found',

Reason:

There is a syntax error in one or more of the optional arguments, 'JID=', 'ADATE=', or 'ATIME='.

Action:

Correct the arguments and resubmit the job.

Examples

```
ADATE=mm/dd/yyyy
```

```
ATIME=hh:mm
```

```
JID=JOBnnnnn
```

SARV0101

VTAM OPEN FAILED, ERROR=xx

Reason:

An error occurs while issuing an open ACB request. Code *xx* is returned in the ACB field ACBERFLG.

Action:

Consult the *IBM VTAM Programmer* manual for explanation on error for open of VTAM ACB, correct, and retry.

SARV0102

VTAM OPENDST FAILED, LU=xxxxxxxx, RTNCD=xx, FDBK2=xx, SENSE=xxxxxxxx

Reason:

An error occurs when issuing an OPENDST for the indicated logical unit. The return code, feedback code, and sense information are shown.

Action:

Consult the *IBM VTAM Programmer* manual for explanation on error for open for OPENDST, correct, and retry.

SARV0103

VTAM SEND FAILED, LU=xxxxxxxx, RTNCD=xx, FDBK2=xx, SENSE=xxxxxxxx

Reason:

An error occurs when issuing a SEND for the indicated logical unit. The return code, feedback code, and sense information are shown.

Action:

Consult the *IBM VTAM Programmer* manual for explanation on error for SEND to VTAM Device, correct, and retry.

SARV0104**INVALID DEVICE FOR VTAM PRINT, LU=xxxxxxxx****Reason:**

The logical unit indicates it is not a VTAM logical unit as reported by a value other than DEVLU being returned in the DEVTCODE field of the NIB after the OPENDST is completed.

Action:

Use a VTAM device.

SARV0105**NO AVAILABLE APPLIDS, LU=xxxxxxxx, APPLID=xxxxxxxx****Reason:**

The task of successfully opening the VTAM ACB while processing the logical unit indicates that it is not possible to locate an available APPLID with the indicated value.

Action:

Either define the necessary APPLIDs to VTAM or specify an existing APPLID in the VPRTAPPL initialization parameter.

SARV0106**VTAM SIMLOGON FAILED, LU=xxxxxxxx, RTNCD=xx, FDBK2=xx, SENSE=xxxxxxxx****Reason:**

An error occurs when issuing a SIMLOGON for the indicated logical unit. The return code, feedback code, and sense information are shown.

Action:

Correct the error and retry.

SARV0107

DEVICE NOT AVAILABLE, LU=xxxxxxx

Reason:

The VTAM printer that is specified as xxxxxxx is either not defined to VTAM or is busy longer than the retry limits specify in the VPRTRTRY and VPRTRINT initialization parameters.

Action:

Either use a printer that is defined to VTAM or (if the printer is already defined to VTAM) wait until it is not being used.

SARV0108

LOGMODE NOT AVAILABLE, LU=xxxxxxx, LOGMODE=xxxxxxx

Reason:

The LOGMODE specified in the DEFine DEvice for logical unit xxxxxxx is not available to VTAM.

Action:

Either make the LOGMODE available to VTAM, or specify a usable LOGMODE in the DEFine DEvice panel.

SARVAPI1

applid_termialid_VT ----message text-----

Reason:

This is a replication of a message generated at a terminal and can contain any numbered or unnumbered message. The format contains the VTAM Application Identified, the VTAM Terminal Identifier, the constant 'VI' (indicating VTAM) and a copy of the message text displayed to the terminal user.

Action:

The action depends on the message text; normally the terminal user could be required to perform some action or report a problem.

Example:

SARVAPI1 A03SARVT_TCPL0860_VT

SARDBI00 Database SAR.JCL does not exist

SARVAPI2

applid_terminalid_VT QUERIBLE TERMINAL- ALTERNATE SCREEN SIZE=rr-cc feature

Reason:

A terminal session has been created (this message follows the 'Logon Request' and 'Terminal Connected' messages) and displays the terminal characteristics, that is, screen size and color/highlighting capabilities of the terminal session.

Action:

None. This message is informational.

SARVCL99

INCORRECT LEVEL OF BASE COMMON CODE - BASE=V., REQ=V.M

Reason:

An unusable earlier version of shared common code has been detected. BASE shows the version detected, and REQ shows the version required.

Action:

Correct the error and retry. This can be done by putting the CA View LOADLIB ahead of EXPRESS, BALANCING, and/or ARISE LOADLIBs.

SARVDRV1

xxxxxxxxx TERMINAL CONNECTED

Reason:

The VTAM terminal has been successfully connected to the user subtask in the region. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARVDRV2

xxxxxxxxx APPLICATION ENDED

Reason:

The CA View program has ended normally. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARVDRV3

XXXXXXXXX SESSION CLSDST

Reason:

A VTAM CLSDST to disconnect the terminal is now issued. This message has a MSGLVL of TRCE.

Action:

None. This message is informational.

SARVDRV4

XXXXXXXXX *REJECTED*** XXXXXXXXXXXXX**

Reason:

CA View detected a problem with the session bind parameters and has rejected the terminal logon. This message has a MSGLVL of ACTN.

Action:

Review the REJECT reason for the appropriate action.

SARVDRV5

XXXXXXXXX XXX

Reason:

This message displays the bad bind image data rejected by message SARXDRV5. This message has a MSGLVL of ACTN.

Action:

Contact your VTAM systems programmer or CA Technical Support. This can be a VTAM definition problem.

SARVDRV6

BAD SCREEN SIZE=(nn,nn), CHANGED TO=(nn,nn)

Reason:

The incorrect screen size to bind data changes to conform to normal 3270 screen sizes. This message has a MSGLVL of NORM.

Action:

Contact your VTAM systems programmer. This can be a VTAM definition problem.

SARVEND1

SARAPPLID=xxxxxxx VTAM TPEND RC=nn

Reason:

The VTAM access method has requested closing the VTAM ACB, because of command processing or VTAM shutdown. This message has a MSGLVL of CRIT.

Action:

Contact your VTAM systems programmer.

SARVERO00

ERO table statements and sequence successfully verified

SARVERO01

Next standard backup cycle will be for Gen nnnn

Reason:

The system generated a message to inform you about the next standard backup cycle: *nnnn* is the current database generation number.

Action:

None. This message is informational.

SARVERO02

Next standard backup cycle xxxx of yyyy reports and resource groups will be deleted

Reason:

The system generated a message to inform you of a pending delete:

- *xxxx* is the number of reports that is deleted from the database. If the report is still on the primary and/or secondary disk, this count is also reflected in the SARVERO04 and/or SARVERO05 messages.
- *yyyy* is the number of reports currently in the database.

Action:

None. This message is informational.

SARVERO03

Next standard backup cycle *nnnn* reports will be deleted from primary disk

Reason:

The system generated a message to inform you of a pending delete:

nnnn is the number of reports which is deleted from the primary disk. If these reports are also being deleted from the tape and/or secondary disk, these counts are reflected in the SARVERO01 and/or SARVERO04 messages as well.

Action:

None. This message is informational.

SARVERO04

Next standard backup cycle *nnnn* reports will be deleted from secondary disk

Reason:

The system generated a message to inform you of a pending delete:

nnnn is the number of reports which is deleted from the secondary disk. If these reports are also being deleted from tape and/or primary disk, these counts are reflected in the SARVERO01 and/or SARVERO03 messages as well.

Action:

None. This message is informational.

SARVERO05

Next standard backup cycle *nnnn* reports will be migrated to secondary disk

Reason:

The system generated a message to inform you of a pending migration:

nnnn is the number of reports which are on the primary disk and are migrated to the secondary disk if the secondary disk is defined in this database.

Action:

None. This message is informational.

SARVER006

Next standard backup cycle xxxx of yyyy tapes will be expired

Reason:

The system generated a message to inform you of pending tape expirations:

xxxx is the number of tapes which is uncataloged and removed from the database.

yyyy is the number of tapes currently defined in the database.

Action:

None.

SARVER010

ERO Option is 'NO', cannot validate ERO settings or table

Reason:

The ERO Table Validation Utility cannot run a simulated backup cycle to verify the ERO settings and table because the initialization parameter EROOPT is set to NO.

Action:

The utility can be used to validate an ERO Table pointed to by the SARPATAB DD Statement if the execution parameter is set to PARM='TABLE'. If a full backup cycle validation is desired, then the ERO Option must be turned on in the database.

SARVERR1

xxxxxxxx REQ=xxxxx RC=xxxx FDBK2=xxxxx xxxxxxxxxxxx

Reason:

A VTAM error has occurred processing a request from the VTAM interface. The RC= shows the problem return code. This message has a MSGLVL of ACTN.

Action:

The action to take depends on the session status and type of error. Most errors show communications problems.

SARVETX1

xxxxxxx TASK ENDED or ABENDED nnnnn

Reason:

The VTAM user subtask has ended normally or with an abend condition. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARVLGN1

xxxxxxxxx LOGON REQUEST RTUS=xxxxxxx SLU=xxxxxxxx

Reason:

The VTAM logon request has been received, CA View attaches the user subtask to support the user. This message has a MSGLVL of INFO.

Action:

None. This message is informational.

SARVLGN2

XXXXXXXXXX ***REJECT*** XXXXXXXXXXXXXXXXXXXX

Reason:

The VTAM logon request was rejected, the message shows the reason. This message has a MSGLVL of ACTN.

Action:

Review the REJECT reason for the appropriate action.

The message containing ***REJECTED-NO XMCT AVAILABLE is issued when the maxuser threshold has been reached and no other XMS region is available for use. XMS checks two criteria for determining whether the maxuser threshold per XMS region has been exceeded.

These are as follows:

1. Has maxuser threshold been reached? If yes, XMS attempts to automatically pass the user to another XMS region. If one is not available, XMS issues the NO XMCT AVAILABLE message.
2. If maxuser threshold has not been exceeded, XMS verifies whether there is sufficient storage to log the user on. If the storage is not available, XMS attempts to pass the user to another XMS region automatically. If one is not available, XMS either issues the VTAMPASS=NO message or issues the NO XMCT AVAILABLE message.

Storage constraints govern the maximum users supported by an XMS region. As a rule, XMS regions must have 7 to 8 MB of below the line storage available and 10 MB plus 1 MB for each 3 users of above the line storage available.

SARVLGN3

XXXXXXXXXX PASSING TO APPLID=XXXXXX XXXXXXXXXXXXXXXXXXXX

Reason:

The VTAM logon request was not accepted by this region, the request is passed to the next CA View region for processing. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARVLST1

XXXXXXXXXX LOSTERM RC=XX XXXXXXXXXXXXXXXXXXXXXXXXXX

Reason:

A VTAM session has been lost for this terminal. This message has a MSGLVL of NORM.

Action:

VTAM has disconnected the terminal, possibly due to a terminal or network outage.

SARVLST2

XXXXXXXXXX SESSION CLSDST

Reason:

A VTAM CLSDST to disconnect the terminal is issued. This message has a MSGLVL of INFO. This message occurs at the normal end, or an ABEND, of the VTAM session.

Action:

None. This message is informational.

SARVLST3

XXXXXXXXXX FORCED OFF

Reason:

The VTAM terminal session has been forced off successfully. This message has a MSGLVL of INFO.

Action:

None. This is an informational message.

SARVOP02

NO VIEWS FOUND FOR REPORT "reportid" GEN=xxxxx SEQ=xxxxx

Reason:

An attempt is made to retrieve the logical views for a report, but no logical views are defined for the report.

Action:

None. Only the native view of the report is accessible.

SARVPS01

VTAM OPEN FAILED, ERROR=XX

Reason:

An error occurs while issuing an open ACB request. Code *xx* is returned in the ACB field ACBERFLG.

Action:

Consult the *IBM VTAM Programmer* manual for explanation of errors for open of VTAM ACB; correct, and retry.

SARVPS02

VTAM OPENDST FAILED, LU=XXXXXXXX, RTNCD=XX, FDBK2=XX, SENSE=XXXXXXXX

Reason:

An error occurs when issuing an OPENDST for the indicated logical unit. The return code, feedback code, and sense information are shown.

Action:

Consult the *IBM VTAM Programmer* manual for explanation of errors for open for OPENDST; correct and retry.

SARVPS03

VTAM SEND FAILED, LU=XXXXXXXX',C', RTNCD=XX, FDBK2=XX, SENSE=XXXXXXXX

Reason:

An error occurs when issuing a SEND for the indicated logical unit. The return code, feedback code, and sense information are shown.

Action:

Consult the *IBM VTAM Programmer* manual for explanation of errors for SEND to VTAM Device; correct and retry.

SARVPS04

INVALID DEVICE FOR VTAM PRINT, LU=XXXXXXXX

Reason:

The logical unit indicates it is not a VTAM logical unit as reported by a value other than DEVLU being returned in the DEVTCODE field of the NIB after the OPENDST is completed.

Action:

Use a VTAM device.

SARVPS05

NO AVAILABLE APPLIDS, LU=XXXXXXXX, APPLID=XXXXXXXX

Reason:

The task of successfully opening the VTAM ACB while processing the logical unit indicates that it is not possible to locate an available APPLID with the indicated value.

Action:

Either define the necessary APPLIDs to VTAM or specify an existing APPLID in the VPRTAPPL initialization parameter.

SARVPS06

VTAM SIMLOGON FAILED, LU=XXXXXXXX, RTNCD=XX, FDBK2=XXXX, SENSE=XXXXXXXX

Reason:

An error occurs when issuing a SIMLOGON for the indicated logical unit. The return code, feedback code, and sense information are shown.

Action:

Correct the error and retry.

SARVPS07

DEVICE NOT AVAILABLE, LU=XXXXXXXX

Reason:

The VTAM printer specified as xxxxxxxx is either not defined to VTAM or is busy longer than the retry limits specify in the VPRTRTRY and VPRTRINT initialization parameters.

Action:

Either use a printer defined to VTAM or (if the printer is already defined to VTAM) wait until it is not being used.

SARVPS08

LOGMODE NOT AVAILABLE, LU=XXXXXXXX, LOGMODE=XXXXXXXX

Reason:

The LOGMODE specified in the DEFine DEvice for the logical unit xxxxxxxx is not available to VTAM.

Action:

Either make the LOGMODE available to VTAM, or specify a usable LOGMODE in the DEFine DEvice panel.

SARVSGN1

OPN/CLOSE ERROR APPLID=xxxxxxx ACBERRFLG=xx

Reason:

A VTAM OPEN or CLOSE has not completed successfully. The VTAM signon task is shut down. This message has a MSGLVL of CRIT.

Action:

Contact your VTAM systems programmer.

SARVSGN2

XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX

Reason:

A VTAM OPEN or CLOSE code failure reason. This message has a MSGLVL of CRIT.

Action:

Contact your VTAM systems programmer.

SARVSGN3

MODCB ERROR APPLID=xxxxxx

Reason:

A VTAM MODCB macro has failed, the VTAM session cannot be initialized, and the EC1VTSGN program is shut down. This message has a MSGLVL of CRIT.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARVSGN4

APPLID=xxxxxx NOW ACCEPTING LOGONS

Reason:

VTAM signon initialization is completed. VTAM users can now sign onto the region. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARVSGN5

APPLID=xxxxxx QUIESCE PENDING, WAITING FOR USERS TO LOGOFF

Reason:

The console operator has stopped the region, but users are still active. The VTAM signon task waits for the users to complete processing. This message has a MSGLVL of NORM.

Action:

None. This message is informational.

SARVSGN6

VTAM EXIT xxxxxxxx ACTIVE ADDR=xxxxxx x.x xx/xx/xx

Reason:

The indicated VTAM routine loaded and attached to the VTAM ACB exit list. The release and assembly date and time are displayed. This message has a MSGLVL of INFO.

Action:

None. This is an informational message.

SARVSTA1

xxxxxxx RECOVERY-xxxx

Reason:

A subtask abend has been detected and the session now be cleaned up. This message has a MSGLVL of ACTN.

Action:

None. This message is informational.

SARVSTM1

xxxxxxxxxxx USER HAS EXCEEDED THE LONGWAIT TIME

Reason:

The terminal shown has not had a transaction for a period exceeding the time specified in the LONGWAIT= parameter. This message has a MSGLVL of ACTN.

Action:

If CANCEL=YES is specified for the region, the user is canceled. Otherwise the task status is changed to LONGWAIT.

SARVTA01

OPEN ERROR APPLID=xxxxxxxx ACBERFLG=xx

Reason:

The open has failed for the application program ACB.

Action:

Verify that the SARVTAM APPLID is activated. Normally, inactivating and re-activating the SARVTAM APPLID fixes the problem.

SARVTA02

APPLID=xxxxxxxx NOW ACCEPTING LOGONS

Reason:

The VTAM online retrieval task in now ready for users to log on to it.

Action:

None. This is an informational message.

SARVTA03

APPLID=xxxxxxxx DISABLED FOR LOGONS

Reason:

This message is in response to the successful quiesce request.

Action:

None. This is an informational message.

SARVTA04

APPLID=xxxxxxxx NOW CLOSED

Reason:

The application is terminating.

Action:

None. This is an informational message.

SARVTA05

INVALID COMMAND IGNORED

Reason:

An invalid operator command has been issued.

Action:

Reenter the operator command in its correct form.

SARVTA06

TASK ABEND xxx xxxx

Reason:

The user subtask has abended. Consult message SARVTA14 for further information.

Action:

None. This is an informational message.

SARVTA07**LOSTERM REASON=xxxx FOR LU xxxxxxxx****Reason:**

The losterm exit has been invoked for the session with the specified LU name. The session is terminated.

Action:

None. This is an informational message.

SARVTA08**TPEND REASON xx****Reason:**

VTAM has been terminated with a Z NET or V NET,INACT command. VTAM online retrieval is terminated.

Action:

After VTAM has been started again, start the VTAM online retrieval task.

SARVTA09**LU xxxxxxxx STARTED****Reason:**

A session with the specified logical unit has started.

Action:

None. This is an informational message.

SARVTA10**LU xxxxxxxx ENDED****Reason:**

The session with the specified logical unit has terminated normally.

Action:

None. This is an informational message.

SARVTA11

LU REQ=xxxxxxxx RTNCD=xxxx FDBK2=xxxxxxxx

Reason:

The specified VTAM request has failed.

Action:

Reference the return and feedback codes to determine the cause of the error.

SARVTA12

RECURSIVE ERRORS AT xxxxxxxx xxxx xxxxxxxx

Reason:

An attempt to recover from a previous error has failed.

Action:

Consult the message for the previous error.

SARVTA13

LU xxxxxxxx DFASY REQ - RPLCNTRL=xxxxxx

Reason:

The DFASY exit has been entered for the specified logical unit.

Action:

None. This is an informational message.

SARVTA14

LU xxxxxxxx ABEND CMPC=xxxxxx

Reason:

The user subtask has abended. A completion code of 306000 occurs when the CA View load library is not authorized. The session with the user is terminated.

Action:

None. This is an informational message.

SARVXIT1

xxxxxxxxxxxx xxxxxxx RPLCNL=xxxxxxxx

Reason:

An exceptional condition is reported by VTAM.

Action:

This message has a MSGLVL of NORM. This can occur for a number of reasons. For assistance, contact Technical Support at <http://ca.com/support>.

SARVXIT2

xxxxxxxxxxxx xxxxxxx PCID=xxxxxx REASON=xxxx SENSE=xxxx

Reason:

An exceptional condition is reported by VTAM.

Action:

This message has a MSGLVL of NORM. This can occur for a number of reasons. For assistance, contact Technical Support at <http://ca.com/support>.

SARVXIT9

xxxxxxxxxxxx xxxxxxx xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx

Reason:

An exceptional condition is reported by VTAM.

Action:

This message has a MSGLVL of NORM. This can occur for a number of reasons. For assistance, contact Technical Support at <http://ca.com/support>.

SARXCT01

INVALID EXCEPTION TABLE STATEMENT – IGNORED *control statement*

Reason:

The control statement does not begin with a slash (/), or a percent sign (%). The control statement is ignored.

Action:

Correct the statement.

SARXCT02

INVALID JOBNAME IN EXCEPTION TABLE STATEMENT - IGNORED *control statement*

Reason:

The control statement contains an invalid SYSOUT ID. The control statement is ignored.

Action:

Correct the statement.

SARXCT03

INVALID PARAMETER IN EXCEPTION TABLE STATEMENT '*parameter*' - IGNORED *control statement*

Reason:

The control statement contains an invalid parameter. The parameter is ignored.

Action:

Correct the statement.

SARXCT04

TOO MANY PARAMETERS FOR SYSOUT ID

Reason:

Too many parameters are specified for the SYSOUT ID.

Action:

Reduce the number of parameters on the control statement.

SARXCT05

NEW EXCEPTION CONDITION TABLE LOADED

Reason:

The Exceptional Conditions checking table parameters have been reloaded.

Action:

None. This is an informational message.

SARXCT06**FIRST / LAST / HIGH ARE MUTUALLY EXCLUSIVE - TABLE STATEMENT - IGNORED****Reason:**

The control statement contains two or more of the mutually exclusive FIRST, LAST, and HIGH parameters.

Action:

Correct the entry in the Exceptional Conditions checking table (SARXCTAB) and reload the table.

SARXETX1**xxxxxxx SESSION HAS ABENDED****Reason:**

The XMS user subtask has terminated abnormally. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARXETX2**xxxxxxx SESSION HAS ENDED****Reason:**

The XMS user subtask has terminated normally. This message has a MSGLVL of NORM.

Action:

None. This is an informational message.

SARXETX3**xxxxxxx xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx****Reason:**

The XMS user subtask has terminated and an internal error was detected cleaning up the session. This message has a MSGLVL of NORM.

Action:

Contact CA Technical Support.

SARXFP01

Critical error, program terminated with dump. Invalid blk

Reason:

A CA View program has terminated, and a dump was generated. In this message, *blk* specifies the control block CA View expected but did not receive (usually IFB, SFB, XFB, or DBB). It could be suffixed with a number indicating which test point in the program detected the problem.

Action:

Send the dump to CA Technical Support. Restart whatever program was terminated. If the problem recurs, run SARDBASE VERIFY on the database. For assistance, contact Technical Support at <http://ca.com/support>.

SARXOC04 NO QUALIFIED REPORTS FOR CROSS-REPORT INDEX

Reason:

No reports, indexing information or both are found in the database for the selected cross report index name and filtering criteria.

Action:

Select another cross report index name or change the filtering criteria.

SARXPD02

Report queued to dataset:...dataset_name

Reason:

External Print sample program SARXPDSK has been installed and has queued a report to the named data set.

Action:

None. This is an informational message.

SARXSGN1

XXXXXXXXXXXX SIGNON IN PROGRESS RTUS=XXXXXXXX SLU=XXXXXXXX

Reason:

XMS signon request received, CA View attaches the user subtask to support the user.

Action:

None. This message is informational.

SARXSGN2

XXXXXXXXXX XXXXXXXXXXXXXXXXXXXXXXXXXXXX

Reason:

XMS signon has detected an internal error during processing. This message has a MSGLVL of ACTN.

Action:

Contact CA Technical Support.

SARXSGN3

RTUS COUNT MISMATCH

Reason:

XMS found the count of active users in the XMEMCNTL was bad and corrected it. This message indicates that CA View has lost track of the correct number of users in the region. This message has a MSGLVL of ACTN.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARXSGN4

ASCB LOCATE FAILED

Reason:

XMS has not been able to locate its ASCB control block. This message has a MSGLVL of ACTN.

Action:

Contact CA Technical Support.

SARXSTA1

XXXXXXXXXX RECOVERY-XXXX

Reason:

A subtask abend has been detected and the session is now cleaned up. This message has a MSGLVL of ACTN.

Action:

None. This message is informational.

SARXSTM1

XXXXXXXXXX USER HAS EXCEEDED THE LONGWAIT TIME

Reason:

The terminal shown has not had a transaction for a period exceeding the time specified in the LONGWAIT= parameter. This message has a MSGLVL of ACTN.

Action:

If CANCEL=YES is specified for the region, the user is canceled. Otherwise, the task status is changed to LONGWAIT.

SARXTD01

REPLY Y/N TO AUTHORIZE CHANGE TO CA VIEW SYSTEM EXTENSIONS

Reason:

SARXTD has been started to change or turn off extensions.

Action:

Reply Y to authorize the change, or N to prevent the change.

SARXTD02

INVALID REPLY

Reason:

An invalid reply has been given to message SARXTD01.

Action:

Reply correctly to message SARXTD01.

SARXTD03

AUTHORIZATION DENIED

Reason:

The operator has replied N to message SARXTD01.

Action:

If authorization has been erroneously denied, start SARXTD again.

SARXTD04

JOB ACCOUNTING NOT IN EFFECT

Reason:

SARXTD has been started without a DD statement for the job accounting data set.

Action:

Verify that job accounting is not to be in effect.

SARXTD05

JOB ACCOUNTING DATASET CAN ONLY HAVE ONE EXTENT

Reason:

The job accounting data set can only have one extent.

Action:

Recreate the job accounting data set.

SARXTD06

INVALID PARAMETER AT xxxxx

Reason:

The PARM field contains invalid syntax starting with the first character displayed.

Action:

Correct the PARM field and start SARXTD again.

SARXTD07

SECURITY ENABLED FOR DATASET PREFIX xxxxxxxxxxxxxxxxxxxx

Reason:

Data set security is in effect for all data sets whose names begin with the specified prefix.

Action:

None. This is an informational message.

SARXTD08

ACCOUNTING ENABLED FOR DATASET *dsname*

Reason:

Job accounting information is maintained in the specified accounting data set.

Action:

None. This is an informational message.

SARXTD09

AUTOMATIC REPORT ARCHIVAL ENABLED WITH SPECIFICATIONS *archival-criteria*

Reason:

The automatic report archival feature is active and the specified archival criteria is in effect.

Action:

None. This is an informational message.

SARXTD10

SECURITY DISABLED

Reason:

Data set security is no longer in effect.

Action:

None. This is an informational message.

SARXTD11

ACCOUNTING DISABLED

Reason:

Job accounting data is no longer being maintained.

Action:

None. This is an informational message.

SARXTD12

AUTOMATIC REPORT ARCHIVAL DISABLED

Reason:

The automatic report archival feature is no longer in effect.

Action:

None. This is an informational message.

SARXTD13

INVALID OPERATOR COMMAND

Reason:

When a systems extension is started and contains a NOTERM DD statement, the system extensions task remains active and responds to operator commands. The MODIFY command that is entered at the operator console is invalid.

Action:

The valid operator commands that can be entered are: OFF, OFFSEC, OFFACT, OFFARA, STATUS, and STOP. The system extensions task automatically terminates when the OFF or STOP commands are entered, or when all the system extension facilities have been disabled.

SARXTD14

CA VIEW SYSTEM EXTENSION IS ALREADY ACTIVE ON THE SYSTEM

Reason:

A system extensions task is already active for the subsystem identifier. Each system extensions task is assigned a one-character subsystem identifier, which can be defined by using the SUBSYSx DD statement, and a system extensions task currently is executing with the same identifier. Execution of the recently started task is terminated.

Action:

If an additional system extension task is required, specify a unique subsystem identifier by using the SUBSYSx DD statement. Otherwise, verify that the previously started systems extensions task specifies the desired parameters. If not, terminate the previously started systems extensions task, and start the new task.

SARXTD15

CA VIEW SYSTEM EXTENSIONS 12.1 IS NOW INACTIVE

Reason:

Informational message indicating that all facilities for the system extensions task have been disabled and the systems extensions task is terminating.

Action:

None. This message is informational.

SARXTD16

SARXTD IS NOT A STARTED TASK

Reason:

An attempt has been made to execute SARXTD as other than a started task.

Action:

Execute SARXTD by using the START command.

SARXTD18

SARXTD REQUIRES APF-AUTHORIZATION

Reason:

SARXTD has determined that it lacks required APF-authorization. SARXTD requires APF-authorization to modify the various operating system interfaces dynamically.

Action:

Ensure that SARXTD resides in an APF-authorized load library. Alternatively, SARXTD can be placed in a linklist library provided LNKAUTH=LNKLST has been specified or allowed to default in the active IEASYSxx member of SYS1.PARMLIB. Under no circumstances must SARXTD be placed in any of the link pack areas.

SARXTD20

UCB ADDRESS TRANSLATION FAILED, R15=xxxxxxxx R0=xxxxxxxx

Action:

See the IBM documentation for the IOSCAPU return code indicated in the previously issued SARXTD20 message.

SARXTD21

UCB CAPTURE FUNCTION FAILED, R15=xxxxxxxx R0=xxxxxxxx

Action:

See the IBM documentation for the IOSCAPU return code indicated in the previously issued SARXTD21 message.

SARXTD22

WARNING: THE AUTOMATIC REPORT ARCHIVAL SVC IS ALREADY ACTIVE, IF RESTART IS BEING PERFORMED TO REFRESH THE SVC, REPLY "Y" TO THE FOLLOWING MESSAGE, THEN EITHER ISSUE A " F SARXTD,OFF" (IF RUNNING WITH NOTERM) OR "S SARXTD, PARM=OFF" (IF THE TASK NORMALLY TERMINATES AFTER ACTIVATION), AND REISSUE THE START COMMAND.

Reason:

The SARXTD is being restarted and Automatic Report Archival is active.

Action:

If the restart is being performed to refresh the Automatic Report Archival SVC, the previous execution of the task was not properly terminated. Reply 'Y' to the SARXTD01 message, and then issue a "F SARXTD,OFF" (if running with NOTERM) or "S SARXTD,PARM=OFF" (if the task normally terminates after activation), and re-issue the start command to refresh the Automatic Report Archival SVC.

SARXTD23

**CSVDYLPA macro failed for module xxxxxxxx, R15=xxxx R0=xxxx FLAGS=xxxx
PROCESSING CONTINUES**

Reason:

SARXTD was unable to add the above module to the MLPA CDE directory. This is required only by product support and does not affect normal product performance.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

SARXTD99

action SUPPRESSED FOR *dsname*

Reason:

CA View system extensions have prevented the specified action (OPEN, OPEN J, SCRATCH, or RENAME) from being performed on the specified data set. With the security feature of system extensions enabled, only authorized programs recognized by CA View are allowed to access CA View data sets.

Action:

Normally, no action is required; system extensions are controlling access to CA View data sets as requested. However, in an emergency, the security feature of system extensions can be disabled in order to allow unrestricted access to CA View data sets.

SAR42B

MEMORY EXCEEDED

Reason:

When a user is logged on to CA View using XMS and uses a wildcard to select cross-indexed reports, this message can be issued depending upon the number of SYSOUTs which meet the selection criteria.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

Chapter 4: Cross-Memory Services Messages

This section contains the following topics:

[Error Messages](#) (see page 583)

Error Messages

This topic covers the error messages that are associated with cross-memory services.

XMSCG001

USERMAX CHANGED

Reason:

This is an informational message.

Action:

None. This is an informational message.

XMSCG002

CHANGE REQUEST DOES NOT SPECIFY *parameter*, REQUEST IGNORED

Reason:

Change request has specified an unknown parameter.

Action:

Correct and retry.

XMSCG003

INVALID QUOTED STRING, REQUEST IGNORED

Reason:

Invalid quoted string.

Action:

Correct and retry.

XMSCG004

USERMAX VALUE NOT SPECIFIED, REQUEST IGNORED

Reason:

USERMAX value is not specified.

Action:

Correct and retry.

XMSCG005

INVALID USERMAX VALUE - EITHER NOT A NUMBER OR ZERO, REQUEST IGNORED

Reason:

An invalid USERMAX parameter has been specified.

Action:

Correct and retry.

XMSCL001

CANCEL REQUEST MUST SPECIFY EITHER ALL, USER= OR UID#=: REQUEST IGNORED

Reason:

An invalid CANCEL REQUEST has been specified.

Action:

Correct and retry.

XMSCL002

INVALID QUOTED STRING, REQUEST IGNORED

Reason:

An invalid QUOTED STRING has been specified.

Action:

Correct and retry.

XMSCL003

INVALID USER NAME - ONLY 20 CHARACTERS ALLOWED, REQUEST IGNORED

Reason:

An invalid USER NAME has been specified.

Action:

Correct and retry.

XMSCL004

USER NAME OR NUMBER NOT SPECIFIED, REQUEST IGNORED

Reason:

The USER NAME or USER NUMBER has not been specified.

Action:

Correct and retry.

XMSCL005

INVALID USER NUMBER - EITHER NOT A NUMBER OR ZERO, REQUEST IGNORED

Reason:

An invalid USER NUMBER has been specified.

Action:

Correct and retry.

XMSCL006

CANCEL REQUEST SPECIFIED SOME USERS WHO WERE NOT FOUND AND CANCELED

Reason:

This is an informational message.

Action:

None.

XMSCL007

NO USERS CURRENTLY CONNECTED, CANCEL REQUEST IGNORED

Reason:

This is an informational message.

Action:

None.

XMSCL099

INTERNAL ERROR HAS OCCURRED IN CANCEL COMMAND, REQUEST IGNORED

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSLS001

NO. USERID APPL STATUS DATABASE

Reason:

This is an informational message in response to a list request.

Action:

None.

XMSLS002

nnn uuuuuuuu aaaaaaaaa ssssssss ddddddddddddddd

Reason:

This is an informational message in response to a list request, issued with XMSLS001, which identifies the fields (USERID, APPL, and so forth).

Action:

None. This is an informational message.

XMSLS003**NAME USERMAX USERS STATUS****Reason:**

This is an informational message in response to a list request.

Action:

None. This is an informational message.

XMSLS004

XXXXXXXX XXX XXX XXXXXXXXXXXX

Reason:

This is an informational message in response to a list request.

Action:

None. This is an informational message.

XMSLS005**LIST REQUEST DOES NOT SPECIFY STATUS, USERS OR USER/UID#, REQUEST IGNORED****Reason:**

The LIST REQUEST does not specify STATUS, USERS, or USER ID number.

Action:

Correct the problem, and then retry.

XMSLS006**INVALID USER NAME - ONLY 20 CHARACTERS ALLOWED, REQUEST IGNORED****Reason:**

An invalid USER NAME has been specified.

Action:

Correct the problem, and then retry.

XMSLS007

INVALID QUOTED STRING, REQUEST IGNORED

Reason:

An invalid QUOTED STRING has been specified.

Action:

Correct the problem, and then retry.

XMSLS008

NO USER NAME OR UID# IS SPECIFIED, REQUEST IGNORED

Reason:

No USER NAME or UID# has been specified.

Action:

Correct the problem, and then retry.

XMSLS009

INVALID UID# VALUE - EITHER NOT A NUMBER OR ZERO, REQUEST IGNORED

Reason:

An invalid UID# has been specified.

Action:

Correct the problem, and then retry.

XMSLS010

THERE ARE NO USERS CURRENTLY CONNECTED

Reason:

No users are connected.

Action:

None. This is an informational message.

XMSLS011

NO USERS DISPLAYED

Reason:

No users are displayed.

Action:

None. This is an informational message.

XMSLS098

LIST command

Reason:

This message displays the previously entered cross-memory started task command.

Action:

None. This is an informational message.

XMSLS099

INTERNAL ERROR HAS OCCURRED IN LIST COMMAND, REQUEST IGNORED

Reason:

This message is informational.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSPM001

REQUESTED COMMAND IS UNKNOWN - REQUEST WILL BE IGNORED

Reason:

The request from an operating system modify command cannot be recognized.

Action:

Correct the problem, and then retry.

XMSQU001

CROSS-MEMORY SYSTEM QUIESCE HAS BEEN INITIATED

Reason:

The quiesce has been initiated.

Action:

None. This is an informational message.

XMSRS001

SIGNONS RESUMED

Reason:

The login is resumed.

Action:

None. This message is informational.

XMSRS002

SIGNONS NOT SUSPENDED - REQUEST IGNORED

Reason:

The request is ignored.

Action:

None. This is an informational message.

XMSRS003

SYSTEM IS QUIESCING - REQUEST IGNORED

Reason:

The request is ignored.

Action:

None. This is an informational message.

XMSSD001

IMMEDIATE SHUTDOWN HAS BEEN STARTED

Reason:

Shutdown has been started.

Action:

None. This is an informational message.

XMSSP001

SIGNONS SUSPENDED

Reason:

The login is suspended.

Action:

None. This is an information message.

XMSSP002

SIGNONS ALREADY SUSPENDED - REQUEST IGNORED

Reason:

The request is ignored.

Action:

None. This is an informational message.

XMSSP003

SYSTEM IS QUIESCING - REQUEST IGNORED

Reason:

The request is ignored.

Action:

None. This is an informational message.

XMSXD001

PARAMETER STRING TOO LONG - RUN ABORTED

Reason:

Input parameter is too long.

Action:

Check the parameter field on the EXEC statement.

XMSXD002

CROSS-MEMORY SYSTEM MUST BE A STARTED TASK - RUN ABORTED

Reason:

CA View has aborted the job run because the cross-memory system is not a started task.

Action:

Correct and retry.

XMSXD003

NO MEMORY FOR ANCHOR SSCT - RUN ABORTED

Reason:

Unable to obtain CSA for SSCT.

Action:

Contact your systems programmer.

XMSXD004

NO MEMORY FOR CROSS-MEMORY SYSTEM CONTROL BLOCK - RUN ABORTED

Reason:

Unable to obtain CSA for XMCT.

Action:

Contact your systems programmer.

XMSXD005**A CROSS-MEMORY SYSTEM WITH THE SAME IDENTIFICATION IS CURRENTLY ACTIVE****Reason:**

A cross-memory system running has the same ID.

Action:

Change XMS identification and retry.

XMSXD006**ATTACH OF THE OPERATOR COMMUNICATION INTERFACE ROUTINE FAILED - RUN ABORTED****Reason:**

The cross-memory system is not able to attach to the operator communication interface.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXD007**ATTACH OF CROSS-MEMORY SIGNON ROUTINE FAILED - RUN ABORTED****Reason:**

The cross-memory login is not able to attach.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXD008**NO STARTUP PARAMETER SPECIFIED - RUN ABORTED****Reason:**

The cross-memory system startup parameter is not specified.

Action:

Specify a parameter field on the EXEC statement.

XMSXD009

INVALID CROSS-MEMORY IDENTIFICATION PARAMETER - RUN ABORTED

Reason:

The input XMS ID is too long.

Action:

Check the parameter field on EXEC statement.

XMSXD010

INVALID USERMAX PARAMETER - RUN ABORTED

Reason:

The USERMAX initialization parameter is not specified.

Action:

Specify a USERMAX parameter on the EXEC statement.

XMSXD011

SPECIFIED PARAMETER IS UNKNOWN - RUN ABORTED

Reason:

The input parameter is unknown.

Action:

Check the parameter field on EXEC statement.

XMSXD012

INVALID LONGWAIT PARAMETER - RUN ABORTED

Reason:

The LONGWAIT parameter on the EXEC statement is invalid.

Action:

Correct and retry.

XMSXD013**INVALID CANCEL PARAMETERS - RUN ABORTED****Reason:**

The CANCEL parameter on the EXEC statement is invalid.

Action:

Correct and retry.

XMSXD014**INVALID SUBSYS PARM, RUN ABORTED****Reason:**

The SUBSYS parameter on the cross-memory EXEC statement is invalid.

Action:

Correct the SUBSYS parameter, and then restart.

XMSXD090**PC ROUTINE *rrrrrrr* ACTIVE ADDR=*aaaaaaaa vv dd/mm/yy hh/mm*****Reason:**

This is an informational message.

Action:

None.

XMSXD091**PC ASID=*xxxx* XMEMCNTL ADDR=*aaaaaaaa* ID=*xxxxxxxx*****Reason:**

This is an informational message.

Action:

None.

XMSXE001

USER CONNECTION xxxxxxxxxxxxxxxxxxxxxxxx HAS ENDED

Reason:

The user connection has ended.

Action:

None. This is an informational message.

XMSXE002

USER CONNECTION xxxxxxxxxxxxxxxxxxxxxxxx ABEND xxxx

Reason:

The user connection has abended.

Action:

None. This is an informational message.

XMSXE003

UNABLE TO LOCATE USERS ASCB - CONNECTION TERMINATED

Reason:

This message is informational.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXE004

UNABLE TO LOCATE CROSS-MEMORY CONTROL BLOCK - RUN ABORTED

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXE005

CROSS-MEMORY CONTROL BLOCK IS INVALID - RUN ABORTED

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXE006

UNABLE TO LOCATE USER INFORMATION CONSOLE TABLE - RUN ABORTED

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXE007

UNABLE TO LOCATE USER CONNECTION TCB - RUN ABORTED

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSX0001

OPERATOR FUNCTION REQUESTED IS NOT SUPPORTED

Reason:

The request from an operating system modify command cannot be recognized.

Action:

Correct and retry.

XMSXS001

USER CONNECTION *XXXXXXXXXXXXXXXXXXXXXXXXXXXX* SIGNON IN PROGRESS

Reason:

The login is in progress.

Action:

None. This message is informational.

XMSXS002

UNABLE TO LOCATE USER SIGNON ASCB - SIGNON IGNORED

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXS901

INTERNAL ERROR - INVALID RTUS FOUND:*aaaaaaaa nnn xxxxxxxxxxxx*

Reason:

Internal error.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

XMSXS902

**INTERNAL ERROR - RTUS COUNT MISMATCH, CONTROL TABLE ADJUSTED ACTIVE
INACT TOTAL|(COMPUTED) *nnnnn nnnnn nnnnn***

Reason:

The cross-memory system has detected an internal error and has recovered from it.

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

Chapter 5: Abends

This chapter explains the User and System abends.

This section contains the following topics:

[User Abends](#) (see page 599)

[System Abends](#) (see page 607)

User Abends

This topic covers some of the user abends associated with CA View.

U0001

Reason:

A permanent archival control statement is invalid. The backup cycle of the CA View started task terminates. The abend is accompanied by messages beginning with SARPARxx, and message text identifying the type of error that occurred:

SARPARxx (CARD xxxx) INVALID xxxxxxxxxxxxxxxxxxxxxx

Action:

To complete the backup cycle or SARVERO utility correct the control statement, and then restart the started task.

U0001

Reason:

This abend is issued by EBCTMR12, EBCTMRR, EBCTMRS, EBCTMRT, and EBCTMRX when a screen service could not be performed successfully. This abend occurs if the address space with which XMS is communicating has abended or been canceled.

Action:

If the associated address space being canceled or abended causes the abend, then restart the abended task to stop the abends. The XMS address spaces must continue to process other requests. For assistance, contact Technical Support at <http://ca.com/support>.

U0003

Reason:

Copying a tape using the ADDHDR parameter but the input tape has a CA View Header (SARHDR).

Action:

Remove the ADDHDR parameter and rerun the tape copy.

U0005

Reason:

The XMS logon request queue storage was overlaid. The XMS region abends when this occurs.

Action:

Restart your XMS region. Save the dump that is created by the U0005 abend and for assistance, contact Technical Support at <http://ca.com/support>.

U0011

Reason:

Copying full tapes using the Tape Copy Utility SARTCP to output tapes which are not long enough to hold all of the input tape data and results in the message SARTCP11. The job step also terminates with a user abend U0011.

Action:

Rerun the step with a new scratch tape. The differences in physical tape lengths cause this problem and several attempts are required to obtain a tape which is long enough to hold the input data. SARPAC can also be used to create a tape rather than copying the tape.

U0024

Reason:

The database has no more space to hold direct-to-CA View archival reports from CA Deliver, and the operator responded T(Terminate) to the following message:

SARPAM24 DATABASE *database-name* FULL - REPLY R (RETRY) OR T (TERMINATE)

Action:

Either create more space in the database by deleting SYSOUTS or add more space to the database by either ADDDS or SARDBASE.

U0027**Reason:**

The EMC Centera API modules (FPAPIDLL, FPMDZDLL, FPPOSDLL, FPPAIDLL, and/or XERCES26) were not found. This message occurs if a release 3.0 or prior EMC Centera load library is referenced.

Action:

Add the EMC Centera load library to JOBLIB, STEPLIB, or the link list. The EMC Centera load library can also be copied to CVDELOAD.

U0028**Reason:**

An unsupported version of the EMC Centera API modules is found in JOBLIB, STEPLIB, or the link list.

Action:

Add the EMC Centera load library distribute with CA View to JOBLIB, STEPLIB, or the link list. The EMC Centera load library can also be copied to CVDELOAD.

U0030**Reason:**

The direct-to-CA View archival feature is attempting to write report data to an encrypted database but the external key manager product (ICSF) is not active, not installed, or has rejected the service request to obtain the encryption key. The operator responded T(Terminate) to the following message:

SARPAM30 External key manager error obtaining key for database-name - Reply R (retry) or T (terminate).

Action:

See the 'ACTION' section under the [SARPAM30 message](#) (see page 465) for instructions.

U0046

Reason:

If DFSORT ABEND or ABSTP is in effect, and DFSORT terminates with an error message, you receive a user abend. If the DFSORT installation option is set to the default value (ABCODE=MSG), the user abend code is equal to the error message (for example, U0046 for message ICE046A). For user abend codes that are error message numbers (ABCODE=MSG), see the explanation for the corresponding message (for example, the ICE046A Explanation for U0046).

Action:

Correct the sort error and restart the function.

U0049

CA View is modified to prevent a loop in IOCS when I/O errors occur on 'fenced' tape devices. The modification causes SARTPO (CA View Tape Output Processor) to abend when an unrecoverable tape I/O error occurs.

A user abend 0049 can occur during a backup cycle or a tape consolidation (SARPAC) run.

A U0049 abend during a backup cycle terminates the archival task (SARSTC). The task must be restarted with the execution parameter STOPBU to reset backup cycle processing, and start a new backup cycle using the modify command.

Example:

```
F SARSTC,NEW
```

A U0049 abend during a tape consolidation run terminates the job. Until a new backup cycle has completed the run must not restart. Start a new backup cycle using the modify command as described previously.

The tape that caused the U0049 abend contains valid reports and is usable. Customer tape library systems must be set up to keep tapes created by CA View tasks that abend.

The tape that caused the U0049 abend produces block ID errors when used. When MVS closes some high-density tapes from tasks that are terminated abnormally, the tape's Record 0 is set to 'corrupted'. Record 0 is a hardware control record on a high-density tape which is used with block ID processing. If Record 0 is corrupt, you can see an I/O error when CA View is positioning the tape. This caused a tape rewind and multiple 'forward space files' to reposition the tape.

A tape consolidation run against this tape copies all active reports to new tape media that restores the block ID processing.

U0055**Reason:**

The DSK2PARM specifies a unit that is not a tape device. The following message displays along with the abend:

```
SARTPO55 SECONDARY DISK DOES NOT EMULATE 3480 TAPES
```

Action:

Correct the DSK2DRVR name to use the correct driver if it is in error, correct the DSK2PARM to use a tape device, or correct the tape unit's system definition.

U0056**Reason:**

The TAPEOPT parameter specifies EAST, but the tape unit does not support block ID processing. The abend is accompanied by the following message:

```
SARTPO56 IMMEDIATE TAPE ACCESS REQUIRES 3480 TAPES
```

Action:

Correct the tape unit name in the STORGRP_x definition, correct the tape unit's system definition, or change TAPEOPT to use 3420 processing.

U0057**Reason:**

CA View has to create a tape volume, but the specified range has been exhausted. The following message displays with the abend:

```
SARTPO57 VOLSER RANGE xxxxxx-xxxxxx EXCEEDED (VOLSER RANGE MUST BE EXTENDED OR CHANGED), PROCESSING TERMINATED
```

Action:

Define new volumes and modify the range in the STORGRP_x or STORGRX_x parameter.

U0058**Reason:**

CA View writes several blocks to a tape volume simultaneously. The maxblks specification in the STORGRX_x parameter is below this number (currently 10). The following message displays with the abend:

```
SARTPO58 MAXBLKS FOR STORAGE GROUP SET TOO LOW
```

Action:

Correct the maxblks specification in the STORGRX_x parameter.

U0100

Reason:

An attempt is made to add or update a SYSOUT group index record with an invalid generation and sequence number. Processing is terminated. The following message displays along with the abend:

SARIFP01 INVALID GROUP CONTROL RECORD ID=xxxxxxxxxxxxx, GEN=nnnn, AND SEQ=nnnn ENCOUNTERED, PROGRAM TERMINATED.

Action:

If this occurs during a SARDBASE REORG, the program automatically corrects the error, and you can ignore this message. If bad records reside in the database from earlier releases of the product, the database needs correction with the VERIFY control statement from the SARDBASE utility. Otherwise, the processing can be resumed. For assistance, contact Technical Support at <http://ca.com/support>.

U1009

Reason:

ERO processing is selected (EROOPT=YES initialization parameter) with the ERO table being the single source of retention information (PRETAIN=TABLE initialization parameter), but the ERO table that is referenced by the SARPATAB DD statement is not specified in the archival task (SARSTC) job stream. This following message displays along with the abend:

SARPAR09 SARPATAB DD STATEMENT MISSING

Action:

Add the SARPATAB DD statement to the archival task job stream referencing a sequential file or a member of a PDS that containing the ERO table entries or change PRETAIN to INIT if there is no ERO Table.

U1010

Reason:

ERO processing was selected (EROOPT=YES initialization parameter) with the ERO table being the single source of retention information (PRETAIN=TABLE initialization parameter), but the data set referenced by the SARPATAB DD statement in the archival task (SARSTC) job stream does not contain any ERO table entries. This following message displays along with the abend:

SARPAR10 SARPATAB DATA SET EMPTY

Action:

Point the SARPATAB DD statement to a sequential file or member of a PDS that contains the table entries or change PRETAIN to INIT if there is no ERO Table.

U1012**Reason:**

The logical record length (LRECL) of data set pointed to by the SARPATAB DD Statement in the Archival Task (SARSTC) procedure exceeds 256 characters. The following message displays along with the abend:

SARPAR12 SARPATAB data set LRECL greater than 256.

Action:

Reallocate the data set with a logical record length (LRECL) of 256 characters or less and restart the Archival Task.

U1015**Reason:**

CA View is attempting to allocate dynamically a SYSOUT data set to print a SYSOUT group, and an internal program logic error occurred. The online print or batch print terminates. The following message displays along with the abend:

SARPR99 Unexpected return code - xxxx

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

U1111**Reason:**

CA View is attempting to allocate dynamically a SYSOUT data set to print a SYSOUT group, and an internal program logic error occurred. The online print or batch print terminates. The following message displays along with the abend:

SARBCP44 Unexpected return code – xxxx

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

U1111**Reason:**

CA View is attempting to dynamically allocate a SYSOUT data set to print a SYSOUT group, and an internal program logic error occurred. The online print or batch print terminates. The abend is accompanied by the following message:

SARBPT99 Unexpected return code - xxxx

Action:

For assistance, contact Technical Support at <http://ca.com/support>.

U2100-U2127

Reason:

An internal processing error occurred while performing I/O on a database sub-file.

Action:

Secure all system and job logs and dumps. For assistance, contact Technical Support at <http://ca.com/support>.

U2151

Reason:

The ACIF compression dictionary (SARCED01) is incorrectly linked (not on the page boundary). This error must never occur, but if it does, the cause is either an internal or packaging error. Specifying ACIFCOMP=NO in your SARINIT parameters allows the FSS collectors to process, but you are not able to access any compressed ACIF reports until this is corrected.

Action:

Do not modify the compression dictionary in any way. For assistance, contact Technical Support at <http://ca.com/support>.

U2152

Reason:

The ACIF compression dictionary (SARCED01) is corrupted (size is not a multiple of 4 KB). This error must never occur, but if it does, the cause is either an internal or packaging error. Specifying ACIFCOMP=NO in your SARINIT parameters allows the FSS collectors to process, but you are not able to access any compressed ACIF reports until the error is solved.

Action:

Do not modify the compression dictionary in any way. For assistance, contact Technical Support at <http://ca.com/support>.

U2153

Reason:

This indicates MVS Compression Services returned a non-zero return code. Specifying ACIFCOMP=NO in your SARINIT parameters allows the FSS collectors to process, but you are not able to access any compressed ACIF reports until this is corrected.

Action:

This is a problem with the MVS Compression Services themselves, not with the interface supplied with CA View. The return code from MVS Compression Services is in R7.

Note: For more information about the return codes, see the chapter "CSRCMPSC – Compress and Expand Data" in the *MVS Assembler Services Reference Manual*.

System Abends

This section provides some of the system abends associated with CA View.

S013-18 SARSTC , SARBKT

Reason:

CA View Archival task uses two optional sequential files, specified by the SARXCTAB and SARPATAB DD statements in the SARSTC JCL. You can use the JCL equivalent of a sequential dataset by coding a member name for a partitioned dataset as 'PDS (member)'. CA View requires a sequential dataset, it has no logic to verify that these members are actually in the PDS. If either member is not available during the dataset OPEN, the S013-18 occurs.

Action:

The accompanying message identifies the dataset and member:

```
IEC141I 013-18, IGG0191B, jobname, stepname, ddname, device#, volser,  
dataset_name(member_name)
```

Correct the JCL, or create the required data in a dataset with the correct member name.

S013-20 Any batch View Utility

Reason:

A CA View utility program output DD statement contained the data set name of a CA View or CA Deliver database extent. The register dump produced by the operating system contains the DD name which caused the problem, the name is in General Registers 8 and 9 in EBCDIC.

Action:

To contain a valid output data set or SYSOUT correct the DD Statement.